Symmetrical 2-extensions of the 3-dimensional grid. I

Kirill V. Kostousov*

*Krasovskii Institute of Mathematics and Mechanics,
S. Kovalevskaya Str, 16, 620108, Yekaterinburg, Russia*

Received 24 January 2020, accepted 30 May 2020, published online 10 March 2021

Abstract

For a positive integer d , a connected graph Γ is a symmetrical 2-extension of the d -dimensional grid Λ^d if there exists a vertex-transitive group G of automorphisms of Γ and its imprimitivity system σ with blocks of size 2 such that there exists an isomorphism φ of the quotient graph Γ/σ onto Λ^d . The tuple $(\Gamma, G, \sigma, \varphi)$ with specified components is called a realization of the symmetrical 2-extension Γ of the grid Λ^d . Two realizations $(\Gamma_1, G_1, \sigma_1, \varphi_1)$ and $(\Gamma_2, G_2, \sigma_2, \varphi_2)$ are called equivalent if there exists an isomorphism of the graph Γ_1 onto Γ_2 which maps σ_1 onto σ_2 . V.I. Trofimov proved that, up to equivalence, there are only finitely many realizations of symmetrical 2-extensions of Λ^d for each positive integer d . E.A. Konovalchik and K.V. Kostousov found all, up to equivalence, realizations of symmetrical 2-extensions of the grid Λ^2 . In this work we found all, up to equivalence, realizations $(\Gamma, G, \sigma, \varphi)$ of symmetrical 2-extensions of the grid Λ^3 for which only the trivial automorphism of Γ preserves all blocks of σ . Namely we prove that there are 5573 such realizations, and that among corresponding graphs Γ there are 5350 pairwise non-isomorphic.

Keywords: Symmetrical extensions of a graph, d -dimensional grid.

Math. Subj. Class.: 20H15

1 Introduction

Recall that, for a positive integer d , a d -dimensional grid Λ^d is a graph whose vertices are integer tuples $(a_1, \dots, a_d)$ and two vertices $(a'_1, \dots, a'_d)$ and $(a''_1, \dots, a''_d)$ are adjacent if and only if $|a'_1 - a''_1| + \dots + |a'_d - a''_d| = 1$. According to [6] for a finite graph Δ , define

*Our work was performed using ‘Uran’ supercomputer of IMM UB RAS, Yekaterinburg, Russia.

E-mail address: kkostousov@gmail.com (Kirill V. Kostousov)

a connected graph Γ to be a *symmetrical extension of Λ^d by Δ* if there exists a vertex-transitive group G of automorphisms of Γ and an imprimitivity system σ of G on $V(\Gamma)$ such that subgraphs of Γ generated by blocks of σ are isomorphic to Δ and there exists an isomorphism of Γ/σ (i.e., of factor-graph of Γ by partition σ of its vertex set) onto Λ^d . A tuple $(\Gamma, G, \sigma, \varphi)$ with specified components is called a *realization of symmetrical extension Γ of the grid Λ^d by the graph Δ* . For a positive integer q , a graph Γ is called a *symmetrical q -extension of the grid Λ^d* , if Γ is a symmetrical extension of the grid Λ^d by some graph Δ such that $|V(\Delta)| = q$. In this situation the tuple $(\Gamma, G, \sigma, \varphi)$ with specified components is called a *realization of the symmetrical q -extension Γ of the grid Λ^d* , and we say that Γ is a graph of this realization. Along with purely mathematical interest, symmetrical q -extensions of the grid Λ^d for small $d \geq 1$ and $q > 1$ are interesting for crystallography and some physical theories (see [5]). For crystallography, symmetrical 2-extensions of grids Λ^d are of the most interest. They naturally arise when considering “molecular” crystals whose “molecules” consist of two “atoms” or, more generally, have a distinguished axis.

It is natural to consider realizations of symmetric q -extensions of the grid Λ^d up to equivalence defined as follows (see [5]). We call two such realizations $R_1 = (\Gamma_1, G_1, \sigma_1, \varphi_1)$ and $R_2 = (\Gamma_2, G_2, \sigma_2, \varphi_2)$ *equivalent* and write $R_1 \sim R_2$ if there exists an isomorphism of the graph Γ_1 to the graph Γ_2 which maps σ_1 onto σ_2 . We say that the realization $(\Gamma, G, \sigma, \varphi)$ of the symmetrical q -extension of the grid Λ^d is *maximal* if $G = \text{Aut}_\sigma(\Gamma)$ is the group of all automorphisms of the graph Γ which preserve the partition σ . It is clear that each realization of the symmetrical q -extension of the grid Λ^d has an equivalent maximal realization (unique up to equivalence). V.I. Trofimov proved that, up to equivalence, for an arbitrary positive integer d , there is only a finite number of realizations of symmetrical 2-extensions of d -dimensional grid (see [7, Theorem 2]). An algorithm for constructing these extensions is also proposed in [7].

Using this algorithm, in [3] and [4] were found all, up to equivalence, realizations of symmetrical 2-extensions of the grid Λ^2 (162 realizations). Among the graphs of these realizations, there are exactly 152 pairwise nonisomorphic graphs.

For an arbitrary realization $(\Gamma, G, \sigma, \varphi)$ of the symmetrical 2-extension of the grid Λ^d and an arbitrary pair of adjacent vertices B_1, B_2 of the graph Γ/σ , the set of edges of the graph Γ , one end of which lies in B_1 and the other in B_2 , will be called a *connection*. The following types of connections are possible: *type 1* means a single edge; *type $2_{||}$* means two non-adjacent edges; *type 2_V* means two adjacent edges; *type 3* means three edges; *type 4* means full connection (4 edges). A realization that necessarily has connections of types not equal to $2_{||}$ and 4 will be called a *realization of class I*. A realization that have connections only of types $2_{||}$ and 4 (maybe only of one type) will called a *realizations of class II*. By Proposition 4 from [7], realizations of class I are exactly the realizations of symmetrical 2-extensions of the grid Λ^d such that only a trivial automorphism of their graph fixes all blocks.

All 162 realizations of symmetrical 2-extensions of the grid Λ^2 are distributed in classes I and II as follows: 87 realizations of class I (see [3]) and 75 realizations of class II (see [4]). This paper is devoted to the description of all, up to equivalence, realizations of symmetrical 2-extensions of the grid Λ^3 of class I.

A realization of symmetrical extension of the grid Λ^d by the graph K_2 (full graph on two vertices) will be called a *saturated realization of the symmetrical 2-extension of the grid Λ^d* . Accordingly, a realization of symmetrical extension of the grid Λ^d by the

graph complemented to K_2 will be call a it non-saturated realization of the symmetrical 2-extension of the grid Λ^d .

In this paper, we have proved that, up to equivalence, there are 5573 realizations of symmetrical 2-extensions of the grid Λ^3 of class I, among which 2872 are saturated and 2701 are non-saturated (see Theorem 1 and Corollary 1). Among the graphs of saturated realizations of symmetrical 2-extensions of the grid Λ^3 of class I there are exactly 2792 pairwise nonisomorphic; among the graphs of non-saturated realizations of class I there are exactly 2594 pairwise nonisomorphic; and among all graphs of realizations of class I there are 5350 pairwise nonisomorphic (see Corollary 2).

In Sec. 3, we give the description of all, up to equivalence, realizations of symmetrical 2-extensions of the grid Λ^3 of class I (Theorem 1 and Corollary 1). This is obtained using the approach from [7] implemented in GAP [2] (Algorithms 1 and 2 from [3]). Sec. 2 contains preliminary results.

2 Preliminaries

Using GAP [2], we have listed all conjugacy classes of vertex-transitive subgroups of the group $\text{Aut}(\Lambda^3)$. It turned out that there are 786 such classes.

The details are as follows. Each vertex-transitive group of automorphisms of Λ^3 is generated by the stabilizer in this group of the vertex $(0, 0, 0)$ and six elements of this group that translate the vertex $(0, 0, 0)$ to the vertices adjacent to it. Let S_0 be a stabilizer of $(0, 0, 0)$ in $\text{Aut}(\Lambda^3)$, $N_1 = S_0 t_x$, $N_2 = t_x^{-1}$, $N_3 = S_0 t_y$, $N_4 = t_x^{-1}$, $N_5 = S_0 t_z$, $N_6 = t_z^{-1}$, and $N = N_1 \cup N_2 \cup \dots \cup N_6$. We look over all subgroups S of S_0 , up to conjugation in S_0 . For every S , using backtracking, we search for all minimal subsets N' of N such that $|N' \cap N_i| \leq 1$ for all $i = 1, \dots, 6$ and $\langle S, N' \rangle \cap N_i \neq \emptyset$ for all $i = 1, \dots, 6$. For every found N' , if $\langle S, N' \rangle$ is a proper subgroup of $\text{Aut}(\Lambda^3)$, then we put this group into the resulting list $\mathbf{H}$. At the end, we thin out the list L up to conjugation in $\text{Aut}(\Lambda^3)$.

It turned out that $|\mathbf{H}| = 786$, $\mathbf{H} = \{H_1, \dots, H_{786}\}$. These groups are given in Table 2 below by their generating systems. The following notation is used for certain automorphisms of the grid Λ^3 :

$$\begin{aligned} r_x : (x, y, z) &\mapsto (x, -z, y), & r_y : (x, y, z) &\mapsto (z, y, -x), \\ r_z : (x, y, z) &\mapsto (y, -x, z), & m_x : (x, y, z) &\mapsto (-x, y, z), \\ m_y : (x, y, z) &\mapsto (x, -y, z), & m_z : (x, y, z) &\mapsto (x, y, -z), \\ i : (x, y, z) &\mapsto (-x, -y, -z), & t_x : (x, y, z) &\mapsto (x + 1, y, z), \\ t_y : (x, y, z) &\mapsto (x, y + 1, z), & t_z : (x, y, z) &\mapsto (x, y, z + 1), \end{aligned}$$

where $x, y, z \in \mathbb{Z}$.

Remark 2.1. In the natural embedding of the grid Λ^3 in the Euclidean space $\mathbb{R}^3$, each automorphism $g \in \text{Aut}(\Lambda^3)$ is induced by the only isometry $\tilde{g}$ of this space. The isometries that induce the above automorphisms of Λ^3 have the following geometric meaning: $\tilde{r}_x, \tilde{r}_y, \tilde{r}_z$ are rotations by the angle $\frac{\pi}{2}$ around coordinate axes x, y , and z respectively, $\tilde{m}_x, \tilde{m}_y, \tilde{m}_z$ are reflections relative coordinate planes, $\tilde{i}$ — central symmetry about the origin, $\tilde{t}_x, \tilde{t}_y, \tilde{t}_z$ are translations by 1 along axes x, y , and z respectively.

Using GAP, we constructed and tested 786 stabilizers $\{H_{(0,0,0)} : H \in \mathbf{H}\}$ for conjugacy in $\text{Aut}(\Lambda^3)_{(0,0,0)}$. It turned out that, up to conjugation, there are only 33 such

stabilizers. We give them in Table 1 by their generators indicated in column 3. For each of the 33 groups, the abstract group structure is given in column 2.

Table 1

**Stabilizers of vertex $(0, 0, 0)$ in vertex-transitive subgroups of $\text{Aut}(\Lambda^3)$
up to conjugation in $\text{Aut}(\Lambda^3)_{(0,0,0)}$**

Nº	Group structure	Generators
1	1	1
2	C_2	$\langle i \rangle$
3	C_2	$\langle m_z \rangle$
4	C_2	$\langle r_z^2 r_x \rangle$
5	C_2	$\langle r_z^2 \rangle$
6	C_2	$\langle m_z r_x \rangle$
7	C_3	$\langle r_y^{-1} r_z^{-1} \rangle$
8	$C_2 \times C_2$	$\langle r_y^2, r_z^2 \rangle$
9	$C_2 \times C_2$	$\langle i, r_z^2 \rangle$
10	$C_2 \times C_2$	$\langle m_z r_x^{-1}, r_x^2 \rangle$
11	$C_2 \times C_2$	$\langle m_x, r_y^2 r_x \rangle$
12	$C_2 \times C_2$	$\langle i, r_z^2 r_x \rangle$
13	$C_2 \times C_2$	$\langle r_y^2 r_x, r_z^2 r_x \rangle$
14	$C_2 \times C_2$	$\langle m_x, r_z^2 \rangle$
15	C_4	$\langle r_x^{-1}, r_x^2 \rangle$
16	C_4	$\langle m_x r_x^{-1} \rangle$
17	C_6	$\langle i, m_x r_y^{-1} r_x^{-1} \rangle$
18	S_3	$\langle m_x r_y, r_y^{-1} r_z^{-1} \rangle$
19	S_3	$\langle r_y^2 r_z, r_z^2 r_x \rangle$
20	$C_2 \times C_2 \times C_2$	$\langle i, r_y^2 r_x, r_z^2 r_x \rangle$
21	$C_2 \times C_2 \times C_2$	$\langle i, r_y^2, r_z^2 \rangle$
22	$C_4 \times C_2$	$\langle i, m_x r_x^{-1} \rangle$
23	D_8	$\langle m_x r_x^{-1}, r_z^2 r_x \rangle$
24	D_8	$\langle r_z^2, r_z^2 r_x \rangle$
25	D_8	$\langle m_y, m_z r_x^{-1}, r_x^2 \rangle$
26	D_8	$\langle m_x r_x^{-1}, r_z^2 \rangle$
27	A_4	$\langle r_y r_x^{-1}, r_y^2, r_z^2 \rangle$
28	D_{12}	$\langle i, r_y^2 r_z, r_z^2 r_x \rangle$
29	$C_2 \times D_8$	$\langle i, r_z^2, r_z^2 r_x \rangle$
30	$C_2 \times A_4$	$\langle i, m_x r_y^{-1} r_x^{-1}, r_y^2, r_z^2 \rangle$
31	S_4	$\langle m_x r_x^{-1}, m_x r_z, r_z^2 \rangle$
32	S_4	$\langle r_y^2 r_z, r_z^2, r_z^2 r_x \rangle$
33	$C_2 \times S_4$	$\langle i, r_y^2 r_z, r_z^2, r_z^2 r_x \rangle$

Each group $H \in \mathbf{H}$ is identified with some space group and, therefore, has a point group $P(H)$ and a translation basis (see [1]). Using GAP, we verified that the set of point groups $\{P(H) : H \in \mathbf{H}\}$ is equal, up to conjugation in $P(\text{Aut}(\Lambda^3))$, to the set of 33 stabilizers given in Table 1. In column 1 of Table 2 below, we give the set of groups $\mathbf{H}$ defined by their generators. In column 2, for each group $H \in \mathbf{H}$, we give the Nº of the group from Table 1 conjugate to the stabilizer $H_{(0,0,0)}$ in $\text{Aut}(\Lambda^3)_{(0,0,0)}$. In column 3, for

each group $H \in \mathbf{H}$, we give the $\mathbb{N}^3$ of the group from Table 1 conjugate to the point group $P(H)$ in $P(\text{Aut}(\Lambda^3))$. In column 4, for each group $H \in \mathbf{H}$, we give its translation basis. The groups in Table 2 are sorted lexicographically first by $\mathbb{N}^3$ in column 2 and then by $\mathbb{N}^3$ in column 3.

**Representatives of conjugacy classes for
vertex-transitive subgroups of $\text{Aut}(\Lambda^3)$**

Table 2

H	$H_{0,0,0}$	$P(H)$	Translation basis of H
$H_1 = \langle tx, ty^{-1}, tz^{-1} \rangle$	1	1	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_2 = \langle itz, itz^{-1}, tx, ty^{-1} \rangle$	1	2	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_3 = \langle ity, ity^{-1}, itz, itz^{-1}, tx \rangle$	1	2	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_4 = \langle itx, itx^{-1}, ity, ity^{-1}, itz, itz^{-1} \rangle$	1	2	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_5 = \langle mxty^{-1}, tx, tz^{-1} \rangle$	1	3	$[[1, 0, 0], [0, 2, 0], [0, 0, 1]]$
$H_6 = \langle myty, myty^{-1}, tx, tz^{-1} \rangle$	1	3	$[[1, 0, 0], [0, 2, 0], [0, 0, 1]]$
$H_7 = \langle myty, myty^{-1}, mytz^{-1}, tx \rangle$	1	3	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_8 = \langle mytx, mytz^{-1}, ty^{-1} \rangle$	1	3	$[[1, 0, 1], [0, 1, 0], [0, 0, 2]]$
$H_9 = \langle mytx, myty, myty^{-1}, mytz^{-1} \rangle$	1	3	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{10} = \langle r_x^2 ryty, r_x^2 ryty^{-1}, tx, tz^{-1} \rangle$	1	4	$[[1, 0, 0], [0, 2, 0], [0, 0, 1]]$
$H_{11} = \langle r_x^2 rxty^{-1}, r_x^2 rxtx, tx \rangle$	1	4	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{12} = \langle ry r_x^2 tx, ry r_x^2 tx^{-1}, ry r_x^2 ty, ry r_x^2 ty^{-1} \rangle$	1	4	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{13} = \langle r_x^2 ty, r_x^2 ty^{-1}, tx, tz^{-1} \rangle$	1	5	$[[1, 0, 0], [0, 2, 0], [0, 0, 1]]$
$H_{14} = \langle r_x^2 tz^{-1}, tx, ty^{-1} \rangle$	1	5	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{15} = \langle r_x^2 ty, r_x^2 ty^{-1}, r_x^2 tz, r_x^2 tz^{-1}, tx \rangle$	1	5	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{16} = \langle r_x^2 ty, r_x^2 ty^{-1}, r_x^2 tz^{-1}, tx \rangle$	1	5	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{17} = \langle r_y^2 tx, r_y^2 tx^{-1}, r_y^2 ty^{-1}, r_y^2 ty, r_y^2 tz, r_y^2 tz^{-1} \rangle$	1	5	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{18} = \langle mx r_y^{-1} ty^{-1}, tx, tz^{-1} \rangle$	1	6	$[[1, 0, 0], [0, 2, 0], [0, 0, 1]]$
$H_{19} = \langle mz r_x^{-1} ty^{-1}, mz r_x^{-1} tx, tx \rangle$	1	6	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{20} = \langle mz r_x^{-1} tx, mz r_x^{-1} ty^{-1}, mz r_x^{-1} tx \rangle$	1	6	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{21} = \langle ry r_x tx^{-1}, ry r_x tx^{-1}, r_y^{-1} r_x^{-1} tx \rangle$	1	7	$[[1, 0, 2], [0, 1, 2], [0, 0, 3]]$
$H_{22} = \langle r_x^2 ty^{-1}, r_x^2 ty, tx, tz^{-1} \rangle$	1	8	$[[1, 0, 0], [0, 4, 0], [0, 0, 1]]$
$H_{23} = \langle r_x^2 ty, r_x^2 ty^{-1}, r_x^2 tz, tx \rangle$	1	8	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{24} = \langle r_x^2 ty, r_x^2 ty^{-1}, r_x^2 tz, r_x^2 tz^{-1}, tx \rangle$	1	8	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{25} = \langle r_x^2 ty, r_x^2 ty^{-1}, r_y tx, r_y tx^{-1}, tz^{-1} \rangle$	1	8	$[[2, 0, 0], [0, 2, 0], [0, 0, 1]]$
$H_{26} = \langle r_x^2 ty^{-1}, r_x^2 ty^{-1}, tx \rangle$	1	8	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{27} = \langle r_y^2 ty^{-1}, r_y^2 ty, r_y^2 tx^{-1}, r_y^2 ty, tx \rangle$	1	8	$[[1, 0, 0], [0, 2, 1], [0, 0, 2]]$
$H_{28} = \langle r_x^2 ty, r_x^2 ty^{-1}, r_x^2 tx, r_x^2 tx^{-1}, r_y^2 tx, r_y^2 tx^{-1} \rangle$	1	8	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{29} = \langle r_x^2 tx, r_x^2 tx^{-1}, r_y^2 ty, r_y^2 ty^{-1}, r_y^2 tx^{-1} \rangle$	1	8	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{30} = \langle r_y^2 tx, r_y^2 tx^{-1}, r_y^2 ty^{-1}, r_y^2 ty, tx \rangle$	1	8	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{31} = \langle r_x^2 ty, r_x^2 ty^{-1}, r_x^2 tx, r_x^2 tx^{-1}, r_y^2 tx, r_y^2 tx^{-1} \rangle$	1	8	$[[2, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{32} = \langle r_x^2 tx, r_x^2 tx^{-1}, r_y^2 ty, r_y^2 ty^{-1}, r_y^2 tx, r_y^2 tx^{-1} \rangle$	1	8	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{33} = \langle r_x^2 ty, r_x^2 ty^{-1}, r_y^2 tx, r_y^2 tx^{-1}, r_y^2 tx^{-1} \rangle$	1	8	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{34} = \langle r_x^2 tx, r_x^2 tx^{-1}, r_y^2 tx^{-1} \rangle$	1	8	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{35} = \langle ity, r_x^2 ty^{-1}, tx, tz^{-1} \rangle$	1	9	$[[1, 0, 0], [0, 4, 0], [0, 0, 1]]$
$H_{36} = \langle ity, myty^{-1}, tx, tz^{-1} \rangle$	1	9	$[[1, 0, 0], [0, 4, 0], [0, 0, 1]]$
$H_{37} = \langle ity, itz^{-1}, r_x^2 ty^{-1}, r_x^2 tx, tx \rangle$	1	9	$[[1, 0, 0], [0, 1, 1], [0, 0, 4]]$
$H_{38} = \langle itz^{-1}, myty, myty^{-1}, r_y^2 tx, tx \rangle$	1	9	$[[1, 0, 0], [0, 1, 2], [0, 0, 4]]$
$H_{39} = \langle mxty^{-1}, r_x^2 tx, r_x^2 tx^{-1}, tx \rangle$	1	9	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{40} = \langle itz, itz^{-1}, r_x^2 ty, r_x^2 ty^{-1}, tx \rangle$	1	9	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{41} = \langle itz, itz^{-1}, myty, myty^{-1}, tx \rangle$	1	9	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{42} = \langle myty, myty^{-1}, r_y^2 tx, r_y^2 tx^{-1}, r_y^2 tx^{-1}, tx \rangle$	1	9	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{43} = \langle itz, itz^{-1}, mzty^{-1}, tx \rangle$	1	9	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{44} = \langle mzty^{-1}, r_x^2 tx^{-1}, tx \rangle$	1	9	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{45} = \langle itz, itz^{-1}, mytx, ty^{-1} \rangle$	1	9	$[[2, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{46} = \langle ity, ity^{-1}, r_x^2 tx^{-1}, tx \rangle$	1	9	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{47} = \langle ity, ity^{-1}, r_y^2 tx, r_y^2 tx^{-1}, tx \rangle$	1	9	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{48} = \langle ity, mxty^{-1}, r_x^2 ty^{-1}, tx \rangle$	1	9	$[[1, 0, 0], [0, 2, 1], [0, 0, 2]]$
$H_{49} = \langle ity, myty^{-1}, r_y^2 tx, r_y^2 tx^{-1}, tx \rangle$	1	9	$[[1, 0, 0], [0, 2, 1], [0, 0, 2]]$
$H_{50} = \langle myty, myty^{-1}, r_y^2 tx, r_y^2 tx^{-1}, r_y^2 tx, r_y^2 tx^{-1} \rangle$	1	9	$[[1, 0, 1], [0, 2, 0], [0, 0, 2]]$
$H_{51} = \langle myty, myty^{-1}, mytz^{-1}, r_y^2 tx, r_y^2 tx^{-1} \rangle$	1	9	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{52} = \langle itz, itz^{-1}, mytx, myty, myty^{-1} \rangle$	1	9	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{53} = \langle ity, ity^{-1}, itz, itz^{-1}, mztx \rangle$	1	9	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{54} = \langle mztx, r_x^2 ty, r_x^2 ty^{-1}, r_x^2 tx^{-1} \rangle$	1	9	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{55} = \langle itz, itz^{-1}, mztx, mztx^{-1} \rangle$	1	9	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{56} = \langle mztx, mztx^{-1}, r_x^2 tx^{-1} \rangle$	1	9	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{57} = \langle itx, itx^{-1}, ity, ity^{-1}, r_x^2 tx^{-1} \rangle$	1	9	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$

H	$H_{0,0,0}$	$P(H)$	Translation basis of H
$H58 = \langle it_x, it_x^{-1}, it_y, it_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1} \rangle$	1	9	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H59 = \langle it_x, it_x^{-1}, it_y, it_y^{-1}, m_z t_z, m_z t_z^{-1} \rangle$	1	9	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H60 = \langle it_x, it_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_z^2 t_z^{-1} \rangle$	1	9	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H61 = \langle it_x, it_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1} \rangle$	1	9	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H62 = \langle it_x, it_y^{-1}, m_z t_z, m_z t_z^{-1}, r_z^2 t_z^{-1}, r_z^2 t_y \rangle$	1	9	[[1, 1, 0], [0, 2, 1], [0, 0, 2]]
$H63 = \langle it_y, m_y t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_z, r_y^2 t_z^{-1} \rangle$	1	9	[[1, 0, 1], [0, 2, 1], [0, 0, 2]]
$H64 = \langle it_z^{-1}, m_y t_x, m_y t_y, m_y t_y^{-1}, r_y^2 t_z \rangle$	1	9	[[1, 0, 2], [0, 1, 2], [0, 0, 4]]
$H65 = \langle it_z, it_z^{-1}, m_y t_y, m_y t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	1	9	[[1, 1, 1], [0, 2, 0], [0, 0, 2]]
$H66 = \langle it_y, it_y^{-1}, m_z t_x, r_z^2 t_z^{-1} \rangle$	1	9	[[1, 1, 1], [0, 2, 0], [0, 0, 2]]
$H67 = \langle it_z, it_z^{-1}, m_z t_x, r_z^2 t_y, r_z^2 t_z^{-1} \rangle$	1	9	[[1, 1, 1], [0, 2, 0], [0, 0, 2]]
$H68 = \langle m_z r_x^{-1} t_z, r_x^2 t_y^{-1}, r_x^2 t_z^{-1}, t_x \rangle$	1	10	[[1, 0, 0], [0, 1, 3], [0, 0, 4]]
$H69 = \langle m_z r_x^{-1} t_x, r_x^2 t_y, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1} \rangle$	1	10	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H70 = \langle m_z r_x t_y^{-1}, m_z r_x t_z^{-1}, m_z r_x^{-1} t_x \rangle$	1	10	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H71 = \langle m_x r_y t_x, m_x r_y t_x^{-1}, r_y^2 t_y^{-1} \rangle$	1	10	[[1, 0, 1], [0, 2, 0], [0, 0, 2]]
$H72 = \langle m_x r_y t_y^{-1}, m_x r_y^{-1} t_x^{-1}, r_y^2 t_x, r_y^2 t_z \rangle$	1	10	[[1, 0, 3], [0, 1, 2], [0, 0, 4]]
$H73 = \langle m_y t_y, r_x^2 r_y t_y^{-1}, t_x, t_z^{-1} \rangle$	1	11	[[1, 1, 0], [0, 4, 0], [0, 0, 1]]
$H74 = \langle m_z r_x^{-1} t_y^{-1}, r_z^2 r_x t_z, t_x \rangle$	1	11	[[1, 1, 0], [0, 1, 3], [0, 0, 4]]
$H75 = \langle m_z r_x^{-1} t_x, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z \rangle$	1	11	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H76 = \langle m_x t_y^{-1}, m_x t_z^{-1}, m_z r_x^{-1} t_x \rangle$	1	11	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H77 = \langle m_z t_x, m_z t_z^{-1}, r_z^2 r_z t_z, r_z^2 t_z t_z^{-1} \rangle$	1	11	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H78 = \langle m_x t_x, m_x t_x^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z \rangle$	1	11	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H79 = \langle m_x r_y t_x, m_x r_y t_x^{-1}, r_y r_x t_y, r_y r_x t_y^{-1} \rangle$	1	11	[[1, 0, 1], [0, 2, 0], [0, 0, 2]]
$H80 = \langle m_x r_y t_x, m_x r_y t_x^{-1}, m_y t_y, m_y t_y^{-1} \rangle$	1	11	[[1, 0, 1], [0, 2, 0], [0, 0, 2]]
$H81 = \langle m_x t_x, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z, r_z^2 r_x t_x^{-1} \rangle$	1	11	[[2, 0, 1], [0, 1, 1], [0, 0, 2]]
$H82 = \langle m_x t_x, m_x t_x^{-1}, m_z r_x^{-1} t_z, r_z^2 r_x t_y^{-1} \rangle$	1	11	[[1, 0, 2], [0, 1, 3], [0, 0, 4]]
$H83 = \langle it_y, r_z^2 r_y t_y^{-1}, t_x, t_z^{-1} \rangle$	1	12	[[1, 0, 0], [0, 4, 0], [0, 0, 1]]
$H84 = \langle it_y, it_z, m_z r_x^{-1} t_y^{-1}, t_x \rangle$	1	12	[[1, 0, 0], [0, 1, 3], [0, 0, 4]]
$H85 = \langle it_y^{-1}, it_z^{-1}, r_z^2 r_x t_z, t_x \rangle$	1	12	[[1, 0, 0], [0, 1, 3], [0, 0, 4]]
$H86 = \langle it_y^{-1}, it_z, m_z r_x^{-1} t_x, r_z^2 r_x t_z^{-1} \rangle$	1	12	[[1, 0, 2], [0, 1, 1], [0, 0, 4]]
$H87 = \langle it_x, it_y^{-1}, it_z^{-1}, r_z^2 r_x t_z^{-1}, r_z^2 r_x t_z \rangle$	1	12	[[1, 0, 1], [0, 1, 3], [0, 0, 4]]
$H88 = \langle it_y, it_y^{-1}, it_z, it_z^{-1}, m_z r_x^{-1} t_x \rangle$	1	12	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H89 = \langle m_z r_x^{-1} t_x, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z^{-1} \rangle$	1	12	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H90 = \langle it_x, it_x^{-1}, it_y, it_y^{-1}, r_z^2 r_z t_z, r_y^2 r_z t_z^{-1} \rangle$	1	12	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H91 = \langle it_x, it_x^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z \rangle$	1	12	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H92 = \langle it_x, it_x^{-1}, m_z r_x t_y^{-1}, m_z r_x^{-1} t_z \rangle$	1	12	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H93 = \langle m_x r_y t_x, m_x r_y t_x^{-1}, r_z^2 r_y t_y, r_z^2 r_y t_z^{-1} \rangle$	1	12	[[1, 0, 1], [0, 2, 0], [0, 0, 2]]
$H94 = \langle it_x, m_z r_x t_y^{-1}, m_z r_x t_z^{-1}, r_z^2 r_x t_x^{-1} \rangle$	1	12	[[2, 0, 1], [0, 1, 1], [0, 0, 2]]
$H95 = \langle it_x, it_y, m_x r_z t_z^{-1}, r_x^2 r_z t_z, r_x^2 r_z t_z^{-1} \rangle$	1	12	[[1, 1, 1], [0, 2, 1], [0, 0, 2]]
$H96 = \langle r_z^2 r_y t_y^{-1}, r_y r_x^2 t_y, t_x, t_z^{-1} \rangle$	1	13	[[1, 0, 0], [0, 4, 0], [0, 0, 1]]
$H97 = \langle r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 r_x t_z^{-1}, t_x \rangle$	1	13	[[1, 0, 0], [0, 1, 1], [0, 0, 4]]
$H98 = \langle r_y r_x^2 t_x, r_y r_x^2 t_x^{-1}, r_y^2 t_z^{-1} \rangle$	1	13	[[1, 0, 1], [0, 2, 0], [0, 0, 2]]
$H99 = \langle r_z^2 r_y t_y, r_z^2 r_y t_y^{-1}, r_y r_z^2 t_x, r_y r_z^2 t_x^{-1} \rangle$	1	13	[[1, 0, 1], [0, 2, 0], [0, 0, 2]]
$H100 = \langle r_z^2 t_y, r_x^2 t_y^{-1}, r_z^2 t_z, r_x^2 t_z^{-1}, r_y^2 r_x t_x, r_y^2 r_x t_x^{-1} \rangle$	1	13	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H101 = \langle r_x^2 r_y t_y^{-1}, r_y r_z^2 t_y, r_y t_x, r_y t_x^{-1}, r_y^2 t_z, r_y^2 t_z^{-1} \rangle$	1	13	[[1, 0, 1], [0, 2, 1], [0, 0, 2]]
$H102 = \langle r_x^2 r_y t_x^{-1}, r_y r_x^2 t_y, r_y r_x^2 t_y^{-1}, r_y^2 t_x, r_y^2 t_z \rangle$	1	13	[[1, 0, 3], [0, 1, 2], [0, 0, 4]]
$H103 = \langle m_y t_y, r_x^2 t_y^{-1}, t_x, t_z^{-1} \rangle$	1	14	[[1, 0, 0], [0, 4, 0], [0, 0, 1]]
$H104 = \langle m_x t_y^{-1}, m_z t_z^{-1}, r_z^2 t_z, t_x \rangle$	1	14	[[1, 0, 0], [0, 1, 2], [0, 0, 4]]
$H105 = \langle m_x t_y^{-1}, m_y t_z^{-1}, t_x \rangle$	1	14	[[1, 0, 0], [0, 2, 0], [0, 0, 2]]
$H106 = \langle m_x t_y^{-1}, m_z t_z, m_z t_z^{-1}, t_x \rangle$	1	14	[[1, 0, 0], [0, 2, 0], [0, 0, 2]]
$H107 = \langle m_y t_z^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, t_x \rangle$	1	14	[[1, 0, 0], [0, 2, 0], [0, 0, 2]]
$H108 = \langle m_z t_z, m_z t_z^{-1}, r_z^2 t_y, r_x^2 t_z^{-1}, t_x \rangle$	1	14	[[1, 0, 0], [0, 2, 0], [0, 0, 2]]
$H109 = \langle m_y t_y, m_y t_y^{-1}, r_z^2 t_z^{-1}, t_x \rangle$	1	14	[[1, 0, 0], [0, 2, 0], [0, 0, 2]]
$H110 = \langle m_y t_y, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1}, t_x \rangle$	1	14	[[1, 0, 0], [0, 2, 0], [0, 0, 2]]
$H111 = \langle m_z t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, t_x \rangle$	1	14	[[1, 0, 0], [0, 2, 0], [0, 0, 2]]
$H112 = \langle m_y t_z^{-1}, m_z t_y^{-1}, t_x \rangle$	1	14	[[1, 0, 0], [0, 2, 0], [0, 0, 2]]
$H113 = \langle m_z t_y^{-1}, r_z^2 t_x, r_z^2 t_x^{-1}, t_z^{-1} \rangle$	1	14	[[2, 0, 0], [0, 2, 0], [0, 0, 1]]
$H114 = \langle m_y t_x, r_z^2 t_z^{-1}, t_y^{-1} \rangle$	1	14	[[2, 0, 0], [0, 1, 0], [0, 0, 2]]
$H115 = \langle m_y t_y, m_z t_z, m_z t_z^{-1}, r_z^2 t_y^{-1}, t_x \rangle$	1	14	[[1, 0, 0], [0, 2, 1], [0, 0, 2]]
$H116 = \langle m_z t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1}, r_z^2 t_z, r_z^2 t_z^{-1} \rangle$	1	14	[[1, 0, 1], [0, 2, 0], [0, 0, 2]]
$H117 = \langle m_z t_y^{-1}, m_z t_z, m_z t_z^{-1}, r_y^2 t_z, r_y^2 t_x^{-1} \rangle$	1	14	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H118 = \langle m_y t_x, m_y t_y, m_y t_y^{-1}, r_z^2 t_z^{-1} \rangle$	1	14	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H119 = \langle m_x t_z^{-1}, m_y t_x, m_y t_y, m_y t_y^{-1} \rangle$	1	14	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H120 = \langle m_y t_x, m_y t_y, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1} \rangle$	1	14	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H121 = \langle m_y t_x, m_y t_z^{-1}, m_z t_z^{-1} \rangle$	1	14	[[1, 0, 1], [0, 2, 0], [0, 0, 2]]
$H122 = \langle m_z t_x, r_z^2 t_y^{-1}, r_z^2 t_z, r_y^2 t_z^{-1} \rangle$	1	14	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H123 = \langle m_z t_x, m_z t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1} \rangle$	1	14	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H124 = \langle m_x t_x, m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_z^2 t_z^{-1} \rangle$	1	14	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]

H	$H_{0,0,0}$	$P(H)$	Translation basis of H
$H_{125} = \langle m_x t_x^{-1}, m_z t_y^{-1}, m_z t_z, m_z t_z^{-1}, r_y^2 t_x \rangle$	1	14	$[[2, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{126} = \langle m_x t_z^{-1}, m_z t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	1	14	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{127} = \langle m_x t_z^{-1}, m_z t_x, r_y^2 t_y^{-1} \rangle$	1	14	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{128} = \langle m_y t_y, m_y t_y^{-1}, m_z t_x, m_z t_z, r_x^2 t_z^{-1} \rangle$	1	14	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{129} = \langle m_x t_x, m_x t_x^{-1}, m_z t_z, m_z t_z^{-1}, r_y^2 t_y^{-1} \rangle$	1	14	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{130} = \langle r_y t_y^{-1}, t_x, t_z \rangle$	1	15	$[[1, 0, 0], [0, 4, 0], [0, 0, 1]]$
$H_{131} = \langle r_x t_z^{-1}, r_x^{-1} t_y^{-1}, t_x \rangle$	1	15	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{132} = \langle r_x^{-1} t_x, r_x^2 t_y, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1} \rangle$	1	15	$[[2, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{133} = \langle r_y^{-1} t_x, r_y^{-1} t_x^{-1}, r_y^2 t_z^{-1} \rangle$	1	15	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{134} = \langle m_x r_x t_z^{-1}, m_x r_x^{-1} t_y^{-1}, t_x \rangle$	1	16	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{135} = \langle m_z r_z t_x, m_z r_z t_x^{-1}, r_z^2 t_z^{-1} \rangle$	1	16	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{136} = \langle r_y r_x^2 t_x, r_y r_x^2 t_y, r_y r_x^2 t_z^{-1}, r_y^2 r_z t_z \rangle$	1	19	$[[1, 0, 1], [0, 1, 1], [0, 0, 6]]$
$H_{137} = \langle i t_y^{-1}, i t_z, m_z r_x^{-1} t_x, r_x^2 t_y, r_x^2 t_z^{-1} \rangle$	1	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 4]]$
$H_{138} = \langle i t_y^{-1}, i t_z, m_z r_x t_z^{-1}, m_z r_x^{-1} t_x \rangle$	1	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 4]]$
$H_{139} = \langle m_z r_x t_z^{-1}, m_z r_x^{-1} t_x, r_y r_x t_y^{-1} \rangle$	1	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 4]]$
$H_{140} = \langle i t_x, i t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z^{-1}, r_z^2 t_y^{-1}, r_z^2 t_y \rangle$	1	20	$[[1, 1, 0], [0, 4, 0], [0, 0, 2]]$
$H_{141} = \langle m_x r_y t_x^{-1}, r_x^2 r_y t_y, r_x^2 r_y t_y^{-1}, r_y r_x^2 t_x \rangle$	1	20	$[[1, 1, 0], [0, 2, 0], [0, 0, 4]]$
$H_{142} = \langle m_y t_y^{-1}, r_x^2 r_y t_y, r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_z, r_y^2 t_z^{-1} \rangle$	1	20	$[[1, 0, 1], [0, 4, 0], [0, 0, 2]]$
$H_{143} = \langle i t_x^{-1}, m_x t_x, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z \rangle$	1	20	$[[4, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{144} = \langle m_x t_x, m_z r_x t_x^{-1}, m_z r_x t_x^{-1}, r_z^2 r_x t_x^{-1} \rangle$	1	20	$[[4, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{145} = \langle i t_x, r_x^2 t_y, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}, r_z^2 r_x t_x^{-1} \rangle$	1	20	$[[4, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{146} = \langle i t_x, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z, r_z^2 r_x t_x^{-1} \rangle$	1	20	$[[4, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{147} = \langle m_x r_y t_x, m_x r_y t_x^{-1}, r_z^2 r_y t_y^{-1}, r_y r_x^2 t_y \rangle$	1	20	$[[1, 0, 1], [0, 4, 0], [0, 0, 2]]$
$H_{148} = \langle m_x r_y t_y^{-1}, r_x^2 r_y t_y^{-1}, r_y^2 t_x, r_y^2 t_z \rangle$	1	20	$[[1, 0, 3], [0, 2, 0], [0, 0, 4]]$
$H_{149} = \langle m_y t_y, m_y t_y^{-1}, r_x^2 r_y t_x^{-1}, r_y^2 t_x, r_y^2 t_z \rangle$	1	20	$[[1, 0, 3], [0, 2, 0], [0, 0, 4]]$
$H_{150} = \langle m_x r^{-1} t^{-1}, r_y r_x^2 t_y, r_y r_x^2 t_y^{-1}, r_y^2 t_x, r_y^2 t_z \rangle$	1	20	$[[1, 0, 3], [0, 2, 0], [0, 0, 4]]$
$H_{151} = \langle m_x r_y^{-1} t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_y^2 t_x, r_y^2 t_z \rangle$	1	20	$[[1, 0, 3], [0, 2, 0], [0, 0, 4]]$
$H_{152} = \langle i t_x, i t_y, r_x^2 r_z t_z, r_x^2 r_z^{-1}, r_y^2 r_z t_z^{-1} \rangle$	1	20	$[[1, 3, 0], [0, 4, 0], [0, 0, 2]]$
$H_{153} = \langle i t_x, i t_y, m_z t_z, m_z t_z^{-1}, r_y^2 r_z t_z^{-1} \rangle$	1	20	$[[1, 3, 0], [0, 4, 0], [0, 0, 2]]$
$H_{154} = \langle i t_x, i t_y, m_x r_z t_x^{-1}, m_z t_z, m_z t_z^{-1} \rangle$	1	20	$[[1, 3, 0], [0, 4, 0], [0, 0, 2]]$
$H_{155} = \langle m_x r_y^{-1} t_x^{-1}, m_y t_y, r_y r_x^2 t_x^{-1}, r_y^2 t_x, r_y^2 t_z \rangle$	1	20	$[[1, 0, 3], [0, 2, 1], [0, 0, 4]]$
$H_{156} = \langle i t_y, i t_y^{-1}, m_z t_x, r_x^2 r_z t_z, r_y^2 r_z t_z^{-1} \rangle$	1	20	$[[1, 1, 2], [0, 2, 0], [0, 0, 4]]$
$H_{157} = \langle m_x t_y^{-1}, m_z t_z, r_x^2 t_z^{-1}, t_x \rangle$	1	21	$[[1, 0, 0], [0, 2, 0], [0, 0, 4]]$
$H_{158} = \langle i t_z, m_x t_y^{-1}, m_z t_z^{-1}, t_x \rangle$	1	21	$[[1, 0, 0], [0, 2, 0], [0, 0, 4]]$
$H_{159} = \langle i t_y, r_x^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, t_x \rangle$	1	21	$[[1, 0, 0], [0, 4, 0], [0, 0, 2]]$
$H_{160} = \langle m_y t_y, r_x^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, t_x \rangle$	1	21	$[[1, 0, 0], [0, 4, 0], [0, 0, 2]]$
$H_{161} = \langle m_x t_z^{-1}, r_x^2 t_y^{-1}, r_y^2 t_y, t_x \rangle$	1	21	$[[1, 0, 0], [0, 4, 0], [0, 0, 2]]$
$H_{162} = \langle i t_y, m_z t_z, m_z t_z^{-1}, r_x^2 t_y^{-1}, t_x \rangle$	1	21	$[[1, 0, 0], [0, 4, 0], [0, 0, 2]]$
$H_{163} = \langle m_z t_z, m_z t_z^{-1}, r_x^2 t_y^{-1}, r_y^2 t_y, t_x \rangle$	1	21	$[[1, 0, 0], [0, 4, 0], [0, 0, 2]]$
$H_{164} = \langle i t_z^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z, t_x \rangle$	1	21	$[[1, 0, 0], [0, 2, 0], [0, 0, 4]]$
$H_{165} = \langle m_y t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2 t_y, t_x \rangle$	1	21	$[[1, 0, 0], [0, 4, 0], [0, 0, 2]]$
$H_{166} = \langle m_y t_y, m_y t_y^{-1}, m_z t_z, r_y^2 t_z^{-1}, t_x \rangle$	1	21	$[[1, 0, 0], [0, 2, 0], [0, 0, 4]]$
$H_{167} = \langle i t_y, r_x^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, t_z^{-1} \rangle$	1	21	$[[2, 0, 0], [0, 4, 0], [0, 0, 1]]$
$H_{168} = \langle i t_z^{-1}, m_y t_y, r_x^2 t_z, t_y^{-1} \rangle$	1	21	$[[2, 0, 0], [0, 1, 0], [0, 0, 4]]$
$H_{169} = \langle m_y t_y^{-1}, m_z t_z, r_x^2 t_z^{-1}, r_y^2 t_y, t_x \rangle$	1	21	$[[1, 0, 0], [0, 2, 2], [0, 0, 4]]$
$H_{170} = \langle m_y t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2 t_y \rangle$	1	21	$[[1, 0, 1], [0, 4, 0], [0, 0, 2]]$
$H_{171} = \langle m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_y t_z^{-1}, r_y^2 t_x \rangle$	1	21	$[[4, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{172} = \langle i t_x^{-1}, m_x t_x, m_y t_y, m_y t_y^{-1}, m_y t_z^{-1} \rangle$	1	21	$[[4, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{173} = \langle i t_z^{-1}, m_y t_y, m_y t_y, m_y t_y^{-1}, r_x^2 t_z^{-1} \rangle$	1	21	$[[1, 1, 0], [0, 2, 0], [0, 0, 4]]$
$H_{174} = \langle m_y t_x, m_y t_y, m_y t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1} \rangle$	1	21	$[[1, 1, 0], [0, 2, 0], [0, 0, 4]]$
$H_{175} = \langle i t_x, r_x^2 t_y, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}, r_z^2 t_x^{-1} \rangle$	1	21	$[[4, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{176} = \langle m_z t_z, m_z t_z^{-1}, r_x^2 t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1}, r_z^2 t_y \rangle$	1	21	$[[1, 2, 0], [0, 4, 0], [0, 0, 2]]$
$H_{177} = \langle i t_y, m_x t_z^{-1}, m_y t_y^{-1}, r_x^2 t_y, r_y^2 t_x^{-1} \rangle$	1	21	$[[1, 2, 0], [0, 4, 0], [0, 0, 2]]$
$H_{178} = \langle i t_y, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1}, r_y^2 t_z, r_y^2 t_x^{-1} \rangle$	1	21	$[[1, 2, 0], [0, 4, 0], [0, 0, 2]]$
$H_{179} = \langle i t_y^{-1}, m_z t_x, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2 t_y \rangle$	1	21	$[[1, 2, 0], [0, 4, 0], [0, 0, 2]]$
$H_{180} = \langle i t_y^{-1}, m_x t_z^{-1}, m_z t_x, r_y^2 t_y \rangle$	1	21	$[[1, 2, 0], [0, 4, 0], [0, 0, 2]]$
$H_{181} = \langle i t_y, m_z t_z, m_z t_z^{-1}, r_x^2 t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	1	21	$[[1, 2, 1], [0, 4, 0], [0, 0, 2]]$
$H_{182} = \langle m_x t_z^{-1}, m_y t_y^{-1}, r_x^2 t_y, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	1	21	$[[1, 2, 1], [0, 4, 0], [0, 0, 2]]$
$H_{183} = \langle m_y t_y^{-1}, m_z t_z, m_z t_z^{-1}, r_x^2 t_x, r_y^2 t_x^{-1}, r_z^2 t_y \rangle$	1	21	$[[1, 2, 1], [0, 4, 0], [0, 0, 2]]$
$H_{184} = \langle i t_y^{-1}, m_z t_x, r_x^2 t_y, r_y^2 t_z, r_y^2 t_z^{-1} \rangle$	1	21	$[[1, 2, 1], [0, 4, 0], [0, 0, 2]]$
$H_{185} = \langle m_x t_z^{-1}, m_z t_x, r_y^2 t_y, r_z^2 t_y^{-1} \rangle$	1	21	$[[1, 2, 1], [0, 4, 0], [0, 0, 2]]$
$H_{186} = \langle m_x t_x, m_x t_x^{-1}, m_z t_z, m_z t_z^{-1}, r_x^2 t_y, r_z^2 t_y^{-1} \rangle$	1	21	$[[1, 2, 1], [0, 4, 0], [0, 0, 2]]$
$H_{187} = \langle m_y t_z^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	1	21	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{188} = \langle m_z t_z, m_z t_z^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_x^{-1} \rangle$	1	21	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{189} = \langle m_y t_y, m_y t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1}, r_z^2 t_y^{-1} \rangle$	1	21	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{190} = \langle m_x t_z^{-1}, m_y t_y, m_y t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	1	21	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{191} = \langle m_y t_y, m_y t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	1	21	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$

H	$H_{0,0,0}$	$P(H)$	Translation basis of H
$H_{192} = \langle m_y t_y, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{193} = \langle it_z, it_z^{-1}, m_z t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{194} = \langle m_z t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_z \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{195} = \langle m_z t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_z, r_y^2 t_x^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{196} = \langle m_y t_z^{-1}, m_z t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{197} = \langle it_z, it_z^{-1}, m_y t_x, m_z t_y^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{198} = \langle m_y t_x, m_z t_y^{-1}, r_y^2 t_z \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{199} = \langle m_y t_x, m_z t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{200} = \langle m_x t_z^{-1}, m_y t_x, m_z t_y^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{201} = \langle it_y, it_y^{-1}, m_z t_x, r_y^2 t_z, r_y^2 t_z^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{202} = \langle it_y, it_y^{-1}, m_x t_z^{-1}, m_z t_x \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{203} = \langle it_y, it_y^{-1}, m_z t_x, r_y^2 t_z, r_y^2 t_z^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{204} = \langle m_z t_x, r_y^2 t_z, r_y^2 t_z^{-1}, r_y^2 t_y, r_y^2 t_y^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{205} = \langle it_z, it_z^{-1}, m_z t_x, r_y^2 t_y \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{206} = \langle m_z t_x, r_y^2 t_z, r_y^2 t_z^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{207} = \langle m_z t_x, r_y^2 t_z, r_y^2 t_z^{-1}, r_y^2 t_y \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{208} = \langle it_z, it_z^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_x \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{209} = \langle m_y t_y, m_y t_y^{-1}, m_z t_x, r_y^2 t_z^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{210} = \langle m_x t_z^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_x \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{211} = \langle it_x, it_x^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_y^2 t_y^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{212} = \langle it_x, it_x^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_y^2 t_y, r_y^2 t_y^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{213} = \langle it_x, it_x^{-1}, r_y^2 t_y, r_y^2 t_z^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{214} = \langle it_x, it_x^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_y^2 t_y \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{215} = \langle it_x, it_x^{-1}, m_z t_z, m_z t_z^{-1}, r_y^2 t_y^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{216} = \langle it_x, it_x^{-1}, m_z t_z, m_z t_z^{-1}, r_y^2 t_y, r_y^2 t_y^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{217} = \langle it_x, it_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{218} = \langle m_x t_x, m_x t_x^{-1}, r_y^2 t_y^{-1}, r_y^2 t_z^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{219} = \langle m_x t_x, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1} \rangle$	1	21	[[2,0,0],[0,2,0],[0,0,2]]
$H_{220} = \langle m_y t_y, m_z t_z, m_z t_z^{-1}, r_y^2 t_x^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	1	21	[[2,0,0],[0,2,1],[0,0,2]]
$H_{221} = \langle m_x t_z^{-1}, m_y t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_z \rangle$	1	21	[[2,0,0],[0,2,1],[0,0,2]]
$H_{222} = \langle m_x t_z^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1}, r_y^2 t_x \rangle$	1	21	[[2,0,1],[0,2,0],[0,0,2]]
$H_{223} = \langle m_x t_x^{-1}, m_y t_z^{-1}, m_z t_x^{-1}, r_y^2 t_x \rangle$	1	21	[[2,1,0],[0,2,0],[0,0,2]]
$H_{224} = \langle m_z t_x, r_y^2 t_y, r_y^2 t_z, r_y^2 t_z^{-1}, r_y^2 t_y^{-1} \rangle$	1	21	[[2,0,0],[0,2,1],[0,0,2]]
$H_{225} = \langle it_x, m_z t_z, m_z t_z^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_y^2 t_z^{-1} \rangle$	1	21	[[2,0,1],[0,2,0],[0,0,2]]
$H_{226} = \langle it_x, m_y t_y, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1}, r_y^2 t_x^{-1} \rangle$	1	21	[[2,0,1],[0,2,0],[0,0,2]]
$H_{227} = \langle it_x^{-1}, m_x t_x, m_y t_y, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1} \rangle$	1	21	[[2,1,1],[0,2,0],[0,0,2]]
$H_{228} = \langle it_x^{-1}, m_x t_x, m_y t_y^{-1}, m_z t_y^{-1} \rangle$	1	21	[[2,1,1],[0,2,0],[0,0,2]]
$H_{229} = \langle m_y t_x^{-1}, m_y t_y, m_z t_z, m_z t_z^{-1}, r_y^2 t_x^{-1}, r_y^2 t_x \rangle$	1	21	[[2,0,1],[0,2,1],[0,0,2]]
$H_{230} = \langle m_x r_x t_x^{-1}, r_x^{-1} t_y^{-1}, t_x \rangle$	1	22	[[1,0,0],[0,2,2],[0,0,4]]
$H_{231} = \langle m_x r_x^{-1} t_y^{-1}, m_x t_x, m_x t_x^{-1}, r_x t_x^{-1} \rangle$	1	22	[[1,0,2],[0,2,2],[0,0,4]]
$H_{232} = \langle it_x, it_x^{-1}, m_x r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1} \rangle$	1	22	[[2,0,0],[0,2,0],[0,0,2]]
$H_{233} = \langle it_x, it_x^{-1}, r_x t_z^{-1}, r_x^{-1} t_y^{-1} \rangle$	1	22	[[2,0,0],[0,2,0],[0,0,2]]
$H_{234} = \langle m_x r_x t_z^{-1}, m_x r_x^{-1} t_y^{-1}, m_x t_x, m_x t_x^{-1} \rangle$	1	22	[[2,0,0],[0,2,0],[0,0,2]]
$H_{235} = \langle m_y t_y, m_y t_y^{-1}, r_x^{-1} t_x, r_x^{-1} t_y^{-1} \rangle$	1	22	[[2,0,0],[0,2,0],[0,0,2]]
$H_{236} = \langle it_x^{-1}, m_x t_x, r_x t_z^{-1}, r_x^{-1} t_y^{-1} \rangle$	1	22	[[2,1,1],[0,2,0],[0,0,2]]
$H_{237} = \langle it_y, it_y^{-1}, m_x t_z^{-1}, r_x^{-1} t_x \rangle$	1	22	[[2,1,1],[0,2,0],[0,0,2]]
$H_{238} = \langle m_x r_x t_z^{-1}, m_x r_x^{-1} t_y^{-1}, r_x^{-1} t_x \rangle$	1	22	[[2,1,1],[0,2,0],[0,0,2]]
$H_{239} = \langle m_x r_x t_z^{-1}, m_y t_y^{-1}, m_z t_z, t_x \rangle$	1	23	[[1,0,0],[0,2,2],[0,0,4]]
$H_{240} = \langle m_x t_z^{-1}, m_z t_x, r_x r_y t_y^{-1}, r_y r_x^2 t_y \rangle$	1	23	[[1,2,1],[0,4,0],[0,0,2]]
$H_{241} = \langle m_x t_x, m_x t_x^{-1}, m_z t_z, m_z t_z^{-1}, r_x^2 r_y t_y^{-1}, r_y r_x^2 t_y \rangle$	1	23	[[1,2,1],[0,4,0],[0,0,2]]
$H_{242} = \langle m_x t_z^{-1}, m_z t_x, r_x^2 r_y t_y, r_x^2 r_y t_y^{-1} \rangle$	1	23	[[2,0,0],[0,2,0],[0,0,2]]
$H_{243} = \langle m_x t_x, m_x t_x^{-1}, m_z t_z, m_z t_z^{-1}, r_x^2 r_y t_y, r_x^2 r_y t_y^{-1} \rangle$	1	23	[[2,0,0],[0,2,0],[0,0,2]]
$H_{244} = \langle m_z r_z t_x, m_z r_z t_x^{-1}, r_x^2 r_z t_z, r_x^2 r_z t_z^{-1} \rangle$	1	23	[[2,0,0],[0,2,0],[0,0,2]]
$H_{245} = \langle m_z r_z t_x, m_z r_z t_x^{-1}, r_x^2 r_z t_z, r_x^2 r_z t_z^{-1} \rangle$	1	23	[[2,0,0],[0,2,0],[0,0,2]]
$H_{246} = \langle m_x t_x^{-1}, m_y t_y^{-1}, m_z r_z t_z, r_x^2 r_z t_z, r_x^2 r_z t_z^{-1} \rangle$	1	23	[[2,0,0],[0,2,0],[0,0,2]]
$H_{247} = \langle r_x^2 r_y t_y^{-1}, r_x^2 t_y, t_x, t_x^{-1} \rangle$	1	24	[[1,0,0],[0,8,0],[0,0,1]]
$H_{248} = \langle r_x^{-1} t_y^{-1}, r_x^2 t_z^{-1}, r_x^2 t_y, t_x \rangle$	1	24	[[1,0,0],[0,2,2],[0,0,4]]
$H_{249} = \langle r_x^{-1} t_x, r_x^2 t_y, r_x^2 t_z^{-1}, r_x^2 t_z^{-1} \rangle$	1	24	[[4,0,0],[0,1,1],[0,0,2]]
$H_{250} = \langle r_x^{-1} t_x, r_x^2 r_x t_y^{-1}, r_x^2 r_x t_z \rangle$	1	24	[[4,0,0],[0,1,1],[0,0,2]]
$H_{251} = \langle r_x^2 t_y, r_y r_x^2 t_x, r_y r_x^2 t_x^{-1}, r_x^2 t_z^{-1} \rangle$	1	24	[[1,0,1],[0,4,0],[0,0,2]]
$H_{252} = \langle r_x^2 r_z t_z, r_y r_z t_z^{-1}, r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_y^{-1} \rangle$	1	24	[[1,1,0],[0,2,0],[0,0,4]]
$H_{253} = \langle r_x^2 t_y, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}, r_x^2 r_x t_x, r_y^2 t_x^{-1} \rangle$	1	24	[[4,0,1],[0,1,1],[0,0,2]]
$H_{254} = \langle r_x^2 r_y t_y^{-1}, r_y r_x^2 t_x, r_y^{-1} t_x, r_y^{-1} t_x^{-1} \rangle$	1	24	[[1,2,1],[0,4,0],[0,0,2]]
$H_{255} = \langle r_x^2 t_y, r_x^2 t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	1	24	[[2,0,0],[0,2,0],[0,0,2]]
$H_{256} = \langle r_x^2 r_y t_y, r_x^2 r_y t_y^{-1}, r_y^{-1} t_x, r_y^{-1} t_x^{-1} \rangle$	1	24	[[2,0,0],[0,2,0],[0,0,2]]
$H_{257} = \langle r_y r_x^2 t_y, r_y r_x^2 t_y^{-1}, r_y^{-1} t_x, r_y^{-1} t_x^{-1} \rangle$	1	24	[[2,0,0],[0,2,0],[0,0,2]]
$H_{258} = \langle r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_y^2 t_y^{-1}, r_y^2 t_z^{-1} \rangle$	1	24	[[2,0,0],[0,2,0],[0,0,2]]

H	$H_{0,0,0}$	$P(H)$	Translation basis of H
$H_{259} = \langle r_x^2 t_y^{-1}, r_y^2 r_z t_z, r_z^2 r_x t_x^{-1}, r_y^2 t_x, r_z^{-1} t_x^{-1} \rangle$	1	24	$[[2, 0, 1], [0, 2, 1], [0, 0, 2]]$
$H_{260} = \langle m_y t_y^{-1}, m_z t_z, r_x t_x^{-1}, t_x \rangle$	1	25	$[[1, 0, 0], [0, 2, 2], [0, 0, 4]]$
$H_{261} = \langle m_y t_y^{-1}, m_z r_x^{-1} t_x, m_z t_z, r_x t_x^{-1} \rangle$	1	25	$[[1, 0, 2], [0, 2, 2], [0, 0, 4]]$
$H_{262} = \langle m_y t_y, m_y t_y^{-1}, m_z r_x^{-1} t_x, m_z t_z, m_z t_z^{-1} \rangle$	1	25	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{263} = \langle m_z r_x^{-1} t_x, r_x t_x^{-1}, r_x^{-1} t_y^{-1} \rangle$	1	25	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{264} = \langle m_z r_x^{-1} t_x, r_x t_x^{-1}, r_x^{-1} t_z \rangle$	1	25	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{265} = \langle m_y t_z^{-1}, m_z r_x^{-1} t_x, m_z t_y^{-1} \rangle$	1	25	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{266} = \langle m_y t_y, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1}, r_x^{-1} t_x \rangle$	1	25	$[[2, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{267} = \langle m_y t_z^{-1}, m_z t_y^{-1}, r_x^{-1} t_x \rangle$	1	25	$[[2, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{268} = \langle m_z r_x^{-1} t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 t_x, t_z^{-1} \rangle$	1	26	$[[2, 2, 0], [0, 4, 0], [0, 0, 1]]$
$H_{269} = \langle m_z r_z t_x, m_z r_z t_x^{-1}, r_x^2 t_z, r_y t_z^{-1} \rangle$	1	26	$[[1, 1, 2], [0, 2, 0], [0, 0, 4]]$
$H_{270} = \langle m_x r_z t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, r_y^2 t_x, r_x^2 t_x^{-1} \rangle$	1	26	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{271} = \langle m_x r_x t_z^{-1}, m_x r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_x \rangle$	1	26	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{272} = \langle m_x r_x t_y^{-1}, m_x r_x^{-1} t_z, m_z r_x^{-1} t_x \rangle$	1	26	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{273} = \langle m_z r_x^{-1} t_x, r_y^2 t_y^{-1}, r_z^2 t_z^{-1} \rangle$	1	26	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{274} = \langle m_x r_z t_z^{-1}, m_z r_x^{-1} t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 t_x \rangle$	1	26	$[[2, 0, 1], [0, 2, 1], [0, 0, 2]]$
$H_{275} = \langle m_x t_z^{-1}, m_z t_x, r_z^2 r_y t_y, r_z^2 t_y^{-1} \rangle$	1	29	$[[1, 4, 1], [0, 8, 0], [0, 0, 2]]$
$H_{276} = \langle m_x t_x, m_x t_x^{-1}, m_z t_z, m_z t_z^{-1}, r_x^2 r_y t_y, r_z^2 t_y^{-1} \rangle$	1	29	$[[1, 4, 1], [0, 8, 0], [0, 0, 2]]$
$H_{277} = \langle m_x t_x, m_y t_y, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1}, r_z^2 r_x t_x^{-1} \rangle$	1	29	$[[4, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{278} = \langle m_x t_x, r_x t_x^{-1}, r_x^{-1} t_y^{-1}, r_z^2 r_x t_x^{-1} \rangle$	1	29	$[[4, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{279} = \langle m_x t_x, r_x t_x^{-1}, r_x^{-1} t_z, r_z^2 r_x t_x^{-1} \rangle$	1	29	$[[4, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{280} = \langle m_x t_x, m_y t_z^{-1}, m_z t_y^{-1}, r_z^2 r_x t_x^{-1} \rangle$	1	29	$[[4, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{281} = \langle i t_y^{-1}, m_x t_x^{-1}, m_z t_x, r_z^2 r_y t_y \rangle$	1	29	$[[2, 0, 0], [0, 4, 0], [0, 0, 2]]$
$H_{282} = \langle i t_x, m_y t_y, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1}, r_z^2 r_x t_x^{-1} \rangle$	1	29	$[[4, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{283} = \langle i t_x, r_x t_x^{-1}, r_x^{-1} t_y^{-1}, r_z^2 r_x t_x^{-1} \rangle$	1	29	$[[4, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{284} = \langle i t_x, r_x t_x^{-1}, r_x^{-1} t_z, r_z^2 r_x t_x^{-1} \rangle$	1	29	$[[4, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{285} = \langle m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_y^2 t_x \rangle$	1	29	$[[2, 2, 0], [0, 4, 0], [0, 0, 2]]$
$H_{286} = \langle m_x r_z t_z^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_y^2 t_x \rangle$	1	29	$[[2, 2, 0], [0, 4, 0], [0, 0, 2]]$
$H_{287} = \langle m_z r_x^{-1} t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_y^2 t_x \rangle$	1	29	$[[2, 2, 0], [0, 4, 0], [0, 0, 2]]$
$H_{288} = \langle m_z r_x^{-1} t_x^{-1}, m_z t_z, m_z t_z^{-1}, r_x^2 t_y^{-1}, r_y^2 t_x \rangle$	1	29	$[[2, 2, 0], [0, 4, 0], [0, 0, 2]]$
$H_{289} = \langle m_x r_z t_z^{-1}, r_x^2 t_y^{-1}, r_y^2 t_x, r_z^{-1} t_x^{-1} \rangle$	1	29	$[[2, 2, 0], [0, 4, 0], [0, 0, 2]]$
$H_{290} = \langle m_z t_z, m_z t_z^{-1}, r_x^2 t_y^{-1}, r_y^2 t_x, r_z^{-1} t_x^{-1} \rangle$	1	29	$[[2, 2, 0], [0, 4, 0], [0, 0, 2]]$
$H_{291} = \langle m_x r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_x, r_x t_z^{-1} \rangle$	1	29	$[[2, 0, 0], [0, 2, 2], [0, 0, 4]]$
$H_{292} = \langle m_x r_x^{-1} t_y^{-1}, m_y t_y, m_z r_x^{-1} t_x, m_z t_z^{-1} \rangle$	1	29	$[[2, 0, 0], [0, 2, 2], [0, 0, 4]]$
$H_{293} = \langle m_x r_x^{-1} t_y^{-1}, m_x t_x, m_x t_x^{-1}, m_y t_y, m_z t_z^{-1} \rangle$	1	29	$[[2, 0, 0], [0, 2, 2], [0, 0, 4]]$
$H_{294} = \langle m_x t_x^{-1}, m_z t_z^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_y^{-1} t_x \rangle$	1	29	$[[2, 0, 2], [0, 2, 0], [0, 0, 4]]$
$H_{295} = \langle m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}, r_x^{-1} t_x \rangle$	1	29	$[[2, 0, 2], [0, 2, 0], [0, 0, 4]]$
$H_{296} = \langle r_y^2 t_x, r_y^2 t_x^{-1}, r_y^{-1} m_y t_x^{-1}, r_y^{-1} t_x \rangle$	1	29	$[[2, 0, 2], [0, 2, 0], [0, 0, 4]]$
$H_{297} = \langle i t_z^{-1}, m_z r_x^{-1} t_x^{-1}, r_x r_z t_z, r_z^2 t_y^{-1}, r_y^2 t_x \rangle$	1	29	$[[2, 0, 2], [0, 2, 2], [0, 0, 4]]$
$H_{298} = \langle m_x t_x, m_y t_y^{-1}, m_z t_z, r_x t_z^{-1}, r_z^2 r_x t_x^{-1} \rangle$	1	29	$[[2, 0, 2], [0, 2, 2], [0, 0, 4]]$
$H_{299} = \langle i, i t_x, i t_y^{-1}, i t_z^{-1} \rangle$	2	2	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{300} = \langle i, i t_x, i t_y^{-1}, r_z^2 t_z^{-1} \rangle$	2	9	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{301} = \langle i, i t_x, i t_y^{-1}, r_y^2 t_z^{-1} \rangle$	2	9	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{302} = \langle i, i t_x, r_z^2 t_y^{-1}, r_z^2 t_z^{-1} \rangle$	2	9	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{303} = \langle i, i t_x, m_x t_x^{-1}, m_z t_z^{-1} \rangle$	2	9	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{304} = \langle i, r_z^2 t_x, r_z^2 t_y^{-1}, r_z^2 t_z^{-1} \rangle$	2	9	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{305} = \langle i, i t_x, i t_y^{-1}, r_y^2 r_z t_z^{-1} \rangle$	2	12	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{306} = \langle i, i t_x, r_z^2 r_x t_x^{-1} \rangle$	2	12	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{307} = \langle i, r_z^2 r_x t_x, r_z^2 r_x t_x^{-1} \rangle$	2	12	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{308} = \langle i, r_y^2 r_z t_z^{-1}, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	2	20	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{309} = \langle i, r_y^2 r_x t_y^{-1}, r_z^2 r_x t_x \rangle$	2	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{310} = \langle i, m_x t_x, r_z^2 r_x t_x^{-1} \rangle$	2	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{311} = \langle i, i t_x, r_y^2 t_z^{-1}, r_z^2 t_y^{-1} \rangle$	2	21	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{312} = \langle i, i t_x, m_x t_z^{-1}, r_z^2 t_y^{-1} \rangle$	2	21	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{313} = \langle i, i t_x, r_y^2 t_y^{-1}, r_z^2 t_z^{-1} \rangle$	2	21	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{314} = \langle i, i t_x, m_x t_z^{-1}, r_y^2 t_y^{-1} \rangle$	2	21	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{315} = \langle i, r_y^2 t_z^{-1}, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	2	21	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{316} = \langle i, r_y^2 t_z^{-1}, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	2	21	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{317} = \langle i, r_y^2 t_y^{-1}, r_z^2 t_z^{-1}, r_z^2 t_x \rangle$	2	21	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{318} = \langle i, m_x t_z^{-1}, r_y^2 t_y^{-1}, r_z^2 t_x \rangle$	2	21	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{319} = \langle i, m_x t_y^{-1}, r_y^2 t_z^{-1}, r_z^2 t_x \rangle$	2	21	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{320} = \langle i, m_x t_x, r_y^2 t_y^{-1}, r_z^2 t_z^{-1} \rangle$	2	21	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{321} = \langle i, i t_x, m_x r_x^{-1} t_y^{-1} \rangle$	2	22	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{322} = \langle i, m_x r_x^{-1} t_y^{-1}, m_x t_x \rangle$	2	22	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{323} = \langle i, m_x t_z^{-1}, r_x^2 r_y t_y^{-1}, r_z^2 t_x \rangle$	2	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{324} = \langle i, m_x r_x^{-1} t_y^{-1}, r_z^2 r_x t_x \rangle$	2	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{325} = \langle i, m_x r_x t_y^{-1}, r_z^2 r_x t_x \rangle$	2	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$

H	$H_{0,0,0}$	$P(H)$	Translation basis of H
$H_{326} = \langle i, r_y^2 t_y^{-1}, r_z^2 r_x t_x, r_z^2 t_z^{-1} \rangle$	2	29	[[2,0,0],[0,2,0],[0,0,2]]
$H_{327} = \langle m_z, m_z t_x, m_z t_y^{-1}, m_z t_z^{-1} \rangle$	3	3	[[1,0,0],[0,1,0],[0,0,1]]
$H_{328} = \langle i t_x, i t_x^{-1}, m_z, m_z t_y^{-1}, m_z t_z^{-1} \rangle$	3	9	[[2,0,0],[0,1,0],[0,0,1]]
$H_{329} = \langle i t_z^{-1}, m_z, m_z t_x, m_z t_y^{-1} \rangle$	3	9	[[1,0,0],[0,1,0],[0,0,2]]
$H_{330} = \langle i t_x, i t_x^{-1}, i t_y, i t_y^{-1}, m_z, m_z t_z^{-1} \rangle$	3	9	[[1,1,0],[0,2,0],[0,0,1]]
$H_{331} = \langle i t_x, i t_x^{-1}, i t_z^{-1}, m_z, m_z t_y^{-1} \rangle$	3	9	[[1,0,1],[0,1,0],[0,0,2]]
$H_{332} = \langle i t_x, i t_x^{-1}, i t_y, i t_y^{-1}, i t_z^{-1}, m_z \rangle$	3	9	[[1,0,1],[0,1,1],[0,0,2]]
$H_{333} = \langle m_z, m_z t_x, m_z t_y^{-1}, r_y^2 r_z t_z^{-1} \rangle$	3	11	[[1,0,0],[0,1,0],[0,0,2]]
$H_{334} = \langle m_z, m_z t_z^{-1}, r_y^2 r_z t_x, r_y^2 r_z t_z^{-1} \rangle$	3	11	[[1,1,0],[0,2,0],[0,0,1]]
$H_{335} = \langle m_z, r_y^2 r_z t_x, r_y^2 r_z t_z^{-1}, r_y^2 r_z t_z^{-1} \rangle$	3	11	[[1,0,1],[0,1,1],[0,0,2]]
$H_{336} = \langle m_z, m_z t_y^{-1}, m_z t_z^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	3	14	[[2,0,0],[0,1,0],[0,0,1]]
$H_{337} = \langle m_z, m_z t_y^{-1}, m_z t_z^{-1}, r_x^2 t_x \rangle$	3	14	[[2,0,0],[0,1,0],[0,0,1]]
$H_{338} = \langle m_z, m_z t_x, m_z t_y^{-1}, r_y^2 t_z^{-1} \rangle$	3	14	[[1,0,0],[0,1,0],[0,0,2]]
$H_{339} = \langle m_z, m_z t_z^{-1}, r_x^2 t_x, r_x^2 t_x^{-1}, r_y^2 t_y \rangle$	3	14	[[1,1,0],[0,2,0],[0,0,1]]
$H_{340} = \langle m_z, m_z t_y^{-1}, r_x^2 t_x, r_x^2 t_x^{-1}, r_y^2 t_z^{-1} \rangle$	3	14	[[1,0,1],[0,1,0],[0,0,2]]
$H_{341} = \langle m_z, m_z t_y^{-1}, r_x^2 t_x, r_x^2 t_x^{-1}, r_y^2 t_z^{-1} \rangle$	3	14	[[1,0,1],[0,1,0],[0,0,2]]
$H_{342} = \langle m_z, r_y^2 t_x, r_y^2 t_z^{-1}, r_y^2 t_z^{-1}, r_y^2 t_z^{-1} \rangle$	3	14	[[1,0,1],[0,1,1],[0,0,2]]
$H_{343} = \langle i t_x, i t_y, m_z, m_z t_z^{-1}, r_y^2 r_z t_z^{-1} \rangle$	3	20	[[1,3,0],[0,4,0],[0,0,1]]
$H_{344} = \langle i t_x, i t_x^{-1}, i t_y, i t_y^{-1}, m_z, r_y^2 r_z t_z^{-1} \rangle$	3	20	[[1,1,0],[0,2,0],[0,0,2]]
$H_{345} = \langle i t_z^{-1}, m_z, r_y^2 r_z t_x, r_y^2 r_z t_z^{-1} \rangle$	3	20	[[1,1,0],[0,2,0],[0,0,2]]
$H_{346} = \langle m_z, r_x^2 r_z t_z^{-1}, r_y^2 r_z t_x, r_y^2 r_z t_z^{-1} \rangle$	3	20	[[1,1,0],[0,2,0],[0,0,2]]
$H_{347} = \langle i t_x, i t_y, m_z, r_x^2 r_z t_z^{-1}, r_y^2 r_z t_x^{-1} \rangle$	3	20	[[1,1,1],[0,2,1],[0,0,2]]
$H_{348} = \langle i t_x, m_z, m_z t_y^{-1}, m_z t_z^{-1}, r_y^2 t_x^{-1} \rangle$	3	21	[[4,0,0],[0,1,0],[0,0,1]]
$H_{349} = \langle i t_x, i t_x^{-1}, m_z, m_z t_z^{-1}, r_y^2 t_y \rangle$	3	21	[[2,0,0],[0,2,0],[0,0,1]]
$H_{350} = \langle i t_x, i t_x^{-1}, m_z, m_z t_z^{-1}, r_y^2 t_y, r_y^2 t_y^{-1} \rangle$	3	21	[[2,0,0],[0,2,0],[0,0,1]]
$H_{351} = \langle i t_x, i t_x^{-1}, m_z, m_z t_y^{-1}, r_y^2 t_z^{-1} \rangle$	3	21	[[2,0,0],[0,1,0],[0,0,2]]
$H_{352} = \langle i t_x, i t_x^{-1}, m_z, m_z t_y^{-1}, r_x^2 t_z^{-1} \rangle$	3	21	[[2,0,0],[0,1,0],[0,0,2]]
$H_{353} = \langle m_z, m_z t_z^{-1}, r_x^2 t_y, r_x^2 t_z^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	3	21	[[2,0,0],[0,2,0],[0,0,1]]
$H_{354} = \langle i t_z^{-1}, m_z, m_z t_y^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	3	21	[[2,0,0],[0,1,0],[0,0,2]]
$H_{355} = \langle m_z, m_z t_y^{-1}, r_x^2 t_z^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	3	21	[[2,0,0],[0,1,0],[0,0,2]]
$H_{356} = \langle m_z, m_z t_z^{-1}, r_x^2 t_x, r_y^2 t_x^{-1} \rangle$	3	21	[[2,0,0],[0,2,0],[0,0,1]]
$H_{357} = \langle i t_z^{-1}, m_z, m_z t_y^{-1}, r_x^2 t_x \rangle$	3	21	[[2,0,0],[0,1,0],[0,0,2]]
$H_{358} = \langle m_z, m_z t_y^{-1}, r_x^2 t_x, r_y^2 t_z^{-1} \rangle$	3	21	[[2,0,0],[0,1,0],[0,0,2]]
$H_{359} = \langle i t_x, m_z, m_z t_z^{-1}, r_x^2 t_y, r_x^2 t_z^{-1}, r_y^2 t_x^{-1} \rangle$	3	21	[[2,1,0],[0,2,0],[0,0,1]]
$H_{360} = \langle i t_x, m_z, m_z t_y^{-1}, r_x^2 t_z^{-1}, r_y^2 t_x^{-1} \rangle$	3	21	[[2,0,1],[0,1,0],[0,0,2]]
$H_{361} = \langle i t_x, i t_x^{-1}, i t_y, i t_y^{-1}, m_z, r_y^2 t_z^{-1} \rangle$	3	21	[[1,1,0],[0,2,0],[0,0,2]]
$H_{362} = \langle i t_x, i t_x^{-1}, i t_z^{-1}, m_z, r_y^2 t_z^{-1} \rangle$	3	21	[[1,0,1],[0,2,0],[0,0,2]]
$H_{363} = \langle i t_x, i t_x^{-1}, m_z, r_y^2 t_y^{-1}, r_y^2 t_z^{-1} \rangle$	3	21	[[2,0,0],[0,1,1],[0,0,2]]
$H_{364} = \langle i t_x, i t_x^{-1}, i t_z^{-1}, m_z, r_x^2 t_y, r_x^2 t_y^{-1} \rangle$	3	21	[[1,0,1],[0,2,0],[0,0,2]]
$H_{365} = \langle i t_x, i t_x^{-1}, m_z, r_x^2 t_y, r_x^2 t_y^{-1}, r_x^2 t_z^{-1} \rangle$	3	21	[[2,0,0],[0,1,1],[0,0,2]]
$H_{366} = \langle i t_x^{-1}, m_z, r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_z^{-1} \rangle$	3	21	[[1,1,0],[0,2,0],[0,0,2]]
$H_{367} = \langle m_z, r_x^2 t_z^{-1}, r_y^2 t_x, r_y^2 t_z^{-1}, r_y^2 t_z^{-1} \rangle$	3	21	[[1,1,0],[0,2,0],[0,0,2]]
$H_{368} = \langle m_z, r_x^2 t_y, r_x^2 t_z^{-1}, r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_z^{-1} \rangle$	3	21	[[1,0,1],[0,2,0],[0,0,2]]
$H_{369} = \langle m_z, r_x^2 t_x, r_y^2 t_z^{-1}, r_y^2 t_z^{-1} \rangle$	3	21	[[2,0,0],[0,1,1],[0,0,2]]
$H_{370} = \langle i t_x, m_z, r_x^2 t_y, r_x^2 t_z^{-1}, r_y^2 t_x^{-1}, r_y^2 t_x^{-1} \rangle$	3	21	[[2,0,1],[0,1,1],[0,0,2]]
$H_{371} = \langle i t_x, i t_x^{-1}, m_z, r_x^2 t_z^{-1}, r_y^2 t_y \rangle$	3	21	[[1,1,1],[0,2,0],[0,0,2]]
$H_{372} = \langle i t_x, i t_x^{-1}, m_z, r_x^2 t_y, r_x^2 t_z^{-1}, r_y^2 t_z^{-1} \rangle$	3	21	[[1,1,1],[0,2,0],[0,0,2]]
$H_{373} = \langle i t_z^{-1}, m_z, r_x^2 t_y, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}, r_y^2 t_x^{-1} \rangle$	3	21	[[1,1,1],[0,2,0],[0,0,2]]
$H_{374} = \langle i t_z^{-1}, m_z, r_x^2 t_x, r_y^2 t_y \rangle$	3	21	[[1,1,1],[0,2,0],[0,0,2]]
$H_{375} = \langle m_z, m_z r_z^{-1} t_x, m_z r_z^{-1} t_x^{-1}, m_z t_z^{-1} \rangle$	3	22	[[2,0,0],[0,2,0],[0,0,1]]
$H_{376} = \langle i t_z^{-1}, m_z, m_z r_z^{-1} t_x, m_z r_z^{-1} t_x^{-1}, m_z t_z^{-1} \rangle$	3	22	[[1,1,1],[0,2,0],[0,0,2]]
$H_{377} = \langle m_z, m_z r_z^{-1} t_x, m_z t_z^{-1}, r_y^2 t_y, r_y^2 t_x \rangle$	3	29	[[2,2,0],[0,4,0],[0,0,1]]
$H_{378} = \langle m_z, r_x^2 t_y, r_x^2 t_z^{-1}, r_y^2 r_z t_z^{-1}, r_y^2 t_x, r_y^2 t_x^{-1} \rangle$	3	29	[[2,0,0],[0,2,0],[0,0,2]]
$H_{379} = \langle m_z, m_z r_z^{-1} t_x, m_z r_z^{-1} t_x^{-1}, r_y^2 r_z t_z^{-1} \rangle$	3	29	[[2,0,0],[0,2,0],[0,0,2]]
$H_{380} = \langle m_z, m_z r_z^{-1} t_x, m_z r_z^{-1} t_x^{-1}, r_x^2 r_z t_z^{-1} \rangle$	3	29	[[2,0,0],[0,2,0],[0,0,2]]
$H_{381} = \langle m_z, r_x^2 t_x, r_y^2 r_z t_z^{-1}, r_y^2 t_x \rangle$	3	29	[[2,0,0],[0,2,0],[0,0,2]]
$H_{382} = \langle m_z, m_z r_z^{-1} t_x^{-1}, r_y^2 t_z^{-1}, r_y^2 r_z t_z^{-1}, r_y^2 t_x \rangle$	3	29	[[2,0,1],[0,2,1],[0,0,2]]
$H_{383} = \langle r_z^2 r_x, r_z^2 r_x t_x, r_z^2 r_x t_y^{-1} \rangle$	4	4	[[1,0,0],[0,1,0],[0,0,1]]
$H_{384} = \langle m_x t_x, r_z^2 r_x, r_z^2 r_x t_y^{-1} \rangle$	4	11	[[2,0,0],[0,1,0],[0,0,1]]
$H_{385} = \langle m_x t_y^{-1}, r_z^2 r_x, r_z^2 r_x t_x \rangle$	4	11	[[1,0,0],[0,1,1],[0,0,2]]
$H_{386} = \langle m_x t_x, m_x t_y^{-1}, r_z^2 r_x \rangle$	4	11	[[1,0,1],[0,1,1],[0,0,2]]
$H_{387} = \langle i t_x, r_z^2 r_x, r_z^2 r_x t_y^{-1} \rangle$	4	12	[[2,0,0],[0,1,0],[0,0,1]]
$H_{388} = \langle i t_y^{-1}, i t_z^{-1}, r_z^2 r_x, r_z^2 r_x t_x \rangle$	4	12	[[1,0,0],[0,1,1],[0,0,2]]
$H_{389} = \langle i t_x, i t_y^{-1}, i t_z^{-1}, r_z^2 r_x \rangle$	4	12	[[1,0,1],[0,1,1],[0,0,2]]
$H_{390} = \langle r_y^2 r_x t_x, r_y^2 r_x, r_y^2 r_x t_y^{-1} \rangle$	4	13	[[2,0,0],[0,1,0],[0,0,1]]
$H_{391} = \langle r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z^{-1}, r_y^2 r_x, r_y^2 r_x t_x \rangle$	4	13	[[1,0,0],[0,1,1],[0,0,2]]
$H_{392} = \langle r_y^2 r_x t_x, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z^{-1}, r_y^2 r_x \rangle$	4	13	[[1,0,1],[0,1,1],[0,0,2]]

H	$H_{0,0,0}$	$P(H)$	Translation basis of H
$H_{393} = \langle r_x^2 r_y t_y^{-1}, r_y^2 r_z t_x, r_z^2 r_x \rangle$	4	19	$[[1, 0, 2], [0, 1, 2], [0, 0, 3]]$
$H_{394} = \langle it_y^{-1}, r_y^2 r_x t_z^{-1}, r_z^2 r_x, r_z^2 r_x t_x \rangle$	4	20	$[[1, 0, 0], [0, 1, 1], [0, 0, 4]]$
$H_{395} = \langle it_y^{-1}, m_x t_x, r_y^2 r_x t_z^{-1}, r_z^2 r_x \rangle$	4	20	$[[1, 0, 2], [0, 1, 1], [0, 0, 4]]$
$H_{396} = \langle it_x, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z^{-1}, r_z^2 r_x \rangle$	4	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{397} = \langle it_x, m_x t_y^{-1}, r_z^2 r_x \rangle$	4	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{398} = \langle it_y^{-1}, it_z^{-1}, r_y^2 r_x t_x, r_z^2 r_x \rangle$	4	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{399} = \langle m_x t_y^{-1}, r_y^2 r_x t_x, r_z^2 r_x \rangle$	4	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{400} = \langle it_y^{-1}, it_z^{-1}, m_x t_x, r_z^2 r_x \rangle$	4	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{401} = \langle m_x t_x, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z^{-1}, r_z^2 r_x \rangle$	4	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{402} = \langle m_x r_x t_z^{-1}, m_x r_x^{-1} t_y^{-1}, r_z^2 r_x, r_z^2 r_x t_x \rangle$	4	23	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{403} = \langle m_x r_x t_y^{-1}, r_z^2 r_x, r_z^2 r_x t_x \rangle$	4	23	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{404} = \langle m_x r_x t_z^{-1}, m_x r_x^{-1} t_y^{-1}, r_y^2 r_x t_x, r_z^2 r_x \rangle$	4	23	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{405} = \langle m_x r_x t_y^{-1}, r_y^2 r_x t_x, r_z^2 r_x \rangle$	4	23	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{406} = \langle r_z^2 r_x, r_z^2 r_x t_y^{-1}, r_z^2 t_x \rangle$	4	24	$[[4, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{407} = \langle r_y^2 t_z^{-1}, r_z^2 r_x, r_z^2 r_x t_x, r_z^2 t_y^{-1} \rangle$	4	24	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{408} = \langle r_y^2 t_y^{-1}, r_z^2 r_x, r_z^2 r_x t_x \rangle$	4	24	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{409} = \langle r_z^2 r_x t_y^{-1}, r_y^2 r_x t_z^{-1}, r_z^2 r_x, r_z^2 t_x \rangle$	4	24	$[[2, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{410} = \langle r_y^2 r_x t_x, r_z^2 t_z^{-1}, r_z^2 r_x, r_z^2 t_y^{-1} \rangle$	4	24	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{411} = \langle r_y^2 r_x t_x, r_y^2 t_y^{-1}, r_z^2 r_x \rangle$	4	24	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{412} = \langle m_x r_x t_z^{-1}, r_z^2 r_x, r_z^2 r_x t_x, r_z^2 t_y^{-1} \rangle$	4	29	$[[1, 0, 0], [0, 2, 2], [0, 0, 4]]$
$H_{413} = \langle m_x r_x t_z^{-1}, m_x t_x, r_z^2 r_x, r_z^2 t_y^{-1} \rangle$	4	29	$[[1, 0, 2], [0, 2, 2], [0, 0, 4]]$
$H_{414} = \langle it_x, r_y^2 t_z^{-1}, r_z^2 r_x, r_z^2 t_y^{-1} \rangle$	4	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{415} = \langle it_x, m_x r_x t_z^{-1}, m_x r_x^{-1} t_y^{-1}, r_z^2 r_x \rangle$	4	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{416} = \langle it_x, m_x r_x t_y^{-1}, r_z^2 r_x \rangle$	4	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{417} = \langle it_x, r_y^2 t_y^{-1}, r_z^2 r_x \rangle$	4	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{418} = \langle m_x t_x, r_y^2 t_z^{-1}, r_z^2 r_x, r_z^2 t_y^{-1} \rangle$	4	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{419} = \langle m_x r_x t_z^{-1}, m_x r_x^{-1} t_y^{-1}, m_x t_x, r_z^2 r_x \rangle$	4	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{420} = \langle m_x r_x t_y^{-1}, m_x t_x, r_z^2 r_x \rangle$	4	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{421} = \langle m_x t_x, r_y^2 t_y^{-1}, r_z^2 r_x \rangle$	4	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{422} = \langle m_x r_x t_z^{-1}, m_x r_x^{-1} t_y^{-1}, r_z^2 r_x, r_z^2 t_x \rangle$	4	29	$[[2, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{423} = \langle m_x r_x t_y^{-1}, r_z^2 r_x, r_z^2 t_x \rangle$	4	29	$[[2, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{424} = \langle r_z^2, r_z^2 t_x, r_z^2 t_y^{-1}, r_z^2 t_z^{-1} \rangle$	5	5	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{425} = \langle r_z^2 t_z, r_y^2 t_z^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	5	8	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{426} = \langle r_y^2 t_y^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_z^{-1} \rangle$	5	8	$[[1, 0, 0], [0, 2, 0], [0, 0, 1]]$
$H_{427} = \langle r_y^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2, r_z^2 t_x \rangle$	5	8	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{428} = \langle r_z^2 t_x, r_y^2 t_z^{-1}, r_z^2, r_z^2 t_y^{-1} \rangle$	5	8	$[[1, 1, 0], [0, 1, 0], [0, 0, 1]]$
$H_{429} = \langle r_y^2 t_x, r_y^2 t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, r_z^2 \rangle$	5	8	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{430} = \langle it_x, r_z^2, r_z^2 t_y^{-1}, r_z^2 t_z^{-1} \rangle$	5	9	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{431} = \langle it_z, it_z^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	5	9	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{432} = \langle it_x, it_y^{-1}, r_z^2, r_z^2 t_z^{-1} \rangle$	5	9	$[[1, 1, 0], [0, 2, 0], [0, 0, 1]]$
$H_{433} = \langle it_x, it_z, it_z^{-1}, r_z^2, r_z^2 t_y^{-1} \rangle$	5	9	$[[1, 0, 1], [0, 1, 0], [0, 0, 2]]$
$H_{434} = \langle it_x, it_y^{-1}, it_z, it_z^{-1}, r_z^2 \rangle$	5	9	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{435} = \langle m_x r_z t_z^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	5	10	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{436} = \langle m_x r_z t_x, r_z^2, r_z^2 t_z^{-1} \rangle$	5	10	$[[1, 1, 0], [0, 2, 0], [0, 0, 1]]$
$H_{437} = \langle m_x r_z t_x, m_x r_z t_z^{-1}, r_z^2 \rangle$	5	10	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{438} = \langle r_z^2 r_z t_z, r_z^2 r_z t_z^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	5	13	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{439} = \langle r_y^2 r_z t_x, r_z^2, r_z^2 t_z^{-1} \rangle$	5	13	$[[1, 1, 0], [0, 2, 0], [0, 0, 1]]$
$H_{440} = \langle r_y^2 r_z t_x, r_z^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	5	13	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{441} = \langle m_x t_z^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	5	14	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{442} = \langle m_x t_y^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_z^{-1} \rangle$	5	14	$[[1, 0, 0], [0, 2, 0], [0, 0, 1]]$
$H_{443} = \langle m_x t_y^{-1}, m_x t_z^{-1}, r_z^2, r_z^2 t_x \rangle$	5	14	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{444} = \langle m_x t_x, m_x t_y^{-1}, r_z^2, r_z^2 t_z^{-1} \rangle$	5	14	$[[1, 1, 0], [0, 2, 0], [0, 0, 1]]$
$H_{445} = \langle m_x t_x, m_x t_y^{-1}, m_x t_z^{-1}, r_z^2 \rangle$	5	14	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{446} = \langle r_z^{-1} t_z^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	5	15	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{447} = \langle r_z^{-1} t_x, r_z^2, r_z^2 t_z^{-1} \rangle$	5	15	$[[1, 1, 0], [0, 2, 0], [0, 0, 1]]$
$H_{448} = \langle r_z^{-1} t_x, r_z^{-1} t_z, r_z^2 \rangle$	5	15	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{449} = \langle m_z r^{-1} t_z, m_z r^{-1} t_z^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	5	16	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{450} = \langle m_z r_z^{-1} t_x, r_z^2, r_z^2 t_z^{-1} \rangle$	5	16	$[[1, 1, 0], [0, 2, 0], [0, 0, 1]]$
$H_{451} = \langle m_z r_z^{-1} t_x, m_z r_z^{-1} t_z, m_z r_z^{-1} t_z^{-1}, r_z^2 \rangle$	5	16	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{452} = \langle it_z^{-1}, r_y^2 r_z t_z, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	5	20	$[[1, 0, 0], [0, 1, 0], [0, 0, 4]]$
$H_{453} = \langle it_x, it_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	5	20	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{454} = \langle it_x, it_y^{-1}, m_x r_z t_z^{-1}, r_z^2 \rangle$	5	20	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{455} = \langle it_z, it_z^{-1}, r_y^2 r_z t_x, r_z^2 \rangle$	5	20	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{456} = \langle m_x r_z t_z^{-1}, r_y^2 r_z t_x, r_z^2 \rangle$	5	20	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{457} = \langle it_z, it_z^{-1}, m_x r_z t_x, r_z^2 \rangle$	5	20	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{458} = \langle m_x r_z t_x, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	5	20	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{459} = \langle it_z^{-1}, m_x r_z t_x, r_y^2 r_z t_z, r_z^2 \rangle$	5	20	$[[1, 0, 2], [0, 1, 2], [0, 0, 4]]$
$H_{460} = \langle it_z^{-1}, r_y^2 t_z, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	5	21	$[[1, 0, 0], [0, 1, 0], [0, 0, 4]]$

H	$H_{0,0,0}$	$P(H)$	Translation basis of H
$H_{461} = \langle it_z^{-1}, m_x t_z^{-1}, r_z^2 t_z, r_z^2 t_x \rangle$	5	21	[[1,0,0],[0,1,2],[0,0,4]]
$H_{462} = \langle it_x, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2, r_z^2 t_y^{-1} \rangle$	5	21	[[2,0,0],[0,1,0],[0,0,2]]
$H_{463} = \langle it_x, m_x t_z^{-1}, r_z^2, r_z^2 t_z^{-1} \rangle$	5	21	[[2,0,0],[0,1,0],[0,0,2]]
$H_{464} = \langle it_x, r_y^2 t_z^{-1}, r_z^2, r_z^2 t_z^{-1} \rangle$	5	21	[[2,0,0],[0,2,0],[0,0,1]]
$H_{465} = \langle it_x, m_x t_y^{-1}, r_z^2, r_z^2 t_z^{-1} \rangle$	5	21	[[2,0,0],[0,2,0],[0,0,1]]
$H_{466} = \langle it_z, it_z^{-1}, r_y^2 t_z^{-1}, r_z^2, r_z^2 t_x \rangle$	5	21	[[1,0,0],[0,2,0],[0,0,2]]
$H_{467} = \langle m_x t_z^{-1}, r_y^2 t_y^{-1}, r_z^2, r_z^2 t_x \rangle$	5	21	[[1,0,0],[0,2,0],[0,0,2]]
$H_{468} = \langle it_z, it_z^{-1}, m_x t_y^{-1}, r_z^2, r_z^2 t_x \rangle$	5	21	[[1,0,0],[0,2,0],[0,0,2]]
$H_{469} = \langle m_x t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, r_z^2, r_z^2 t_x \rangle$	5	21	[[1,0,0],[0,2,0],[0,0,2]]
$H_{470} = \langle m_x t_y^{-1}, r_y^2 t_x, r_z^2, r_z^2 t_z^{-1} \rangle$	5	21	[[2,0,0],[0,2,0],[0,0,1]]
$H_{471} = \langle it_x, it_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2 \rangle$	5	21	[[1,1,0],[0,2,0],[0,0,2]]
$H_{472} = \langle it_x, it_y^{-1}, m_x t_z^{-1}, r_z^2 \rangle$	5	21	[[1,1,0],[0,2,0],[0,0,2]]
$H_{473} = \langle it_x, it_z, it_z^{-1}, r_y^2 t_y^{-1}, r_z^2 \rangle$	5	21	[[1,0,1],[0,2,0],[0,0,2]]
$H_{474} = \langle it_x, r_y^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2 \rangle$	5	21	[[2,0,0],[0,1,1],[0,0,2]]
$H_{475} = \langle it_x, it_z, it_z^{-1}, m_x t_y^{-1}, r_z^2 \rangle$	5	21	[[1,0,1],[0,2,0],[0,0,2]]
$H_{476} = \langle it_x, m_x t_y^{-1}, m_x t_z^{-1}, r_z^2 \rangle$	5	21	[[2,0,0],[0,1,1],[0,0,2]]
$H_{477} = \langle it_z, it_z^{-1}, r_y^2 t_x, r_y^2 t_y^{-1}, r_z^2 \rangle$	5	21	[[1,1,0],[0,2,0],[0,0,2]]
$H_{478} = \langle m_x t_z^{-1}, r_z^2 t_x, r_z^2 t_z^{-1}, r_z^2 \rangle$	5	21	[[1,1,0],[0,2,0],[0,0,2]]
$H_{479} = \langle m_x t_y^{-1}, r_y^2 t_x, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2 \rangle$	5	21	[[1,0,1],[0,2,0],[0,0,2]]
$H_{480} = \langle m_x t_y^{-1}, m_x t_z^{-1}, r_z^2 t_x, r_z^2 \rangle$	5	21	[[2,0,0],[0,1,1],[0,0,2]]
$H_{481} = \langle it_z, it_z^{-1}, m_x t_x, m_x t_y^{-1}, r_z^2 \rangle$	5	21	[[1,1,0],[0,2,0],[0,0,2]]
$H_{482} = \langle m_x t_x, m_x t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2 \rangle$	5	21	[[1,1,0],[0,2,0],[0,0,2]]
$H_{483} = \langle it_z^{-1}, m_x t_x, m_x t_y^{-1}, r_y^2 t_z, r_z^2 \rangle$	5	21	[[1,0,2],[0,1,2],[0,0,4]]
$H_{484} = \langle it_x, m_x t_z^{-1}, r_y^2 t_y^{-1}, r_z^2 \rangle$	5	21	[[1,1,1],[0,2,0],[0,0,2]]
$H_{485} = \langle it_x, m_x t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2 \rangle$	5	21	[[1,1,1],[0,2,0],[0,0,2]]
$H_{486} = \langle it_z, it_z^{-1}, m_x t_y^{-1}, r_y^2 t_x, r_z^2 \rangle$	5	21	[[1,1,1],[0,2,0],[0,0,2]]
$H_{487} = \langle it_z^{-1}, m_z r_z^{-1} t_z, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	5	22	[[1,0,0],[0,1,0],[0,0,4]]
$H_{488} = \langle it_x, it_y^{-1}, m_z r_z^{-1} t_z, m_z r_z^{-1} t_z^{-1}, r_z^2 \rangle$	5	22	[[1,1,0],[0,2,0],[0,0,2]]
$H_{489} = \langle it_x, it_y^{-1}, r_z^{-1} t_z^{-1}, r_z^2 \rangle$	5	22	[[1,1,0],[0,2,0],[0,0,2]]
$H_{490} = \langle it_z, it_z^{-1}, m_z r_z^{-1} t_x, r_z^2 \rangle$	5	22	[[1,1,0],[0,2,0],[0,0,2]]
$H_{491} = \langle m_z r_z^{-1} t_x, r_z^{-1} t_z^{-1}, r_z^2 \rangle$	5	22	[[1,1,0],[0,2,0],[0,0,2]]
$H_{492} = \langle it_z, it_z^{-1}, r_z^{-1} t_x, r_z^2 \rangle$	5	22	[[1,1,0],[0,2,0],[0,0,2]]
$H_{493} = \langle m_z r_z^{-1} t_z, m_z r_z^{-1} t_z^{-1}, r_z^{-1} t_x, r_z^2 \rangle$	5	22	[[1,1,0],[0,2,0],[0,0,2]]
$H_{494} = \langle it_z^{-1}, m_z r_z^{-1} t_z, r_z^{-1} t_x, r_z^2 \rangle$	5	22	[[1,0,2],[0,1,2],[0,0,4]]
$H_{495} = \langle m_z r_z^{-1} t_z, r_y^2 t_z^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	5	23	[[1,0,0],[0,1,0],[0,0,4]]
$H_{496} = \langle m_x t_x, m_x t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	5	23	[[1,1,0],[0,2,0],[0,0,2]]
$H_{497} = \langle m_x t_x, m_x t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z^{-1} t_z^{-1}, r_z^2 \rangle$	5	23	[[1,1,0],[0,2,0],[0,0,2]]
$H_{498} = \langle m_x t_z^{-1}, r_y^2 r_z t_x, r_z^2 \rangle$	5	23	[[1,1,0],[0,2,0],[0,0,2]]
$H_{499} = \langle m_z r_z^{-1} t_z, m_z r_z^{-1} t_z^{-1}, r_y^2 r_z t_x, r_z^2 \rangle$	5	23	[[1,1,0],[0,2,0],[0,0,2]]
$H_{500} = \langle m_x t_z^{-1}, m_z r_z^{-1} t_x, r_z^2 \rangle$	5	23	[[1,1,0],[0,2,0],[0,0,2]]
$H_{501} = \langle m_z r_z^{-1} t_x, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	5	23	[[1,1,0],[0,2,0],[0,0,2]]
$H_{502} = \langle m_x t_x, m_x t_y^{-1}, m_z r_z^{-1} t_z, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	5	23	[[1,0,2],[0,1,2],[0,0,4]]
$H_{503} = \langle r_y^2 r_z t_z, r_y^2 t_z^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	5	24	[[1,0,0],[0,1,0],[0,0,4]]
$H_{504} = \langle r_y^2 r_y t_y^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_z^{-1} \rangle$	5	24	[[1,0,0],[0,4,0],[0,0,1]]
$H_{505} = \langle r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_y^2 t_x, r_y^2 t_y^{-1}, r_z^2 \rangle$	5	24	[[1,1,0],[0,2,0],[0,0,2]]
$H_{506} = \langle r_y^2 t_x, r_y^2 t_y^{-1}, r_z^{-1} t_z^{-1}, r_z^2 \rangle$	5	24	[[1,1,0],[0,2,0],[0,0,2]]
$H_{507} = \langle r_y^2 r_z t_x, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2 \rangle$	5	24	[[1,1,0],[0,2,0],[0,0,2]]
$H_{508} = \langle r_y^2 r_z t_x, r_z^{-1} t_z^{-1}, r_z^2 \rangle$	5	24	[[1,1,0],[0,2,0],[0,0,2]]
$H_{509} = \langle r_y^2 t_z, r_y^2 t_z^{-1}, r_z^{-1} t_x, r_z^2 \rangle$	5	24	[[1,1,0],[0,2,0],[0,0,2]]
$H_{510} = \langle r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_z^{-1} t_x, r_z^2 \rangle$	5	24	[[1,1,0],[0,2,0],[0,0,2]]
$H_{511} = \langle r_y^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2, r_z^2 t_x t_x \rangle$	5	24	[[2,0,1],[0,1,1],[0,0,2]]
$H_{512} = \langle r_y^2 r_z t_z, r_y^2 t_z^{-1}, r_z^{-1} t_x, r_z^2 \rangle$	5	24	[[1,0,2],[0,1,2],[0,0,4]]
$H_{513} = \langle m_x r_z t_z^{-1}, m_x t_x, m_x t_y^{-1}, r_z^2 \rangle$	5	25	[[1,1,0],[0,2,0],[0,0,2]]
$H_{514} = \langle m_x t_x, m_x t_y^{-1}, r_z^{-1} t_z^{-1}, r_z^2 \rangle$	5	25	[[1,1,0],[0,2,0],[0,0,2]]
$H_{515} = \langle m_x r_z t_x, m_x t_z^{-1}, r_z^2 \rangle$	5	25	[[1,1,0],[0,2,0],[0,0,2]]
$H_{516} = \langle m_x r_z t_x, r_z^{-1} t_z^{-1}, r_z^2 \rangle$	5	25	[[1,1,0],[0,2,0],[0,0,2]]
$H_{517} = \langle m_x t_z^{-1}, r_z^{-1} t_x, r_z^2 \rangle$	5	25	[[1,1,0],[0,2,0],[0,0,2]]
$H_{518} = \langle m_x r_z t_z^{-1}, r_z^{-1} t_x, r_z^2 \rangle$	5	25	[[1,1,0],[0,2,0],[0,0,2]]
$H_{519} = \langle m_z r_z^{-1} t_z, r_z^2 t_z^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	5	26	[[1,0,0],[0,1,0],[0,0,4]]
$H_{520} = \langle m_x r_z t_z^{-1}, r_y^2 t_x, r_y^2 t_z^{-1}, r_z^2 \rangle$	5	26	[[1,1,0],[0,2,0],[0,0,2]]
$H_{521} = \langle m_z r_z^{-1} t_z, m_z r_z^{-1} t_z^{-1}, r_y^2 t_z, r_y^2 t_y^{-1}, r_z^2 \rangle$	5	26	[[1,1,0],[0,2,0],[0,0,2]]
$H_{522} = \langle m_x r_z t_x, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2 \rangle$	5	26	[[1,1,0],[0,2,0],[0,0,2]]
$H_{523} = \langle m_x r_z t_x, m_z r_z^{-1} t_z, m_z r_z^{-1} t_z^{-1}, r_z^2 \rangle$	5	26	[[1,1,0],[0,2,0],[0,0,2]]
$H_{524} = \langle m_z r_z^{-1} t_x, r_y^2 t_z, r_y^2 t_z^{-1}, r_z^2 \rangle$	5	26	[[1,1,0],[0,2,0],[0,0,2]]
$H_{525} = \langle m_x r_z t_z^{-1}, m_z r_z^{-1} t_x, r_z^2 \rangle$	5	26	[[1,1,0],[0,2,0],[0,0,2]]
$H_{526} = \langle m_x r_z t_x, m_z r_z^{-1} t_z, r_y^2 t_z^{-1}, r_z^2 \rangle$	5	26	[[1,0,2],[0,1,2],[0,0,4]]
$H_{527} = \langle it_z^{-1}, m_x t_x, m_x t_y^{-1}, r_y^2 r_z t_z, r_z^2 \rangle$	5	29	[[1,1,0],[0,2,0],[0,0,4]]
$H_{528} = \langle it_z^{-1}, m_x t_x, m_x t_y^{-1}, m_z r_z^{-1} t_z, r_z^2 \rangle$	5	29	[[1,1,0],[0,2,0],[0,0,4]]

H	$H_{0,0,0}$	$P(H)$	Translation basis of H
$H_{529} = \langle m_x t x, m_x t_y^{-1}, r_y^2 r_z t_z, r_z^2 t_x^{-1}, r_z^2 \rangle$	5	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 4]]$
$H_{530} = \langle m_x t x, m_x t_y^{-1}, m_z r_z^{-1} t_z, r_y^2 t_z^{-1}, r_z^2 \rangle$	5	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 4]]$
$H_{531} = \langle i t_z^{-1}, m_x r_z t_x, r_y^2 t_z, r_z^2 \rangle$	5	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 4]]$
$H_{532} = \langle i t_z^{-1}, m_x r_z t_x, m_z r_z^{-1} t_z, r_z^2 \rangle$	5	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 4]]$
$H_{533} = \langle m_x r_z t_x, r_y^2 r_z t_z, r_z^2 t_x^{-1}, r_z^2 \rangle$	5	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 4]]$
$H_{534} = \langle m_x r_z t_x, m_z r_z^{-1} t_z, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	5	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 4]]$
$H_{535} = \langle i t_z^{-1}, r_z^2 t_z, r_z^{-1} t_x, r_z^2 \rangle$	5	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 4]]$
$H_{536} = \langle i t_z^{-1}, r_y^2 r_z t_z, r_z^{-1} t_x, r_z^2 \rangle$	5	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 4]]$
$H_{537} = \langle m_z r_z^{-1} t_z, r_z^2 t_x^{-1}, r_z^{-1} t_x, r_z^2 \rangle$	5	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 4]]$
$H_{538} = \langle m_z r_z^{-1} t_z, r_y^2 r_z t_z^{-1}, r_z^{-1} t_x, r_z^2 \rangle$	5	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 4]]$
$H_{539} = \langle i t_x, m_z r_z^{-1} t_z, r_y^2 r_z t_z^{-1}, r_y^2 t_y^{-1}, r_z^2 \rangle$	5	29	$[[1, 1, 2], [0, 2, 0], [0, 0, 4]]$
$H_{540} = \langle i t_x, m_x t_x^{-1}, r_z^2 r_y t_y^{-1}, r_z^2 \rangle$	5	29	$[[1, 2, 1], [0, 4, 0], [0, 0, 2]]$
$H_{541} = \langle i t_z, i t_z^{-1}, m_x t_y^{-1}, r_z^2, r_z^2 r_x t_x \rangle$	5	29	$[[2, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{542} = \langle m_z r_x, m_z r_x t_x, m_z r_x t_y^{-1} \rangle$	6	6	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{543} = \langle m_z r_x, m_z r_x t_y^{-1}, r_x^2 t_x \rangle$	6	10	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{544} = \langle m_z r_x, m_z r_x t_x, r_x^2 t_y^{-1}, r_x^2 t_z \rangle$	6	10	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{545} = \langle m_z r_x, r_x^2 t_x, r_x^2 t_y^{-1}, r_x^2 t_z \rangle$	6	10	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{546} = \langle m_z r_x, m_z r_x t_y^{-1}, r_y^2 r_x t_x, r_y^2 r_x t_x^{-1} \rangle$	6	11	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{547} = \langle m_z r_x, m_z r_x t_x, r_y^2 r_x t_y^{-1} \rangle$	6	11	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{548} = \langle m_z r_x, r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_y^2 r_x t_y^{-1} \rangle$	6	11	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{549} = \langle i t_x, i t_x^{-1}, m_z r_x, m_z r_x t_y^{-1} \rangle$	6	12	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{550} = \langle i t_y^{-1}, i t_z, m_z r_x, m_z r_x t_x \rangle$	6	12	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{551} = \langle i t_x, i t_x^{-1}, i t_z, m_z r_x \rangle$	6	12	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{552} = \langle i t_x, m_z r_x, m_z r_x t_y^{-1}, r_y^2 r_x t_x^{-1} \rangle$	6	20	$[[4, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{553} = \langle i t_y^{-1}, m_z r_x, m_z r_x t_x, r_x^2 t_z \rangle$	6	20	$[[1, 0, 0], [0, 1, 3], [0, 0, 4]]$
$H_{554} = \langle i t_x, i t_x^{-1}, m_z r_x, r_x^2 r_x t_y^{-1} \rangle$	6	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{555} = \langle i t_x, i t_x^{-1}, m_z r_x, r_x^2 t_y^{-1}, r_x^2 t_z \rangle$	6	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{556} = \langle i t_y^{-1}, i t_z, m_z r_x, r_y^2 r_x t_x, r_y^2 r_x t_x^{-1} \rangle$	6	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{557} = \langle m_z r_x, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 r_x t_x, r_y^2 r_x t_x^{-1} \rangle$	6	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{558} = \langle i t_y^{-1}, i t_z, m_z r_x, r_x^2 t_x \rangle$	6	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{559} = \langle m_z r_x, r_x^2 t_x, r_y^2 r_x t_y^{-1} \rangle$	6	20	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{560} = \langle i t_x, m_z r_x, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 r_x t_x^{-1} \rangle$	6	20	$[[2, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{561} = \langle i t_y^{-1}, m_z r_x, r_x^2 t_z, r_y^2 r_x t_x, r_y^2 r_x t_x^{-1} \rangle$	6	20	$[[1, 0, 2], [0, 1, 3], [0, 0, 4]]$
$H_{562} = \langle m_y t_y^{-1}, m_z r_x, m_z r_x t_x, r_x^{-1} t_z \rangle$	6	25	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{563} = \langle m_z r_x, m_z r_x t_x, r_x^{-1} t_y^{-1} \rangle$	6	25	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{564} = \langle m_y t_y^{-1}, m_z r_x, r_x^{-1} t_z, r_x^2 t_x \rangle$	6	25	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{565} = \langle m_z r_x, r_x^{-1} t_y^{-1}, r_x^2 t_x \rangle$	6	25	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{566} = \langle m_x r_x^{-1} t_z, m_z r_x, m_z r_x t_x, r_z^2 t_y^{-1} \rangle$	6	26	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{567} = \langle m_x r_x^{-1} t_y^{-1}, m_z r_x, m_z r_x t_x \rangle$	6	26	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{568} = \langle m_x r_x^{-1} t_z, m_z r_x, r_x^2 t_x, r_z^2 t_y^{-1} \rangle$	6	26	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{569} = \langle m_x r_x^{-1} t_y^{-1}, m_z r_x, r_x^2 t_x \rangle$	6	26	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{570} = \langle m_z r_x, m_z r_x t_x, r_x^{-1} t_z, r_z^2 t_y^{-1} \rangle$	6	29	$[[1, 0, 0], [0, 2, 2], [0, 0, 4]]$
$H_{571} = \langle m_z r_x, r_x^{-1} t_z, r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 t_y^{-1} \rangle$	6	29	$[[1, 0, 2], [0, 2, 2], [0, 0, 4]]$
$H_{572} = \langle i t_x, i t_x^{-1}, m_x r_x^{-1} t_z, m_z r_x, r_z^2 t_y^{-1} \rangle$	6	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{573} = \langle i t_x, i t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_z r_x \rangle$	6	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{574} = \langle i t_x, i t_x^{-1}, m_y t_y^{-1}, m_z r_x, r_x^{-1} t_z \rangle$	6	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{575} = \langle i t_x, i t_x^{-1}, m_z r_x, r_x^{-1} t_y^{-1} \rangle$	6	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{576} = \langle m_x r_x^{-1} t_z, m_z r_x, r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 t_y^{-1} \rangle$	6	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{577} = \langle m_x r_x^{-1} t_y^{-1}, m_z r_x, r_y^2 r_x t_x, r_y^2 r_x t_x^{-1} \rangle$	6	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{578} = \langle m_y t_y^{-1}, m_z r_x, r_x^{-1} t_z, r_y^2 r_x t_x, r_y^2 r_x t_x^{-1} \rangle$	6	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{579} = \langle m_z r_x, r_x^{-1} t_y^{-1}, r_y^2 r_x t_x, r_y^2 r_x t_x^{-1} \rangle$	6	29	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{580} = \langle i t_x, m_y t_y^{-1}, m_z r_x, r_x^{-1} t_z, r_y^2 r_x t_x^{-1} \rangle$	6	29	$[[2, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{581} = \langle i t_x, m_z r_x, r_x^{-1} t_y^{-1}, r_y^2 r_x t_x^{-1} \rangle$	6	29	$[[2, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{582} = \langle r_y r_x, r_y^{-1} r_z^{-1} t_x \rangle$	7	7	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{583} = \langle i t_x, i t_x^{-1}, r_y r_x \rangle$	7	17	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{584} = \langle m_x r_y t_x, r_y r_x \rangle$	7	18	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{585} = \langle r_y r_x, r_z^2 r_x t_x, r_z^2 r_x t_x^{-1} \rangle$	7	19	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{586} = \langle r_y r_x, r_z^2 t_x, r_z^2 t_x^{-1} \rangle$	7	27	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{587} = \langle r_y r_x, r_y r_x^{-1} t_x \rangle$	7	27	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{588} = \langle i t_x, r_y r_x, r_z^2 r_x t_x^{-1} \rangle$	7	28	$[[1, 0, 3], [0, 1, 3], [0, 0, 4]]$
$H_{589} = \langle m_x t_x, m_x t_x^{-1}, r_y r_x \rangle$	7	30	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{590} = \langle m_x r_y r_x t_x, r_y r_x \rangle$	7	30	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{591} = \langle m_z r_z^{-1} t_x, r_y r_x \rangle$	7	31	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{592} = \langle r_y r_x, r_y^2 r_x t_x, r_y^2 r_x t_x^{-1} \rangle$	7	32	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{593} = \langle m_x t_x^{-1}, r_y r_x, r_y^2 r_x t_x \rangle$	7	33	$[[2, 0, 2], [0, 2, 2], [0, 0, 4]]$
$H_{594} = \langle r_z^2, r_z^2 r_z t_x, r_z^2 t_x^{-1}, r_z^2 t_x^{-1} \rangle$	8	8	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{595} = \langle i t_x, r_x^2, r_z^2, r_z^2 t_y^{-1}, r_z^2 t_z^{-1} \rangle$	8	21	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{596} = \langle i t_x, i t_y^{-1}, r_x^2, r_z^2, r_z^2 t_z^{-1} \rangle$	8	21	$[[1, 1, 0], [0, 2, 0], [0, 0, 1]]$

H	$H_{0,0,0}$	$P(H)$	Translation basis of H
$H_{597} = \langle itx, ity^{-1}, itz^{-1}, r_x^2, r_z^2 \rangle$	8	21	[[1, 0, 1], [0, 1, 1], [0, 0, 2]]
$H_{598} = \langle r_x^2, r_y^2, r_z^2 t_z^{-1}, r_x^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	8	24	[[1, 0, 0], [0, 1, 0], [0, 0, 2]]
$H_{599} = \langle r_x^2, r_z^2, r_z^2 r_x t_y^{-1}, r_z^2 t_x \rangle$	8	24	[[1, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{600} = \langle r_x^2, r_z^2, r_z^2 r_x t_x, r_z^2 r_x t_y^{-1} \rangle$	8	24	[[1, 0, 1], [0, 1, 1], [0, 0, 2]]
$H_{601} = \langle m_x r_z t_z^{-1}, r_x^2, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	8	26	[[1, 0, 0], [0, 1, 0], [0, 0, 2]]
$H_{602} = \langle m_x r_x^{-1} t_y^{-1}, r_x^2, r_z^2, r_z^2 t_x \rangle$	8	26	[[1, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{603} = \langle m_x r_x^{-1} t_x, m_x r_x^{-1} t_y^{-1}, r_x^2, r_z^2 \rangle$	8	26	[[1, 0, 1], [0, 1, 1], [0, 0, 2]]
$H_{604} = \langle itx, ity^{-1}, r_x^2, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	8	29	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H_{605} = \langle itx, ity^{-1}, m_x r_z t_z^{-1}, r_x^2, r_z^2 \rangle$	8	29	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H_{606} = \langle itx, r_x^2, r_z^2, r_z^2 r_x t_y^{-1} \rangle$	8	29	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{607} = \langle itx, m_x r_x^{-1} t_y^{-1}, r_x^2, r_z^2 \rangle$	8	29	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{608} = \langle m_x r_x^{-1} t_y^{-1}, r_x^2, r_z^2, r_z^2 r_x t_x \rangle$	8	29	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{609} = \langle m_x r_x^{-1} t_x, r_x^2, r_z^2, r_z^2 r_x t_y^{-1} \rangle$	8	29	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{610} = \langle i, itx, ity^{-1}, itz^{-1}, r_z^2 \rangle$	9	9	[[1, 0, 0], [0, 1, 0], [0, 0, 1]]
$H_{611} = \langle i, itx, ity^{-1}, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	9	20	[[1, 0, 0], [0, 1, 0], [0, 0, 2]]
$H_{612} = \langle i, itz^{-1}, r_y^2 r_z t_x, r_z^2 \rangle$	9	20	[[1, 1, 0], [0, 2, 0], [0, 0, 1]]
$H_{613} = \langle i, r_y^2 r_z t_x, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	9	20	[[1, 0, 1], [0, 1, 1], [0, 0, 2]]
$H_{614} = \langle i, itx, ity^{-1}, r_y^2 t_z^{-1}, r_z^2 \rangle$	9	21	[[1, 0, 0], [0, 1, 0], [0, 0, 2]]
$H_{615} = \langle i, itx, itz^{-1}, r_y^2 t_y^{-1}, r_z^2 \rangle$	9	21	[[1, 0, 0], [0, 2, 0], [0, 0, 1]]
$H_{616} = \langle i, itx, r_y^2 t_z^{-1}, r_y^2 t_y^{-1}, r_z^2 \rangle$	9	21	[[1, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{617} = \langle i, itz^{-1}, r_y^2 t_x, r_y^2 t_y^{-1}, r_z^2 \rangle$	9	21	[[1, 1, 0], [0, 2, 0], [0, 0, 1]]
$H_{618} = \langle i, r_y^2 t_x, r_y^2 t_y^{-1}, r_y^2 t_z^{-1}, r_z^2 \rangle$	9	21	[[1, 0, 1], [0, 1, 1], [0, 0, 2]]
$H_{619} = \langle i, itx, ity^{-1}, m_z r_z^{-1} t_z^{-1}, r_z^2 \rangle$	9	22	[[1, 0, 0], [0, 1, 0], [0, 0, 2]]
$H_{620} = \langle i, itz^{-1}, m_z r_z^{-1} t_x, r_z^2 \rangle$	9	22	[[1, 1, 0], [0, 2, 0], [0, 0, 1]]
$H_{621} = \langle i, m_z r_z^{-1} t_x, m_z r_z^{-1} t_z^{-1}, r_z^2 \rangle$	9	22	[[1, 0, 1], [0, 1, 1], [0, 0, 2]]
$H_{622} = \langle i, r_y^2 r_z t_z^{-1}, r_y^2 t_x, r_y^2 t_y^{-1}, r_z^2 \rangle$	9	29	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H_{623} = \langle i, m_z r_z^{-1} t_z^{-1}, r_y^2 t_x, r_y^2 t_y^{-1}, r_z^2 \rangle$	9	29	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H_{624} = \langle i, r_y^2 r_z t_x, r_y^2 t_z^{-1}, r_z^2 \rangle$	9	29	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H_{625} = \langle i, m_z r_z^{-1} t_z^{-1}, r_y^2 r_z t_x, r_z^2 \rangle$	9	29	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H_{626} = \langle i, m_z r_z^{-1} t_x, r_y^2 r_z^{-1}, r_z^2 \rangle$	9	29	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H_{627} = \langle i, m_z r_z^{-1} t_x, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	9	29	[[1, 1, 0], [0, 2, 0], [0, 0, 2]]
$H_{628} = \langle m_z r_x, r_x^2, r_x^2 t_x, r_x^2 t_y^{-1} \rangle$	10	10	[[1, 0, 0], [0, 1, 0], [0, 0, 1]]
$H_{629} = \langle itx, itx^{-1}, m_z r_x, r_x^2, r_x^2 t_y^{-1} \rangle$	10	20	[[2, 0, 0], [0, 1, 0], [0, 0, 1]]
$H_{630} = \langle ity^{-1}, m_z r_x, r_x^2, r_x^2 t_x \rangle$	10	20	[[1, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{631} = \langle itx, itx^{-1}, ity^{-1}, m_z r_x, r_x^2 \rangle$	10	20	[[1, 0, 1], [0, 1, 1], [0, 0, 2]]
$H_{632} = \langle m_y t_x, m_z r_x, r_x^2, r_x^2 t_y^{-1} \rangle$	10	25	[[2, 0, 0], [0, 1, 0], [0, 0, 1]]
$H_{633} = \langle m_y t_y^{-1}, m_z r_x, r_x^2, r_x^2 t_x \rangle$	10	25	[[1, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{634} = \langle m_y t_x, m_y t_y^{-1}, m_z r_x, r_x^2 \rangle$	10	25	[[1, 0, 1], [0, 1, 1], [0, 0, 2]]
$H_{635} = \langle m_z r_x, r_x^2, r_x^2 t_z^{-1}, r_x^2 t_x, r_x^2 t_y^{-1} \rangle$	10	26	[[2, 0, 0], [0, 1, 0], [0, 0, 1]]
$H_{636} = \langle m_z r_x, r_x^2, r_x^2 t_x, r_x^2 t_y^{-1} \rangle$	10	26	[[1, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{637} = \langle m_z r_x, r_x^2, r_x^2 t_x, r_x^2 t_y^{-1}, r_x^2 t_z^{-1} \rangle$	10	26	[[1, 0, 1], [0, 1, 1], [0, 0, 2]]
$H_{638} = \langle itx, m_z r_x, r_x^2, r_x^2 t_z^{-1}, r_x^2 t_y^{-1} \rangle$	10	29	[[4, 0, 0], [0, 1, 0], [0, 0, 1]]
$H_{639} = \langle itx, itx^{-1}, m_z r_x, r_x^2, r_x^2 t_y^{-1} \rangle$	10	29	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{640} = \langle itx, itx^{-1}, m_y t_y^{-1}, m_z r_x, r_x^2 \rangle$	10	29	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{641} = \langle ity^{-1}, m_z r_x, r_x^2, r_x^2 t_x, r_x^2 t_y^{-1} \rangle$	10	29	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{642} = \langle m_y t_y^{-1}, m_z r_x, r_x^2, r_x^2 t_x, r_x^2 t_y^{-1} \rangle$	10	29	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{643} = \langle ity^{-1}, m_y t_x, m_z r_x, r_x^2 \rangle$	10	29	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{644} = \langle m_y t_x, m_z r_x, r_x^2, r_x^2 t_z^{-1} \rangle$	10	29	[[2, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{645} = \langle itx, m_y t_y^{-1}, m_z r_x, r_x^2, r_x^2 t_z^{-1} \rangle$	10	29	[[2, 0, 1], [0, 1, 1], [0, 0, 2]]
$H_{646} = \langle m_x, m_z r_x, r_y^2 r_x t_x, r_y^2 r_x t_y^{-1} \rangle$	11	11	[[1, 0, 0], [0, 1, 0], [0, 0, 1]]
$H_{647} = \langle itx, m_x, m_z r_x, r_y^2 r_x t_y^{-1} \rangle$	11	20	[[2, 0, 0], [0, 1, 0], [0, 0, 1]]
$H_{648} = \langle ity^{-1}, itz, m_x, m_z r_x, r_y^2 r_x t_x \rangle$	11	20	[[1, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{649} = \langle itx, ity^{-1}, itz, m_x, m_z r_x \rangle$	11	20	[[1, 0, 1], [0, 1, 1], [0, 0, 2]]
$H_{650} = \langle m_x, m_x r_x^{-1} t_z, m_z r_x, r_y^2 r_x t_x, r_z^2 t_y^{-1} \rangle$	11	29	[[1, 0, 0], [0, 2, 0], [0, 0, 2]]
$H_{651} = \langle m_x, m_x r_x^{-1} t_y^{-1}, m_z r_x, r_y^2 r_x t_x \rangle$	11	29	[[1, 0, 0], [0, 2, 0], [0, 0, 2]]
$H_{652} = \langle itx, m_x, m_x r_x^{-1} t_z, m_z r_x, r_z^2 t_y^{-1} \rangle$	11	29	[[1, 1, 1], [0, 2, 0], [0, 0, 2]]
$H_{653} = \langle itx, m_x, m_x r_x^{-1} t_y^{-1}, m_z r_x \rangle$	11	29	[[1, 1, 1], [0, 2, 0], [0, 0, 2]]
$H_{654} = \langle i, itx, ity^{-1}, m_z r_x \rangle$	12	12	[[1, 0, 0], [0, 1, 0], [0, 0, 1]]
$H_{655} = \langle i, ity^{-1}, m_z r_x, r_y^2 r_x t_x \rangle$	12	20	[[2, 0, 0], [0, 1, 0], [0, 0, 1]]
$H_{656} = \langle i, itx, m_z r_x, r_y^2 r_x t_y^{-1} \rangle$	12	20	[[1, 0, 0], [0, 1, 1], [0, 0, 2]]
$H_{657} = \langle i, m_z r_x, r_y^2 r_x t_x, r_y^2 r_x t_y^{-1} \rangle$	12	20	[[1, 0, 1], [0, 1, 1], [0, 0, 2]]
$H_{658} = \langle i, itx, m_z r_x, r_x^2 t_y^{-1} \rangle$	12	29	[[1, 0, 0], [0, 2, 0], [0, 0, 2]]
$H_{659} = \langle i, itx, m_x r_x^{-1} t_y^{-1}, m_z r_x \rangle$	12	29	[[1, 0, 0], [0, 2, 0], [0, 0, 2]]
$H_{660} = \langle i, m_z r_x, r_y^2 r_x t_x, r_z^2 t_y^{-1} \rangle$	12	29	[[1, 1, 1], [0, 2, 0], [0, 0, 2]]
$H_{661} = \langle i, m_z r_x^{-1} t_y^{-1}, m_z r_x, r_y^2 r_x t_x \rangle$	12	29	[[1, 1, 1], [0, 2, 0], [0, 0, 2]]
$H_{662} = \langle r_x^2, r_z^2 r_x, r_z^2 r_x t_x, r_z^2 r_x t_y^{-1} \rangle$	13	13	[[1, 0, 0], [0, 1, 0], [0, 0, 1]]
$H_{663} = \langle itx, r_x^2, r_z^2 r_x, r_z^2 r_x t_y^{-1} \rangle$	13	20	[[2, 0, 0], [0, 1, 0], [0, 0, 1]]

H	$H_{0,0,0}$	$P(H)$	Translation basis of H
$H_{664} = \langle it_y^{-1}, r_x^2, r_z^2 r_x, r_z^2 r_x t_x \rangle$	13	20	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{665} = \langle it_x, it_y^{-1}, r_x^2, r_z^2 r_x \rangle$	13	20	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{666} = \langle m_x r_x^{-1} t_x, r_x^2, r_z^2 r_x, r_z^2 r_x t_y^{-1} \rangle$	13	23	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{667} = \langle m_x r_x^{-1} t_y^{-1}, r_x^2, r_z^2 r_x, r_z^2 r_x t_x \rangle$	13	23	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{668} = \langle m_x r_x^{-1} t_x, m_x r_x^{-1} t_y^{-1}, r_x^2, r_z^2 r_x \rangle$	13	23	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{669} = \langle r_x^2, r_z^2 r_x, r_z^2 r_x t_y^{-1}, r_z^2 t_x \rangle$	13	24	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{670} = \langle r_x^2, r_z^2 r_x, r_z^2 r_x t_x, r_z^2 t_y^{-1} \rangle$	13	24	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{671} = \langle r_x^2, r_z^2 r_x, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	13	24	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{672} = \langle it_x, r_x^2, r_z^2 r_x, r_z^2 t_y^{-1} \rangle$	13	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{673} = \langle it_x, m_x r_x^{-1} t_y^{-1}, r_x^2, r_z^2 r_x \rangle$	13	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{674} = \langle it_y^{-1}, r_x^2, r_z^2 r_x, r_z^2 t_x \rangle$	13	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{675} = \langle m_x r_x^{-1} t_y^{-1}, r_x^2, r_z^2 r_x, r_z^2 t_x \rangle$	13	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{676} = \langle it_y^{-1}, m_x r_x^{-1} t_x, r_x^2, r_z^2 r_x \rangle$	13	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{677} = \langle m_x r_x^{-1} t_x, r_x^2, r_z^2 r_x, r_z^2 t_y^{-1} \rangle$	13	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{678} = \langle m_x, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1}, r_z^2 t_z^{-1} \rangle$	14	14	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{679} = \langle it_x, m_x, r_z^2, r_z^2 t_y, r_z^2 t_z^{-1} \rangle$	14	21	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{680} = \langle it_z, it_z^{-1}, m_x, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	14	21	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{681} = \langle it_x, it_y^{-1}, m_x, r_z^2, r_z^2 t_z^{-1} \rangle$	14	21	$[[1, 1, 0], [0, 2, 0], [0, 0, 1]]$
$H_{682} = \langle it_x, it_z, it_z^{-1}, m_x, r_z^2, r_z^2 t_y \rangle$	14	21	$[[1, 0, 1], [0, 1, 0], [0, 0, 2]]$
$H_{683} = \langle it_x, it_y^{-1}, it_z, it_z^{-1}, m_x, r_z^2 \rangle$	14	21	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{684} = \langle m_x, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	14	23	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{685} = \langle m_x, r_y^2 r_z t_x, r_z^2, r_z^2 t_z^{-1} \rangle$	14	23	$[[1, 1, 0], [0, 2, 0], [0, 0, 1]]$
$H_{686} = \langle m_x, r_y^2 r_z t_x, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	14	23	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{687} = \langle m_x, m_x r_z t_z^{-1}, r_z^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	14	25	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{688} = \langle m_x, m_x r_z t_x, r_z^2, r_z^2 t_z^{-1} \rangle$	14	25	$[[1, 1, 0], [0, 2, 0], [0, 0, 1]]$
$H_{689} = \langle m_x, m_x r_z t_x, m_x r_z t_z^{-1}, r_z^2 \rangle$	14	25	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{690} = \langle it_z^{-1}, m_x, r_y^2 r_z t_z, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1} \rangle$	14	29	$[[1, 0, 0], [0, 1, 0], [0, 0, 4]]$
$H_{691} = \langle it_x, it_y^{-1}, m_x, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	14	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{692} = \langle it_x, it_y^{-1}, m_x, m_x r_z t_z^{-1}, r_z^2 \rangle$	14	29	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{693} = \langle it_z, it_z^{-1}, m_x, r_y^2 r_z t_x, r_z^2 \rangle$	14	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{694} = \langle m_x, m_x r_z t_z^{-1}, r_y^2 r_z t_z, r_z^2 \rangle$	14	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{695} = \langle it_z, it_z^{-1}, m_x, m_x r_z t_x, r_z^2 \rangle$	14	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{696} = \langle m_x, m_x r_z t_x, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	14	29	$[[1, 1, 0], [0, 2, 0], [0, 0, 2]]$
$H_{697} = \langle it_z^{-1}, m_x, m_x r_z t_x, r_y^2 r_z t_z, r_z^2 \rangle$	14	29	$[[1, 0, 2], [0, 1, 2], [0, 0, 4]]$
$H_{698} = \langle r_x^{-1}, r_x^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	15	15	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{699} = \langle it_x, it_y^{-1}, r_x^{-1}, r_x^2, r_z^2 t_y^{-1} \rangle$	15	22	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{700} = \langle it_y^{-1}, r_x^{-1}, r_x^2, r_z^2 t_x \rangle$	15	22	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{701} = \langle it_x, it_z^{-1}, it_y^{-1}, r_x^{-1}, r_x^2 \rangle$	15	22	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{702} = \langle r_x^{-1}, r_x^2, r_z^2 t_y^{-1}, r_z^2 t_x, r_z^2 t_x^{-1} \rangle$	15	24	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{703} = \langle r_x^{-1}, r_x^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	15	24	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{704} = \langle r_x^{-1}, r_x^2, r_z^2 t_x, r_z^2 t_x^{-1}, r_z^2 t_y^{-1} \rangle$	15	24	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{705} = \langle m_y t_x, r_x^{-1}, r_x^2, r_z^2 t_y^{-1} \rangle$	15	25	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{706} = \langle m_y t_y^{-1}, r_x^{-1}, r_x^2, r_z^2 t_x \rangle$	15	25	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{707} = \langle m_y t_x, m_y t_y^{-1}, r_x^{-1}, r_x^2 \rangle$	15	25	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{708} = \langle it_x, r_x^{-1}, r_x^2, r_z^2 t_y^{-1}, r_z^2 t_x^{-1} \rangle$	15	29	$[[4, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{709} = \langle it_x, it_x^{-1}, r_x^{-1}, r_x^2, r_z^2 t_y^{-1} \rangle$	15	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{710} = \langle it_x, it_x^{-1}, m_y t_y^{-1}, r_x^{-1}, r_x^2 \rangle$	15	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{711} = \langle it_y^{-1}, r_x^{-1}, r_x^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	15	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{712} = \langle m_y t_y^{-1}, r_x^{-1}, r_x^2, r_z^2 t_x, r_z^2 t_x^{-1} \rangle$	15	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{713} = \langle it_y^{-1}, m_y t_x, r_x^{-1}, r_x^2 \rangle$	15	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{714} = \langle m_y t_x, r_x^{-1}, r_x^2, r_z^2 t_x^{-1} \rangle$	15	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{715} = \langle it_x, m_y t_y^{-1}, r_x^{-1}, r_x^2, r_z^2 t_x^{-1} \rangle$	15	29	$[[2, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{716} = \langle m_x r_x, m_x r_x^{-1} t_x, m_x r_x^{-1} t_y^{-1}, r_x^2 \rangle$	16	16	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{717} = \langle it_x, m_x r_x, m_x r_x^{-1} t_x^{-1}, r_x^2 \rangle$	16	22	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{718} = \langle it_y^{-1}, m_x r_x, m_x r_x^{-1} t_x, r_x^2 \rangle$	16	22	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{719} = \langle it_x, it_y^{-1}, m_x r_x, r_x^2 \rangle$	16	22	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{720} = \langle m_x r_x, m_x r_x^{-1} t_y^{-1}, r_x^2, r_z^2 r_x t_x \rangle$	16	23	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{721} = \langle m_x r_x, m_x r_x^{-1} t_x, r_x^2, r_z^2 t_y^{-1} \rangle$	16	23	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{722} = \langle m_x r_x, r_x^2, r_z^2 r_x t_x, r_z^2 r_x t_x^{-1} \rangle$	16	23	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{723} = \langle m_x r_x, m_x r_x^{-1} t_y^{-1}, r_x^2, r_z^2 t_x \rangle$	16	26	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{724} = \langle m_x r_x, m_x r_x^{-1} t_x, r_x^2, r_z^2 t_y^{-1} \rangle$	16	26	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{725} = \langle m_x r_x, r_x^2, r_z^2 t_x, r_z^2 t_x^{-1} \rangle$	16	26	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{726} = \langle it_x, m_x r_x, r_x^2, r_z^2 t_y^{-1} \rangle$	16	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{727} = \langle it_x, m_x r_x, r_x^2, r_z^2 t_y^{-1} \rangle$	16	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{728} = \langle it_y^{-1}, m_x r_x, r_x^2, r_z^2 t_x \rangle$	16	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{729} = \langle m_x r_x, r_x^2, r_z^2 r_x t_y^{-1}, r_z^2 t_x \rangle$	16	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{730} = \langle it_y^{-1}, m_x r_x, r_x^2, r_z^2 r_x t_x \rangle$	16	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$

H	$H_{0,0,0}$	$P(H)$	Translation basis of H
$H_{731} = \langle m_x r_x, r_x^2, r_z^2 r_x t_x, r_z^2 t_y^{-1} \rangle$	16	29	$[[2, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{732} = \langle i, it_x, r_y r_x \rangle$	17	17	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{733} = \langle i, r_y r_x, r_z^2 r_x t_x \rangle$	17	28	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{734} = \langle i, r_y r_x, r_z^2 t_x \rangle$	17	30	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{735} = \langle i, m_x t_x, r_y r_x \rangle$	17	30	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{736} = \langle i, r_y r_x, r_y^2 r_x t_x \rangle$	17	33	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{737} = \langle m_x r_y t_x, m_z r_x, r_y r_x \rangle$	18	18	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{738} = \langle it_x, it_x^{-1}, m_z r_x, r_y r_x \rangle$	18	28	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{739} = \langle m_z r_x, r_y r_x, r_y r_x^{-1} t_x \rangle$	18	31	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{740} = \langle m_z r_x, r_y r_x, r_y^2 r_x t_x, r_y^2 r_x t_x^{-1} \rangle$	18	33	$[[2, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{741} = \langle r_y r_x, r_z^2 r_x, r_z^2 r_x t_x \rangle$	19	19	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{742} = \langle it_x, r_y r_x, r_z^2 r_x \rangle$	19	28	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{743} = \langle r_y r_x, r_y^2 r_x t_x, r_z^2 r_x \rangle$	19	32	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{744} = \langle m_x t_x, r_y r_x, r_z^2 r_x \rangle$	19	33	$[[1, 0, 0], [0, 2, 0], [0, 0, 2]]$
$H_{745} = \langle i, it_x, it_y^{-1}, m_z r_x, r_x^2 \rangle$	20	20	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{746} = \langle i, it_y^{-1}, m_z r_x, r_x^2, r_z^2 t_x \rangle$	20	29	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{747} = \langle i, it_x, m_z r_x, r_x^2, r_z^2 t_y^{-1} \rangle$	20	29	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{748} = \langle i, m_z r_x, r_x^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	20	29	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{749} = \langle i, it_x, it_y^{-1}, it_z^{-1}, r_x^2, r_z^2 \rangle$	21	21	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{750} = \langle i, it_x, it_y^{-1}, r_x^2, r_y^2 r_z t_z^{-1}, r_z^2 \rangle$	21	29	$[[1, 0, 0], [0, 1, 0], [0, 0, 2]]$
$H_{751} = \langle i, it_x, r_x^2, r_z^2, r_z^2 r_x t_y^{-1} \rangle$	21	29	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{752} = \langle i, r_x^2, r_z^2 r_x t_x, r_z^2 r_x t_y^{-1} \rangle$	21	29	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{753} = \langle i, it_x, it_y^{-1}, m_x r_x, r_x^2 \rangle$	22	22	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{754} = \langle i, it_y^{-1}, m_x r_x, r_x^2, r_z^2 t_x \rangle$	22	29	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{755} = \langle i, it_x, m_x r_x, r_x^2, r_z^2 t_y^{-1} \rangle$	22	29	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{756} = \langle i, m_x r_x, r_x^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	22	29	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{757} = \langle m_x r_x, m_z, r_x^2, r_z^2 r_x t_x, r_z^2 r_x t_y^{-1} \rangle$	23	23	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{758} = \langle it_x, m_x r_x, m_z, r_x^2, r_z^2 r_x t_y^{-1} \rangle$	23	29	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{759} = \langle it_y^{-1}, m_x r_x, m_z, r_x^2, r_z^2 r_x t_x \rangle$	23	29	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{760} = \langle it_x, it_y^{-1}, m_x r_x, m_z, r_x^2 \rangle$	23	29	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{761} = \langle r_x^2, r_z^2, r_z^2 r_x, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	24	24	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{762} = \langle it_x, r_x^2, r_z^2, r_z^2 r_x, r_z^2 t_y^{-1} \rangle$	24	29	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{763} = \langle it_y^{-1}, r_x^2, r_z^2, r_z^2 r_x, r_z^2 t_x \rangle$	24	29	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{764} = \langle it_x, it_y^{-1}, r_x^2, r_z^2, r_z^2 r_x \rangle$	24	29	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{765} = \langle m_z, m_z r_x, r_x^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	25	25	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{766} = \langle it_x, it_x^{-1}, m_z, m_z r_x, r_x^2, r_z^2 t_y^{-1} \rangle$	25	29	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{767} = \langle it_y^{-1}, m_z, m_z r_x, r_x^2, r_z^2 t_x \rangle$	25	29	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{768} = \langle it_x, it_x^{-1}, it_y^{-1}, m_z, m_z r_x, r_x^2 \rangle$	25	29	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{769} = \langle m_z r_x, r_x^2, r_z^2 t_x, r_z^2 t_y^{-1} \rangle$	26	26	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{770} = \langle it_x, m_z r_x, r_x^2, r_z^2, r_z^2 t_y^{-1} \rangle$	26	29	$[[2, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{771} = \langle it_y^{-1}, m_z r_x, r_x^2, r_z^2, r_z^2 t_x \rangle$	26	29	$[[1, 0, 0], [0, 1, 1], [0, 0, 2]]$
$H_{772} = \langle it_x, it_y^{-1}, m_z r_x, r_x^2, r_z^2 \rangle$	26	29	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{773} = \langle r_x^2, r_y r_x, r_z^2, r_z^2 t_x \rangle$	27	27	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{774} = \langle it_x, r_x^2, r_y r_x, r_z^2 \rangle$	27	30	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{775} = \langle m_x r_x^{-1} t_x, r_x^2, r_y r_x, r_z^2 \rangle$	27	31	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{776} = \langle r_x^2, r_y r_x, r_z^2, r_z^2 r_x t_x \rangle$	27	32	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{777} = \langle i, it_x, m_z r_x, r_y r_x \rangle$	28	28	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{778} = \langle i, m_z r_x, r_y r_x, r_y^2 r_x t_x \rangle$	28	33	$[[1, 1, 1], [0, 2, 0], [0, 0, 2]]$
$H_{779} = \langle i, it_x, it_y^{-1}, m_z r_x, r_x^2, r_z^2 \rangle$	29	29	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{780} = \langle i, it_x, r_x^2, r_y r_x, r_z^2 \rangle$	30	30	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{781} = \langle i, r_x^2, r_y r_x, r_z^2, r_z^2 r_x t_x \rangle$	30	33	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{782} = \langle m_z r_x, r_x^2, r_y r_x, r_z^2, r_z^2 t_x \rangle$	31	31	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{783} = \langle it_x, m_z r_x, r_x^2, r_y r_x, r_z^2 \rangle$	31	33	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{784} = \langle r_x^2, r_y r_x, r_z^2, r_z^2 r_x, r_z^2 t_x \rangle$	32	32	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$
$H_{785} = \langle it_x, r_x^2, r_y r_x, r_z^2, r_z^2 r_x \rangle$	32	33	$[[1, 0, 1], [0, 1, 1], [0, 0, 2]]$
$H_{786} = \langle i, it_x, m_z r_x, r_x^2, r_y r_x, r_z^2 \rangle$	33	33	$[[1, 0, 0], [0, 1, 0], [0, 0, 1]]$

According to [5], we say that the realization $R = (\Gamma, G, \sigma, \varphi)$ of symmetrical 2-extension of Λ^3 satisfies the $[p_x, p_y, p_z]$ -periodicity condition, where p_x, p_y, p_z are positive integers, if there exist $g_1, g_2, g_3 \in \text{Aut}_\sigma(\Gamma)$ such that $[g_1, g_2] = 1, [g_2, g_3] = 1, [g_1, g_3] = 1$ and $\varphi g_1^\sigma \varphi^{-1} = t_x^{p_x}, \varphi g_2^\sigma \varphi^{-1} = t_y^{p_y}, \varphi g_3^\sigma \varphi^{-1} = t_z^{p_z}$.

3 Main result

We have done a computer implementation of the proposed in [7] approach, which can be called a coordinatization of symmetrical extensions of graphs. According to it, the

realization of symmetrical 2-extension of the grid Λ^3 of class I can be defined by a triple H, L, X , where H is a vertex-transitive subgroup of $\text{Aut}(\Lambda^3)$, L is subgroup of index 2 of the stabilizer of the vertex $(0, 0, 0)$ in H , and X is some subset of elements of H mapping the vertex $(0, 0, 0)$ of Λ^3 to some its adjacent vertices (see [3] for details).

Below we give adaptations of Algorithm 1 and Algorithm 2 from [3] to Λ^3 :

Algorithm 1. *Generation of all saturated realizations of symmetrical 2-extensions of Λ^3 .*

Output: A list of realizations $R_{H_i, L_i, \mathcal{P}_i}$, $i = 1, \dots, n$.

Description. Look over all groups H from $\mathbf{H}_I$. For each such group let $K = H_{(0,0)}$. Choose elements $h_1, \dots, h_6 \in H$ such that $\{h_1(0, 0, 0), \dots, h_6(0, 0, 0)\} = \{(1, 0, 0), (-1, 0, 0), (0, 1, 0), (0, -1, 0), (0, 0, 1), (0, 0, -1)\}$. Look over all subgroups L of K of index 2. For each such group L , choose $g \in K$, such that $K = L \cup gL$. Look over all subsets N of the set $\{h_1L, \dots, h_6L, h_1gL, \dots, h_6gL\}$ such that N is invariant relative left multiplication by elements from L and such that $hL \in N$ imply $h^{-1}L \in N$. For each of such set N let $\mathcal{P} = \{L, gL\} \cup \{L, L_1\} : L_1 \in N\}$ and we obtain the graph $\Gamma_{H, L, \mathcal{P}}$. If between the block $\{L, gL\}$ and the blocks $\{h_jL, h_jgL\}$, $j = 1, \dots, 6$, there are connections of a type non-equal to $2_{||}$ or 4, then the realization $(\Gamma_{H, L, \mathcal{P}}, \lambda_{H/L}(H), \sigma_{H, K, L}, \tilde{\varphi}_{H, K, L})$ is of type I, and we put it into the output list.

Let $R_{H_i, L_i, \mathcal{P}_i}$, $i = 1, 2$, be two realizations generated by the Algorithm 1. Further we describe an algorithm which tests them for equivalency. Let $K_i = (H_i)_{(0,0)}$ for $i = 1, 2$. Sets of cosets H_1/K_1 and H_2/K_2 are essentially identified with the grid Λ^2 . If the realizations are equivalent, then there exists an isomorphism ψ between them which preserves blocks, and therefore, can be extended to some automorphism $g \in \text{Aut}(\Lambda^2)$. Vertex symmetry of the extension $\Gamma_{H_2, L_2, \mathcal{P}_2}$ implies that ψ can be multiplied by some automorphism of the extension $\Gamma_{H_2, L_2, \mathcal{P}_2}$, which preserves blocks, in such a way that the resulting isomorphism between $\Gamma_{H_1, L_1, \mathcal{P}_1}$ and $\Gamma_{H_2, L_2, \mathcal{P}_2}$, while mapping H_1/K_1 onto H_2/K_2 , will give some element $\tilde{g}$ already from $\text{Aut}(\Lambda^2)_{(0,0)}$. An element $\tilde{g}$ takes one of 48 possible values. Algorithm 2, described below, allows to check whether two realizations are equivalent or not, under the assumption that $\tilde{g} = 1$. In general case, to test two realizations $R_{H_i, L_i, \mathcal{P}_i}$, $i = 1, 2$, for equivalency we must look over all $\tilde{g} \in \text{Aut}(\Lambda^2)_{(0,0)}$, and for each $\tilde{g}$ execute algorithm 2 to check realizations $R_{H_i, L_i, \mathcal{P}_i}$ and $\tilde{g}^{-1}(R_{H_2, L_2, \mathcal{P}_2})$ for equivalence.

Algorithm 2. *Test two realizations for equivalency, under assumption $\tilde{g} = 1$.*

Input: Realizations $R_{H_i, L_i, \mathcal{P}_i} = (\Gamma_{H_i, L_i, \mathcal{P}_i}, G_i, \sigma_i, \varphi_i)$, $i = 1, 2$.

Output: Test result ('yes' or 'no').

Description. Let (n_1, n_2, n_3) be the lexicographically minimal triple of positive integers such that both implementations satisfy the condition $[n_1, n_2]$ - periodicity.

Let F_i , $i = 1, 2$, be a subgraph of $\Gamma_{H_i, L_i, \mathcal{P}_i}$ generated by the vertex set $\varphi_i^{-1}(0, 0, 0) \cup \dots \cup \varphi_i^{-1}(n_1 - 1, 0, 0) \cup \dots \cup \varphi_i^{-1}(0, n_2 - 1, 0) \cup \dots \cup \varphi_i^{-1}(n_1 - 1, n_2 - 1, 0) \cup \dots \cup \varphi_i^{-1}(0, 0, n_3 - 1) \cup \dots \cup \varphi_i^{-1}(n_1 - 1, 0, n_3 - 1) \cup \dots \cup \varphi_i^{-1}(0, n_2 - 1, n_3 - 1) \cup \dots \cup \varphi_i^{-1}(n_1 - 1, n_2 - 1, n_3 - 1)$ of Λ^3 . Comparing the blocks $\varphi_1^{-1}(k, l, m)$ and $\varphi_2^{-1}(k, l, m)$ for all $k \in \{0, \dots, n_1\}$, $l \in \{0, \dots, n_2\}$, $m \in \{0, \dots, n_3\}$, we can construct $2^{n_1 n_2 n_3}$ correspondences of the vertices of the subgraphs F_1 and F_2 . If among them there is a correspondence defining an isomorphism of the subgraphs F_1 and F_2 with additional matching on the boundary, so that this correspondence in periodicity can be extended to an isomorphism of the graphs $\Gamma_{H_i, L_i, \mathcal{P}_i}$, $i = 1, 2$, then these realizations are equivalent, and if not, then nonequivalent. Looking over $2^{n_1 n_2 n_3}$ correspondences of the vertices of subgraphs is accelerated by using a backtracking.

We applied these algorithms and get the following results. A list of saturated realizations generated by Algorithm 1 and thinned out by Algorithm 2, contains 2872 realizations given in Table 4 below. When executing Algorithm 2, the realization with maximal by inclusion group H_i was selected in each class of equivalent realizations. Due to this, the realizations in the resulting list are maximal.

We split the set of all realizations of the symmetrical 2-extensions of Λ^3 of the class I into subclasses defined by the types of connections in the neighborhood of vertex. In the first column of Table 3 below, we give all occurring combinations of connection types in the neighborhood of vertex (59 combinations). Combinations are of the form $x_1x_2-y_1y_2-z_1z_2$, where x_1 is the type of the first connection by the first direction (the grid Λ^3 , and therefore a 2-extension, has three directions along coordinate axes), x_2 is the type of the second connection by the first direction, y_1 is the type of the first connection by the second direction, y_2 is the type of the second connection by the second direction, z_1 is the type of the first connection by the third direction, z_2 is the type of the second connection by the third direction. Here, for each extension, the numbering of directions and connections within the direction is performed so that the combination turned out to be lexicographically minimal. In the pictures of combinations in the first column of Table 3 the first direction is shown horizontally (first connection to the left, second to the right), the second direction is shown vertically (bottom connection is first, top connection is second), the third direction is shown diagonally (bottom-left connection is first, top-right connection is second). For each combination of connection types, the remaining columns in Table 3 contain pictures of all found corresponding extensions of vertex neighborhood up to equivalence. In these pictures, the edges in blocks are not shown because we use these types of vertex neighborhood both for saturated and non-saturated realizations.

Table 3

**Vertex neighborhood extensions for
2-extensions of Λ^3 of class I**

Connection types	Vertex neighborhood extensions
11.11.11	1A	1B
11.11.2 2	2A	2B

Connection types

Vertex neighborhood extensions

11_11_2||4

11_11_33

11_11_44

11_12||_12||

11_13_13

11_14_14

3A

3B

4A

4B

5A

5B

6

7A

7B

8

Connection types	Vertex neighborhood extensions
11_2 2 _2 2	9
11_2 2 _2 4	10
11_2 2 _33	11
11_2 2 _44	12
11_2 3_2 3	13
11_2 4_2 4	14

Connection types

Vertex neighborhood extensions

11.2||4.33

11.2||4.44

11.2_v2_v.2_v2_v

11.33.33

11.33.44

11.34.34

15

16

17A

17B

18A

18B

19

20

Connection types

Vertex neighborhood extensions

11.44.44

12||-12||-2||2||

12||-12||-2||4

12||-12||-33

12||-12||-44

12_V-12_V-2_V2_V

21

22

23

24

25

26A

26B

26C

Connection types

Vertex neighborhood extensions

13.13.2||2||

13.13.2||4

13.13.33

13.13.44

14.14.2||2||

14.14.2||4

27A

27B

28A

28B

29A

29B

30A

30B

31

32

Connection types

Vertex neighborhood extensions

14.14.33

33

14.14.44

34

2||2||-2||2||-33

35

2||2||-2||3-2||3

36

2||2||-2||4-33

37

2||2||-2V2V-2V2V

38A

38B

Connection types

Vertex neighborhood extensions

2||2||-33.33

39A

39B

2||2||-33.44

40

2||2||-34.34

41

2||2V-2||2V-2V2V

42A

42B

2||3.2||3.2||4

43

2||3.2||3.33

44

Connection types

Vertex neighborhood extensions

2||3.2||3.44

2||4.2||4.33

2||4.2v.2v.2v.2v

2||4.33.33

2||4.33.44

2||4.34.34

45

46

47A

47B

48A

48B

49

50

Connection types

Vertex neighborhood extensions

$2V_2V_2V_2V_33$ $2V_2V_2V_2V_44$ $2V_2V_2V_3_2V_3$ $2V_2V_2V_4_2V_4$ 33_33_33 33_33_44

51A

51B

52A

52B

53A

53B

53C

54A

54B

55A

55B

56A

56B

Connection types

Vertex neighborhood extensions

33.34.34

57

33.44.44

58

34.34.44

59

A list of 2872 saturated realizations generated using Algorithm 1 and thinned out using Algorithm 2 is given below in Table 5 at the end of the paper. Saturated realizations are defined by triples H, L, X (see above): group $H \in \mathbf{H}$ is given in the fourth column, subgroup L of index 2 in $H_{(0,0,0)}$ is presented in the fifth column, a subset of X of elements of the group H is in the seventh column. In addition, the sixth column contains an element m such that $L \cup mL = H_{(0,0,0)}$. The realization $\mathbb{N}^{\mathfrak{b}}$ is given in the third column. Saturated realizations are sorted by vertex neighborhood extensions given in Table 3. ($\mathbb{N}^{\mathfrak{b}}$ of vertex neighborhood extension is given in the first column of Table 5). The set of realizations with given vertex neighborhood extension, in turn, are divided into classes defined by sizes of spheres of radii 1, 2, ..., 10 of graph of a realization. We call such a set of sizes of spheres of radii 1, 2, ..., 10 *growth* and give it in the second column of Table 5. In this subdivision, classes are lexicographically sorted by growth increasing. In Table 5, along with saturated realizations, we give non-saturated realizations by $\mathbb{N}^{\mathfrak{b}}$ of saturated realizations with an asterisk in the third column (see details before Corollary 1 below).

Theorem 3.1. *The saturated realizations of symmetrical 2-extensions of the grid Λ^3 of class I up to equivalence are exhausted by 2872 pairwise nonequivalent saturated realizations given in Table 5.*

Note that listing all, up to equivalence, realizations of the symmetrical 2-extensions of the grid Λ^3 is reduced to listing all, up to equivalence, saturated realizations of symmetrical 2-extensions of Λ^3 . Indeed, it is obvious that every non-saturated realization of a symmetrical 2-extension of Λ^3 is obtained from a uniquely defined saturated realization by removing an edge in each block. All maximal non-saturated realizations obtained in this way are given in Table 5 by $\mathbb{N}^{\mathfrak{b}}$ of saturated maximal realizations taken with an asterisk.

Corollary 3.2. *The non-saturated realizations of symmetrical 2-extensions of the grid Λ^3 of class I up to equivalence are exhausted by 2701 pairwise nonequivalent non-saturated realizations given in Table 5.*

Proof. Using a computer, it is easily verified that when removing edges inside blocks of 2872 realizations given in Table 5, 171 their graphs become disconnected and the remaining 2701 realizations (see № with an asterisk in Table 5) give all, up to equivalence, non-saturated realizations of symmetrical 2-extensions of the grid Λ^3 of class I. $\square$

According to Theorem 1 and Corollary 1, all realizations given in Table 5 are pairwise nonequivalent. However, among the graphs of these realizations, isomorphic ones are found. With GAP, we built partition of the set of graphs of realizations from Table 5 into classes of isomorphic graphs (for details, see the proof of Corollary 3.3 below). In the following Table 4, we give all the non-singleton classes of this partition.

Table 4

**Non-singleton classes of isomorphic graphs of realizations
of symmetrical 2-extensions of Λ^3 of class I**

1) 1, 45*	51) 1282, 1412*	102) 2492, 2495	153) 1759*, 1760*
2) 7, 8, 76*	52) 1283, 1414*	103) 2552, 2553	154) 1762*, 1763*
3) 9, 10	53) 1288, 664*, 1423*	104) 2651, 2659	155) 1857*, 1858*
4) 16, 17	54) 1289, 1420*	105) 2652, 2660	156) 1919*, 1920*
5) 18, 19	55) 1290, 1424*	106) 2653, 2658	157) 1928*, 1929*
6) 26, 64*	56) 1294, 672*	107) 2654, 2655	158) 1941*, 1943*
7) 30, 97*	57) 1295, 673*	108) 2656, 2657	159) 1944*, 1945*
8) 36, 198*, 199*, 337*	58) 1307, 1437*	109) 2702, 2703	160) 1962*, 1963*
9) 37, 38, 202*, 203*, 204*, 205*, 206*,	59) 1313, 712*	110) 2707, 2708	161) 1990*, 1991*
207*, 1119*, 1120*, 1484*	60) 1314, 713*	111) 2713, 2714	162) 1998*, 1999*
10) 39, 1121*	61) 1716, 1717	112) 2718, 2720	163) 2002*, 2006*
11) 41, 279	62) 1720, 1721	113) 2724, 2726	164) 2004*, 2005*
12) 42, 280	63) 1722, 1724	114) 63*, 64*, 65*	165) 2043*, 2047*
13) 43, 44, 214*, 215*, 343*	64) 1725, 1726	115) 89*, 314*	166) 2050*, 2051*
14) 46, 123*	65) 1727, 1728	116) 102*, 105*	167) 2053*, 2054*
15) 47, 122*	66) 1756, 1757	117) 116*, 1121*	168) 2055*, 2056*
16) 54, 293	67) 1759, 1760	118) 117*, 339*	169) 2058*, 2059*
17) 55, 294	68) 1762, 1763	119) 121*, 219*	170) 2071*, 2085*
18) 57, 348*, 352*	69) 1857, 1858	120) 130*, 1127*	171) 2072*, 2086*
19) 59, 144*	70) 1919, 1920	121) 141*, 1125*	172) 2075*, 2084*
20) 64, 65	71) 1928, 1929	122) 146*, 353*	173) 2080*, 2082*
21) 110, 250*	72) 1941, 1943	123) 167*, 245*	174) 2089*, 2090*
22) 122, 123	73) 1944, 1945	124) 175*, 1139*	175) 2091*, 2092*
23) 198, 199	74) 1962, 1963	125) 209*, 210*	176) 2093*, 2094*
24) 202, 203	75) 1990, 1991	126) 211*, 212*	177) 2109*, 2110*
25) 206, 207	76) 1998, 1999	127) 228*, 350*	178) 2346*, 2349*
26) 216, 343	77) 2002, 2006	128) 234*, 235*	179) 2347*, 2348*
27) 229, 348	78) 2004, 2005	129) 328*, 329*	180) 2353*, 2355*
28) 233, 352	79) 2043, 2047	130) 360*, 361*	181) 2357*, 2358*
29) 286, 216*	80) 2050, 2051	131) 651*, 652*, 653*, 654*, 2114*	182) 2362*, 2365*
30) 296, 1123*, 1124*	81) 2053, 2054	132) 660*, 2115*	183) 2363*, 2364*
31) 299, 229*	82) 2055, 2056	133) 662*, 2116*	184) 2368*, 2369*
32) 301, 233*	83) 2058, 2059	134) 817*, 818*	185) 2371*, 2372*
33) 324, 363*	84) 2071, 2085	135) 819*, 820*	186) 2374*, 2375*
34) 332, 366*	85) 2072, 2086	136) 821*, 2117*	187) 2376*, 2378*
35) 427, 2114*	86) 2075, 2084	137) 825*, 2118*	188) 2492*, 2495*
36) 428, 503*, 658*	87) 2080, 2082	138) 1091*, 1094*	189) 2552*, 2553*
37) 431, 667*, 1489*	88) 2089, 2090	139) 1092*, 1093*	190) 2651*, 2659*
38) 439, 1422*	89) 2091, 2092	140) 1133*, 1134*	191) 2652*, 2660*
39) 440, 1421*	90) 2093, 2094	141) 1136*, 1137*	192) 2653*, 2658*
40) 455, 1440*	91) 2109, 2110	142) 1143*, 1144*	193) 2654*, 2655*
41) 456, 1439*	92) 2346, 2349	143) 1147*, 1148*	194) 2656*, 2657*
42) 651, 652	93) 2347, 2348	144) 1149*, 1150*	195) 2702*, 2703*
43) 653, 654	94) 2353, 2355	145) 1152*, 2521*	196) 2707*, 2708*
44) 664, 1489	95) 2357, 2358	146) 1163*, 1622*	197) 2713*, 2714*
45) 672, 1421	96) 2362, 2365	147) 1716*, 1717*	198) 2718*, 2720*
46) 673, 1422	97) 2363, 2364	148) 1720*, 1721*	199) 2724*, 2726*
47) 712, 1439	98) 2368, 2369	149) 1722*, 1724*	
48) 713, 1440	99) 2371, 2372	150) 1725*, 1726*	
49) 1091, 1094	100) 2374, 2375	151) 1727*, 1728*	
50) 1092, 1093	101) 2376, 2378	152) 1756*, 1757*	

Corollary 3.3. *(i) Up to isomorphism, there are 2792 graphs of saturated realizations of symmetrical 2-extensions of the grid Λ^3 of class I.*

(ii) Up to isomorphism, there are 2594 graphs of non-saturated realizations of symmetrical 2-extensions of the grid Λ^3 of class I.

Corollary 3.4. Up to isomorphism, there are 5350 graphs of realizations of symmetrical 2-extensions of the grid Λ^3 of class I.

Proof. (for Corollaries 3.3 and 3.4) Using GAP for each of the graphs of 5573 (2872 saturated and 2701 non-saturated) realizations of symmetrical 2-extensions of Λ^3 of class I, a subgraph B was generated by a set of vertices that are at a distance of ≤ 4 from some arbitrary vertex (i.e., B is a ball of radius 4). In the obtained set of 5573 finite graphs, balls are isomorphic if and only if they correspond to realizations which are in the same line of Table 4. After that, we continued each isomorphism φ_b between the balls B_1 and B_2 to the isomorphism φ of whole graphs of the corresponding realizations $R_1 = (\Gamma_1, G_1, \sigma_1, \varphi_1)$ and $R_2 = (\Gamma_2, G_2, \sigma_2, \varphi_2)$ as follows.

Let a realization R_1 satisfies the condition of $[p_{x1}, p_{y1}, p_{z1}]$ -periodicity and R_2 satisfies the condition of $[p_{x2}, p_{y2}, p_{z2}]$ -periodicity. Recall that, according to [5], a realization $R = (\Gamma, G, \sigma, \varphi)$ of a symmetrical 2-extension of Λ^3 satisfies the condition of $[p_x, p_y, p_z]$ -periodicity, where p_x, p_y, p_z are positive integers, if there exist $g_1, g_2, g_3 \in G$ such that $[g_i, g_j] = 1$ for $i \neq j$ and $\varphi g_1^\sigma \varphi^{-1} = t_{p_x}^{p_x}, \varphi g_2^\sigma \varphi^{-1} = t_{p_y}^{p_y}, \varphi g_3^\sigma \varphi^{-1} = t_{p_z}^{p_z}$. We identify the set of vertices of Γ_1 with the set $\{(x, y, z, w) : x, y, z \in \mathbb{Z}, w \in \{0, 1\}\}$, so that $\sigma_1 = \{\{(x, y, z, 0), (x, y, z, 1)\} : x, y, z \in \mathbb{Z}\}$ and $\{(x_1, y_1, z_1, w_1), (x_2, y_2, z_2, w_2)\} \in E(\Gamma_1) \Leftrightarrow \{(x_1 + p_{x1}, y_1, z_1, w_1), (x_2 + p_{x1}, y_2, z_2, w_2)\} \in E(\Gamma_1) \Leftrightarrow \{(x_1, y_1 + p_{y1}, z_1, w_1), (x_2, y_2 + p_{y1}, z_2, w_2)\} \in E(\Gamma_1) \Leftrightarrow \{(x_1, y_1, z_1 + p_{z1}, w_1), (x_2, y_2, z_2 + p_{z1}, w_2)\} \in E(\Gamma_1)$. Similarly, we identify the set of vertices of Γ_2 with the set $\{(x, y, z, w) : x, y, z \in \mathbb{Z}, w \in \{0, 1\}\}$.

We select positive integers p_x, p_y, p_z so that the realization R_1 satisfies the conditions of $[p_x, p_y, p_z]$ -periodicity, $p_x | p_{x1}, p_y | p_{y1}, p_z | p_{z1}$ and $(p_x, 0, 0)M, (0, p_y, 0)M, (0, 0, p_z)M \in \langle (p_{x2}, 0, 0), (0, p_{y2}, 0), (0, 0, p_{z2}) \rangle$, where angle brackets mean generation in the additive group of row-vectors and the 3×3 -matrix M is obtained from the 3×4 matrix

$$\begin{pmatrix} (p_x, 0, 0, 0)\varphi_b/p_x \\ (0, p_y, 0, 0)\varphi_b/p_y \\ (0, 0, p_z, 0)\varphi_b/p_z \end{pmatrix}$$

by deleting the last column. We need to ensure that the extension of the fragment $[0 \dots p_x - 1] \times [0 \dots p_y - 1] \times [0 \dots p_z - 1]$ is inside of the ball B_1 . To choose p_x, p_y, p_z in such a way for some pairs of realizations R_1 and R_2 we had to take the radii of balls B_1 and B_2 greater than 4.

The image of an arbitrary vertex u of the extension Γ_1 is now defined by $u\varphi = ut^{-1}\varphi_b t^M$, where the shift $t^{-1} = t_{p_x n_1}^{p_x} t_{p_y n_2}^{p_y} t_{p_z n_3}^{p_z}$ maps u into the extension of the fragment $[0 \dots p_x - 1] \times [0 \dots p_y - 1] \times [0 \dots p_z - 1]$, where n_1, n_2, n_3 are suitable positive integers. $\square$

Table 5

**2872 saturated and 2701 non-saturated maximal realizations
of symmetrical 2-extensions of the grid Λ^3 of class I**

Nbr.	gr	N ₀	H_i	L	m	X
1A						
			[3, 6, 12, 20, 32, 50, 65, 82, 105, 132]			
			20*			
			[4, 9, 19, 35, 52, 72, 100, 131, 163, 201]			
	1	H_{778}	$\langle m_z r_x, r_y r_x \rangle$	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^{-1} t_y^{-1}, m_x r_y^{-1} r_z^{-1} t_z^{-1}$	
			[4, 10, 21, 36, 54, 78, 106, 136, 173, 214]			
	2	H_{657}	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 t_y^{-1}, m_z r_x^{-1} t_z^{-1}$	
			[4, 10, 21, 37, 57, 81, 109, 142, 180, 222]			
	3	H_{316}	1	i	$r_z^2 t_x^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$	
			[4, 10, 21, 37, 57, 81, 110, 143, 180, 223]			
	4	H_{413}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 t_y^{-1}, m_z t_z^{-1}$	
			[4, 10, 21, 37, 58, 83, 111, 145, 184, 226]			
	5	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, m_y t_y^{-1}, m_z t_z^{-1}$	
			[4, 11, 22, 39, 60, 86, 116, 151, 190, 235]			
	6	H_{660}	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 t_y^{-1}, m_x r_x^{-1} t_z^{-1}$	
			[4, 11, 24, 41, 62, 90, 122, 157, 200, 247]			
	7	H_{302}	1	i	$it_x^{-1}, r_z^2 t_y^{-1}, m_z t_z^{-1}$	
			[4, 11, 24, 41, 63, 91, 123, 160, 202, 249]			
	8	H_{659}	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_y t_y^{-1}, r_x^{-1} t_z^{-1}$	
			[4, 11, 24, 41, 63, 91, 123, 160, 202, 249]			
	9	H_{317}	1	i	$r_z^2 t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z^{-1}$	
			[4, 11, 24, 43, 68, 102, 138, 181, 229, 283]			
	10	H_{395}	1	$r_z^2 r_x$	$m_x t_x^{-1}, it_y^{-1}, r_z^2 t_z^{-1}$	
			[4, 11, 24, 43, 68, 102, 138, 181, 229, 283]			
	11	H_{315}	1	i	$r_z^2 t_x^{-1}, r_z^2 t_y^{-1}, r_y t_z^{-1}$	
			[4, 11, 24, 43, 68, 102, 139, 183, 230, 283]			
	12	H_{423}	1	$r_z^2 r_x$	$r_z^2 t_x, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$	
			[4, 11, 24, 43, 69, 102, 141, 184, 233, 287]			
	13	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_z^2 t_y^{-1}, r_z^2 t_z^{-1}$	
			[4, 11, 24, 43, 69, 104, 148, 195, 245, 304]			
	14	H_{412}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_z^2 t_y^{-1}, m_z t_z^{-1}$	
			[4, 11, 24, 45, 76, 118, 162, 213, 280, 361]			
	15	H_{658}	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_z^2 t_y^{-1}, m_x r_x^{-1} t_z^{-1}$	
			[4, 12, 24, 42, 64, 92, 124, 162, 204, 252]			
	16	H_{777}	$\langle m_z r_x, r_y r_x \rangle$	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_y^{-1}, r_x^{-1} t_y^{-1}, r_z^2 r_y t_z^{-1}$	
			[4, 12, 25, 44, 67, 96, 130, 170, 214, 264]			
	17	H_{656}	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_z^2 t_y^{-1}, m_z r_x^{-1} t_z^{-1}$	
			[4, 12, 25, 44, 67, 96, 130, 170, 214, 264]			
	18	H_{655}	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$m_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_z^{-1}$	
			[4, 12, 26, 44, 72, 104, 138, 178, 228, 282]			
	19	H_{314}	1	i	$it_x^{-1}, m_y t_y^{-1}, r_z^2 t_z^{-1}$	
			[4, 12, 26, 44, 72, 104, 138, 178, 228, 282]			
	20	H_{393}	1	$r_z^2 r_x$	$r_y^{-1} r_z^{-1} t_x^{-1}, r_y r_x t_y, r_y^2 r_z t_z$	
			[4, 12, 27, 49, 77, 109, 148, 194, 244, 301]			
	21	H_{734}	$\langle r_y^{-1} r_x^{-1} \rangle$	i	$r_z^2 t_x^{-1}, r_y r_x^{-1} t_y^{-1}, r_y r_z t_z^{-1}$	
			[4, 12, 27, 50, 78, 116, 159, 210, 266, 330]			
	22	H_{301}	1	i	$it_x^{-1}, it_y^{-1}, r_z^2 t_z^{-1}$	
			[4, 12, 27, 50, 78, 116, 162, 216, 272, 334]			
	23	H_{394}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, it_y^{-1}, r_z^2 t_z^{-1}$	
			[4, 12, 27, 50, 79, 118, 162, 214, 271, 336]			
	24	H_{406}	1	$r_z^2 r_x$	$r_z^2 t_x, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z^{-1}$	
			[4, 12, 27, 50, 80, 120, 167, 222, 279, 344]			
	25	H_{312}	1	i	$it_x^{-1}, r_z^2 t_y^{-1}, r_z^2 t_z^{-1}$	
1B						
			[4, 10, 24, 50, 86, 130, 182, 242, 310, 386]			
	26	H_{758}	$\langle m_z, r_x^2 \rangle$	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}$	
			[4, 11, 27, 55, 97, 153, 220, 300, 393, 497]			
	27	H_{413}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}$	
			[4, 11, 27, 55, 97, 153, 221, 302, 395, 501]			
	28	H_{395}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 t_y, it_y^{-1}$	
			[4, 12, 28, 58, 102, 162, 234, 322, 422, 538]			
	29	H_{760}	$\langle m_z, r_x^2 \rangle$	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}$	
			[4, 12, 30, 58, 94, 138, 190, 250, 318, 394]			
	30	H_{757}	$\langle m_z, r_x^2 \rangle$	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}$	
			[4, 12, 30, 60, 105, 165, 232, 306, 398, 507]			
	31	H_{412}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}$	
			[4, 12, 30, 62, 108, 166, 231, 308, 397, 498]			
	32	H_{393}	1	$r_z^2 r_x$	$r_z^2 r_y t_x^{-1}, r_y^2 r_z t_z, r_x^2 r_y t_z^{-1}$	
			[4, 12, 30, 62, 108, 172, 244, 328, 429, 548]			
	33	H_{394}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_z^2 t_y, it_y^{-1}$	
			[4, 12, 30, 66, 112, 174, 246, 334, 432, 546]			
	34	H_{759}	$\langle m_z, r_x^2 \rangle$	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}$	
			[4, 12, 33, 69, 124, 179, 247, 330, 429, 525]			
	35	H_{393}	1	$r_z^2 r_x$	$r_y r_x t_x, r_y^2 r_z t_z, r_y^{-1} r_z^{-1} t_z^{-1}$	

Nbr.	gr	N ₀	H_i	L	m	X
2A						
						[4, 9, 19, 35, 52, 72, 100, 131, 163, 201]
						45*
						[4, 9, 19, 39, 64, 97, 136, 171, 217, 271]
						48*
						[4, 9, 19, 39, 76, 140, 229, 329, 437, 556]
						52*
						[4, 10, 24, 50, 86, 130, 182, 242, 310, 386]
						64*, 65*, 63*
						[4, 10, 24, 52, 91, 135, 183, 239, 307, 380]
						66*
						[4, 10, 24, 52, 91, 137, 192, 257, 332, 414]
						69*
						[4, 10, 24, 53, 93, 140, 202, 271, 339, 421]
						68*
						[4, 10, 24, 54, 96, 150, 216, 292, 377, 473]
						67*
						[4, 10, 24, 54, 104, 168, 243, 333, 436, 551]
						73*
						[4, 10, 24, 56, 111, 177, 257, 353, 461, 581]
						74*
						[4, 10, 24, 56, 112, 187, 263, 344, 448, 573]
						75*
						[4, 11, 24, 41, 62, 90, 122, 157, 200, 247]
						76*
						[4, 11, 27, 57, 102, 156, 214, 280, 358, 446]
						84*
						[4, 11, 27, 57, 102, 156, 214, 281, 363, 456]
						83*
						[4, 11, 27, 57, 105, 172, 250, 338, 442, 559]
						85*
						[4, 11, 27, 62, 103, 143, 201, 274, 345, 421]
						82*
						[4, 11, 30, 63, 100, 142, 194, 254, 322, 398]
						86*
						[4, 11, 30, 65, 107, 155, 216, 284, 362, 451]
						87*
						[4, 11, 30, 65, 109, 159, 217, 283, 357, 442]
						89*
						[4, 11, 30, 66, 110, 159, 222, 293, 370, 458]
						88*
						[4, 11, 30, 66, 110, 160, 222, 294, 378, 467]
						90*
						[4, 11, 30, 67, 117, 179, 258, 341, 430, 541]
						93*
						[4, 11, 30, 68, 111, 159, 219, 286, 366, 453]
						92*
						[4, 11, 30, 69, 113, 160, 222, 294, 372, 461]
						91*
						[4, 12, 30, 58, 94, 138, 190, 250, 318, 394]
						97*
						[4, 12, 30, 64, 105, 151, 210, 279, 358, 447]
						96*
						[4, 12, 33, 69, 114, 168, 230, 301, 382, 474]
						100*
						[4, 12, 33, 69, 123, 197, 278, 369, 469, 583]
						101*
						[4, 12, 33, 70, 121, 182, 251, 331, 422, 523]
						105*, 102*
						[4, 12, 33, 70, 121, 184, 260, 350, 453, 570]
						106*
						[4, 12, 33, 71, 116, 166, 230, 305, 390, 485]
						103*
						[4, 12, 33, 73, 133, 206, 288, 383, 491, 611]
						108*
						[4, 12, 33, 74, 128, 191, 266, 352, 450, 560]
						104*
						[4, 12, 33, 75, 138, 208, 288, 383, 491, 611]
						109*
						[4, 12, 36, 76, 128, 190, 264, 350, 448, 558]
						107*
						[5, 13, 26, 45, 69, 98, 133, 173, 218, 269]
						36 $H_{747} \langle m_z r_x^{-1}, r_z^2 r_x \rangle$ i $r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, r_y^2 t_z$
						[5, 14, 29, 50, 77, 110, 149, 194, 245, 302]
						37 $H_{745} \langle m_z r_x^{-1}, r_z^2 r_x \rangle$ i $r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x t_x^{-1}, r_x^2 t_z$
						38 $H_{615} \langle m_z \rangle$ r_z^2 $r_z^2 t_x^{-1}, m_y t_y^{-1}, m_z t_z, t_z^{-1}$
						[5, 14, 30, 52, 79, 114, 155, 200, 254, 314]
						39 H_{483} 1 r_z^2 $m_x t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, m_z t_z^{-1}$
						[5, 14, 30, 53, 83, 121, 164, 212, 270, 335]
						40 H_{529} 1 r_z^2 $m_x t_x^{-1}, m_y t_y, r_y^2 r_z t_z, r_z^2 t_z^{-1}$
						[5, 14, 30, 54, 87, 130, 182, 242, 310, 386]
						41 H_{326} 1 i $r_z^2 r_x t_x^{-1}, m_y t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
						42 H_{541} 1 r_z^2 $r_z^2 r_x t_x, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1}$
						[5, 15, 32, 55, 85, 122, 165, 215, 272, 335]
						43 $H_{618} \langle m_z \rangle$ r_z^2 $m_x t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, m_x t_z^{-1}$
						44 H_{461} 1 r_z^2 $r_z^2 t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, m_z t_z^{-1}$
						[5, 15, 34, 60, 92, 132, 178, 234, 299, 363]
						45 H_{535} 1 r_z^2 $r_z^{-1} t_x^{-1}, r_z t_y, r_y^2 t_z, m_z t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
		84	H_{485}	1	r_z^2	$it_x^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
		[5, 17, 41, 79, 135, 209, 296, 395, 506, 629]				
		85	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_y t_y, m_z t_z, it_z^{-1}$
		[5, 17, 42, 79, 119, 170, 231, 301, 380, 469]				
		86	H_{671}	$\langle r_y^2 r_x \rangle$	$r_z^2 r_x$	$r_y^2 t_x, r_z^2 t_x^{-1}, r_z^2 t_y^{-1}, r_x^{-1} t_z^{-1}$
		[5, 17, 43, 77, 119, 171, 234, 303, 386, 475]				
		87	H_{433}	1	r_z^2	$it_x^{-1}, r_z^2 t_y^{-1}, m_z t_z, it_z^{-1}$
		[5, 17, 43, 77, 122, 176, 241, 312, 397, 489]				
		88	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, it_y^{-1}, r_x^2 t_z$
		[5, 17, 43, 78, 121, 174, 235, 307, 386, 477]				
		89	H_{512}	1	r_z^2	$r_z t_x^{-1}, r_x^{-1} t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
		[5, 17, 43, 79, 124, 176, 242, 316, 402, 492]				
		90	H_{466}	1	r_z^2	$r_z^2 t_x^{-1}, r_x^2 t_y^{-1}, m_z t_z, it_z^{-1}$
		[5, 17, 43, 80, 121, 175, 240, 313, 392, 487]				
		91	H_{535}	1	r_z^2	$r_z^{-1} t_x^{-1}, r_z t_y, r_y^2 t_z, it_z^{-1}$
		[5, 17, 43, 81, 124, 177, 243, 317, 400, 494]				
		92	H_{427}	1	r_z^2	$r_z^2 t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
		[5, 17, 43, 82, 135, 199, 281, 362, 462, 575]				
		93	H_{462}	1	r_z^2	$it_x^{-1}, r_z^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
		[5, 18, 39, 72, 113, 166, 227, 300, 381, 474]				
		94	H_{745}	$\langle m_z r_x^{-1}, r_z^2 r_x \rangle$	i	$r_y^2 r_x t_x, m_z r_x t_x^{-1}, m_z r_x t_y^{-1}, r_x^2 t_z$
		[5, 18, 41, 76, 119, 174, 239, 316, 401, 498]				
		95	H_{615}	$\langle m_z \rangle$	r_z^2	$r_z^2 t_x^{-1}, m_y t_y^{-1}, it_z, r_z^2 t_z^{-1}$
		[5, 18, 42, 81, 124, 179, 244, 319, 404, 499]				
		96	H_{631}	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, it_z$
		[5, 18, 43, 76, 123, 178, 245, 319, 406, 500]				
		97	H_{624}	$\langle m_z \rangle$	r_z^2	$m_x r_z t_x^{-1}, m_x r_z t_y^{-1}, r_y^2 t_z, m_x t_z^{-1}$
		[5, 18, 43, 84, 135, 204, 285, 382, 489, 612]				
		98	H_{305}	1	i	$it_x^{-1}, it_y, it_y^{-1}, r_y^2 r_z t_z^{-1}$
		[5, 18, 43, 84, 137, 208, 291, 390, 499, 624]				
		99	H_{504}	1	r_z^2	$r_z^2 t_x^{-1}, r_x^2 r_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}$
		[5, 18, 44, 82, 132, 188, 255, 331, 420, 517]				
		100	H_{474}	1	r_z^2	$it_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
		[5, 18, 44, 85, 149, 223, 301, 398, 505, 629]				
		101	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x^2 t_y, r_x^2 t_z, r_y^2 t_z^{-1}$
		[5, 18, 45, 83, 138, 201, 280, 367, 468, 576]				
		102	H_{533}	1	r_z^2	$m_x r_z t_x^{-1}, m_x r_z t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
		[5, 18, 45, 84, 131, 186, 257, 334, 425, 522]				
		103	H_{473}	1	r_z^2	$it_x^{-1}, r_x^2 t_y^{-1}, m_z t_z, it_z^{-1}$
		[5, 18, 45, 85, 140, 206, 289, 377, 484, 596]				
		104	H_{531}	1	r_z^2	$m_x r_z t_x^{-1}, m_x r_z t_y^{-1}, r_y^2 t_z, it_z^{-1}$
		[5, 18, 46, 85, 139, 206, 285, 376, 481, 597]				
		105	H_{323}	1	i	$r_z^2 t_x^{-1}, r_x^2 r_y t_y^{-1}, m_x t_z, m_x t_z^{-1}$
		[5, 18, 46, 85, 139, 207, 288, 383, 492, 614]				
		106	H_{540}	1	r_z^2	$it_x^{-1}, r_x^2 r_y t_y^{-1}, m_x t_z, m_x t_z^{-1}$
		[5, 18, 47, 88, 147, 209, 293, 379, 485, 595]				
		107	H_{674}	$\langle r_y^2 r_x \rangle$	$r_z^2 r_x$	$r_y^2 t_x, r_z^2 t_x^{-1}, it_y^{-1}, m_z r_x^{-1} t_z^{-1}$
		[5, 18, 49, 94, 151, 224, 310, 408, 518, 640]				
		108	H_{326}	1	i	$r_z^2 r_x t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}$
		[5, 18, 49, 95, 152, 223, 311, 407, 519, 639]				
		109	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_y t_y^{-1}, it_z, it_z^{-1}$

2B

		[4, 11, 30, 73, 147, 243, 346, 462, 602, 756]				
		112*				
		[4, 11, 30, 76, 156, 253, 350, 466, 608, 762]				
		113*				
		[4, 12, 33, 85, 153, 240, 344, 464, 600, 752]				
		115*				
		[5, 14, 32, 64, 112, 176, 256, 352, 464, 592]				
		110	H_{779}	$\langle i, r_x^2, r_z^2 \rangle$	$r_z^2 r_x$	$m_x t_x, t_x^{-1}, m_y t_y, t_y^{-1}$
		[5, 16, 42, 88, 152, 232, 328, 440, 568, 712]				
		111	H_{766}	$\langle m_y, r_x^2 \rangle$	$m_z r_x^{-1} r_z^2 r_x t_x, m_x t_x^{-1}, m_y t_y, t_y^{-1}$	
		[5, 17, 46, 101, 177, 262, 364, 490, 628, 774]				
		112	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}$
		[5, 17, 46, 103, 179, 266, 365, 493, 629, 777]				
		113	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y, it_y^{-1}$
		[5, 18, 48, 96, 160, 240, 336, 448, 576, 720]				
		114	H_{779}	$\langle i, r_x^2, r_z^2 \rangle$	$r_z^2 r_x$	$m_z r_x^{-1} t_x, r_z^2 r_x t_x^{-1}, m_y t_y, t_y^{-1}$
		[5, 18, 48, 106, 174, 266, 366, 490, 622, 778]				
		115	H_{768}	$\langle m_y, r_x^2 \rangle$	$m_z r_x^{-1} r_z^2 r_x t_x, m_x t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}$	

3A

		[5, 14, 30, 52, 79, 114, 155, 200, 254, 314]				
		116*				
		[5, 14, 31, 57, 90, 131, 181, 238, 303, 377]				
		117*				
		[5, 14, 31, 58, 95, 141, 195, 260, 335, 416]				
		119*				
		[5, 14, 31, 59, 96, 141, 200, 268, 338, 421]				

Nbr.	gr	N_0	H_i	L	m	X
		118°				
		[5, 14, 31, 61, 100, 143, 201, 274, 345, 421]				
		120°				
		[5, 15, 34, 61, 94, 135, 185, 242, 306, 378]				
		123°				
		[5, 15, 34, 61, 95, 138, 189, 247, 314, 389]				
		122°				
		[5, 15, 34, 61, 96, 141, 193, 253, 324, 401]				
		121°				
		[5, 15, 34, 62, 97, 139, 190, 249, 314, 387]				
		125°				
		[5, 15, 34, 62, 98, 142, 194, 254, 322, 398]				
		128°				
		[5, 15, 34, 62, 99, 145, 199, 262, 334, 415]				
		124°				
		[5, 15, 34, 63, 102, 151, 210, 279, 358, 447]				
		131°				
		[5, 15, 34, 63, 103, 154, 214, 284, 366, 458]				
		129°				
		[5, 15, 35, 64, 100, 146, 201, 264, 337, 418]				
		126°				
		[5, 15, 35, 65, 103, 150, 206, 271, 345, 427]				
		127°				
		[5, 15, 35, 67, 114, 178, 255, 344, 446, 560]				
		132°, 133°				
		[5, 15, 37, 68, 108, 158, 218, 287, 365, 453]				
		134°				
		[5, 15, 37, 68, 108, 159, 222, 293, 370, 458]				
		135°				
		[5, 15, 37, 69, 111, 163, 224, 297, 381, 469]				
		136°				
		[5, 15, 37, 70, 111, 166, 228, 301, 392, 487]				
		137°				
		[5, 15, 37, 70, 113, 166, 230, 305, 390, 485]				
		138°				
		[5, 15, 37, 74, 122, 178, 244, 322, 410, 508]				
		130°				
		[5, 15, 37, 84, 147, 214, 293, 387, 495, 615]				
		139°				
		[5, 16, 36, 62, 96, 140, 189, 246, 314, 386]				
		140°				
		[5, 16, 36, 63, 97, 139, 189, 247, 312, 384]				
		141°				
		[5, 16, 36, 64, 100, 144, 196, 256, 324, 400]				
		147°, 142°, 143°				
		[5, 16, 37, 66, 104, 151, 206, 271, 344, 426]				
		144°				
		[5, 16, 37, 66, 105, 157, 217, 283, 357, 442]				
		146°				
		[5, 16, 37, 67, 106, 155, 213, 280, 357, 443]				
		145°				
		[5, 16, 37, 67, 107, 159, 222, 294, 372, 461]				
		148°				
		[5, 16, 37, 67, 108, 159, 218, 289, 369, 457]				
		154°				
		[5, 16, 39, 72, 113, 164, 223, 292, 373, 461]				
		152°				
		[5, 16, 39, 73, 115, 165, 224, 294, 375, 467]				
		151°				
		[5, 16, 39, 73, 115, 166, 228, 300, 381, 473]				
		153°				
		[5, 16, 39, 75, 124, 186, 259, 342, 436, 541]				
		149°				
		[5, 16, 39, 76, 125, 189, 265, 349, 444, 550]				
		150°				
		[5, 16, 40, 75, 115, 165, 228, 298, 378, 471]				
		155°				
		[5, 16, 42, 77, 118, 172, 234, 305, 389, 480]				
		158°				
		[5, 16, 42, 82, 132, 192, 263, 346, 440, 545]				
		156°				
		[5, 16, 42, 82, 132, 199, 278, 360, 454, 571]				
		159°				
		[5, 16, 42, 83, 133, 194, 266, 349, 444, 550]				
		157°				
		[5, 16, 43, 89, 144, 210, 292, 387, 495, 615]				
		160°				
		[5, 17, 39, 71, 112, 162, 221, 289, 369, 455]				
		161°				
		[5, 17, 39, 72, 115, 168, 231, 303, 384, 476]				
		166°				
		[5, 17, 40, 76, 129, 197, 277, 369, 470, 585]				
		170°				
		[5, 17, 40, 76, 129, 198, 279, 368, 469, 587]				
		171°				
		[5, 17, 41, 73, 114, 168, 229, 298, 381, 471]				
		164°				
		[5, 17, 41, 74, 114, 165, 228, 298, 378, 471]				
		162°, 163°				
		[5, 17, 41, 74, 116, 170, 232, 303, 387, 478]				
		169°				
		[5, 17, 41, 75, 118, 171, 234, 307, 390, 483]				
		165°				

Nbr.	gr	N ₀	H _i	L	m	X
		140	H ₄₇₉	1	r_z^2	$r_y^2 t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 20, 43, 75, 117, 167, 226, 296, 374, 461]				
		141	H ₅₃₇	1	r_z^2	$r_z^{-1} t_x^{-1}, r_z t_y, m_z r_z^{-1} t_z, m_z r_z t_z, r_y^2 t_z^{-1}$
		[6, 20, 43, 76, 119, 170, 231, 301, 380, 469]				
		142	H ₅₂₄	1	r_z^2	$m_z r_z^{-1} t_x^{-1}, m_z r_z t_y, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		143	H ₅₀₉	1	r_z^2	$r_z^{-1} t_x^{-1}, r_z t_y, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 20, 44, 75, 118, 168, 229, 298, 377, 465]				
		144	H ₄₆₉	1	r_z^2	$r_z^2 t_x^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 20, 44, 76, 118, 170, 230, 300, 380, 468]				
		145	H ₄₆₁	1	r_z^2	$r_z^2 t_x^{-1}, m_y t_y^{-1}, r_x^2 t_z, i t_z^{-1}, m_z t_z^{-1}$
		[6, 20, 44, 76, 120, 174, 235, 307, 386, 477]				
		146	H ₅₁₂	1	r_z^2	$r_z^{-1} t_x^{-1}, r_z t_y, r_y^2 r_z t_z, r_x^2 r_z t_z, r_y^2 t_z^{-1}$
		[6, 20, 44, 77, 119, 170, 231, 301, 380, 469]				
		147	H ₄₂₉	1	r_z^2	$r_y^2 t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 20, 44, 77, 121, 175, 240, 313, 392, 487]				
		148	H ₅₃₅	1	r_z^2	$r_z^{-1} t_x^{-1}, r_z t_y, r_y^2 t_z, i t_z^{-1}, m_z t_z^{-1}$
		[6, 20, 45, 83, 134, 197, 275, 359, 456, 563]				
		149	H ₄₆₀	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z, i t_z^{-1}, m_z t_z^{-1}$
		[6, 20, 45, 84, 134, 201, 278, 366, 463, 572]				
		150	H ₅₀₃	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 r_z t_z, r_x^2 r_z t_z, r_y^2 t_z^{-1}$
		[6, 20, 46, 81, 124, 176, 239, 313, 395, 488]				
		151	H ₆₄₅	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_y^2 r_x t_x, r_z^2 t_x^{-1}, m_x r_x t_x^{-1}, r_x^{-1} t_y^{-1}, m_z t_z$
		[6, 20, 46, 81, 125, 179, 243, 317, 401, 495]				
		152	H ₄₆₉	1	r_z^2	$r_z^2 t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 20, 46, 82, 125, 179, 245, 318, 402, 497]				
		153	H ₄₆₁	1	r_z^2	$r_z^2 t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, i t_z^{-1}, m_z t_z^{-1}$
		[6, 20, 46, 82, 130, 186, 254, 331, 419, 517]				
		154	H ₄₈₅	1	r_z^2	$i t_x^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 20, 47, 82, 123, 178, 243, 313, 398, 493]				
		155	H ₆₄₀	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 r_x t_x^{-1}, r_x^{-1} t_y^{-1}, m_z t_z$
		[6, 20, 48, 88, 143, 204, 279, 363, 460, 567]				
		156	H ₄₂₅	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 20, 48, 89, 143, 207, 280, 367, 463, 572]				
		157	H ₅₁₉	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z, r_y^2 t_z^{-1}$
		[6, 20, 50, 84, 131, 188, 255, 332, 421, 518]				
		158	H ₄₂₇	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 20, 50, 90, 147, 216, 295, 379, 483, 602]				
		159	H ₄₆₂	1	r_z^2	$i t_x^{-1}, r_z^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 20, 54, 101, 155, 226, 312, 410, 520, 642]				
		160	H ₅₄₁	1	r_z^2	$r_z^2 r_x t_x, m_y t_y^{-1}, i t_z, m_z t_z, i t_z^{-1}$
		[6, 21, 45, 81, 126, 178, 244, 319, 401, 495]				
		161	H ₄₂₇	1	r_z^2	$r_z^2 t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 21, 47, 81, 123, 178, 243, 313, 398, 493]				
		162	H ₄₈₆	1	r_z^2	$r_z^2 t_x^{-1}, m_y t_y^{-1}, i t_z, i t_z^{-1}, m_z t_z^{-1}$
		163	H ₅₇₁	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y^{-1}, m_z t_z$
		[6, 21, 47, 81, 128, 184, 249, 325, 412, 507]				
		164	H ₄₈₅	1	r_z^2	$i t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 21, 47, 82, 127, 182, 247, 322, 407, 502]				
		165	H ₆₂₉	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 r_x t_x^{-1}, m_z r_x t_y^{-1}, r_x^2 t_z$
		[6, 21, 47, 83, 131, 187, 255, 331, 420, 517]				
		166	H ₄₇₄	1	r_z^2	$i t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 21, 47, 84, 138, 201, 280, 367, 468, 576]				
		167	H ₅₃₃	1	r_z^2	$m_x r_z t_x^{-1}, m_x r_z t_y^{-1}, r_y^2 r_z t_z, r_x^2 r_z t_z, r_y^2 t_z^{-1}$
		[6, 21, 47, 85, 140, 206, 289, 377, 484, 596]				
		168	H ₅₃₁	1	r_z^2	$m_x r_z t_x^{-1}, m_x r_z t_y^{-1}, r_y^2 t_z, i t_z^{-1}, m_z t_z^{-1}$
		[6, 21, 48, 83, 131, 188, 255, 332, 421, 518]				
		169	H ₄₇₄	1	r_z^2	$i t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 21, 48, 89, 150, 222, 302, 397, 506, 628]				
		170	H ₅₁₁	1	r_z^2	$r_z^2 r_x t_x, r_y^2 t_y, r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 21, 48, 92, 149, 220, 302, 397, 508, 628]				
		171	H ₅₁₁	1	r_z^2	$r_z^2 r_x t_x, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 21, 49, 86, 134, 190, 259, 336, 426, 525]				
		172	H ₄₆₁	1	r_z^2	$r_z^2 t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_x^2 t_z, i t_z^{-1}$
		[6, 21, 49, 87, 134, 190, 259, 338, 427, 526]				
		173	H ₄₆₈	1	r_z^2	$r_z^2 t_x^{-1}, m_y t_y^{-1}, i t_z, i t_z^{-1}, m_z t_z^{-1}$
		[6, 21, 49, 87, 143, 205, 282, 368, 468, 576]				
		174	H ₄₆₂	1	r_z^2	$i t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 21, 50, 89, 146, 208, 284, 370, 469, 577]				
		175	H ₅₂₆	1	r_z^2	$m_x r_z t_x^{-1}, m_x r_z t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z, r_y^2 t_z^{-1}$
		[6, 21, 50, 89, 147, 212, 296, 384, 488, 600]				
		176	H ₆₃₈	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_y^2 r_x t_x, r_z^2 t_x^{-1}, m_x r_x t_x^{-1}, m_z r_x t_y^{-1}, r_x^2 t_z$
		[6, 21, 50, 90, 148, 212, 292, 380, 484, 596]				
		177	H ₅₀₇	1	r_z^2	$r_y^2 r_z t_x^{-1}, r_y^2 r_z t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		178	H ₅₂₂	1	r_z^2	$m_x r_z t_x^{-1}, m_x r_z t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 21, 51, 91, 149, 213, 294, 382, 486, 598]				

Nbr.	gr	N ₀	H_i	L	m	X
		179	H_{471}	1	r_z^2	$it_x^{-1}, it_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 21, 53, 99, 155, 226, 312, 410, 520, 642]				
		180	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		[6, 22, 46, 81, 123, 178, 243, 313, 398, 493]				
		181	H_{639}	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, r_y^2 t_z$
		[6, 22, 48, 82, 127, 182, 247, 322, 407, 502]				
		182	H_{433}	1	r_z^2	$it_x^{-1}, r_z^2 t_y^{-1}, it_z, it_z^{-1}, m_z t_z^{-1}$
		183	H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y^{-1}, r_x^2 t_z$
		[6, 22, 50, 86, 133, 190, 259, 338, 427, 526]				
		184	H_{475}	1	r_z^2	$it_x^{-1}, m_y t_y^{-1}, it_z, it_z^{-1}, m_z t_z^{-1}$
		185	H_{466}	1	r_z^2	$r_z^2 t_x^{-1}, r_x^2 t_y^{-1}, it_z, it_z^{-1}, m_z t_z^{-1}$
		[6, 22, 55, 98, 155, 226, 312, 410, 520, 642]				
		186	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_y t_y^{-1}, it_z, it_z^{-1}, m_z t_z^{-1}$
		[6, 23, 47, 82, 127, 182, 247, 322, 407, 502]				
		187	H_{631}	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, it_z$
		[6, 23, 49, 86, 133, 190, 259, 338, 427, 526]				
		188	H_{473}	1	r_z^2	$it_x^{-1}, r_x^2 t_y^{-1}, it_z, it_z^{-1}, m_z t_z^{-1}$
		[6, 23, 50, 87, 141, 202, 277, 360, 459, 566]				
		189	H_{539}	1	r_z^2	$it_x^{-1}, r_x^2 t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z, r_y^2 r_z t_z^{-1}$

3B

[5, 15, 37, 78, 142, 228, 332, 452, 588, 740]						
190*						
[5, 15, 37, 80, 151, 242, 342, 460, 602, 756]						
191*						
[5, 15, 37, 83, 156, 248, 348, 466, 608, 762]						
192*						
[5, 15, 37, 84, 150, 240, 344, 464, 600, 752]						
193*						
[5, 17, 47, 100, 172, 260, 364, 484, 620, 772]						
194*						
[5, 18, 49, 101, 172, 260, 364, 484, 620, 772]						
195*, 196*						
[5, 19, 49, 100, 172, 260, 364, 484, 620, 772]						
197*						
[6, 19, 46, 94, 164, 252, 356, 476, 612, 764]						
190	H_{766}	$\langle m_y, r_x^2 \rangle$			$m_z r_x^{-1} m_x t_x, m_x t_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, t_y^{-1}$	
[6, 19, 48, 103, 178, 262, 364, 490, 628, 774]						
191	H_{571}	1			$m_z r_x m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}$	
[6, 19, 48, 105, 179, 265, 365, 493, 629, 777]						
192	H_{561}	1			$m_z r_x m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, it_y^{-1}$	
[6, 19, 50, 104, 174, 266, 366, 490, 622, 778]						
193	H_{768}	$\langle m_y, r_x^2 \rangle$			$m_z r_x^{-1} m_x t_x, m_x t_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}$	
[6, 21, 56, 112, 184, 272, 376, 496, 632, 784]						
194	H_{766}	$\langle m_y, r_x^2 \rangle$			$m_z r_x^{-1} r_z^2 r_x t_x, m_x t_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, t_y^{-1}$	
[6, 22, 57, 112, 184, 272, 376, 496, 632, 784]						
195	H_{561}	1			$m_z r_x r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, it_y^{-1}$	
196	H_{571}	1			$m_z r_x r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}$	
[6, 23, 56, 112, 184, 272, 376, 496, 632, 784]						
197	H_{768}	$\langle m_y, r_x^2 \rangle$			$m_z r_x^{-1} r_z^2 r_x t_x, m_x t_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}$	

4A

[5, 13, 26, 45, 69, 98, 133, 173, 218, 269]						
198*, 199*						
[5, 13, 26, 46, 75, 112, 157, 213, 275, 343]						
200*						
[5, 13, 26, 47, 81, 126, 176, 236, 309, 396]						
201*						
[5, 14, 29, 50, 77, 110, 149, 194, 245, 302]						
202*, 206*, 203*, 207*, 204*, 205*						
[5, 14, 31, 57, 88, 125, 173, 228, 287, 355]						
208*						
[5, 14, 32, 59, 94, 139, 193, 256, 327, 406]						
209*, 210*						
[5, 14, 32, 59, 94, 139, 195, 262, 335, 414]						
212*, 211*						
[5, 14, 32, 68, 117, 178, 256, 346, 449, 564]						
213*						
[5, 15, 32, 55, 85, 122, 165, 215, 272, 335]						
214*, 215*						
[5, 15, 33, 58, 89, 127, 173, 226, 285, 351]						
216*						
[5, 15, 33, 59, 94, 138, 190, 250, 318, 394]						
217*						
[5, 15, 34, 61, 96, 141, 193, 253, 324, 401]						
219*						
[5, 15, 35, 64, 99, 141, 192, 251, 318, 393]						
218*						
[5, 15, 35, 65, 103, 152, 212, 279, 357, 447]						
220*						
[5, 15, 37, 70, 112, 166, 228, 299, 383, 474]						
221*						
[5, 15, 37, 71, 113, 165, 227, 299, 381, 473]						
222*						
[5, 15, 37, 76, 130, 193, 264, 353, 458, 566]						

Nbr.	gr	N ₀	H _i	L	m	X
		223*,				
		[5, 15, 38, 79, 135, 206, 290, 385, 493, 613]				
		225*,				
		[5, 15, 39, 75, 120, 177, 243, 320, 409, 507]				
		224*,				
		[5, 16, 36, 66, 106, 156, 216, 286, 366, 456]				
		226*,				
		[5, 16, 36, 67, 105, 149, 205, 268, 338, 419]				
		227*,				
		[5, 16, 36, 67, 109, 162, 225, 296, 378, 471]				
		228*,				
		[5, 16, 37, 69, 111, 163, 226, 300, 384, 478]				
		232*,				
		[5, 16, 37, 70, 115, 170, 235, 310, 395, 490]				
		234*, 235*,				
		[5, 16, 38, 68, 106, 156, 213, 278, 356, 440]				
		229*,				
		[5, 16, 38, 69, 109, 160, 218, 285, 365, 452]				
		233*,				
		[5, 16, 38, 71, 112, 163, 226, 296, 376, 469]				
		230*,				
		[5, 16, 38, 71, 113, 165, 228, 298, 378, 471]				
		231*,				
		[5, 16, 40, 80, 135, 204, 286, 381, 489, 609]				
		239*,				
		[5, 16, 41, 78, 125, 183, 252, 332, 423, 525]				
		236*,				
		[5, 16, 41, 79, 128, 187, 258, 342, 436, 540]				
		237*,				
		[5, 16, 43, 84, 133, 194, 266, 349, 444, 550]				
		238*,				
		[5, 17, 40, 73, 114, 165, 228, 298, 378, 471]				
		240*,				
		[5, 17, 40, 73, 116, 169, 232, 305, 388, 481]				
		241*,				
		[5, 17, 40, 74, 118, 171, 234, 307, 390, 483]				
		242*,				
		[5, 17, 41, 76, 121, 176, 242, 319, 406, 503]				
		243*, 244*,				
		[5, 17, 41, 76, 124, 184, 253, 333, 424, 525]				
		245*,				
		[5, 17, 43, 84, 139, 208, 290, 385, 493, 613]				
		247*,				
		[5, 17, 43, 86, 148, 224, 311, 415, 535, 664]				
		246*,				
		[5, 18, 42, 75, 118, 171, 234, 307, 390, 483]				
		248*,				
		[5, 18, 43, 78, 123, 178, 244, 321, 408, 505]				
		249*,				
		[6, 17, 36, 63, 96, 138, 188, 243, 308, 381]				
		198	H ₃₀₂	1	i	$t_x, it_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, m_z t_z^{-1}$
		199	H ₆₅₉	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, r_x^{-1} t_z^{-1}$
		[6, 17, 36, 65, 101, 146, 203, 264, 333, 416]				
		200	H ₄₁₂	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, m_z t_z^{-1}$
		[6, 17, 36, 67, 106, 154, 213, 281, 363, 459]				
		201	H ₆₅₈	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
		[6, 18, 38, 66, 102, 146, 198, 258, 326, 402]				
		202	H ₆₅₄	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, it_y^{-1}, r_z^2 r_x t_z^{-1}$
		203	H ₆₅₆	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z^{-1}$
		204	H ₃₀₄	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_z^{-1}, r_z^2 t_y^{-1}, m_z t_z^{-1}$
		[6, 18, 38, 67, 104, 148, 201, 262, 331, 409]				
		205	H ₃₁₆	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_z^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
		[6, 18, 39, 68, 105, 150, 204, 266, 336, 414]				
		206	H ₃₀₀	1	i	$t_x, it_x^{-1}, t_x^{-1}, it_y^{-1}, m_z t_z^{-1}$
		207	H ₃₁₄	1	i	$t_x, it_x^{-1}, t_x^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
		[6, 18, 40, 72, 111, 160, 219, 284, 360, 447]				
		208	H ₄₂₂	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
		[6, 18, 41, 72, 113, 162, 222, 292, 370, 458]				
		209	H ₃₀₁	1	i	$t_x, it_x^{-1}, t_x^{-1}, it_y^{-1}, r_z^2 t_z^{-1}$
		210	H ₃₀₁	1	i	$it_x^{-1}, t_y, it_y^{-1}, t_y^{-1}, r_y^2 t_z^{-1}$
		[6, 18, 41, 72, 113, 162, 223, 292, 370, 456]				
		211	H ₃₉₄	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, it_y^{-1}, r_z^2 t_z^{-1}$
		[6, 18, 41, 72, 114, 166, 230, 304, 384, 474]				
		212	H ₃₁₂	1	i	$t_x, it_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_x^2 t_z^{-1}$
		[6, 18, 45, 87, 138, 208, 292, 388, 496, 616]				
		213	H ₃₀₈	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_z^{-1}, r_z^2 t_y, r_y^2 r_z t_z^{-1}$
		[6, 19, 41, 71, 110, 158, 214, 279, 353, 435]				
		214	H ₃₀₂	1	i	$it_x^{-1}, m_z t_y, r_z^2 t_y^{-1}, m_z t_y^{-1}, m_z t_z^{-1}$
		[6, 19, 41, 71, 111, 158, 216, 280, 355, 437]				
		215	H ₃₁₇	1	i	$r_z^2 t_x^{-1}, m_y t_y^{-1}, m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
		[6, 19, 41, 72, 111, 159, 217, 282, 356, 440]				
		216	H ₃₁₇	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_z^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
		[6, 19, 41, 73, 114, 164, 225, 295, 374, 463]				
		217	H ₃₁₅	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_z^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$

Nbr.	gr	N ₀	H _i	L	m	X
[6, 19, 42, 75, 116, 166, 226, 293, 372, 458]		218	H ₄₂₃	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
[6, 19, 43, 75, 118, 170, 231, 302, 383, 472]		219	H ₃₁₈	1	i	$r_z^2 t_x^{-1}, m_y t_y^{-1}, m_x t_z, m_x t_z^{-1}, r_x^2 t_z^{-1}$
[6, 19, 43, 76, 117, 171, 234, 303, 387, 480]		220	H ₆₆₁	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_y t_y^{-1}, r_x^{-1} t_z^{-1}$
[6, 19, 45, 79, 126, 183, 250, 327, 416, 513]		221	H ₃₁₅	1	i	$r_z^2 t_x^{-1}, m_z t_y, r_z^2 t_y^{-1}, m_z t_y^{-1}, r_y^2 t_z^{-1}$
[6, 19, 45, 82, 134, 193, 264, 345, 438, 541]		222	H ₃₁₅	1	i	$r_z^2 t_x^{-1}, r_z^2 t_y^{-1}, m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
[6, 19, 45, 86, 143, 206, 283, 375, 480, 590]		223	H ₃₁₁	1	i	$it_x^{-1}, r_z^2 t_y^{-1}, m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
[6, 19, 47, 84, 140, 201, 275, 360, 458, 564]		224	H ₄₀₉	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z^{-1}$
[6, 19, 50, 95, 152, 225, 311, 409, 519, 641]		225	H ₃₂₆	1	i	$r_z^2 r_x t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, m_z t_z, r_z^2 t_z^{-1}$
[6, 20, 43, 77, 120, 174, 237, 311, 394, 488]		226	H ₆₅₇	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z^{-1}$
[6, 20, 44, 79, 123, 174, 239, 311, 392, 485]		227	H ₃₁₉	1	i	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z^{-1}$
[6, 20, 44, 80, 126, 180, 248, 326, 414, 512]		228	H ₃₁₂	1	i	$it_x^{-1}, m_z t_y, r_z^2 t_y^{-1}, m_z t_y^{-1}, r_x^2 t_z^{-1}$
[6, 20, 45, 77, 120, 173, 234, 305, 387, 476]		229	H ₃₀₃	1	i	$it_x^{-1}, m_x t_y, m_x t_y^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z^{-1}$
[6, 20, 45, 80, 122, 177, 242, 312, 397, 492]		230	H ₃₁₆	1	i	$r_z^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
[6, 20, 45, 80, 123, 178, 243, 313, 398, 493]		231	H ₄₁₃	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_x^2 t_y^{-1}, m_z t_z^{-1}$
[6, 20, 45, 81, 126, 182, 249, 327, 414, 512]		232	H ₃₁₆	1	i	$r_z^2 t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$
[6, 20, 46, 80, 125, 179, 243, 317, 402, 495]		233	H ₃₁₄	1	i	$it_x^{-1}, m_y t_y^{-1}, m_x t_z, m_x t_z^{-1}, r_x^2 t_z^{-1}$
[6, 20, 46, 83, 134, 197, 272, 358, 456, 565]		234	H ₃₀₅	1	i	$t_x, it_x^{-1}, t_x^{-1}, it_y^{-1}, r_y^2 r_z t_z^{-1}$
[6, 20, 47, 85, 137, 201, 278, 366, 466, 577]		235	H ₃₀₅	1	i	$t_x, it_x^{-1}, t_x^{-1}, it_y, r_y^2 r_z t_z^{-1}$
[6, 20, 48, 85, 138, 197, 270, 351, 446, 549]		236	H ₃₀₁	1	i	$it_x^{-1}, it_y^{-1}, m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
[6, 20, 48, 87, 143, 203, 280, 365, 463, 569]		237	H ₃₁₂	1	i	$it_x^{-1}, r_z^2 t_y^{-1}, m_x t_z, m_x t_z^{-1}, r_x^2 t_z^{-1}$
[6, 20, 49, 89, 143, 207, 280, 367, 463, 572]		238	H ₄₀₆	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z^{-1}$
[6, 20, 50, 93, 150, 221, 307, 405, 515, 637]		239	H ₃₀₈	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
[6, 21, 46, 81, 123, 178, 243, 313, 398, 493]		240	H ₆₆₀	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_x^2 t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
[6, 21, 46, 81, 126, 181, 246, 321, 406, 501]		241	H ₃₀₂	1	i	$it_x^{-1}, r_z^2 t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$
[6, 21, 46, 82, 127, 182, 247, 322, 407, 502]		242	H ₃₉₅	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, it_y^{-1}, r_x^2 t_z^{-1}$
[6, 21, 48, 85, 132, 189, 258, 337, 426, 525]		243	H ₃₁₃	1	i	$it_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$
[6, 21, 48, 86, 133, 190, 259, 338, 427, 526]		244	H ₃₁₇	1	i	$r_z^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
[6, 21, 50, 90, 146, 213, 292, 384, 488, 603]		245	H ₃₂₃	1	i	$r_z^2 t_x^{-1}, r_x^2 r_y t_y^{-1}, m_x t_z, r_x^2 t_z, m_x t_z^{-1}$
[6, 21, 51, 95, 157, 232, 323, 428, 549, 680]		246	H ₃₂₃	1	i	$r_z^2 t_x^{-1}, r_x^2 r_y t_y^{-1}, m_x t_z, m_x t_z^{-1}, r_x^2 t_z^{-1}$
[6, 21, 53, 97, 154, 225, 311, 409, 519, 641]		247	H ₃₂₆	1	i	$r_z^2 r_x t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$
[6, 22, 47, 82, 127, 182, 247, 322, 407, 502]		248	H ₆₅₅	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, it_y^{-1}, r_z^2 r_x t_z^{-1}$
[6, 22, 49, 86, 133, 190, 259, 338, 427, 526]		249	H ₃₁₄	1	i	$it_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
4B						
[5, 14, 32, 64, 112, 176, 256, 352, 464, 592]		250*				
[5, 14, 32, 65, 120, 201, 300, 409, 537, 692]		251*				
[5, 14, 32, 68, 124, 208, 312, 424, 555, 711]		252*				
[5, 14, 32, 68, 130, 210, 310, 430, 566, 718]		253*				
[5, 16, 42, 88, 152, 232, 328, 440, 568, 712]		254*				
[5, 17, 46, 98, 171, 260, 364, 484, 620, 772]		255*				
[5, 17, 46, 98, 172, 261, 364, 484, 620, 772]		256*				

4B

Nbr.	gr	N ₀	H_i	L	m	X
		275	H_{323}	1	i	$r_z^2 t_x, m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 r_y t_y^{-1}, r_z^2 t_z^{-1}$
5B						
[6, 19, 48, 100, 172, 260, 364, 484, 620, 772]						
276*						
[7, 22, 56, 112, 184, 272, 376, 496, 632, 784]						
		276	H_{779}	$\langle i, r_x^2, r_z^2 \rangle$	$r_z^2 r_x$	$m_x t_x, m_z r_x^{-1} t_x, t_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, t_y^{-1}$
6						
[4, 10, 24, 52, 104, 180, 268, 354, 452, 570]						
308*						
[4, 11, 27, 64, 127, 209, 291, 377, 477, 591]						
317*						
[4, 11, 30, 65, 109, 159, 217, 283, 357, 442]						
314*						
[4, 11, 30, 65, 112, 164, 229, 302, 383, 486]						
316*						
[4, 11, 30, 65, 116, 181, 258, 347, 449, 565]						
315*						
[4, 11, 30, 66, 119, 190, 262, 342, 438, 547]						
318*						
[4, 11, 30, 67, 135, 213, 285, 375, 478, 600]						
319*						
[4, 12, 30, 66, 107, 154, 211, 278, 353, 438]						
328*, 329*						
[4, 12, 30, 66, 114, 174, 243, 326, 419, 526]						
333*						
[4, 12, 30, 66, 124, 195, 272, 368, 472, 589]						
335*						
[4, 12, 33, 73, 129, 189, 257, 343, 441, 549]						
334*						
[4, 12, 33, 78, 140, 210, 292, 389, 499, 617]						
331*						
[4, 12, 36, 76, 123, 176, 241, 318, 401, 500]						
336*						
[5, 13, 27, 51, 86, 130, 182, 242, 310, 386]						
		277	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
		278	H_{419}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
[5, 14, 30, 54, 87, 130, 182, 242, 310, 386]						
		279	H_{415}	1	$r_z^2 r_x$	$it_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
		280	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1}$
[5, 14, 31, 56, 85, 120, 165, 216, 271, 334]						
		281	H_{413}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_y t_y, r_x^{-1} t_y^{-1}, r_x t_z$
[5, 14, 31, 58, 94, 138, 190, 250, 318, 394]						
		282	H_{402}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
		283	H_{404}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
[5, 14, 31, 59, 100, 155, 223, 303, 395, 500]						
		284	H_{413}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, m_z t_z^{-1}$
[5, 14, 31, 60, 105, 165, 232, 306, 398, 507]						
		285	H_{412}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, m_z t_z^{-1}$
[5, 15, 33, 58, 89, 127, 173, 226, 285, 351]						
		286	H_{395}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, r_x^2 t_z^{-1}$
[5, 15, 33, 59, 94, 138, 190, 250, 318, 394]						
		287	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^2 t_y, r_x^2 t_y^{-1}, r_x^2 t_z^{-1}$
		288	H_{401}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
[5, 15, 33, 60, 101, 156, 222, 303, 396, 499]						
		289	H_{413}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_y^2 t_z$
[5, 15, 34, 59, 89, 130, 177, 227, 290, 359]						
		290	H_{412}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_y t_y, r_x^{-1} t_y^{-1}, r_x t_z$
[5, 15, 36, 68, 106, 152, 208, 271, 344, 427]						
		291	H_{418}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x t_z^{-1}$
[5, 15, 36, 71, 115, 175, 248, 322, 415, 519]						
		292	H_{407}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x t_z^{-1}$
[5, 16, 34, 60, 95, 138, 190, 250, 318, 394]						
		293	H_{396}	1	$r_z^2 r_x$	$it_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
		294	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
[5, 16, 34, 64, 107, 166, 238, 326, 426, 542]						
		295	H_{418}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
[5, 16, 35, 60, 93, 134, 181, 236, 299, 368]						
		296	H_{394}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, r_x^2 t_z^{-1}$
[5, 16, 35, 62, 98, 142, 194, 254, 322, 398]						
		297	H_{391}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
		298	H_{392}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
[5, 16, 38, 68, 106, 156, 213, 278, 356, 440]						
		299	H_{388}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_z^{-1}$
[5, 16, 38, 69, 108, 155, 209, 274, 347, 427]						
		300	H_{419}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z$
[5, 16, 38, 69, 109, 160, 218, 285, 365, 452]						
		301	H_{400}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_z^{-1}$
[5, 16, 38, 70, 114, 174, 246, 329, 427, 537]						
		302	H_{395}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_x^2 t_y, it_y^{-1}, r_x^2 t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
		[5, 16, 38, 72, 120, 186, 261, 344, 447, 566]				
	303	H_{394}	1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_x^2 t_y, it_y^{-1}, r_x^2 t_z^{-1}$
		[5, 16, 38, 74, 125, 189, 265, 354, 455, 568]				
	304	H_{412}	1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_y^2 t_z$
		[5, 16, 38, 78, 133, 204, 288, 388, 500, 628]				
	305	H_{407}	1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
		[5, 16, 39, 78, 126, 190, 266, 358, 462, 582]				
	306	H_{414}	1		$r_z^2 r_x$	$it_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
		[5, 16, 39, 80, 136, 208, 292, 392, 504, 632]				
	307	H_{410}	1		$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
		[5, 16, 43, 81, 137, 201, 286, 377, 482, 597]				
	308	H_{422}	1		$r_z^2 r_x$	$r_z^2 t_x, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z, m_z t_z^{-1}$
		[5, 17, 39, 74, 116, 168, 228, 298, 376, 466]				
	309	H_{413}	1		$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x^{-1} t_y, r_z^2 t_y^{-1}, m_x r_x t_z^{-1}$
		[5, 17, 40, 78, 126, 192, 269, 352, 449, 562]				
	310	H_{412}	1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, r_z^2 t_y^{-1}, m_x r_x t_z^{-1}$
		[5, 17, 41, 74, 117, 171, 232, 304, 388, 478]				
	311	H_{401}	1		$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
		[5, 17, 41, 75, 122, 184, 256, 343, 445, 555]				
	312	H_{395}	1		$r_z^2 r_x$	$m_x t_x^{-1}, it_y^{-1}, it_z, r_x^2 t_z^{-1}$
		[5, 17, 41, 76, 123, 182, 248, 324, 417, 516]				
	313	H_{402}	1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z$
		[5, 17, 44, 81, 130, 188, 256, 334, 419, 524]				
	314	H_{410}	1		$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x t_z^{-1}$
		[5, 17, 44, 81, 136, 205, 286, 381, 493, 616]				
	315	H_{414}	1		$r_z^2 r_x$	$it_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x t_z^{-1}$
		[5, 17, 44, 83, 129, 185, 261, 329, 423, 533]				
	316	H_{422}	1		$r_z^2 r_x$	$r_z^2 t_x, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z$
		[5, 17, 46, 88, 149, 218, 299, 396, 498, 618]				
	317	H_{409}	1		$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
		[5, 17, 47, 88, 140, 209, 286, 378, 469, 586]				
	318	H_{404}	1		$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z$
		[5, 17, 47, 91, 150, 223, 308, 402, 503, 631]				
	319	H_{415}	1		$r_z^2 r_x$	$it_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z$
		[5, 18, 41, 78, 124, 182, 249, 328, 417, 518]				
	320	H_{393}	1		$r_z^2 r_x$	$r_y^2 r_z t_x, r_y^2 r_z t_y, r_x^2 r_y t_y^{-1}, r_y^2 r_z t_z$
		[5, 18, 41, 78, 128, 194, 272, 366, 472, 594]				
	321	H_{389}	1		$r_z^2 r_x$	$it_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$
		[5, 18, 42, 79, 124, 181, 247, 325, 412, 511]				
	322	H_{395}	1		$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y, it_y^{-1}, r_y^2 r_x t_z^{-1}$
		[5, 18, 42, 80, 129, 194, 272, 366, 472, 594]				
	323	H_{400}	1		$r_z^2 r_x$	$m_x t_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$
		[5, 18, 43, 81, 131, 191, 263, 347, 443, 549]				
	324	H_{391}	1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
		[5, 18, 43, 82, 135, 202, 280, 372, 478, 594]				
	325	H_{394}	1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, it_y^{-1}, it_z, r_x^2 t_z^{-1}$
		[5, 18, 43, 83, 134, 199, 275, 367, 467, 581]				
	326	H_{394}	1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y, it_y^{-1}, r_y^2 r_x t_z^{-1}$
		[5, 18, 43, 84, 137, 206, 286, 382, 489, 612]				
	327	H_{388}	1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$
		[5, 18, 44, 82, 126, 183, 248, 325, 411, 508]				
	328	H_{389}	1		$r_z^2 r_x$	$it_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_z^{-1}$
		[5, 18, 44, 83, 129, 185, 254, 332, 420, 518]				
	329	H_{398}	1		$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_z^{-1}$
		[5, 18, 44, 86, 140, 210, 292, 390, 500, 626]				
	330	H_{398}	1		$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$
		[5, 18, 46, 94, 160, 233, 318, 430, 547, 665]				
	331	H_{393}	1		$r_z^2 r_x$	$r_y^{-1} r_z^{-1} t_x^{-1}, r_y r_x t_y, r_x^2 r_y t_y^{-1}, r_y^2 r_z t_z$
		[5, 18, 47, 87, 140, 207, 284, 376, 480, 596]				
	332	H_{393}	1		$r_z^2 r_x$	$r_y^{-1} r_z^{-1} t_x^{-1}, r_y r_x t_y, r_y^{-1} r_z^{-1} t_y^{-1}, r_y r_x t_z$
		[5, 18, 47, 88, 141, 204, 282, 369, 471, 582]				
	333	H_{392}	1		$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
		[5, 18, 47, 88, 142, 203, 279, 368, 467, 576]				
	334	H_{409}	1		$r_z^2 r_x$	$r_z^2 t_x, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z$
		[5, 18, 47, 91, 146, 217, 305, 401, 508, 633]				
	335	H_{396}	1		$r_z^2 r_x$	$it_x^{-1}, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
		[5, 18, 49, 90, 137, 199, 270, 351, 446, 548]				
	336	H_{393}	1		$r_z^2 r_x$	$r_y^2 r_z t_x, r_y^2 r_z t_y, r_y^{-1} r_z^{-1} t_y^{-1}, r_y r_x t_z$

7A

- [5, 13, 26, 45, 69, 98, 133, 173, 218, 269]
 337*,
 [5, 14, 31, 57, 90, 131, 181, 238, 303, 377]
 339*,
 [5, 14, 31, 57, 91, 134, 185, 244, 313, 390]
 338*,
 [5, 14, 31, 57, 91, 136, 192, 253, 320, 399]
 340*,

Nbr.	gr	Nº	H_i	L	m	X
[5, 14, 34, 71, 120, 185, 258, 341, 438, 547]						
			342*			
[5, 14, 34, 72, 127, 193, 269, 359, 461, 573]			341*			
[5, 15, 32, 55, 85, 122, 165, 215, 272, 335]			343*			
[5, 15, 33, 61, 99, 146, 202, 267, 341, 425]			344*			
[5, 15, 34, 67, 111, 162, 229, 302, 383, 486]			345*			
[5, 15, 38, 74, 127, 194, 270, 356, 457, 571]			346*			
[5, 16, 36, 67, 109, 162, 225, 296, 378, 471]			350*			
[5, 16, 37, 66, 103, 150, 205, 268, 341, 422]			348*, 352*			
[5, 16, 37, 66, 105, 157, 217, 283, 357, 442]			353*			
[5, 16, 37, 67, 107, 158, 217, 286, 367, 455]			349*			
[5, 16, 37, 71, 117, 170, 236, 314, 399, 498]			351*			
[5, 16, 37, 72, 117, 176, 245, 328, 421, 528]			355*			
[5, 16, 37, 72, 122, 188, 271, 355, 445, 559]			347*			
[5, 16, 39, 78, 134, 202, 280, 374, 485, 604]			354*			
[5, 16, 39, 79, 135, 204, 281, 373, 481, 602]			356*			
[5, 17, 40, 73, 116, 170, 235, 310, 395, 491]			357*			
[5, 17, 41, 77, 127, 187, 258, 345, 443, 551]			358*			
[5, 17, 41, 81, 137, 204, 283, 373, 478, 597]			359*			
[5, 18, 39, 70, 109, 158, 215, 282, 357, 442]			360*, 361*			
[5, 18, 43, 76, 121, 176, 241, 318, 401, 500]			362*			
[5, 18, 43, 81, 131, 191, 263, 347, 443, 549]			363*			
[5, 18, 43, 83, 136, 203, 282, 377, 481, 599]			365*			
[5, 18, 46, 88, 140, 204, 284, 376, 478, 594]			364*			
[5, 18, 47, 87, 140, 207, 284, 376, 480, 596]			366*			
[6, 17, 36, 64, 98, 140, 191, 248, 313, 387]			337	H_{413}	1	$r_z^2 r_x$ $m_x t_x^{-1}$, $r_z^2 t_y^{-1}$, $r_x^{-1} t_y^{-1}$, $r_x t_z$, $m_z t_z^{-1}$
[6, 18, 40, 71, 109, 156, 211, 275, 348, 429]			338	H_{419}	1	$r_z^2 r_x$ $m_x t_x^{-1}$, $m_x r_x^{-1} t_y^{-1}$, $m_y t_y^{-1}$, $m_x r_x t_z$, $m_z t_z^{-1}$
[6, 18, 41, 73, 114, 163, 222, 289, 366, 452]			339	H_{418}	1	$r_z^2 r_x$ $m_x t_x^{-1}$, $r_z^2 t_y^{-1}$, $r_x^{-1} t_y^{-1}$, $r_x t_z$, $r_y^2 t_z^{-1}$
[6, 18, 41, 74, 115, 171, 236, 304, 387, 479]			340	H_{412}	1	$r_z^2 r_x$ $r_z^2 r_x t_x^{-1}$, $r_z^2 t_y^{-1}$, $r_x^{-1} t_y^{-1}$, $r_x t_z$, $m_z t_z^{-1}$
[6, 18, 43, 83, 141, 208, 292, 382, 487, 607]			341	H_{407}	1	$r_z^2 r_x$ $r_z^2 r_x t_x^{-1}$, $r_z^2 t_y^{-1}$, $r_x^{-1} t_y^{-1}$, $r_x t_z$, $r_y^2 t_z^{-1}$
[6, 18, 47, 88, 140, 209, 286, 378, 469, 586]			342	H_{404}	1	$r_z^2 r_x$ $r_y^2 r_x t_x^{-1}$, $m_x r_x^{-1} t_y^{-1}$, $m_y t_y^{-1}$, $m_x r_x t_z$, $m_z t_z^{-1}$
[6, 19, 41, 72, 111, 159, 217, 282, 356, 440]			343	H_{395}	1	$r_z^2 r_x$ $m_x t_x^{-1}$, $i t_y^{-1}$, $m_z r_x t_y^{-1}$, $m_z r_x t_z$, $r_x^2 t_z^{-1}$
[6, 19, 42, 76, 118, 170, 230, 300, 378, 468]			344	H_{413}	1	$r_z^2 r_x$ $m_x t_x^{-1}$, $m_x r_x^{-1} t_y$, $r_z^2 t_y^{-1}$, $m_x r_x t_z^{-1}$, $m_z t_z^{-1}$
[6, 19, 43, 83, 129, 185, 261, 329, 423, 533]			345	H_{422}	1	$r_z^2 r_x$ $r_z^2 t_x$, $m_y t_y$, $m_x r_x^{-1} t_y^{-1}$, $m_x r_x t_z$, $m_z t_z$
[6, 19, 48, 87, 145, 211, 290, 379, 483, 600]			346	H_{422}	1	$r_z^2 r_x$ $r_z^2 t_x$, $m_x r_x^{-1} t_y^{-1}$, $m_y t_y^{-1}$, $m_x r_x t_z$, $m_z t_z^{-1}$
[6, 20, 44, 85, 137, 208, 293, 372, 471, 591]			347	H_{412}	1	$r_z^2 r_x$ $r_z^2 r_x t_x^{-1}$, $m_x r_x^{-1} t_y$, $r_z^2 t_y^{-1}$, $m_x r_x t_z^{-1}$, $m_z t_z^{-1}$
[6, 20, 45, 77, 120, 173, 234, 305, 387, 476]			348	H_{388}	1	$r_z^2 r_x$ $r_z^2 r_x t_x^{-1}$, $i t_y^{-1}$, $m_z r_x t_y^{-1}$, $m_z r_x t_z$, $i t_z^{-1}$
[6, 20, 45, 79, 124, 177, 240, 315, 397, 489]			349	H_{401}	1	$r_z^2 r_x$ $m_x t_x^{-1}$, $r_y^2 r_x t_y^{-1}$, $r_x^2 t_y^{-1}$, $r_y^2 r_x t_z$, $r_x^2 t_z^{-1}$
[6, 20, 45, 81, 128, 188, 259, 339, 427, 529]			350	H_{394}	1	$r_z^2 r_x$ $r_z^2 r_x t_x^{-1}$, $i t_y^{-1}$, $m_z r_x t_y^{-1}$, $m_z r_x t_z$, $r_x^2 t_z^{-1}$
[6, 20, 45, 85, 132, 188, 262, 339, 428, 535]			351	H_{402}	1	$r_z^2 r_x$ $r_z^2 r_x t_x^{-1}$, $m_x r_x^{-1} t_y^{-1}$, $m_y t_y^{-1}$, $m_x r_x t_z^{-1}$, $m_z t_z^{-1}$
[6, 20, 46, 80, 125, 179, 243, 317, 402, 495]			352	H_{400}	1	$r_z^2 r_x$ $m_x t_x^{-1}$, $i t_y^{-1}$, $m_z r_x t_y^{-1}$, $m_z r_x t_z$, $i t_z^{-1}$
[6, 20, 47, 81, 131, 191, 259, 338, 423, 526]			353	H_{410}	1	$r_z^2 r_x$ $r_y^2 r_x t_x^{-1}$, $r_z^2 t_y^{-1}$, $r_x^{-1} t_y^{-1}$, $r_x t_z$, $r_y^2 t_z^{-1}$
[6, 20, 48, 88, 145, 214, 297, 395, 508, 628]			354	H_{414}	1	$r_z^2 r_x$ $i t_x^{-1}$, $r_z^2 t_y^{-1}$, $r_x^{-1} t_y^{-1}$, $r_x t_z$, $r_y^2 t_z^{-1}$
[6, 20, 49, 88, 142, 205, 283, 370, 472, 583]						

Nbr.	gr	N _i	H_i	L	m	X
		355	H_{392}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
[6, 20, 50, 94, 152, 220, 305, 402, 508, 629]		356	H_{415}	1	$r_z^2 r_x$	$it_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z^{-1}$
[6, 21, 48, 85, 132, 190, 258, 337, 426, 526]		357	H_{395}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y, it_y^{-1}, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
[6, 21, 49, 88, 142, 204, 280, 369, 468, 577]		358	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z$
[6, 21, 50, 93, 150, 219, 300, 393, 502, 618]		359	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
[6, 22, 47, 83, 128, 185, 250, 327, 413, 510]		360	H_{389}	1	$r_z^2 r_x$	$it_x^{-1}, it_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, it_z^{-1}$
[6, 22, 48, 85, 132, 189, 258, 336, 425, 524]		361	H_{398}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, it_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, it_z^{-1}$
[6, 22, 50, 89, 137, 199, 270, 351, 446, 548]		362	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_y, r_y^{-1} r_z^{-1} t_y^{-1}, r_y^2 r_x t_z, r_y r_x t_z$
[6, 22, 50, 92, 144, 206, 282, 370, 466, 576]		363	H_{391}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
[6, 22, 52, 96, 151, 219, 301, 394, 498, 617]		364	H_{394}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y, it_y^{-1}, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
[6, 22, 53, 96, 155, 224, 309, 405, 515, 637]		365	H_{396}	1	$r_z^2 r_x$	$it_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
[6, 22, 56, 96, 156, 222, 306, 398, 508, 624]		366	H_{393}	1	$r_z^2 r_x$	$r_y^{-1} r_z^{-1} t_x^{-1}, r_y r_x t_y, r_y^{-1} r_z^{-1} t_y^{-1}, r_y^2 r_x t_z, r_y r_x t_z$

7B

[5, 14, 34, 68, 112, 170, 244, 326, 420, 532]
367 ^a ,
[5, 15, 37, 77, 129, 189, 267, 358, 454, 569]
369 ^a ,
[5, 15, 38, 77, 126, 183, 253, 336, 429, 535]
368 ^a ,
[5, 15, 39, 77, 128, 193, 266, 350, 453, 570]
370 ^a ,
[5, 15, 39, 81, 135, 202, 284, 380, 490, 614]
371 ^a ,
[5, 15, 41, 84, 134, 200, 278, 367, 471, 591]
372 ^a ,
[5, 15, 41, 86, 147, 226, 320, 418, 530, 661]
374 ^a ,
[5, 15, 41, 91, 152, 230, 320, 421, 537, 670]
375 ^a ,
[5, 15, 42, 90, 151, 228, 315, 412, 525, 654]
373 ^a ,
[5, 16, 41, 84, 142, 211, 294, 390, 499, 624]
376 ^a ,
[5, 16, 41, 84, 142, 212, 289, 382, 493, 613]
377 ^a ,
[5, 16, 42, 89, 149, 214, 289, 380, 485, 599]
378 ^a ,
[5, 16, 42, 89, 152, 227, 313, 413, 530, 661]
379 ^a ,
[5, 16, 42, 95, 157, 229, 317, 421, 534, 663]
382 ^a ,
[5, 16, 45, 95, 155, 225, 308, 403, 513, 637]
380 ^a ,
[5, 16, 45, 96, 154, 217, 297, 392, 499, 618]
381 ^a ,
[5, 16, 45, 98, 161, 234, 319, 418, 530, 655]
383 ^a ,
[5, 17, 45, 87, 141, 207, 285, 378, 482, 597]
385 ^a ,
[5, 17, 45, 88, 153, 236, 323, 420, 531, 661]
384 ^a ,
[5, 17, 45, 96, 165, 242, 330, 430, 544, 674]
386 ^a ,
[5, 17, 47, 93, 155, 232, 317, 419, 541, 672]
389 ^a ,
[5, 17, 47, 94, 155, 229, 318, 419, 536, 665]
387 ^a ,
[5, 17, 49, 96, 155, 227, 316, 415, 528, 655]
388 ^a ,
[5, 18, 48, 102, 161, 233, 320, 423, 538, 669]
392 ^a ,
[5, 18, 50, 100, 155, 223, 305, 399, 509, 629]
390 ^a ,
[5, 18, 50, 101, 160, 225, 309, 407, 509, 632]
395 ^a ,
[5, 18, 50, 102, 161, 233, 321, 423, 539, 669]
396 ^a ,
[5, 18, 50, 104, 162, 231, 318, 419, 532, 661]
393 ^a ,
[5, 18, 51, 103, 166, 239, 327, 429, 542, 672]
391 ^a ,
[5, 18, 52, 102, 156, 222, 303, 396, 503, 622]
394 ^a ,
[6, 18, 45, 87, 138, 205, 287, 374, 477, 599]
367
H_{413}
1
$r_z^2 r_x$
$m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z$
[6, 19, 48, 92, 143, 204, 281, 367, 464, 577]

Nbr.	gr	H_i	L	m	X
		368	H_{419}	1	$r_z^2 r_x m_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z$
	[6, 19, 48, 95, 148, 215, 305, 394, 496, 629]	369	H_{395}	1	$r_z^2 r_x m_x t_x^{-1}, r_z^2 t_y, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z$
	[6, 19, 50, 90, 145, 213, 290, 377, 481, 599]	370	H_{412}	1	$r_z^2 r_x r_z^2 r_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z$
	[6, 19, 50, 97, 157, 230, 319, 420, 537, 666]	371	H_{418}	1	$r_z^2 r_x m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z$
	[6, 19, 52, 98, 150, 226, 302, 400, 506, 636]	372	H_{422}	1	$r_z^2 r_x r_z^2 t_x, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z$
	[6, 19, 52, 101, 162, 241, 323, 428, 541, 673]	373	H_{407}	1	$r_z^2 r_x r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z$
	[6, 19, 53, 101, 164, 242, 332, 434, 549, 680]	374	H_{422}	1	$r_z^2 r_x r_z^2 t_x, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z, m_z t_z, m_z t_z^{-1}$
	[6, 19, 55, 106, 165, 247, 341, 443, 557, 691]	375	H_{415}	1	$r_z^2 r_x i t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z$
	[6, 20, 51, 99, 160, 232, 321, 419, 534, 663]	376	H_{413}	1	$r_z^2 r_x m_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1}, m_x r_x t_z^{-1}$
	[6, 20, 52, 97, 154, 223, 306, 400, 508, 628]	377	H_{394}	1	$r_z^2 r_x r_z^2 r_x t_x^{-1}, r_z^2 t_y, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z$
	[6, 20, 52, 102, 159, 224, 305, 400, 504, 622]	378	H_{401}	1	$r_z^2 r_x m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_z^2 t_y^{-1}, r_z^2 r_x t_z$
	[6, 20, 53, 104, 169, 244, 334, 439, 560, 691]	379	H_{400}	1	$r_z^2 r_x m_x t_x^{-1}, i t_y, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z$
	[6, 20, 55, 104, 163, 234, 319, 417, 530, 654]	380	H_{388}	1	$r_z^2 r_x r_z^2 r_x t_x^{-1}, i t_y, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z$
	[6, 20, 56, 106, 162, 231, 315, 412, 521, 640]	381	H_{409}	1	$r_z^2 r_x r_z^2 t_x, r_z^2 t_y, r_z^2 r_x t_y^{-1}, r_z^2 t_y^{-1}, r_z^2 r_x t_z$
	[6, 20, 56, 109, 169, 248, 340, 444, 559, 696]	382	H_{396}	1	$r_z^2 r_x i t_x^{-1}, r_z^2 t_y, r_z^2 r_x t_y^{-1}, r_z^2 t_y^{-1}, r_z^2 r_x t_z$
	[6, 20, 57, 108, 168, 243, 330, 434, 544, 671]	383	H_{409}	1	$r_z^2 r_x r_z^2 t_x, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z, r_z^2 t_z^{-1}, r_z^2 t_z^{-1}$
	[6, 21, 53, 97, 168, 244, 331, 432, 545, 677]	384	H_{412}	1	$r_z^2 r_x r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1}, m_x r_x t_z^{-1}$
	[6, 21, 54, 97, 154, 220, 302, 397, 500, 619]	385	H_{402}	1	$r_z^2 r_x r_z^2 r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z$
	[6, 21, 55, 109, 175, 249, 340, 441, 559, 690]	386	H_{395}	1	$r_z^2 r_x m_x t_x^{-1}, r_z^2 r_x t_y, r_z^2 t_y, i t_y^{-1}, r_z^2 r_x t_z^{-1}$
	[6, 21, 58, 104, 172, 243, 342, 437, 568, 687]	387	H_{414}	1	$r_z^2 r_x i t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z$
	[6, 21, 59, 104, 168, 238, 332, 427, 550, 670]	388	H_{410}	1	$r_z^2 r_x r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z$
	[6, 21, 59, 105, 170, 245, 338, 444, 561, 690]	389	H_{404}	1	$r_z^2 r_x r_z^2 r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z$
	[6, 22, 59, 106, 162, 232, 316, 414, 522, 644]	390	H_{391}	1	$r_z^2 r_x r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 r_x t_y^{-1}, r_z^2 t_y^{-1}, r_z^2 r_x t_z$
	[6, 22, 59, 108, 173, 244, 336, 437, 554, 684]	391	H_{394}	1	$r_z^2 r_x r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, r_z^2 t_y, i t_y^{-1}, r_z^2 r_x t_z^{-1}$
	[6, 22, 59, 111, 171, 248, 339, 444, 563, 696]	392	H_{389}	1	$r_z^2 r_x i t_x^{-1}, i t_y, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z$
	[6, 22, 60, 111, 168, 242, 330, 433, 548, 678]	393	H_{398}	1	$r_z^2 r_x r_z^2 r_x t_x^{-1}, i t_y, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z$
	[6, 22, 61, 112, 172, 245, 339, 438, 560, 687]	394	H_{393}	1	$r_z^2 r_x r_y r_x t_x, r_y^{-1} r_z^{-1} t_y^{-1}, r_z^2 r_z t_z, r_y r_x t_z, r_y^{-1} r_z^{-1} t_z^{-1}$
	[6, 22, 61, 113, 172, 250, 343, 443, 561, 700]	395	H_{393}	1	$r_z^2 r_x r_z^2 r_y t_x^{-1}, r_y^{-1} r_z^{-1} t_y^{-1}, r_y^{-1} r_z t_z, r_y r_x t_z, r_z^2 r_y t_z^{-1}$
	[6, 22, 62, 111, 173, 249, 341, 445, 565, 697]	396	H_{392}	1	$r_z^2 r_x r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 r_x t_y^{-1}, r_z^2 t_y^{-1}, r_z^2 r_x t_z$

8

- [6, 17, 37, 70, 115, 173, 246, 329, 423, 534]
397*,
[6, 17, 38, 75, 125, 183, 253, 336, 429, 535]
398*,
[6, 17, 40, 82, 134, 200, 278, 367, 471, 591]
399*,
[6, 18, 42, 82, 136, 204, 286, 382, 492, 616]
400*,
[6, 18, 42, 83, 140, 210, 294, 390, 499, 624]
401*,
[6, 18, 44, 85, 140, 208, 285, 375, 481, 600]
403*,
[6, 18, 44, 86, 141, 207, 285, 378, 482, 597]
404*,
[6, 18, 44, 87, 153, 236, 323, 420, 531, 661]
402*,
[6, 18, 45, 90, 153, 229, 317, 416, 532, 663]
405*,
[6, 18, 45, 92, 154, 232, 317, 419, 540, 672]
407*,
[6, 18, 46, 92, 155, 232, 317, 419, 541, 672]

Nbr.	gr	N ₀	H _i	L	m	X
		408*,				
		[6, 18, 47, 96, 160, 238, 327, 431, 549, 681]				
		406*,				
		[6, 20, 47, 89, 145, 212, 289, 380, 485, 599]				
		409*,				
		[6, 20, 47, 89, 145, 213, 294, 389, 496, 615]				
		410*,				
		[6, 20, 48, 93, 150, 216, 297, 392, 499, 618]				
		411*,				
		[6, 20, 52, 99, 164, 241, 332, 433, 553, 685]				
		412*,				
		[6, 20, 52, 101, 165, 241, 332, 435, 554, 685]				
		413*,				
		[6, 21, 50, 99, 158, 233, 321, 423, 538, 669]				
		421*,				
		[6, 21, 51, 96, 153, 223, 304, 399, 510, 629]				
		414*,				
		[6, 21, 51, 97, 153, 223, 305, 399, 509, 629]				
		415*,				
		[6, 21, 51, 99, 159, 233, 321, 423, 539, 669]				
		422*,				
		[6, 21, 51, 100, 159, 231, 318, 417, 530, 657]				
		416*,				
		[6, 21, 52, 99, 161, 237, 326, 428, 544, 674]				
		417*,				
		[6, 21, 52, 99, 161, 237, 326, 429, 547, 679]				
		418*,				
		[6, 21, 54, 101, 159, 231, 317, 416, 528, 654]				
		419*,				
		[6, 21, 54, 103, 162, 236, 327, 429, 542, 672]				
		420*,				
		[6, 23, 54, 100, 159, 225, 309, 407, 509, 632]				
		424*,				
		[6, 23, 54, 103, 163, 239, 327, 431, 547, 679]				
		423*,				
		[6, 23, 56, 105, 166, 241, 330, 435, 552, 683]				
		425*,				
		[6, 23, 59, 105, 160, 230, 312, 407, 515, 635]				
		426*,				
		[7, 20, 46, 88, 139, 204, 287, 375, 476, 599]				
		397	H ₄₁₃	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_y^2 t_z, r_x t_z$
		[7, 20, 47, 91, 143, 204, 281, 367, 464, 577]				
		398	H ₄₁₉	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z$
		[7, 20, 50, 98, 150, 226, 302, 400, 506, 636]				
		399	H ₄₂₂	1	$r_z^2 r_x$	$r_z^2 t_x, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z$
		[7, 21, 51, 97, 157, 230, 319, 420, 537, 666]				
		400	H ₄₁₈	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}, r_x t_z^{-1}$
		[7, 21, 51, 98, 159, 232, 321, 419, 534, 663]				
		401	H ₄₁₃	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1}, m_x r_x t_z^{-1}, m_z t_z^{-1}$
		[7, 21, 52, 97, 168, 244, 331, 432, 545, 677]				
		402	H ₄₁₂	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1}, m_x r_x t_z^{-1}, m_z t_z^{-1}$
		[7, 21, 53, 96, 153, 221, 302, 395, 500, 620]				
		403	H ₄₁₂	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_y^2 t_z, r_x t_z$
		[7, 21, 53, 97, 154, 220, 302, 397, 500, 619]				
		404	H ₄₀₂	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z$
		[7, 21, 55, 103, 166, 244, 330, 433, 549, 683]				
		405	H ₄₂₂	1	$r_z^2 r_x$	$r_z^2 t_x, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z, m_z t_z^{-1}$
		[7, 21, 55, 104, 168, 246, 334, 442, 558, 694]				
		406	H ₄₀₇	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}, r_x t_z^{-1}$
		[7, 21, 57, 105, 170, 245, 338, 443, 562, 689]				
		407	H ₄₁₅	1	$r_z^2 r_x$	$it_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z$
		[7, 21, 58, 105, 170, 245, 338, 444, 561, 690]				
		408	H ₄₀₄	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z$
		[7, 23, 54, 100, 157, 224, 305, 400, 504, 622]				
		409	H ₄₀₁	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_z^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z, r_z^2 t_z^{-1}$
		[7, 23, 54, 100, 157, 226, 312, 409, 515, 641]				
		410	H ₃₉₅	1	$r_z^2 r_x$	$m_x t_x^{-1}, it_y^{-1}, m_z r_x t_y^{-1}, it_z, m_z r_x t_z, r_x^2 t_z^{-1}$
		[7, 23, 56, 103, 161, 231, 315, 412, 521, 640]				
		411	H ₄₀₉	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_z^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z$
		[7, 23, 61, 107, 176, 247, 346, 440, 572, 691]				
		412	H ₄₁₀	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}, r_x t_z^{-1}$
		[7, 23, 61, 108, 176, 247, 346, 441, 572, 691]				
		413	H ₄₁₄	1	$r_z^2 r_x$	$it_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}, r_x t_z^{-1}$
		[7, 24, 58, 103, 162, 232, 316, 414, 522, 643]				
		414	H ₃₉₄	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, it_y^{-1}, m_z r_x t_y^{-1}, it_z, m_z r_x t_z, r_x^2 t_z^{-1}$
		[7, 24, 58, 104, 162, 232, 316, 414, 522, 644]				
		415	H ₃₉₁	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_z^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z, r_x^2 t_z^{-1}$
		[7, 24, 59, 108, 166, 244, 329, 432, 545, 672]				
		416	H ₄₀₉	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_y^{-1}, r_z^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z, r_x^2 t_z^{-1}$
		[7, 24, 59, 108, 172, 247, 338, 441, 559, 690]				
		417	H ₃₉₅	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y, r_x^2 t_y, it_y^{-1}, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
		[7, 24, 59, 108, 172, 247, 338, 443, 564, 695]				
		418	H ₄₀₀	1	$r_z^2 r_x$	$m_x t_x^{-1}, it_y^{-1}, m_z r_x t_y^{-1}, it_z, m_z r_x t_z, it_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
		[7, 24, 60, 105, 166, 238, 326, 425, 540, 666]				
		419	H_{388}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, it_y^{-1}, m_z r_x t_y^{-1}, it_z, m_z r_x t_z, it_z^{-1}$
		[7, 24, 60, 107, 170, 244, 336, 437, 554, 684]				
		420	H_{394}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y, r_x^2 t_y, it_y^{-1}, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
		[7, 24, 60, 109, 172, 250, 340, 445, 564, 698]				
		421	H_{396}	1	$r_z^2 r_x$	$it_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z, r_x^2 t_z^{-1}$
		[7, 24, 61, 109, 173, 249, 341, 445, 565, 697]				
		422	H_{392}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z, r_x^2 t_z^{-1}$
		[7, 26, 61, 110, 173, 250, 341, 446, 565, 698]				
		423	H_{389}	1	$r_z^2 r_x$	$it_x^{-1}, it_y^{-1}, m_z r_x t_y^{-1}, it_z, m_z r_x t_z, it_z^{-1}$
		[7, 26, 61, 112, 172, 250, 343, 443, 561, 700]				
		424	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_x t_z, r_y^2 r_z t_y, r_x^2 r_y t_y^{-1}, r_y^{-1} r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, r_y r_x t_z$
		[7, 26, 63, 111, 174, 249, 342, 446, 566, 697]				
		425	H_{398}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, it_y^{-1}, m_z r_x t_y^{-1}, it_z, m_z r_x t_z, it_z^{-1}$
		[7, 26, 66, 110, 176, 249, 344, 444, 566, 694]				
		426	H_{393}	1	$r_z^2 r_x$	$r_y^{-1} r_z^{-1} t_x^{-1}, r_y r_x t_y, r_x^2 r_y t_y^{-1}, r_y^{-1} r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, r_y r_x t_z$

9

- [5, 14, 32, 66, 117, 179, 251, 335, 431, 539]
435*,
- [5, 14, 33, 68, 119, 182, 254, 336, 431, 539]
437*,
- [5, 14, 33, 68, 119, 183, 259, 347, 448, 563]
438*,
- [5, 15, 38, 77, 126, 186, 260, 342, 434, 541]
442*,
- [5, 15, 39, 85, 152, 236, 336, 452, 584, 732]
445*,
- [5, 15, 39, 87, 158, 247, 353, 474, 610, 762]
446*,
- [5, 15, 40, 89, 154, 226, 310, 408, 520, 646]
448*,
- [5, 15, 40, 89, 158, 231, 313, 413, 526, 653]
449*,
- [5, 15, 40, 89, 158, 236, 322, 421, 536, 667]
450*,
- [5, 15, 40, 91, 155, 228, 316, 415, 530, 660]
451*,
- [5, 15, 41, 85, 137, 198, 271, 356, 455, 566]
447*,
- [5, 16, 42, 86, 141, 204, 279, 367, 467, 579]
457*,
- [5, 16, 42, 86, 143, 211, 292, 387, 495, 615]
461*,
- [5, 16, 42, 86, 145, 216, 297, 391, 499, 619]
458*,
- [5, 16, 42, 96, 160, 229, 317, 419, 535, 665]
464*,
- [5, 16, 42, 96, 165, 235, 319, 425, 547, 674]
465*,
- [5, 16, 43, 90, 150, 220, 302, 396, 505, 629]
459*,
- [5, 16, 45, 97, 168, 256, 360, 480, 616, 768]
462*,
- [5, 16, 45, 98, 163, 237, 327, 431, 549, 681]
466*,
- [5, 16, 45, 99, 170, 256, 360, 480, 616, 768]
463*,
- [5, 16, 45, 102, 168, 236, 323, 427, 543, 671]
467*,
- [5, 16, 45, 102, 171, 243, 331, 435, 553, 685]
468*,
- [5, 16, 46, 90, 144, 216, 299, 389, 491, 607]
460*,
- [5, 17, 44, 83, 132, 196, 268, 350, 450, 556]
469*,
- [5, 17, 44, 85, 138, 203, 276, 362, 464, 575]
470*,
- [5, 17, 45, 93, 158, 235, 322, 422, 538, 666]
472*,
- [5, 17, 47, 96, 155, 225, 309, 405, 516, 641]
471*,
- [5, 17, 47, 99, 170, 259, 364, 484, 620, 772]
473*,
- [5, 17, 47, 101, 174, 264, 371, 492, 628, 780]
474*,
- [5, 17, 48, 101, 167, 240, 327, 430, 545, 675]
475*,
- [5, 17, 50, 103, 162, 232, 318, 416, 528, 654]
476*,
- [5, 17, 50, 112, 188, 276, 383, 505, 640, 790]
477*,
- [5, 17, 51, 112, 188, 278, 383, 503, 639, 790]
478*,
- [5, 18, 47, 90, 142, 205, 281, 369, 469, 581]
479*,
- [5, 18, 48, 89, 142, 213, 294, 386, 492, 609]
481*,
- [5, 18, 48, 90, 143, 210, 289, 379, 480, 597]
482*,

Nbr.	gr	N_i	H_i	L	m	X
[5, 18, 48, 90, 143, 211, 288, 377, 483, 599]						
480*						
[5, 18, 49, 96, 153, 224, 308, 402, 513, 638]						
483*						
[5, 18, 49, 100, 168, 252, 352, 468, 600, 748]						
484*						
[5, 18, 50, 105, 179, 268, 372, 492, 628, 780]						
486*						
[5, 18, 50, 107, 181, 268, 372, 492, 628, 780]						
487*						
[5, 18, 52, 106, 170, 245, 335, 439, 557, 689]						
488*						
[5, 18, 52, 110, 184, 272, 376, 496, 632, 784]						
485*						
[5, 18, 55, 109, 171, 244, 329, 431, 547, 675]						
489*						
[5, 18, 55, 121, 198, 285, 390, 509, 643, 795]						
490*						
[5, 18, 56, 121, 198, 285, 389, 509, 643, 795]						
491*						
[5, 19, 52, 101, 159, 230, 316, 414, 526, 652]						
492*						
[5, 19, 52, 102, 163, 237, 326, 427, 543, 674]						
494*						
[5, 19, 52, 102, 165, 239, 328, 432, 547, 678]						
495*						
[5, 19, 53, 102, 160, 236, 328, 426, 538, 670]						
493*						
[5, 20, 54, 104, 165, 239, 328, 431, 548, 679]						
496*						
[5, 20, 54, 106, 168, 241, 330, 433, 550, 681]						
497*						
[5, 20, 56, 111, 183, 272, 376, 496, 632, 784]						
498*						
[5, 20, 58, 110, 170, 244, 332, 434, 550, 680]						
499*						
[5, 20, 58, 111, 173, 247, 335, 439, 556, 687]						
500*						
[5, 20, 58, 112, 172, 245, 335, 439, 556, 687]						
501*						
[5, 20, 59, 118, 191, 280, 384, 504, 640, 792]						
502*						
[6, 18, 38, 66, 102, 146, 198, 258, 326, 402]						
427	H_{779}	$\langle m_z, m_z r_x, r_x^2 \rangle$	$r_z^2 r_x$	$m_x t_x^{-1}, r_x^2 t_y, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z, r_x^2 t_z^{-1}$		
[6, 19, 43, 78, 123, 179, 246, 323, 411, 510]						
428	H_{680}	$\langle m_x \rangle$	r_z^2	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_x^2 t_z^{-1}$		
[6, 19, 44, 84, 141, 217, 312, 424, 552, 696]						
429	H_{527}	1	r_z^2	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, m_z t_z^{-1}$		
430	H_{529}	1	r_z^2	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$		
[6, 20, 46, 84, 134, 196, 270, 356, 454, 564]						
431	H_{749}	$\langle m_y, r_z^2 \rangle$	i	$r_y^2 t_x, m_z t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_z t_z^{-1}$		
[6, 20, 47, 86, 137, 202, 278, 366, 469, 582]						
432	H_{650}	$\langle m_z r_x \rangle$	m_x	$m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$		
[6, 20, 47, 88, 145, 220, 313, 424, 552, 696]						
433	H_{527}	1	r_z^2	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1}$		
434	H_{529}	1	r_z^2	$m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$		
[6, 20, 47, 89, 144, 210, 288, 378, 480, 594]						
435	H_{682}	$\langle m_y \rangle$	m_x	$r_y^2 t_x^{-1}, m_y t_y, t_y^{-1}, m_z t_z, r_y^2 t_z^{-1}$		
[6, 20, 48, 88, 140, 208, 286, 376, 484, 600]						
436	H_{648}	$\langle m_z r_x \rangle$	m_x	$m_x t_x^{-1}, r_x^2 t_y, i t_y^{-1}, m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1}$		
[6, 20, 48, 91, 145, 208, 283, 371, 472, 585]						
437	H_{378}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_y^2 r_z t_z^{-1}$		
[6, 20, 48, 91, 149, 220, 306, 404, 514, 636]						
438	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_y t_y, m_y t_y^{-1}, m_z t_z, i t_z^{-1}$		
[6, 20, 48, 92, 153, 232, 328, 440, 568, 712]						
439	H_{604}	$\langle r_y^2 \rangle$	r_z^2	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_z t_z^{-1}$		
440	H_{622}	$\langle m_z \rangle$	r_z^2	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, m_x r_z t_z^{-1}$		
[6, 21, 49, 90, 145, 213, 294, 389, 497, 618]						
441	H_{680}	$\langle m_x \rangle$	r_z^2	$r_z^2 t_x, m_y t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_x^2 t_z^{-1}$		
[6, 21, 50, 90, 140, 203, 277, 361, 458, 566]						
442	H_{359}	1	m_z	$r_z^2 t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$		
[6, 21, 50, 94, 155, 233, 328, 440, 568, 712]						
443	H_{452}	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z, m_z t_z^{-1}$		
444	H_{503}	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z, r_x^2 t_z^{-1}$		
[6, 21, 51, 97, 162, 247, 349, 467, 601, 751]						
445	H_{452}	1	r_z^2	$r_z^2 t_x^{-1}, t_y, t_y^{-1}, r_y^2 r_z t_z, m_z t_z^{-1}$		
[6, 21, 51, 98, 165, 254, 359, 479, 615, 767]						
446	H_{503}	1	r_z^2	$r_z^2 t_x^{-1}, t_y, t_y^{-1}, r_y^2 r_z t_z, r_x^2 t_z^{-1}$		
[6, 21, 52, 94, 147, 212, 286, 374, 475, 587]						
447	H_{377}	1	m_z	$r_y^2 t_x, r_z^{-1} t_x^{-1}, r_z t_y, m_y t_y^{-1}, m_z t_z^{-1}$		
[6, 21, 54, 104, 164, 237, 324, 423, 537, 664]						
448	H_{368}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_y^2 t_z^{-1}$		
[6, 21, 54, 104, 168, 239, 328, 429, 544, 670]						

Nbr.	gr	N ₀	H_i	L	m	X
		449	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
	[6, 21, 54, 104, 169, 245, 333, 434, 553, 685]	450	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z, m_z t_z^{-1}$
	[6, 21, 54, 105, 167, 243, 332, 434, 553, 683]	451	H_{361}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_y, i t_y^{-1}, r_y^2 t_z^{-1}$
	[6, 22, 50, 94, 150, 222, 306, 406, 518, 646]	452	H_{779}	$\langle m_z, m_z r_x, r_x^2 \rangle$	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}, m_x r_x^{-1} t_z, r_y^2 r_x t_z^{-1}$
	[6, 22, 51, 96, 157, 234, 329, 440, 568, 712]	453	H_{452}	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1}$
		454	H_{503}	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
	[6, 22, 52, 98, 161, 240, 336, 448, 576, 720]	455	H_{598}	$\langle r_y^2 \rangle$	r_z^2	$r_z^2 t_x, r_x^2 t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 r_z t_z, r_z t_z^{-1}$
		456	H_{611}	$\langle m_z \rangle$	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z, m_x r_z t_z^{-1}$
	[6, 22, 53, 98, 153, 218, 296, 386, 488, 602]	457	H_{370}	1	m_z	$r_z^2 t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_x^2 t_z^{-1}$
	[6, 22, 54, 100, 158, 228, 312, 407, 516, 639]	458	H_{359}	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$
	[6, 22, 55, 101, 158, 230, 315, 411, 522, 647]	459	H_{359}	1	m_z	$i t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$
	[6, 22, 56, 100, 157, 226, 308, 401, 505, 624]	460	H_{382}	1	m_z	$r_y^2 t_x, r_z^{-1} t_x^{-1}, r_z t_y, m_y t_y^{-1}, r_y^2 r_z t_z^{-1}$
	[6, 22, 56, 102, 160, 230, 316, 414, 524, 646]	461	H_{750}	$\langle m_y, r_z^2 \rangle$	i	$r_y^2 t_x, m_z t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^2 r_z t_z^{-1}$
	[6, 22, 56, 106, 174, 259, 362, 482, 618, 770]	462	H_{503}	1	r_z^2	$r_z^2 t_x^{-1}, t_y, t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
	[6, 22, 56, 107, 174, 259, 362, 482, 618, 770]	463	H_{452}	1	r_z^2	$r_z^2 t_x^{-1}, t_y, t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1}$
	[6, 22, 56, 110, 171, 247, 339, 443, 563, 695]	464	H_{649}	$\langle m_z r_x \rangle$	m_x	$r_z^2 r_x t_x^{-1}, r_x^2 t_y, i t_y^{-1}, m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1}$
	[6, 22, 56, 111, 172, 245, 340, 448, 563, 690]	465	H_{652}	$\langle m_z r_x \rangle$	m_x	$r_z^2 r_x t_x^{-1}, m_y t_y, r_y^2 t_y^{-1}, r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$
	[6, 22, 59, 109, 172, 248, 340, 444, 564, 696]	466	H_{682}	$\langle m_y \rangle$	m_x	$r_y^2 t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}, m_z t_z, r_y^2 t_z^{-1}$
	[6, 22, 59, 112, 171, 245, 337, 441, 557, 686]	467	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_x t_y, m_x t_y^{-1}, m_z t_z, i t_z^{-1}$
	[6, 22, 59, 112, 175, 250, 342, 446, 566, 698]	468	H_{378}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
	[6, 23, 53, 92, 145, 209, 282, 371, 469, 576]	469	H_{682}	$\langle m_x \rangle$	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_x^2 t_z^{-1}$
	[6, 23, 53, 94, 150, 215, 290, 381, 482, 595]	470	H_{343}	1	m_z	$r_z^2 t_x, m_x r_z t_x^{-1}, i t_y, m_x r_z t_y^{-1}, m_z t_z^{-1}$
	[6, 23, 57, 105, 165, 239, 325, 424, 539, 665]	471	H_{370}	1	m_z	$i t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_x^2 t_z^{-1}$
	[6, 23, 57, 105, 168, 243, 332, 435, 552, 681]	472	H_{359}	1	m_z	$i t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$
	[6, 23, 58, 110, 180, 268, 372, 492, 628, 780]	473	H_{527}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, r_y^2 r_z t_z, m_z t_z^{-1}$
	[6, 23, 58, 111, 182, 271, 376, 496, 632, 784]	474	H_{529}	1	r_z^2	$m_y t_x, m_y t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
	[6, 23, 59, 109, 172, 246, 338, 441, 558, 689]	475	H_{377}	1	m_z	$r_y^2 t_x, m_z r_z^{-1} t_x^{-1}, m_z r_z t_y, m_y t_y^{-1}, m_z t_z^{-1}$
	[6, 23, 60, 109, 167, 241, 328, 427, 541, 668]	476	H_{370}	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_x^2 t_z^{-1}$
	[6, 23, 61, 119, 190, 279, 385, 506, 639, 792]	477	H_{541}	1	r_z^2	$r_x t_x, r_x^{-1} t_x^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}$
	[6, 23, 61, 119, 191, 280, 384, 505, 639, 792]	478	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}$
	[6, 24, 55, 99, 152, 218, 296, 386, 488, 602]	479	H_{683}	$\langle m_x \rangle$	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_x^2 t_z^{-1}$
	[6, 24, 56, 100, 158, 225, 304, 400, 506, 622]	480	H_{344}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
	[6, 24, 56, 100, 159, 231, 316, 412, 519, 644]	481	H_{347}	1	m_z	$r_z^2 t_x, m_x r_z t_x^{-1}, i t_y, m_x r_z t_y^{-1}, r_x^2 r_z t_z^{-1}$
	[6, 24, 56, 100, 160, 230, 312, 407, 516, 638]	482	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_z^2 t_y, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
	[6, 24, 58, 103, 161, 234, 319, 416, 529, 653]	483	H_{350}	1	m_z	$r_z^2 t_x, i t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$
	[6, 24, 58, 108, 177, 263, 365, 483, 617, 767]	484	H_{611}	$\langle m_z \rangle$	r_z^2	$r_z^2 t_x^{-1}, t_y, t_y^{-1}, r_y^2 r_z t_z, m_x r_z t_z^{-1}$
	[6, 24, 60, 114, 186, 274, 378, 498, 634, 786]	485	H_{598}	$\langle r_y^2 \rangle$	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 r_z t_z, r_z t_z^{-1}$
	[6, 24, 61, 115, 186, 273, 376, 496, 632, 784]	486	H_{529}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
	[6, 24, 61, 116, 186, 273, 376, 496, 632, 784]	487	H_{527}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1}$

Nbr.	gr	N_b	H_j	L	m	X
[6, 24, 62, 112, 176, 252, 344, 448, 568, 700]	488	H_{370}	1		m_z	$it_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_x^2 t_z^{-1}$
[6, 24, 64, 113, 177, 250, 339, 443, 560, 689]	489	H_{382}	1		m_z	$r_y^2 t_x, m_z r_z^{-1} t_x^{-1}, m_z r_z t_y, m_y t_y^{-1}, r_y^2 r_z t_z^{-1}$
[6, 24, 65, 126, 196, 285, 389, 508, 643, 796]	490	H_{511}	1		r_z^2	$r_x t_x, r_x^{-1} t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[6, 24, 65, 126, 197, 284, 389, 508, 643, 796]	491	H_{511}	1		r_z^2	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[6, 25, 59, 108, 167, 241, 328, 427, 541, 668]	492	H_{365}	1		m_z	$r_z^2 t_x, it_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_x^2 t_z^{-1}$
[6, 25, 60, 108, 170, 248, 335, 434, 554, 686]	493	H_{372}	1		m_z	$r_z^2 t_x, it_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_y^2 t_z^{-1}$
[6, 25, 61, 108, 170, 246, 336, 438, 557, 687]	494	H_{682}	$\langle m_x \rangle$		r_z^2	$it_x, r_x^2 t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_x^2 t_z^{-1}$
[6, 25, 61, 108, 172, 247, 339, 442, 560, 692]	495	H_{343}	1		m_z	$r_z^2 t_x, r_y^2 r_z t_x^{-1}, it_y, r_y^2 r_z t_y^{-1}, m_z t_z^{-1}$
[6, 26, 61, 111, 174, 250, 342, 446, 566, 698]	496	H_{683}	$\langle m_x \rangle$		r_z^2	$it_x, r_x^2 t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_x^2 t_z^{-1}$
[6, 26, 62, 114, 176, 252, 344, 448, 568, 700]	497	H_{364}	1		m_z	$r_z^2 t_x, it_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, it_z^{-1}$
[6, 26, 64, 118, 190, 278, 382, 502, 638, 790]	498	H_{622}	$\langle m_z \rangle$		r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, r_y^2 r_z t_z, m_x r_z t_z^{-1}$
[6, 26, 65, 113, 176, 251, 341, 444, 563, 693]	499	H_{347}	1		m_z	$r_z^2 t_x, r_y^2 r_z t_x^{-1}, it_y, r_y^2 r_z t_y^{-1}, r_x^2 r_z t_z^{-1}$
[6, 26, 65, 114, 177, 251, 343, 447, 566, 697]	500	H_{511}	1		r_z^2	$r_z^2 r_x t_x, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[6, 26, 65, 115, 176, 252, 344, 448, 568, 700]	501	H_{344}	1		m_z	$r_z^2 t_x, it_x^{-1}, it_y, it_y^{-1}, r_y^2 r_z t_z^{-1}$
[6, 26, 66, 122, 194, 282, 386, 506, 642, 794]	502	H_{604}	$\langle r_y^2 \rangle$		r_z^2	$it_x, m_y t_x^{-1}, m_y t_y^{-1}, r_x^2 r_z t_z, r_z t_z^{-1}$

10

- 19, 43, 78, 123, 179, 246, 323, 411, 510
 503*,
 [6, 19, 43, 79, 127, 187, 259, 343, 439, 547]
 504*,
 [6, 19, 43, 79, 128, 190, 262, 344, 439, 547]
 505*,
 [6, 19, 43, 79, 128, 191, 267, 355, 456, 571]
 506*,
 [6, 20, 47, 85, 132, 192, 265, 347, 440, 546]
 507*,
 [6, 20, 47, 87, 139, 203, 279, 367, 467, 579]
 510*,
 [6, 20, 48, 89, 139, 200, 274, 360, 459, 569]
 508*,
 [6, 20, 48, 90, 143, 207, 283, 371, 471, 583]
 509*,
 [6, 20, 48, 90, 144, 211, 290, 381, 486, 602]
 511*,
 [6, 20, 48, 91, 147, 216, 297, 388, 491, 607]
 512*,
 [6, 20, 49, 94, 151, 220, 303, 399, 508, 631]
 513*,
 [6, 20, 49, 96, 161, 245, 348, 468, 604, 756]
 514*, 515*,
 [6, 20, 50, 101, 172, 260, 364, 484, 620, 772]
 516*,
 [6, 20, 51, 100, 160, 232, 318, 416, 528, 654]
 517*,
 [6, 21, 49, 86, 135, 199, 270, 353, 453, 558]
 518*,
 [6, 21, 49, 89, 141, 205, 281, 369, 469, 581]
 520*,
 [6, 21, 49, 89, 143, 210, 289, 379, 480, 597]
 523*,
 [6, 21, 49, 89, 143, 211, 288, 377, 483, 599]
 522*,
 [6, 21, 50, 90, 141, 205, 279, 366, 468, 578]
 519*,
 [6, 21, 50, 91, 143, 207, 283, 371, 471, 583]
 521*,
 [6, 21, 50, 91, 145, 213, 292, 385, 492, 609]
 526*,
 [6, 21, 51, 93, 144, 207, 283, 371, 471, 583]
 524*,
 [6, 21, 51, 94, 149, 219, 295, 386, 492, 607]
 525*,
 [6, 21, 51, 95, 151, 219, 300, 395, 503, 623]
 536*, 537*,
 [6, 21, 51, 96, 155, 227, 312, 411, 523, 648]
 530*,
 [6, 21, 51, 97, 157, 228, 311, 408, 519, 643]
 531*,
 [6, 21, 52, 97, 152, 218, 295, 386, 492, 607]
 527*,
 [6, 21, 52, 97, 153, 221, 302, 397, 504, 624]

Nbr.	gr	N_0	H_i	L	m	X
		529*				
		[6, 21, 52, 97, 153, 223, 306, 401, 511, 634]				
		528*				
		[6, 21, 52, 97, 153, 224, 309, 405, 516, 641]				
		532*				
		[6, 21, 52, 98, 157, 230, 315, 413, 526, 651]				
		533*				
		[6, 21, 52, 101, 164, 236, 320, 419, 531, 656]				
		534*				
		[6, 21, 52, 104, 170, 242, 327, 433, 555, 682]				
		541*				
		[6, 21, 53, 100, 161, 237, 324, 425, 542, 670]				
		538*				
		[6, 21, 53, 104, 169, 242, 327, 433, 555, 682]				
		543*				
		[6, 21, 53, 104, 173, 260, 364, 484, 620, 772]				
		535*				
		[6, 21, 54, 108, 180, 268, 372, 492, 628, 780]				
		539*, 540*				
		[6, 21, 55, 103, 160, 232, 318, 416, 528, 654]				
		542*				
		[6, 21, 56, 107, 169, 245, 335, 439, 557, 689]				
		544*				
		[6, 21, 57, 110, 174, 250, 339, 443, 561, 693]				
		545*				
		[6, 22, 52, 92, 143, 207, 283, 371, 471, 583]				
		546*, 547*				
		[6, 22, 53, 96, 152, 221, 302, 397, 504, 624]				
		548*				
		[6, 22, 54, 97, 150, 217, 295, 386, 492, 607]				
		549*				
		[6, 22, 54, 97, 152, 224, 305, 398, 510, 629]				
		550*				
		[6, 22, 54, 98, 154, 226, 310, 405, 516, 640]				
		551*, 552*				
		[6, 22, 54, 100, 158, 230, 316, 414, 526, 652]				
		556*				
		[6, 22, 54, 102, 165, 241, 331, 435, 553, 685]				
		562*				
		[6, 22, 54, 102, 169, 256, 360, 480, 616, 768]				
		553*, 554*				
		[6, 22, 55, 101, 158, 228, 307, 401, 513, 631]				
		555*				
		[6, 22, 55, 101, 159, 236, 328, 426, 538, 670]				
		557*				
		[6, 22, 55, 102, 160, 232, 318, 416, 528, 654]				
		558*				
		[6, 22, 55, 102, 160, 234, 323, 423, 538, 668]				
		559*				
		[6, 22, 55, 103, 162, 233, 318, 416, 528, 654]				
		560*				
		[6, 22, 55, 103, 164, 238, 325, 427, 543, 671]				
		561*				
		[6, 22, 55, 106, 175, 261, 364, 484, 620, 772]				
		564*, 565*				
		[6, 22, 56, 104, 161, 232, 318, 416, 528, 654]				
		563*				
		[6, 22, 56, 109, 180, 268, 372, 492, 628, 780]				
		566*				
		[6, 22, 57, 106, 168, 245, 335, 439, 557, 689]				
		568*				
		[6, 22, 57, 109, 173, 248, 335, 436, 552, 682]				
		567*				
		[6, 22, 58, 110, 173, 249, 339, 443, 561, 693]				
		569*				
		[6, 22, 59, 110, 170, 243, 329, 431, 547, 675]				
		570*				
		[6, 22, 59, 112, 174, 249, 339, 443, 561, 693]				
		571*				
		[6, 23, 52, 91, 143, 207, 283, 371, 471, 583]				
		572*				
		[6, 23, 53, 95, 151, 219, 300, 395, 503, 623]				
		574*, 575*				
		[6, 23, 55, 102, 162, 233, 318, 417, 529, 654]				
		576*				
		[6, 23, 55, 103, 164, 237, 325, 427, 543, 673]				
		586*				
		[6, 23, 56, 99, 155, 227, 307, 401, 513, 631]				
		573*				
		[6, 23, 56, 103, 163, 237, 325, 427, 543, 673]				
		590*				
		[6, 23, 56, 103, 163, 239, 330, 429, 541, 672]				
		578*				
		[6, 23, 56, 103, 164, 239, 328, 431, 548, 679]				
		585*				
		[6, 23, 56, 104, 164, 235, 320, 419, 531, 656]				
		579*				
		[6, 23, 56, 104, 164, 237, 325, 426, 541, 670]				
		580*				
		[6, 23, 56, 105, 167, 241, 330, 433, 550, 681]				
		591*, 592*				
		[6, 23, 57, 101, 156, 227, 307, 401, 513, 631]				
		577*				

Nbr.	gr	H_i	L	m	X
	505	H_{378}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 23, 52, 95, 153, 224, 310, 408, 518, 640]	506	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_y t_y, m_y t_y^{-1}, m_z t_z, i t_z^{-1}, m_z t_z^{-1}$
[7, 24, 53, 92, 143, 206, 279, 364, 461, 568]	507	H_{359}	1	m_z	$r_z^2 t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 24, 54, 95, 148, 213, 288, 376, 477, 588]	508	H_{377}	1	m_z	$r_y^2 t_x, m_x t_x, r_z^{-1} t_x^{-1}, r_z t_y, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 24, 55, 98, 152, 218, 296, 386, 488, 602]	509	H_{680}	$\langle m_x \rangle$	r_z^2	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
	510	H_{370}	1	m_z	$r_z^2 t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
[7, 24, 55, 99, 155, 223, 304, 398, 503, 621]	511	H_{353}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$
[7, 24, 56, 102, 158, 225, 307, 401, 505, 624]	512	H_{382}	1	m_z	$r_y^2 t_x, m_x t_x, r_z^{-1} t_x^{-1}, r_z t_y, m_y t_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 24, 56, 102, 160, 231, 316, 413, 523, 648]	513	H_{359}	1	m_z	$i t_x, r_z^2 t_x, m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, m_z t_z^{-1}$
[7, 24, 56, 104, 169, 253, 356, 476, 612, 764]	514	H_{527}	1	r_z^2	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1}, m_z t_z^{-1}$
	515	H_{529}	1	r_z^2	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
[7, 24, 56, 105, 173, 260, 364, 484, 620, 772]	516	H_{690}	$\langle m_x \rangle$	r_z^2	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, m_z r_z^{-1} t_z, r_y^2 t_z^{-1}$
[7, 24, 59, 108, 167, 241, 328, 427, 541, 668]	517	H_{368}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_y^2 t_z^{-1}$
[7, 25, 54, 93, 147, 210, 283, 373, 470, 577]	518	H_{682}	$\langle m_x \rangle$	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
[7, 25, 55, 96, 151, 216, 292, 383, 484, 596]	519	H_{343}	1	m_z	$r_z^2 t_x, m_x r_z t_x^{-1}, i t_y, r_z^2 t_y, m_x r_z t_y^{-1}, m_z t_z^{-1}$
[7, 25, 56, 98, 152, 218, 296, 386, 488, 602]	520	H_{683}	$\langle m_x \rangle$	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
	521	H_{682}	$\langle m_y \rangle$	m_x	$r_x^2 t_x^{-1}, m_y t_y, t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, m_z t_z^{-1}$
[7, 25, 56, 100, 158, 225, 304, 400, 506, 622]	522	H_{344}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 25, 56, 100, 160, 230, 312, 407, 516, 638]	523	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x^2 t_y, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
[7, 25, 57, 99, 152, 218, 296, 386, 488, 602]	524	H_{359}	1	m_z	$r_z^2 t_x, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 25, 57, 101, 158, 226, 306, 401, 506, 623]	525	H_{378}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, m_y t_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 25, 57, 102, 160, 230, 315, 412, 519, 644]	526	H_{347}	1	m_z	$r_z^2 t_x, m_x r_z t_x^{-1}, i t_y, r_z^2 t_y, m_x r_z t_y^{-1}, r_x^2 r_z t_z^{-1}$
[7, 25, 58, 103, 159, 226, 306, 401, 506, 623]	527	H_{377}	1	m_z	$r_y^2 t_x, m_x t_x, r_z^{-1} t_x^{-1}, r_z t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$
[7, 25, 58, 103, 161, 233, 317, 414, 525, 649]	528	H_{359}	1	m_z	$i t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 25, 58, 104, 161, 230, 315, 410, 518, 642]	529	H_{359}	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 25, 58, 105, 165, 238, 325, 425, 538, 665]	530	H_{680}	$\langle m_x \rangle$	r_z^2	$r_z^2 t_x, m_y t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
[7, 25, 58, 106, 167, 240, 326, 426, 540, 666]	531	H_{370}	1	m_z	$i t_x, r_z^2 t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_x^2 t_z^{-1}$
[7, 25, 59, 105, 164, 239, 325, 424, 539, 665]	532	H_{370}	1	m_z	$i t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
[7, 25, 59, 106, 166, 240, 326, 426, 540, 666]	533	H_{353}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$
[7, 25, 59, 109, 170, 242, 329, 429, 542, 669]	534	H_{368}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
[7, 25, 59, 109, 176, 261, 364, 484, 620, 772]	535	H_{690}	$\langle m_x \rangle$	r_z^2	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, m_z r_z^{-1} t_z, r_x^2 t_z^{-1}$
[7, 25, 60, 106, 164, 234, 320, 418, 528, 650]	536	H_{378}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_y^2 r_z t_z^{-1}$
	537	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_y t_y, m_y t_y^{-1}, i t_z, i t_z^{-1}, m_z t_z^{-1}$
[7, 25, 60, 107, 170, 245, 334, 437, 554, 683]	538	H_{359}	1	m_z	$i t_x, r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$
[7, 25, 60, 113, 184, 272, 376, 496, 632, 784]	539	H_{496}	1	r_z^2	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
	540	H_{502}	1	r_z^2	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z^{-1}, r_y^2 r_z t_z^{-1}$
[7, 25, 61, 114, 176, 249, 344, 452, 567, 694]	541	H_{373}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, i t_z^{-1}$
[7, 25, 62, 108, 167, 241, 328, 427, 541, 668]	542	H_{370}	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
[7, 25, 62, 113, 176, 249, 344, 452, 567, 694]	543	H_{378}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 25, 64, 112, 176, 252, 344, 448, 568, 700]	544	H_{682}	$\langle m_y \rangle$	m_x	$r_y^2 t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}, m_z t_z, r_y^2 t_z^{-1}, m_z t_z^{-1}$
[7, 25, 65, 114, 179, 254, 346, 450, 570, 702]					

Nbr.	gr	N ₀	H _i	L	m	X
545			H ₃₇₈	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 26, 57, 98, 152, 218, 296, 386, 488, 602]						
546			H ₆₈₂	$\langle m_x \rangle$	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
547			H ₃₇₀	1	m_z	$r_z^2 t_x, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
[7, 26, 58, 103, 161, 230, 315, 410, 518, 642]						
548			H ₃₅₉	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$
[7, 26, 59, 102, 158, 226, 306, 401, 506, 623]						
549			H ₃₈₂	1	m_z	$r_y^2 t_x, m_x t_x, r_z^{-1} t_x^{-1}, r_z t_y, r_x^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 26, 59, 103, 162, 233, 315, 414, 523, 643]						
550			H ₃₃₀	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, i t_y^{-1}, m_z t_z^{-1}$
[7, 26, 59, 104, 163, 235, 320, 418, 530, 654]						
551			H ₃₅₀	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$
552			H ₃₅₀	1	m_z	$r_z^2 t_x, i t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 26, 59, 107, 174, 259, 362, 482, 618, 770]						
553			H ₄₅₂	1	r_z^2	$r_z^2 t_x^{-1}, t_y, t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1}, m_z t_z^{-1}$
554			H ₅₀₃	1	r_z^2	$r_z^2 t_x^{-1}, t_y, t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
[7, 26, 60, 106, 165, 234, 316, 416, 524, 644]						
555			H ₃₄₃	1	m_z	$i t_x, m_x r_z t_x^{-1}, i t_y, r_z^2 t_y, m_x r_z t_y^{-1}, m_z t_z^{-1}$
[7, 26, 60, 107, 167, 241, 328, 427, 541, 668]						
556			H ₃₆₅	1	m_z	$r_z^2 t_x, i t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_z^2 t_z^{-1}$
[7, 26, 61, 107, 170, 248, 335, 434, 554, 686]						
557			H ₃₇₂	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_y^2 t_z^{-1}$
[7, 26, 61, 108, 167, 241, 328, 427, 541, 668]						
558			H ₃₆₈	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_y^2 t_z^{-1}$
[7, 26, 61, 108, 170, 246, 336, 438, 557, 687]						
559			H ₃₆₁	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, i t_y^{-1}, r_y^2 t_z^{-1}$
[7, 26, 61, 109, 168, 241, 328, 427, 541, 668]						
560			H ₃₅₉	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 26, 61, 109, 171, 245, 335, 438, 554, 684]						
561			H ₃₅₉	1	m_z	$i t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 26, 61, 110, 174, 250, 342, 446, 566, 698]						
562			H ₆₈₀	$\langle m_x \rangle$	r_z^2	$r_z^2 t_x, m_y t_x^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
[7, 26, 62, 109, 167, 241, 328, 427, 541, 668]						
563			H ₃₅₉	1	m_z	$i t_x, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 26, 62, 114, 183, 269, 372, 492, 628, 780]						
564			H ₄₅₂	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1}, m_z t_z^{-1}$
565			H ₅₀₃	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
[7, 26, 62, 115, 185, 272, 376, 496, 632, 784]						
566			H ₆₉₀	$\langle m_x \rangle$	r_z^2	$r_z^2 t_x, m_y t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, m_z r_z^{-1} t_z, r_y^2 t_z^{-1}$
[7, 26, 63, 113, 176, 251, 341, 444, 562, 692]						
567			H ₃₇₇	1	m_z	$r_y^2 t_x, m_x t_x, m_z r_z^{-1} t_x^{-1}, m_z r_z t_y, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 26, 64, 111, 176, 252, 344, 448, 568, 700]						
568			H ₃₇₀	1	m_z	$i t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
[7, 26, 65, 114, 178, 254, 346, 450, 570, 702]						
569			H ₃₇₀	1	m_z	$i t_x, r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_x^2 t_z^{-1}$
[7, 26, 66, 113, 176, 250, 339, 443, 560, 689]						
570			H ₃₈₂	1	m_z	$r_y^2 t_x, m_x t_x, m_z r_z^{-1} t_x^{-1}, m_z r_z t_y, m_y t_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 26, 66, 115, 178, 254, 346, 450, 570, 702]						
571			H ₃₆₈	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
[7, 27, 56, 98, 152, 218, 296, 386, 488, 602]						
572			H ₆₈₃	$\langle m_x \rangle$	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
[7, 27, 60, 104, 164, 234, 316, 416, 524, 644]						
573			H ₃₄₄	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, i t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 27, 60, 106, 164, 234, 320, 418, 528, 650]						
574			H ₃₄₄	1	m_z	$i t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
575			H ₅₁₁	1	r_z^2	$r_z^2 r_x t_x, r_z^2 t_y, r_x^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
[7, 27, 60, 109, 169, 242, 329, 429, 542, 669]						
576			H ₃₆₅	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_x^2 t_z^{-1}$
[7, 27, 61, 105, 164, 234, 316, 416, 524, 644]						
577			H ₃₄₇	1	m_z	$i t_x, m_x r_z t_x^{-1}, i t_y, r_z^2 t_y, m_x r_z t_y^{-1}, r_x^2 r_z t_z^{-1}$
[7, 27, 61, 109, 172, 249, 336, 436, 555, 687]						
578			H ₃₇₂	1	m_z	$r_z^2 t_x, i t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
[7, 27, 61, 110, 169, 242, 329, 429, 542, 669]						
579			H ₃₇₀	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_x^2 t_z^{-1}$
[7, 27, 61, 110, 172, 247, 337, 440, 558, 688]						
580			H ₃₆₁	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_y, i t_y^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
[7, 27, 62, 108, 167, 241, 328, 427, 541, 668]						
581			H ₃₅₀	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
582			H ₃₇₀	1	m_z	$i t_x, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
583			H ₃₇₀	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
[7, 27, 62, 109, 172, 247, 337, 440, 558, 688]						
584			H ₆₈₂	$\langle m_x \rangle$	r_z^2	$i t_x, r_x^2 t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
[7, 27, 62, 110, 174, 250, 342, 446, 566, 698]						
585			H ₆₈₃	$\langle m_x \rangle$	r_z^2	$i t_x, r_x^2 t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
[7, 27, 62, 112, 175, 251, 343, 447, 567, 699]		586	H_{332}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, it_y^{-1}, it_z^{-1}$
[7, 27, 62, 117, 186, 276, 378, 500, 634, 788]		587	H_{453}	1	r_z^2	$it_x^{-1}, m_z t_y, m_z t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
		588	H_{539}	1	r_z^2	$m_z t_x, m_z t_x^{-1}, r_x^2 t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z, r_y^2 r_z t_z^{-1}$
[7, 27, 63, 109, 171, 246, 336, 438, 555, 685]		589	H_{359}	1	m_z	$it_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$
[7, 27, 63, 111, 175, 251, 343, 447, 567, 699]		590	H_{344}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, it_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 27, 63, 113, 176, 252, 344, 448, 568, 700]		591	H_{364}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, it_z^{-1}$
		592	H_{364}	1	m_z	$r_z^2 t_x, it_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y, it_z^{-1}$
[7, 27, 63, 116, 187, 275, 379, 499, 635, 787]		593	H_{539}	1	r_z^2	$it_x^{-1}, r_x^2 t_y, r_z^2 t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z, r_z^2 r_z t_z^{-1}$
		594	H_{438}	1	r_z^2	$r_z^2 t_x^{-1}, t_y, t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
		595	H_{495}	1	r_z^2	$r_z^2 t_x^{-1}, t_y, t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z, r_z^2 r_z t_z^{-1}$
		596	H_{505}	1	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
[7, 27, 63, 117, 186, 273, 376, 496, 632, 784]		597	H_{690}	$\langle m_x \rangle$	r_z^2	$r_z^2 t_x, m_y t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, m_z r_z^{-1} t_z, r_x^2 t_z^{-1}$
[7, 27, 64, 110, 172, 248, 338, 440, 559, 689]		598	H_{330}	1	m_z	$r_z^2 t_x, it_x^{-1}, it_y, it_y^{-1}, r_z^2 t_x^{-1}, m_z t_z^{-1}$
		599	H_{350}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$
[7, 27, 64, 112, 176, 252, 344, 448, 568, 700]		600	H_{682}	$\langle m_x \rangle$	m_x	$r_y^2 t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, m_z t_z^{-1}$
[7, 27, 64, 113, 177, 252, 344, 448, 568, 700]		601	H_{359}	1	m_z	$it_x, r_y^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 27, 64, 117, 179, 254, 346, 450, 570, 702]		602	H_{378}	1	m_z	$r_z^2 t_x, r_z^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
		603	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_x t_y, m_x t_y^{-1}, it_z, it_z, m_z t_z^{-1}$
[7, 27, 64, 119, 190, 278, 382, 502, 638, 790]		604	H_{438}	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1}, r_z^2 r_z t_z^{-1}$
		605	H_{495}	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z, r_y^2 r_z t_z^{-1}$
[7, 27, 65, 113, 174, 249, 341, 445, 561, 690]		606	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_x t_y, m_x t_y^{-1}, m_z t_z, it_z^{-1}, m_z t_z^{-1}$
[7, 27, 65, 113, 176, 252, 342, 445, 564, 695]		607	H_{343}	1	m_z	$r_z^2 t_x, r_y^2 r_z t_x^{-1}, it_y, r_z^2 t_y, r_y^2 r_z t_y^{-1}, m_z t_z^{-1}$
[7, 27, 65, 113, 178, 254, 346, 450, 570, 702]		608	H_{378}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, m_y t_y^{-1}, r_y^2 r_z t_z^{-1}$
		609	H_{378}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 27, 65, 115, 178, 254, 346, 450, 570, 702]		610	H_{373}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, it_z^{-1}$
[7, 27, 65, 116, 181, 255, 347, 450, 570, 702]		611	H_{377}	1	m_z	$r_y^2 t_x, m_x t_x, m_z r_z^{-1} t_x^{-1}, m_z r_z t_y, r_x^2 t_y^{-1}, m_z t_z^{-1}$
[7, 27, 67, 113, 176, 252, 344, 448, 568, 700]		612	H_{344}	1	m_z	$r_z^2 t_x, it_x^{-1}, it_y, it_y^{-1}, r_z^2 t_x^{-1}, r_y^2 r_z t_z^{-1}$
[7, 27, 68, 113, 175, 251, 341, 444, 563, 693]		613	H_{347}	1	m_z	$r_z^2 t_x, r_y^2 r_z t_x^{-1}, it_y, r_z^2 t_y, r_y^2 r_z t_y^{-1}, r_x^2 r_z t_z^{-1}$
[7, 27, 68, 126, 194, 281, 385, 506, 641, 793]		614	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_y t_y^{-1}, m_z t_z, it_z^{-1}, m_z t_z^{-1}$
		615	H_{541}	1	r_z^2	$r_x t_x, r_x^{-1} t_x^{-1}, m_y t_y^{-1}, m_z t_z, it_z^{-1}, m_z t_z^{-1}$
[7, 28, 61, 108, 167, 241, 328, 427, 541, 668]		616	H_{365}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
[7, 28, 63, 110, 172, 248, 338, 440, 559, 689]		617	H_{361}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, it_y^{-1}, r_y^2 t_z^{-1}$
		618	H_{372}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_y^2 t_z^{-1}$
[7, 28, 64, 113, 176, 252, 344, 448, 568, 700]		619	H_{361}	1	m_z	$r_z^2 t_x, it_x^{-1}, it_y, it_y^{-1}, r_z^2 t_x^{-1}, r_y^2 t_z^{-1}$
		620	H_{365}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_z^2 t_z^{-1}$
[7, 28, 65, 112, 176, 252, 344, 448, 568, 700]		621	H_{682}	$\langle m_x \rangle$	r_z^2	$it_x, r_z^2 t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, r_y^2 t_z^{-1}$
		622	H_{370}	1	m_z	$it_x, r_y^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_z^2 t_z^{-1}$
[7, 28, 65, 114, 178, 254, 346, 450, 570, 702]		623	H_{370}	1	m_z	$it_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_z^2 t_z^{-1}$
[7, 28, 66, 115, 178, 254, 346, 450, 570, 702]		624	H_{372}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
[7, 28, 66, 115, 180, 255, 347, 450, 570, 702]		625	H_{343}	1	m_z	$it_x, r_y^2 r_z t_x^{-1}, it_y, r_z^2 t_y, r_y^2 r_z t_y^{-1}, m_z t_z^{-1}$
[7, 28, 66, 117, 180, 254, 346, 450, 570, 702]		626	H_{382}	1	m_z	$r_y^2 t_x, m_x t_x, m_z r_z^{-1} t_x^{-1}, m_z r_z t_y, r_x^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 28, 66, 118, 188, 275, 378, 498, 634, 786]		627	H_{527}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, r_y^2 r_z t_z, it_z^{-1}, m_z t_z^{-1}$
		628	H_{529}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, r_y^2 r_z t_z, r_z^2 t_z^{-1}, r_x^2 t_z^{-1}$
[7, 29, 63, 113, 176, 252, 344, 448, 568, 700]						

Nbr.	gr	N ₀	H _i	L	m	X
		629	H ₃₃₂	1	m _z	r _z ² t _x , it _x ⁻¹ , it _y , it _y ⁻¹ , r _z ² t _y ⁻¹ , it _z ⁻¹
		630	H ₃₆₄	1	m _z	it _x , it _x ⁻¹ , r _z ² t _x ⁻¹ , m _y t _y , r _x ² t _y ⁻¹ , it _z ⁻¹
[7, 29, 64, 112, 176, 252, 344, 448, 568, 700]		631	H ₆₈₃	⟨m _x ⟩	r _z ²	it _x , r _x ² t _x ⁻¹ , r _x ² t _y ⁻¹ , r _x ² t _z , r _x ² t _z ⁻¹ , r _y ² t _z ⁻¹
[7, 29, 65, 113, 176, 251, 343, 447, 566, 697]		632	H ₅₁₁	1	r _z ²	r _z ² r _x t _x , r _y ² t _y , r _y ² t _y ⁻¹ , r _x ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
[7, 29, 65, 113, 176, 252, 344, 448, 568, 700]		633	H ₃₄₄	1	m _z	r _z ² t _x , it _x ⁻¹ , r _z ² t _x ⁻¹ , it _y , it _y ⁻¹ , r _y ² r _z t _z ⁻¹
		634	H ₃₄₄	1	m _z	r _z ² t _x , it _x ⁻¹ , it _y , r _z ² t _y , it _y ⁻¹ , r _y ² r _z t _z ⁻¹
[7, 29, 65, 115, 178, 254, 346, 450, 570, 702]		635	H ₃₆₄	1	m _z	r _z ² t _x , it _x ⁻¹ , r _x ² t _y , r _x ² t _y ⁻¹ , m _y t _y ⁻¹ , it _z ⁻¹
[7, 29, 66, 115, 179, 254, 346, 450, 570, 702]		636	H ₅₁₁	1	r _z ²	r _z ² r _x t _x , r _y ² t _y , r _y ² t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
[7, 29, 66, 116, 178, 254, 346, 450, 570, 702]		637	H ₃₄₄	1	m _z	it _x , it _x ⁻¹ , r _z ² t _x ⁻¹ , it _y , it _y ⁻¹ , r _y ² r _z t _z ⁻¹
[7, 29, 67, 116, 179, 254, 346, 450, 570, 702]		638	H ₃₄₇	1	m _z	it _x , r _y ² r _z t _x ⁻¹ , it _y , r _z ² t _y , r _y ² r _z t _y ⁻¹ , r _x ² r _z t _z ⁻¹
[7, 29, 67, 124, 193, 283, 385, 507, 641, 795]		639	H ₅₃₉	1	r _z ²	it _x ⁻¹ , r _y ² t _y , r _y ² t _y ⁻¹ , m _z r _z ⁻¹ t _z , m _z r _z t _z , r _y ² r _z t _z ⁻¹
		640	H ₅₀₅	1	r _z ²	r _y ² t _x ⁻¹ , r _y ² t _y , r _y ² t _y ⁻¹ , r _y ² r _z t _z , r _y ² r _z t _z ⁻¹ , r _x ² r _z t _z ⁻¹
[7, 29, 68, 123, 194, 282, 386, 506, 642, 794]		641	H ₄₅₃	1	r _z ²	it _x ⁻¹ , it _y , it _y ⁻¹ , r _y ² r _z t _z , r _y ² r _z t _z ⁻¹ , r _x ² r _z t _z ⁻¹
		642	H ₅₃₉	1	r _z ²	it _x , it _x ⁻¹ , r _x ² t _y ⁻¹ , m _z r _z ⁻¹ t _z , m _z r _z t _z , r _y ² r _z t _z ⁻¹
		643	H ₄₉₆	1	r _z ²	m _x t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , r _y ² r _z t _z , r _y ² r _z t _z ⁻¹ , r _x ² r _z t _z ⁻¹
		644	H ₅₀₂	1	r _z ²	m _x t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _z r _z ⁻¹ t _z , m _z r _z t _z , r _y ² r _z t _z ⁻¹
[7, 29, 71, 126, 196, 284, 388, 508, 644, 796]		645	H ₅₁₁	1	r _z ²	r _x t _x , r _x ⁻¹ t _x ⁻¹ , r _x ² t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
[7, 29, 71, 128, 196, 284, 388, 508, 644, 796]		646	H ₅₁₁	1	r _z ²	r _x t _x , r _x ⁻¹ t _x ⁻¹ , r _x ² t _y ⁻¹ , r _x ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
[7, 29, 72, 125, 196, 284, 388, 508, 644, 796]		647	H ₅₁₁	1	r _z ²	r _z ² r _x t _x , r _y ² r _x t _x ⁻¹ , r _x ² t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
[7, 29, 72, 127, 196, 284, 388, 508, 644, 796]		648	H ₅₁₁	1	r _z ²	r _z ² r _x t _x , r _y ² r _x t _x ⁻¹ , r _x ² t _y ⁻¹ , r _x ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
[7, 30, 73, 125, 196, 284, 388, 508, 644, 796]		649	H ₅₄₁	1	r _z ²	r _z ² r _x t _x , r _y ² r _x t _x ⁻¹ , m _y t _y ⁻¹ , it _z , it _z ⁻¹ , m _z t _z ⁻¹
		650	H ₅₄₁	1	r _z ²	r _x t _x , r _x ⁻¹ t _x ⁻¹ , m _y t _y ⁻¹ , it _z , it _z ⁻¹ , m _z t _z ⁻¹

11

- [6, 18, 38, 66, 102, 146, 198, 258, 326, 402]
- 651*, 652*, 653*, 654*,
- [6, 19, 43, 78, 122, 175, 239, 314, 398, 491]
- 655*,
- [6, 19, 43, 78, 123, 179, 246, 323, 411, 510]
- 658*,
- [6, 19, 43, 79, 127, 187, 259, 343, 439, 547]
- 656*,
- [6, 19, 43, 79, 128, 191, 267, 355, 455, 567]
- 657*,
- [6, 19, 46, 90, 148, 220, 306, 404, 516, 642]
- 659*,
- [6, 20, 46, 82, 128, 186, 254, 332, 422, 522]
- 660*,
- [6, 20, 46, 84, 134, 194, 263, 343, 434, 535]
- 662*,
- [6, 20, 46, 84, 134, 196, 270, 356, 454, 564]
- 667*,
- [6, 20, 46, 84, 134, 196, 272, 362, 465, 582]
- 663*,
- [6, 20, 46, 84, 135, 199, 275, 363, 463, 575]
- 661*,
- [6, 20, 47, 87, 139, 203, 279, 367, 467, 579]
- 664*, 665*,
- [6, 20, 47, 87, 140, 207, 287, 380, 487, 607]
- 668*,
- [6, 20, 48, 89, 140, 204, 281, 368, 468, 581]
- 666*,
- [6, 20, 48, 90, 143, 207, 283, 370, 469, 581]
- 670*,
- [6, 20, 48, 90, 144, 211, 290, 380, 484, 602]
- 669*,
- [6, 20, 48, 91, 147, 215, 296, 391, 499, 619]
- 674*, 675*,
- [6, 20, 48, 94, 160, 244, 344, 460, 592, 740]
- 671*,
- [6, 20, 49, 96, 160, 240, 336, 448, 576, 720]
- 672*, 673*,
- [6, 20, 51, 98, 156, 228, 314, 412, 524, 650]
- 676*,
- [6, 20, 51, 99, 161, 237, 327, 431, 549, 681]
- 677*,
- [6, 21, 49, 89, 141, 205, 281, 369, 469, 581]
- 678*,
- [6, 21, 49, 91, 147, 217, 301, 399, 511, 637]
- 681*,

Nbr.	gr	N ₀	H_f	L	m	X
	[6, 21, 50, 91, 143, 207, 283, 371, 471, 583]		679°			
	[6, 21, 50, 94, 150, 217, 298, 392, 499, 619]		687°			
	[6, 21, 50, 95, 153, 221, 303, 399, 507, 627]		688°			
	[6, 21, 51, 93, 145, 211, 289, 376, 477, 591]		683°			
	[6, 21, 51, 94, 148, 216, 298, 391, 497, 617]		684°			
	[6, 21, 51, 95, 151, 221, 306, 404, 516, 642]		680°			
	[6, 21, 51, 95, 151, 222, 306, 401, 512, 637]		686°			
	[6, 21, 51, 96, 155, 227, 312, 410, 521, 645]		692°			
	[6, 21, 51, 97, 156, 228, 314, 412, 524, 650]		689°			
	[6, 21, 52, 95, 148, 217, 298, 389, 496, 614]		682°			
	[6, 21, 52, 97, 155, 230, 319, 418, 532, 661]		685°			
	[6, 21, 52, 98, 153, 218, 296, 386, 488, 602]		694°			
	[6, 21, 52, 98, 156, 228, 314, 412, 524, 650]		690°, 691°			
	[6, 21, 52, 100, 162, 239, 329, 428, 543, 679]		695°			
	[6, 21, 53, 100, 161, 237, 327, 431, 549, 681]		693°			
	[6, 21, 53, 104, 174, 263, 368, 488, 624, 776]		696°			
	[6, 21, 53, 106, 179, 268, 373, 493, 629, 781]		697°			
	[6, 21, 56, 110, 181, 269, 373, 493, 629, 781]		698°			
	[6, 21, 56, 115, 188, 275, 383, 506, 640, 789]		699°			
	[6, 21, 57, 110, 171, 243, 331, 435, 551, 679]		700°			
	[6, 22, 51, 91, 143, 207, 283, 371, 471, 583]		701°			
	[6, 22, 52, 95, 151, 219, 300, 395, 503, 623]		705°, 706°			
	[6, 22, 52, 96, 151, 216, 294, 384, 486, 600]		704°			
	[6, 22, 52, 97, 154, 222, 304, 399, 507, 628]		703°			
	[6, 22, 53, 97, 154, 224, 307, 403, 512, 634]		702°			
	[6, 22, 53, 98, 157, 230, 317, 418, 533, 662]		708°			
	[6, 22, 53, 100, 159, 229, 314, 413, 525, 650]		709°			
	[6, 22, 53, 100, 163, 240, 331, 435, 553, 685]		711°			
	[6, 22, 53, 100, 164, 244, 340, 452, 580, 724]		712°, 713°			
	[6, 22, 53, 101, 163, 237, 326, 429, 546, 677]		710°			
	[6, 22, 54, 100, 158, 228, 312, 410, 520, 642]		717°			
	[6, 22, 54, 100, 158, 230, 316, 414, 526, 652]		707°			
	[6, 22, 54, 100, 159, 231, 317, 417, 530, 656]		716°			
	[6, 22, 54, 100, 161, 237, 327, 431, 549, 681]		718°			
	[6, 22, 54, 102, 165, 241, 331, 435, 553, 685]		719°			
	[6, 22, 54, 104, 172, 256, 356, 472, 604, 752]		720°			
	[6, 22, 55, 102, 160, 232, 318, 416, 528, 654]		714°, 715°			
	[6, 22, 55, 103, 165, 241, 331, 435, 553, 685]		725°			
	[6, 22, 56, 104, 163, 238, 328, 429, 545, 676]		723°, 724°			
	[6, 22, 56, 109, 179, 265, 367, 485, 619, 769]		722°			
	[6, 22, 56, 109, 180, 268, 372, 492, 628, 780]		721°			
	[6, 22, 57, 109, 172, 247, 337, 441, 559, 691]		733°, 734°			
	[6, 22, 57, 111, 183, 272, 376, 496, 632, 784]		735°			
	[6, 22, 57, 111, 183, 273, 378, 498, 634, 786]		731°			
	[6, 22, 57, 113, 186, 274, 378, 498, 634, 786]		726°			
	[6, 22, 58, 110, 173, 247, 335, 439, 556, 687]		737°			
	[6, 22, 58, 110, 177, 264, 368, 488, 624, 776]					

Nbr.	gr	N ₀	H_i	L	m	X
			732*,			
			[6, 22, 58, 113, 186, 274, 378, 498, 634, 786]			
			727*, 728*,			
			[6, 22, 58, 114, 186, 274, 378, 498, 634, 786]			
			729*, 730*,			
			[6, 22, 58, 116, 190, 278, 382, 502, 638, 790]			
			736*,			
			[6, 22, 59, 118, 192, 280, 384, 504, 640, 792]			
			738*,			
			[6, 22, 59, 122, 198, 284, 389, 510, 644, 794]			
			739*,			
			[6, 23, 56, 102, 160, 232, 318, 416, 528, 654]			
			740*,			
			[6, 23, 56, 105, 167, 241, 330, 433, 550, 681]			
			741*, 742*,			
			[6, 23, 57, 105, 167, 243, 333, 437, 555, 687]			
			745*,			
			[6, 23, 58, 106, 165, 240, 330, 431, 547, 678]			
			743*, 744*,			
			[6, 23, 58, 107, 169, 245, 335, 439, 557, 689]			
			747*,			
			[6, 23, 59, 109, 169, 242, 331, 435, 551, 679]			
			749*,			
			[6, 23, 59, 111, 174, 249, 339, 443, 561, 693]			
			750*, 751*,			
			[6, 23, 59, 113, 184, 272, 376, 496, 632, 784]			
			746*, 748*,			
			[6, 23, 59, 113, 185, 274, 378, 498, 634, 786]			
			752*,			
			[6, 23, 59, 116, 190, 278, 382, 502, 638, 790]			
			754*, 755*,			
			[6, 23, 60, 117, 190, 279, 382, 502, 640, 791]			
			753*,			
			[6, 23, 61, 116, 185, 272, 376, 496, 632, 784]			
			756*,			
			[6, 23, 62, 117, 186, 274, 378, 498, 634, 786]			
			757*,			
			[6, 24, 58, 104, 163, 235, 321, 421, 534, 660]			
			758*,			
			[6, 24, 58, 104, 164, 238, 326, 428, 543, 671]			
			759*,			
			[6, 24, 58, 107, 169, 243, 332, 435, 552, 683]			
			760*, 761*,			
			[6, 24, 59, 107, 169, 245, 335, 439, 557, 689]			
			762*, 763*,			
			[6, 24, 59, 108, 171, 248, 339, 443, 561, 693]			
			764*,			
			[6, 24, 60, 109, 171, 246, 335, 439, 556, 687]			
			765*,			
			[6, 24, 61, 113, 181, 268, 372, 492, 628, 780]			
			766*,			
			[6, 24, 61, 115, 185, 272, 376, 496, 632, 784]			
			768*,			
			[6, 24, 61, 115, 186, 274, 378, 498, 634, 786]			
			767*,			
			[6, 24, 61, 116, 188, 276, 380, 500, 636, 788]			
			770*,			
			[6, 24, 62, 118, 190, 278, 382, 502, 638, 790]			
			769*,			
			[6, 24, 62, 119, 192, 280, 384, 504, 640, 792]			
			772*,			
			[6, 24, 63, 119, 192, 280, 384, 504, 640, 792]			
			773*, 774*,			
			[6, 24, 63, 120, 192, 280, 384, 504, 640, 792]			
			771*, 775*, 776*,			
			[6, 24, 63, 124, 198, 284, 387, 508, 645, 796]			
			777*,			
			[6, 25, 64, 118, 187, 274, 378, 498, 634, 786]			
			778*,			
			[6, 25, 65, 122, 194, 282, 386, 506, 642, 794]			
			779*, 780*,			
			[6, 26, 65, 120, 192, 280, 384, 504, 640, 792]			
			781*,			
			[6, 27, 67, 122, 194, 282, 386, 506, 642, 794]			
			782*,			
			[7, 22, 47, 82, 127, 182, 247, 322, 407, 502]			
		651	H_{610}	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, m_z t_z, t_z^{-1}$
		652	H_{615}	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, m_z t_z, t_z^{-1}$
			[7, 22, 48, 84, 130, 186, 253, 330, 417, 514]			
		653	H_{305}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, t_y, t_y^{-1}, r_z^2 r_z t_z^{-1}$
		654	H_{504}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_x^2 r_y t_y^{-1}, t_z, t_z^{-1}$
			[7, 23, 51, 90, 139, 199, 271, 354, 447, 551]			
		655	H_{461}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, m_z t_z^{-1}$
			[7, 23, 51, 91, 143, 207, 283, 371, 471, 583]			
		656	H_{617}	$\langle m_z \rangle$	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, t_z^{-1}$
			[7, 23, 51, 91, 143, 207, 284, 374, 476, 590]			
		657	H_{460}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z, m_z t_z^{-1}$
			[7, 23, 52, 93, 145, 210, 287, 375, 476, 589]			
		658	H_{461}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, r_x^2 t_z, m_z t_z^{-1}$

Nbr.	gr	Nº	H_i	L	m	X
[7, 23, 54, 99, 157, 231, 318, 417, 531, 658]		659	H_{460}	1	r_z^2	$r_z^2 t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_x^{-1}, r_y^2 t_z, m_x t_z^{-1}$
[7, 24, 53, 92, 143, 206, 279, 364, 461, 568]		660	H_{616}	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, m_x t_z^{-1}$
[7, 24, 53, 94, 147, 212, 290, 380, 482, 596]		661	H_{614}	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z, m_x t_z^{-1}$
[7, 24, 54, 95, 149, 216, 295, 386, 491, 607]		662	H_{323}	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, r_x^2 r_y t_y^{-1}, m_x t_z, m_x t_z^{-1}$
[7, 24, 54, 95, 149, 217, 298, 393, 502, 624]		663	H_{540}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_x^2 r_y t_y^{-1}, m_x t_z, m_x t_z^{-1}$
[7, 24, 54, 96, 150, 216, 294, 384, 486, 600]		664	H_{615}	$\langle m_z \rangle$	r_z^2	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, t_z^{-1}$
[7, 24, 55, 97, 150, 217, 295, 384, 487, 601]		665	H_{483}	1	r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, m_z t_z^{-1}$
[7, 24, 55, 98, 155, 224, 307, 402, 511, 632]		666	H_{431}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 24, 55, 98, 155, 224, 307, 402, 511, 632]		667	H_{616}	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, m_y t_z^{-1}$
[7, 24, 55, 99, 156, 227, 311, 408, 519, 643]		668	H_{483}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, m_z t_z^{-1}$
[7, 24, 56, 101, 157, 226, 307, 400, 508, 628]		669	H_{468}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 24, 56, 101, 157, 226, 308, 401, 508, 628]		670	H_{469}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, r_y^2 t_z^{-1}$
[7, 24, 56, 104, 170, 255, 357, 475, 609, 759]		671	H_{452}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_x^2 r_z t_z, m_z t_z^{-1}$
[7, 24, 56, 105, 172, 256, 356, 472, 604, 752]		672	H_{326}	1	i	$m_z r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 24, 58, 104, 162, 232, 318, 416, 526, 648]		673	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1}$
[7, 24, 58, 104, 162, 232, 318, 416, 526, 648]		674	H_{326}	1	i	$r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$
[7, 24, 58, 104, 163, 237, 324, 423, 537, 664]		675	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, m_z t_z^{-1}$
[7, 24, 58, 104, 163, 237, 324, 423, 537, 664]		676	H_{425}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 24, 59, 106, 170, 246, 338, 442, 562, 694]		677	H_{614}	$\langle m_z \rangle$	r_z^2	$r_z^2 t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_x^{-1}, r_y^2 t_z, m_x t_z^{-1}$
[7, 25, 55, 97, 151, 217, 295, 385, 487, 601]		678	H_{618}	$\langle m_z \rangle$	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z, m_y t_z^{-1}$
[7, 25, 56, 98, 152, 218, 296, 386, 488, 602]		679	H_{461}	1	r_z^2	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z, m_z t_z^{-1}$
[7, 25, 57, 102, 159, 231, 317, 415, 529, 656]		680	H_{460}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z, i t_z^{-1}$
[7, 25, 57, 103, 163, 237, 325, 427, 543, 673]		681	H_{618}	$\langle m_z \rangle$	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, m_x t_z^{-1}$
[7, 25, 58, 101, 158, 228, 309, 404, 512, 630]		682	H_{433}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 25, 58, 102, 160, 231, 314, 409, 519, 640]		683	H_{485}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 25, 58, 103, 159, 230, 314, 408, 517, 639]		684	H_{461}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, i t_z^{-1}$
[7, 25, 58, 103, 163, 238, 327, 428, 545, 673]		685	H_{462}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 25, 58, 104, 164, 237, 324, 423, 537, 662]		686	H_{475}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 25, 58, 105, 163, 234, 319, 416, 527, 650]		687	H_{433}	1	r_z^2	$i t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 25, 58, 106, 165, 235, 319, 417, 529, 651]		688	H_{466}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_x^2 t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 25, 58, 106, 165, 239, 326, 425, 539, 666]		689	H_{482}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 25, 59, 106, 165, 239, 326, 425, 539, 666]		690	H_{461}	1	r_z^2	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, m_z t_z^{-1}$
[7, 25, 59, 106, 167, 240, 327, 426, 540, 666]		691	H_{481}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 25, 60, 106, 169, 244, 336, 440, 560, 692]		692	H_{461}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, r_x^2 t_z, i t_z^{-1}$
[7, 25, 60, 107, 165, 236, 321, 418, 529, 652]		693	H_{460}	1	r_z^2	$r_z^2 t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 t_z, i t_z^{-1}$
[7, 25, 60, 107, 165, 236, 321, 418, 529, 652]		694	H_{427}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 25, 60, 108, 171, 249, 340, 441, 563, 699]		695	H_{462}	1	r_z^2	$i t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 25, 60, 112, 182, 270, 374, 494, 630, 782]		696	H_{527}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1}, r_y^2 r_z t_z, m_z t_z^{-1}$
[7, 25, 60, 112, 182, 270, 375, 494, 631, 782]		697	H_{503}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_x^2 r_z t_z, r_y^2 t_z^{-1}$
[7, 25, 63, 114, 185, 271, 375, 494, 631, 782]						

Nbr.	gr	N ₀	H _i	L	m	X
698			H ₅₀₃	1	r_z^2	$r_z^2 t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_x^2 r_z t_z, r_y^2 t_z^{-1}$
[7, 25, 63, 121, 190, 278, 386, 506, 639, 791]			699		r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_y t_y, m_z t_z, i t_z^{-1}$
[7, 25, 65, 114, 175, 249, 341, 445, 561, 690]			700		r_z^2	$r_z^2 r_x t_x, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 26, 56, 98, 152, 218, 296, 386, 488, 602]			701		r_z^2	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z, m_y t_z^{-1}$
[7, 26, 59, 104, 163, 234, 319, 416, 527, 650]			702		r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, i t_z, r_z^2 t_z^{-1}$
[7, 26, 59, 106, 164, 235, 320, 417, 528, 651]			703		r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, i t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 26, 59, 106, 165, 236, 321, 418, 529, 652]			704		r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 26, 60, 106, 164, 234, 320, 418, 528, 650]			705		i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 26, 60, 107, 166, 240, 327, 426, 540, 667]			706		r_z^2	$r_z^2 r_x t_x, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
[7, 26, 60, 107, 166, 240, 327, 426, 540, 667]			707		r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, i t_z^{-1}$
[7, 26, 60, 107, 169, 244, 334, 437, 555, 686]			708		i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, m_z t_y, m_z t_y^{-1}, r_z^2 r_z t_z^{-1}$
[7, 26, 60, 109, 170, 243, 332, 433, 548, 675]			709		r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_x^2 t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 26, 60, 109, 171, 247, 340, 444, 564, 696]			710		r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, i t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 26, 60, 109, 173, 250, 342, 446, 566, 698]			711		r_z^2	$r_z^2 r_x t_x, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}$
[7, 26, 60, 111, 178, 262, 362, 478, 610, 758]			712		i	$r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_z^{-1} t_z, r_z^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
[7, 26, 61, 108, 167, 241, 328, 427, 541, 668]			713		r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_x^{-1} t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
[7, 26, 61, 108, 167, 241, 328, 427, 541, 668]			714		r_z^2	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 26, 61, 108, 169, 242, 331, 432, 547, 674]			715		r_z^2	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 26, 61, 108, 169, 242, 331, 432, 547, 674]			716		r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, i t_z, r_z^2 t_z^{-1}$
[7, 26, 61, 108, 170, 243, 332, 433, 548, 675]			717		r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_x^2 r_y t_y^{-1}, m_y t_z, m_y t_z^{-1}$
[7, 26, 61, 108, 171, 247, 340, 444, 564, 696]			718		i	$r_z^2 t_x, r_z^2 t_x^{-1}, r_x^2 r_y t_y^{-1}, m_x t_z, m_x t_z^{-1}, r_x^2 t_z^{-1}$
[7, 26, 61, 110, 174, 250, 342, 446, 566, 698]			719		r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, i t_z^{-1}$
[7, 26, 61, 112, 181, 267, 369, 487, 621, 771]			720		r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_x^2 r_z t_z, m_x r_z^{-1} t_z^{-1}$
[7, 26, 61, 112, 181, 268, 372, 492, 628, 780]			721		r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 r_z t_z, m_z t_z^{-1}$
[7, 26, 61, 113, 183, 270, 373, 492, 627, 778]			722		i	$i t_x^{-1}, t_y, t_y^{-1}, m_x r_z^{-1} t_z, r_y^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
[7, 26, 62, 109, 171, 247, 337, 439, 558, 688]			723		r_z^2	$r_x^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_x^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 26, 62, 110, 174, 250, 342, 446, 566, 698]			724		r_z^2	$r_x^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_x^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 26, 62, 110, 174, 250, 342, 446, 566, 698]			725		r_z^2	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, m_x t_z^{-1}$
[7, 26, 62, 116, 187, 275, 379, 499, 635, 787]			726		r_z^2	$r_z^2 t_x^{-1}, r_y t_y, r_x^2 r_y t_y^{-1}, r_y^{-1} t_y^{-1}, t_z, t_z^{-1}$
[7, 26, 63, 115, 188, 274, 380, 498, 636, 786]			727		i	$r_z^2 t_x^{-1}, m_z t_y, m_z t_y^{-1}, m_x r_z^{-1} t_z, r_y^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
[7, 26, 63, 116, 187, 275, 379, 499, 635, 787]			728		i	$r_z^2 t_x, r_z^2 t_x^{-1}, m_x r_y t_y, r_x^2 r_y t_y^{-1}, m_x r_y t_y^{-1}, r_x^2 t_z^{-1}$
[7, 26, 63, 116, 187, 275, 379, 499, 635, 787]			729		r_z^2	$i t_x^{-1}, r_y t_y, r_x^2 r_y t_y^{-1}, r_x^{-1} t_x^{-1}, m_y t_z, m_y t_z^{-1}$
[7, 26, 63, 117, 188, 276, 380, 499, 636, 786]			730		r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}$
[7, 26, 64, 113, 181, 267, 370, 490, 626, 778]			731		r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_y t_y, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
[7, 26, 64, 114, 177, 253, 345, 449, 569, 701]			732		r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_x^2 r_z t_z, i t_z^{-1}$
[7, 26, 64, 114, 177, 253, 345, 449, 569, 701]			733		r_z^2	$r_y^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 26, 64, 117, 188, 275, 378, 498, 634, 786]			734		r_z^2	$r_y^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 26, 64, 117, 188, 275, 378, 498, 634, 786]			735		r_z^2	$m_x t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
[7, 26, 64, 120, 191, 279, 383, 503, 639, 791]			736		r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, i t_y^{-1}, r_x^2 r_z t_z, r_y^2 r_z t_z^{-1}$
[7, 26, 65, 114, 177, 251, 343, 447, 566, 697]			737		r_z^2	$r_z^2 r_x t_x, r_y^2 t_y, r_y^2 t_y^{-1}, r_z^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 26, 65, 121, 192, 280, 384, 504, 640, 792]			738		r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, i t_y^{-1}, r_z t_z, r_z^{-1} t_z^{-1}$
[7, 26, 66, 127, 196, 284, 389, 509, 643, 795]			739		r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_x^2 t_y, r_x^2 t_z, r_y^2 t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
[7, 27, 61, 108, 167, 241, 328, 427, 541, 668]		740	H_{461}	1	r_z^2	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_z^2 t_z, i t_z^{-1}$
[7, 27, 62, 112, 175, 251, 343, 447, 567, 699]		741	H_{477}	1	r_z^2	$r_y^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, m_z t_z, i t_z^{-1}$
		742	H_{429}	1	r_z^2	$r_y^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 27, 63, 110, 172, 248, 338, 440, 559, 689]		743	H_{466}	1	r_z^2	$r_z^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, m_z t_z, i t_z^{-1}$
		744	H_{427}	1	r_z^2	$r_z^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_z^2 t_z, r_y^2 t_z^{-1}$
[7, 27, 63, 111, 175, 251, 343, 447, 567, 699]		745	H_{617}	$\langle m_z \rangle$	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, i t_z, r_z^2 t_z^{-1}$
[7, 27, 63, 115, 185, 272, 376, 496, 632, 784]		746	H_{503}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_z^2 r_z t_z, r_z^2 t_z^{-1}$
[7, 27, 64, 112, 176, 252, 344, 448, 568, 700]		747	H_{461}	1	r_z^2	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, i t_z^{-1}$
[7, 27, 64, 117, 187, 274, 378, 498, 634, 786]		748	H_{527}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, m_z t_z^{-1}$
[7, 27, 65, 113, 174, 249, 341, 445, 561, 690]		749	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_x t_y, m_y t_y, m_x t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 27, 65, 115, 178, 254, 346, 450, 570, 702]		750	H_{475}	1	r_z^2	$i t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}$
		751	H_{485}	1	r_z^2	$i t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_z^2 t_z, r_y^2 t_z^{-1}$
[7, 27, 65, 119, 191, 279, 383, 503, 639, 791]		752	H_{622}	$\langle m_z \rangle$	r_z^2	$m_x t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1}, r_y^2 r_z t_z, m_x r_z t_z^{-1}$
[7, 27, 65, 121, 192, 280, 383, 505, 640, 792]		753	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}$
[7, 27, 65, 122, 193, 281, 385, 505, 641, 793]		754	H_{505}	1	r_z^2	$r_z^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_x^2 r_z t_z, r_y^2 r_z t_z^{-1}$
		755	H_{506}	1	r_z^2	$r_y^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_z^2 t_z, r_z^{-1} t_z^{-1}$
[7, 27, 66, 117, 186, 273, 376, 496, 632, 784]		756	H_{503}	1	r_z^2	$r_z^2 t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
[7, 27, 68, 119, 189, 276, 379, 499, 635, 787]		757	H_{527}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1}$
[7, 28, 63, 110, 171, 244, 333, 434, 549, 676]		758	H_{305}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, i t_y, i t_y^{-1}, r_y^2 r_z t_z^{-1}$
[7, 28, 63, 110, 173, 248, 339, 442, 559, 688]		759	H_{504}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_x^2 r_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}$
[7, 28, 63, 113, 176, 252, 344, 448, 568, 700]		760	H_{473}	1	r_z^2	$i t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, m_z t_z, i t_z^{-1}$
		761	H_{474}	1	r_z^2	$i t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 28, 64, 112, 176, 252, 344, 448, 568, 700]		762	H_{615}	$\langle m_z \rangle$	r_z^2	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, i t_z, r_z^2 t_z^{-1}$
		763	H_{326}	1	i	$r_z^2 r_x t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}$
[7, 28, 64, 113, 177, 254, 346, 450, 570, 702]		764	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, i t_z, i t_z^{-1}$
[7, 28, 65, 113, 176, 251, 343, 447, 566, 697]		765	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_y^2 t_y, r_x^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[7, 28, 65, 115, 183, 269, 372, 492, 628, 780]		766	H_{452}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1}$
[7, 28, 65, 118, 188, 275, 379, 499, 635, 787]		767	H_{529}	1	r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
[7, 28, 66, 119, 188, 275, 378, 498, 634, 786]		768	H_{529}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
[7, 28, 66, 120, 191, 279, 383, 503, 639, 791]		769	H_{438}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_x^2 r_z t_z, r_y^2 r_z t_z^{-1}$
[7, 28, 66, 121, 192, 280, 384, 504, 640, 792]		770	H_{323}	1	i	$r_z^2 t_x^{-1}, m_x r_y t_y, r_x^2 r_y t_y^{-1}, m_x r_y t_y^{-1}, m_x t_z, m_x t_z^{-1}$
[7, 28, 67, 121, 192, 280, 384, 504, 640, 792]		771	H_{446}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_z t_z, r_z^{-1} t_z^{-1}$
[7, 28, 67, 123, 194, 282, 386, 506, 642, 794]		772	H_{540}	1	r_z^2	$i t_x^{-1}, r_y t_y, r_x^2 r_y t_y^{-1}, r_y^{-1} t_y^{-1}, m_x t_z, m_x t_z^{-1}$
[7, 28, 68, 122, 195, 281, 387, 505, 643, 793]		773	H_{305}	1	i	$i t_x^{-1}, i t_y, i t_y^{-1}, m_x r_z^{-1} t_z, r_z^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
		774	H_{326}	1	i	$m_z r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}$
[7, 28, 68, 123, 194, 282, 386, 506, 642, 794]		775	H_{504}	1	r_z^2	$r_z^2 t_x^{-1}, r_y t_y, r_x^2 r_y t_y^{-1}, r_x^{-1} t_x^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}$
		776	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_y t_y^{-1}, i t_z, i t_z^{-1}$
[7, 28, 68, 127, 196, 284, 387, 509, 644, 796]		777	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_z^2 t_y^{-1}, r_z^2 t_z, r_y^2 t_z^{-1}$
[7, 29, 68, 120, 189, 276, 379, 499, 635, 787]		778	H_{527}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1}$
[7, 29, 69, 124, 195, 283, 387, 507, 643, 795]		779	H_{496}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_z^2 r_z t_z, r_y^2 r_z t_z^{-1}$
		780	H_{514}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_z t_z, r_z^{-1} t_z^{-1}$
[7, 30, 67, 121, 192, 280, 384, 504, 640, 792]						

Nbr.	gr	N ₀	H_i	L	m	X
		781	H_{611}	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 r_z t_z, m_x r_z t_z^{-1}$
[7, 31, 69, 124, 195, 283, 387, 507, 643, 795]						
		782	H_{622}	$\langle m_z \rangle$	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, m_x r_z t_z^{-1}$
[7, 23, 51, 91, 143, 207, 283, 371, 471, 583]						
		783 ^a				
		784 ^a				
		785 ^a				
		786 ^a				
		787 ^a				
		788 ^a				
		789 ^a				
		790 ^a				
		791 ^a				
		792 ^a				
		793 ^a				
		794 ^a				
		795 ^a				
		796 ^a				
		797 ^a				
		798 ^a				
		799 ^a , 800 ^a , 801 ^a , 802 ^a				
		803 ^a				
		804 ^a				
		805 ^a				
		806 ^a , 807 ^a , 808 ^a , 809 ^a				
		810 ^a				
		811 ^a , 812 ^a , 813 ^a , 814 ^a				
		815 ^a				
		816 ^a				
		817 ^a				
		818 ^a				
		819 ^a				
		820 ^a				
		821 ^a				
		822 ^a				
		823 ^a				
		824 ^a				
		825 ^a				
		826 ^a				
		827 ^a				
		828 ^a				
		829 ^a				
		830 ^a				
		831 ^a				
		832 ^a				
		833 ^a				
		834 ^a				
		835 ^a				
		836 ^a				
		837 ^a				
		838 ^a				
		839 ^a				
		840 ^a				
		841 ^a				
		842 ^a				
		843 ^a				
		844 ^a				
		845 ^a				
		846 ^a				
		847 ^a				
		848 ^a				
		849 ^a				
		850 ^a				
		851 ^a				
		852 ^a				
		853 ^a				
		854 ^a				
		855 ^a				
		856 ^a				
		857 ^a				
		858 ^a				
		859 ^a				
		860 ^a				
		861 ^a				
		862 ^a				
		863 ^a				
		864 ^a				
		865 ^a				
		866 ^a				
		867 ^a				
		868 ^a				
		869 ^a				
		870 ^a				
		871 ^a				
		872 ^a				
		873 ^a				
		874 ^a				
		875 ^a				
		876 ^a				
		877 ^a				
		878 ^a				
		879 ^a				
		880 ^a				
		881 ^a				
		882 ^a				
		883 ^a				
		884 ^a				
		885 ^a				
		886 ^a				
		887 ^a				
		888 ^a				
		889 ^a				
		890 ^a				
		891 ^a				
		892 ^a				
		893 ^a				
		894 ^a				
		895 ^a				
		896 ^a				
		897 ^a				
		898 ^a				
		899 ^a				
		900 ^a				
		901 ^a				
		902 ^a				
		903 ^a				
		904 ^a				
		905 ^a				
		906 ^a				
		907 ^a				
		908 ^a				
		909 ^a				
		910 ^a				
		911 ^a				
		912 ^a				
		913 ^a				
		914 ^a				
		915 ^a				
		916 ^a				
		917 ^a				
		918 ^a				
		919 ^a				
		920 ^a				
		921 ^a				
		922 ^a				
		923 ^a				
		924 ^a				
		925 ^a				
		926 ^a				
		927 ^a				
		928 ^a				
		929 ^a				
		930 ^a				
		931 ^a				
		932 ^a				
		933 ^a				
		934 ^a				
		935 ^a				
		936 ^a				
		937 ^a				
		938 ^a				
		939 ^a				
		940 ^a				
		941 ^a				
		942 ^a				
		943 ^a				
		944 ^a				
		945 ^a				
		946 ^a				
		947 ^a				
		948 ^a				
		949 ^a				
		950 ^a				
		951 ^a				
		952 ^a				
		953 ^a				
		954 ^a				
		955 ^a				
		956 ^a				
		957 ^a				
		958 ^a				
		959 ^a				
		960 ^a				
		961 ^a				
		962 ^a				
		963 ^a				
		964 ^a				
		965 ^a				
		966 ^a				
		967 ^a				
		968 ^a				
		969 ^a				
		970 ^a				
		971 ^a				
		972 ^a				
		973 ^a				
		974 ^a				
		975 ^a				
		976 ^a				
		977 ^a				
		978 ^a				
		979 ^a				
		980 ^a				
		981 ^a				
		982 ^a				
		983 ^a				
		984 ^a				
		985 ^a				
		986 ^a				
		987 ^a				
		988 ^a				
		989 ^a				
		990 ^a				
		991 ^a				
		992 ^a				
		993 ^a				
		994 ^a				
		995 ^a				
		996 ^a				
		997 ^a				
		998 ^a				
		999 ^a				
		1000 ^a				

Nbr.	gr	N ₀	H_i	L	m	X
		794	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_y^2 t_y, r_x^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[8, 28, 65, 113, 176, 252, 344, 448, 568, 700]						
		795	H_{344}	1	m_z	$r_z^2 t_x, i t_x^{-1}, i t_y, r_z^2 t_y, i t_y^{-1}, r_z^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
[8, 28, 65, 113, 178, 254, 346, 450, 570, 702]						
		796	H_{378}	1	m_z	$r_y^2 t_x, m_x t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$
[8, 28, 65, 115, 178, 254, 346, 450, 570, 702]						
		797	H_{682}	$\langle m_y \rangle$	m_x	$r_y^2 t_x^{-1}, r_z^2 t_y, m_y t_y, m_x t_y^{-1}, t_y^{-1}, m_z t_z, r_y^2 t_z^{-1}$
[8, 29, 66, 119, 188, 275, 378, 498, 634, 786]						
		798	H_{690}	$\langle m_x \rangle$	r_z^2	$r_z^2 t_x, m_y t_x^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, m_z r_z^{-1} t_z, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
[8, 29, 66, 119, 189, 276, 380, 500, 636, 788]						
		799	H_{452}	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 r_z t_z, m_z t_z^{-1}$
		800	H_{503}	1	r_z^2	$r_z^2 t_x, r_z^2 t_y, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 r_z t_z, r_z^2 t_z^{-1}$
		801	H_{527}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, m_z t_z^{-1}$
		802	H_{529}	1	r_z^2	$m_x t_x, m_y t_x, m_x t_x^{-1}, m_y t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
[8, 29, 67, 121, 192, 280, 384, 504, 640, 792]						
		803	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_y^2 r_x t_x^{-1}, r_x^{-1} t_x^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}$
[8, 30, 66, 114, 178, 254, 346, 450, 570, 702]						
		804	H_{750}	$\langle m_y, r_z^2 \rangle$	i	$r_y^2 t_x, r_z^2 t_x, m_z t_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, m_z t_y^{-1}, r_x^2 r_z t_z^{-1}$
[8, 30, 68, 123, 194, 282, 386, 506, 642, 794]						
		805	H_{750}	$\langle m_y, m_z \rangle$	r_z^2	$m_x t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}, r_y^2 r_z t_z, m_z r_z t_z, m_x r_z t_z^{-1}, r_z t_z^{-1}$
[8, 30, 69, 121, 190, 277, 380, 500, 636, 788]						
		806	H_{452}	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1}$
		807	H_{503}	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
		808	H_{527}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1}$
		809	H_{529}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1}$
[8, 30, 69, 126, 196, 284, 388, 508, 644, 796]						
		810	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_y^2 r_x t_x^{-1}, r_x^{-1} t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}$
[8, 32, 70, 125, 196, 284, 388, 508, 644, 796]						
		811	H_{604}	$\langle r_y^2 \rangle$	r_z^2	$i t_x, m_x t_x, m_y t_x^{-1}, m_x t_x^{-1}, m_y t_y^{-1}, r_x^2 r_z t_z, r_z t_z^{-1}$
		812	H_{598}	$\langle r_y^2 \rangle$	r_z^2	$r_z^2 t_x, r_y^2 t_x, r_x^2 t_x^{-1}, r_y^2 t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 r_z t_z, r_z t_z^{-1}$
		813	H_{611}	$\langle m_z \rangle$	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 r_z t_z, m_x r_z t_z^{-1}$
		814	H_{622}	$\langle m_z \rangle$	r_z^2	$m_x t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, m_x r_z t_z^{-1}$

13

- [6, 19, 44, 83, 134, 196, 272, 361, 460, 573]
816*,
[6, 19, 44, 84, 138, 201, 272, 357, 460, 577]
815*,
[6, 20, 45, 78, 121, 176, 238, 310, 395, 486]
817*, 818*,
[6, 20, 45, 80, 125, 180, 245, 320, 405, 500]
819*, 820*,
[6, 20, 47, 85, 132, 191, 261, 340, 431, 533]
821*,
[6, 20, 47, 87, 137, 195, 263, 343, 434, 535]
825*,
[6, 20, 47, 87, 139, 203, 280, 370, 471, 585]
823*,
[6, 20, 47, 87, 141, 211, 292, 382, 486, 602]
822*,
[6, 20, 47, 87, 141, 211, 297, 397, 509, 635]
826*,
[6, 20, 47, 89, 147, 216, 292, 384, 496, 615]
824*,
[6, 20, 49, 95, 154, 221, 296, 386, 492, 607]
827*,
[6, 20, 52, 105, 170, 243, 329, 429, 544, 675]

Nbr.	gr	N ₀	H_i	L	m	X
		828*, [6, 21, 50, 90, 143, 212, 290, 381, 490, 606]				
		829*, [6, 21, 51, 93, 146, 214, 293, 383, 489, 605]				
		830*, [6, 21, 52, 97, 152, 218, 295, 386, 492, 607]				
		831*, [6, 21, 52, 99, 159, 229, 307, 401, 513, 631]				
		832*, [6, 21, 53, 103, 168, 245, 331, 431, 546, 675]				
		835*, [6, 21, 53, 104, 169, 243, 329, 429, 544, 675]				
		833*, [6, 21, 53, 106, 169, 236, 320, 421, 534, 661]				
		834*, [6, 21, 53, 107, 173, 243, 327, 433, 555, 682]				
		836*, [6, 21, 54, 107, 172, 243, 327, 433, 555, 682]				
		837*, [6, 21, 58, 112, 175, 249, 336, 440, 559, 690]				
		838*, [6, 22, 53, 95, 149, 217, 295, 386, 492, 607]				
		839*, [6, 22, 54, 97, 153, 225, 305, 399, 511, 629]				
		840*, [6, 22, 55, 100, 156, 228, 315, 414, 527, 655]				
		842*, [6, 22, 55, 106, 166, 237, 325, 427, 543, 673]				
		847*, [6, 22, 55, 107, 176, 255, 345, 447, 563, 694]				
		844*, [6, 22, 56, 102, 157, 227, 307, 401, 513, 631]				
		841*, [6, 22, 56, 105, 166, 240, 327, 428, 544, 673]				
		845*, [6, 22, 56, 106, 165, 237, 325, 427, 543, 673]				
		849*, [6, 22, 56, 107, 166, 234, 320, 421, 534, 661]				
		843*, [6, 22, 57, 108, 170, 244, 333, 436, 552, 683]				
		846*, [6, 22, 57, 109, 174, 250, 337, 439, 556, 687]				
		850*, [6, 22, 58, 109, 171, 246, 334, 436, 552, 682]				
		848*, [6, 22, 59, 111, 170, 243, 332, 434, 550, 680]				
		851*, [6, 23, 56, 101, 159, 232, 319, 420, 535, 664]				
		852*, [6, 23, 56, 107, 173, 249, 339, 442, 559, 691]				
		853*, [6, 23, 58, 108, 171, 246, 335, 439, 557, 689]				
		854*, [6, 23, 58, 109, 173, 251, 343, 445, 561, 693]				
		855*, [6, 23, 58, 110, 177, 254, 343, 445, 561, 693]				
		856*, [6, 23, 59, 114, 180, 252, 339, 443, 561, 693]				
		857*, [6, 23, 60, 112, 175, 250, 339, 443, 561, 693]				
		858*, [6, 23, 60, 114, 177, 250, 339, 443, 561, 693]				
		859*, [6, 24, 56, 100, 159, 232, 319, 420, 535, 664]				
		860*, [6, 24, 59, 110, 171, 243, 332, 435, 552, 683]				
		861*, [6, 24, 60, 108, 169, 245, 335, 439, 557, 689]				
		862*, [6, 24, 60, 109, 171, 247, 337, 441, 559, 691]				
		863*, [6, 24, 60, 111, 173, 247, 337, 441, 559, 691]				
		864*, 865*, [6, 24, 60, 113, 177, 250, 339, 443, 561, 693]				
		866*, [6, 24, 61, 112, 172, 245, 335, 439, 556, 687]				
		867*, [6, 24, 62, 112, 173, 249, 339, 443, 561, 693]				
		868*, [6, 24, 62, 114, 175, 249, 339, 443, 561, 693]				
		869*, [6, 24, 62, 115, 177, 250, 339, 443, 561, 693]				
		870*, [7, 23, 52, 95, 150, 216, 293, 381, 485, 603]				
		815 H_{412}	1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, m_z t_z^{-1}$
		[7, 23, 52, 95, 150, 218, 301, 393, 497, 619]				
		816 H_{413}	1		$r_z^2 r_x$	$m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, m_z t_z^{-1}$
		[7, 24, 52, 90, 141, 202, 273, 358, 452, 556]				
		817 H_{388}	1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_z r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, m_z r_x t_z^{-1}$
		[7, 24, 52, 91, 143, 204, 276, 362, 457, 563]				
		818 H_{400}	1		$r_z^2 r_x$	$m_x t_x^{-1}, m_z r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, m_z r_x t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
[7, 24, 53, 93, 145, 208, 283, 369, 467, 576]		819	H_{389}	1	$r_z^2 r_x$	$it_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, m_z r_x t_z^{-1}$
[7, 24, 53, 94, 147, 210, 287, 375, 474, 584]		820	H_{398}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, m_z r_x t_z^{-1}$
[7, 24, 54, 95, 148, 213, 288, 376, 477, 588]		821	H_{418}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, r_x t_z^{-1}$
[7, 24, 54, 96, 152, 221, 301, 395, 501, 618]		822	H_{407}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, r_x t_z^{-1}$
[7, 24, 54, 98, 154, 222, 307, 400, 504, 630]		823	H_{395}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_x^2 t_y, it_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, r_x^2 t_z^{-1}$
[7, 24, 54, 98, 156, 225, 306, 402, 510, 629]		824	H_{394}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_x^2 t_y, it_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, r_x^2 t_z^{-1}$
[7, 24, 55, 99, 154, 219, 298, 389, 493, 610]		825	H_{410}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, r_x t_z^{-1}$
[7, 24, 55, 99, 157, 231, 320, 423, 543, 677]		826	H_{414}	1	$r_z^2 r_x$	$it_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, r_x t_z^{-1}$
[7, 24, 56, 103, 161, 227, 306, 401, 506, 623]		827	H_{419}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z^{-1}$
[7, 24, 60, 112, 175, 249, 337, 438, 557, 689]		828	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z^{-1}$
[7, 25, 56, 99, 157, 226, 307, 405, 512, 631]		829	H_{395}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y, m_z r_x t_y^{-1}, m_z r_x t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
[7, 25, 57, 100, 156, 225, 305, 399, 505, 622]		830	H_{413}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_x^{-1} t_y^{-1}, r_x t_z, m_x r_x t_z^{-1}$
[7, 25, 58, 103, 159, 226, 306, 401, 506, 623]		831	H_{402}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z^{-1}$
[7, 25, 58, 106, 166, 234, 316, 416, 524, 644]		832	H_{401}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
[7, 25, 60, 111, 175, 249, 337, 438, 557, 689]		833	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z, m_z t_z, m_z t_z^{-1}$
[7, 25, 60, 113, 172, 243, 332, 433, 548, 674]		834	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
[7, 25, 61, 111, 177, 253, 343, 447, 566, 698]		835	H_{418}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, r_y^2 t_z^{-1}$
[7, 25, 62, 116, 177, 249, 344, 452, 567, 694]		836	H_{415}	1	$r_z^2 r_x$	$it_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z^{-1}$
[7, 25, 63, 115, 177, 249, 344, 452, 567, 694]		837	H_{404}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z^{-1}$
[7, 25, 65, 114, 178, 251, 343, 448, 567, 699]		838	H_{407}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, r_y^2 t_z^{-1}$
[7, 26, 58, 101, 158, 226, 306, 401, 506, 623]		839	H_{412}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_x^{-1} t_y^{-1}, r_x t_z, m_x r_x t_z^{-1}$
[7, 26, 59, 103, 163, 233, 315, 415, 523, 643]		840	H_{394}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y, m_z r_x t_y^{-1}, m_z r_x t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
[7, 26, 61, 106, 164, 234, 316, 416, 524, 644]		841	H_{391}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
[7, 26, 62, 107, 168, 243, 332, 433, 551, 680]		842	H_{395}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y, it_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, r_y^2 r_x t_z^{-1}$
[7, 26, 62, 112, 170, 243, 332, 433, 548, 674]		843	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z, r_x^2 t_z^{-1}$
[7, 26, 62, 114, 181, 257, 349, 451, 571, 702]		844	H_{413}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1}, r_y^2 t_z, m_x r_x t_z^{-1}$
[7, 26, 63, 111, 174, 249, 338, 441, 559, 688]		845	H_{413}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, m_x r_x t_z^{-1}$
[7, 26, 63, 112, 175, 250, 341, 444, 563, 694]		846	H_{394}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y, it_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, r_y^2 r_x t_z^{-1}$
[7, 26, 63, 114, 175, 251, 343, 447, 567, 699]		847	H_{396}	1	$r_z^2 r_x$	$it_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
[7, 26, 64, 112, 175, 250, 341, 444, 562, 692]		848	H_{412}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, m_x r_x t_z^{-1}$
[7, 26, 64, 113, 175, 251, 343, 447, 567, 699]		849	H_{392}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
[7, 26, 64, 114, 179, 254, 344, 448, 568, 700]		850	H_{400}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_z r_x t_y, it_y^{-1}, it_z, it_z^{-1}, m_z r_x t_z^{-1}$
[7, 26, 65, 113, 174, 249, 339, 442, 560, 690]		851	H_{388}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_z r_x t_y, it_y^{-1}, it_z, it_z^{-1}, m_z r_x t_z^{-1}$
[7, 27, 62, 108, 170, 245, 335, 438, 556, 687]		852	H_{401}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}$
[7, 27, 62, 114, 178, 254, 346, 449, 569, 701]		853	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
[7, 27, 64, 113, 177, 252, 344, 448, 568, 700]		854	H_{419}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}$
[7, 27, 64, 114, 178, 256, 348, 450, 570, 702]		855	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$
[7, 27, 64, 115, 181, 256, 348, 450, 570, 702]						

Nbr.	gr	N ₀	H_i	L	m	X
		856	H_{395}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y, it_y^{-1}, it_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
		[7, 27, 65, 118, 181, 254, 346, 450, 570, 702]				
		857	H_{412}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1}, r_y^2 t_z, m_x r_x t_z^{-1}$
		[7, 27, 66, 115, 179, 254, 346, 450, 570, 702]				
		858	H_{410}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, r_y^2 t_z^{-1}$
		[7, 27, 66, 117, 179, 254, 346, 450, 570, 702]				
		859	H_{414}	1	$r_z^2 r_x$	$it_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, r_y^2 t_z^{-1}$
		[7, 28, 61, 108, 170, 245, 335, 438, 556, 687]				
		860	H_{392}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_z^2 t_y^{-1}, r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}$
		[7, 28, 64, 115, 176, 252, 344, 448, 568, 700]				
		861	H_{389}	1	$r_z^2 r_x$	$it_x^{-1}, m_z r_x t_y, it_y^{-1}, it_z, it_z^{-1}, m_z r_x t_z^{-1}$
		[7, 28, 65, 112, 176, 252, 344, 448, 568, 700]				
		862	H_{404}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}$
		[7, 28, 65, 113, 177, 253, 345, 449, 569, 701]				
		863	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}$
		[7, 28, 65, 115, 177, 253, 345, 449, 569, 701]				
		864	H_{396}	1	$r_z^2 r_x$	$it_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}$
		[7, 28, 65, 117, 179, 254, 346, 450, 570, 702]				
		865	H_{391}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}$
		[7, 28, 65, 117, 179, 254, 346, 450, 570, 702]				
		866	H_{402}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}$
		[7, 28, 66, 115, 176, 252, 344, 448, 568, 700]				
		867	H_{398}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, m_z r_x t_y, it_y^{-1}, it_z, it_z^{-1}, m_z r_x t_z^{-1}$
		[7, 28, 67, 114, 178, 254, 346, 450, 570, 702]				
		868	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}$
		[7, 28, 67, 116, 178, 254, 346, 450, 570, 702]				
		869	H_{415}	1	$r_z^2 r_x$	$it_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}$
		[7, 28, 67, 117, 179, 254, 346, 450, 570, 702]				
		870	H_{394}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y, it_y^{-1}, it_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$

14

- [7, 24, 54, 95, 149, 217, 295, 386, 492, 607]
871*,
[7, 24, 55, 99, 156, 226, 308, 404, 514, 636]
872*,
[7, 24, 55, 99, 156, 227, 311, 408, 519, 643]
873*,
[7, 24, 56, 103, 163, 235, 320, 419, 531, 656]
874*,
[7, 24, 56, 103, 165, 241, 329, 429, 544, 675]
875*,
[7, 24, 56, 105, 169, 242, 327, 433, 555, 682]
876*,
[7, 25, 56, 98, 155, 224, 304, 400, 507, 626]
877*,
[7, 25, 57, 99, 155, 227, 307, 401, 513, 631]
878*,
[7, 25, 57, 100, 157, 229, 312, 408, 519, 642]
879*,
[7, 25, 57, 102, 161, 233, 318, 417, 529, 654]
880*,
[7, 25, 57, 103, 163, 237, 325, 427, 543, 673]
887*,
[7, 25, 58, 103, 162, 239, 330, 429, 541, 672]
881*,
[7, 25, 58, 104, 163, 234, 320, 421, 534, 661]
883*,
[7, 25, 58, 104, 163, 235, 320, 419, 531, 656]
882*,
[7, 25, 58, 104, 163, 237, 325, 426, 541, 670]
884*,
[7, 25, 58, 105, 166, 241, 330, 433, 550, 681]
890*,
[7, 25, 59, 106, 164, 235, 320, 419, 531, 656]
885*, 886*,
[7, 25, 60, 108, 168, 242, 329, 431, 547, 675]
888*,
[7, 25, 60, 109, 170, 245, 334, 436, 552, 682]
889*,
[7, 25, 62, 111, 172, 249, 339, 443, 561, 693]
891*,
[7, 25, 63, 113, 173, 249, 339, 443, 561, 693]
892*,
[7, 26, 60, 105, 163, 235, 320, 419, 531, 656]
893*, 894*, 895*, 896*,
[7, 26, 61, 107, 167, 242, 329, 431, 547, 675]
897*, 900*,
[7, 26, 61, 108, 168, 243, 332, 435, 552, 683]
902*, 903*,
[7, 26, 62, 109, 168, 243, 332, 434, 550, 680]
898*, 899*,
[7, 26, 62, 110, 170, 245, 335, 438, 554, 685]
901*,
[7, 26, 62, 110, 172, 249, 339, 443, 561, 693]
904*, 905*, 906*,
[7, 26, 63, 112, 173, 249, 339, 443, 561, 693]
907*, 908*,
[7, 26, 63, 113, 175, 250, 339, 443, 561, 693]

Nbr.	gr	N ₀	H_i	L	m	X
			909*, 910*, [7, 27, 60, 104, 163, 235, 320, 419, 531, 656]			
			911*, 912*, [7, 27, 61, 107, 168, 243, 332, 435, 552, 683]			
			915*, 916*, [7, 27, 62, 108, 168, 243, 332, 434, 550, 680]			
			913*, 914*, 917*, [7, 27, 62, 109, 170, 245, 335, 439, 556, 687]			
			918*, 919*, [7, 27, 63, 111, 173, 249, 339, 443, 561, 693]			
			920*, [7, 27, 65, 113, 173, 249, 339, 443, 561, 693]			
			921*, 922*, 923*, 924*, 925*, 926*, [7, 28, 65, 112, 173, 249, 339, 443, 561, 693]			
			927*, 928*, 929*, 930*, 931*, 932*, [7, 29, 65, 111, 173, 249, 339, 443, 561, 693]			
			933*, 934*, [8, 27, 58, 101, 158, 226, 306, 401, 506, 623]			
		871	H_{650}	$\langle m_z r_x \rangle$	m_x	$m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, m_y t_y^{-1}, r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1},$ $r_x^{-1} t_z^{-1}$
			[8, 27, 59, 104, 163, 234, 318, 416, 526, 650]			
		872	H_{359}	1	m_z	$it_x, r_z^2 t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_z t_z^{-1}$
			[8, 27, 60, 106, 166, 240, 326, 426, 540, 666]			
		873	H_{370}	1	m_z	$it_x, r_z^2 t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z^{-1}$
			[8, 27, 61, 109, 169, 242, 329, 429, 542, 669]			
		874	H_{368}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_y^2 t_z^{-1}$
			[8, 27, 61, 109, 173, 249, 337, 438, 557, 689]			
		875	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z,$ $m_z t_z^{-1}$
			[8, 27, 63, 113, 176, 249, 344, 452, 567, 694]			
		876	H_{652}	$\langle m_z r_x \rangle$	m_x	$r_z^2 r_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, m_y t_y^{-1}, r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1},$ $r_x^{-1} t_z^{-1}$
			[8, 28, 59, 104, 163, 231, 316, 412, 519, 643]			
		877	H_{359}	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_z t_z^{-1}$
			[8, 28, 60, 104, 164, 234, 316, 416, 524, 644]			
		878	H_{648}	$\langle m_z r_x \rangle$	m_x	$m_x t_x^{-1}, r_x^2 t_y, it_y^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1},$ $m_z r_x^{-1} t_z^{-1}$
			[8, 28, 60, 105, 165, 236, 321, 420, 531, 655]			
		879	H_{350}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_z t_z^{-1}$
			[8, 28, 61, 108, 169, 242, 329, 429, 542, 669]			
		880	H_{365}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z^{-1}$
			[8, 28, 62, 108, 172, 249, 336, 436, 555, 687]			
		881	H_{372}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z^{-1}$
			[8, 28, 62, 109, 169, 242, 329, 429, 542, 669]			
		882	H_{370}	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z^{-1}$
			[8, 28, 62, 109, 170, 243, 332, 433, 548, 674]			
		883	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z,$ $r_x^2 t_z^{-1}$
			[8, 28, 62, 109, 172, 247, 337, 440, 558, 688]			
		884	H_{361}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, it_y^{-1}, r_z^2 t_y^{-1},$ $r_y^2 t_z^{-1}$
			[8, 28, 63, 110, 169, 242, 329, 429, 542, 669]			
		885	H_{359}	1	m_z	$it_x, r_z^2 t_x, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_z t_z^{-1}$
		886	H_{353}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_z t_z^{-1}$
			[8, 28, 63, 111, 175, 251, 343, 447, 567, 699]			
		887	H_{649}	$\langle m_z r_x \rangle$	m_x	$r_z^2 r_x t_x^{-1}, r_x^2 t_y, it_y^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1},$ $m_z r_x^{-1} t_z^{-1}$
			[8, 28, 64, 111, 173, 247, 337, 440, 556, 686]			
		888	H_{359}	1	m_z	$it_x, r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_z t_z^{-1}$
			[8, 28, 64, 112, 174, 250, 341, 444, 562, 692]			
		889	H_{377}	1	m_z	$r_y^2 t_x, m_z r_z^{-1} t_x^{-1}, r_z^{-1} t_x^{-1}, m_z r_z t_y, r_z t_y, m_y t_y^{-1},$ $m_z t_z^{-1}$
			[8, 28, 64, 112, 176, 252, 344, 448, 568, 700]			
		890	H_{364}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ it_z^{-1}
			[8, 28, 67, 113, 178, 254, 346, 450, 570, 702]			

Nbr.	gr	N ₀	H_i	L	m	X
		891	H_{370}	1	m_z	$it_x, r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
[8, 28, 68, 114, 178, 254, 346, 450, 570, 702]						
		892	H_{368}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
[8, 29, 63, 109, 169, 242, 329, 429, 542, 669]						
		893	H_{350}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
		894	H_{370}	1	m_z	$it_x, r_z^2 t_x, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
		895	H_{359}	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
		896	H_{368}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
[8, 29, 64, 110, 173, 247, 337, 440, 556, 686]						
		897	H_{359}	1	m_z	$it_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
[8, 29, 65, 111, 174, 249, 339, 442, 560, 690]						
		898	H_{330}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, it_y, it_y^{-1}, r_z^2 t_y^{-1}, m_z t_z^{-1}$
		899	H_{350}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
[8, 29, 65, 111, 175, 250, 339, 443, 560, 689]						
		900	H_{382}	1	m_z	$r_y^2 t_x, m_z r_z^{-1} t_x^{-1}, r_z^{-1} t_x^{-1}, m_z r_z t_y, r_z t_y, m_y t_y^{-1}, r_y^2 r_z t_z^{-1}$
[8, 29, 65, 112, 175, 251, 342, 445, 564, 695]						
		901	H_{343}	1	m_z	$r_z^2 t_x, r_y^2 r_z t_x^{-1}, m_x r_z t_x^{-1}, it_y, r_y^2 r_z t_y^{-1}, m_x r_z t_y^{-1}, m_z t_z^{-1}$
[8, 29, 65, 112, 176, 252, 344, 448, 568, 700]						
		902	H_{361}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, it_y, it_y^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
		903	H_{365}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
[8, 29, 66, 113, 178, 254, 346, 450, 570, 702]						
		904	H_{370}	1	m_z	$it_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
		905	H_{378}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z^{-1}$
		906	H_{378}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, m_y t_y, m_y t_y^{-1}, r_y^2 r_z t_z^{-1}$
[8, 29, 67, 114, 178, 254, 346, 450, 570, 702]						
		907	H_{372}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
		908	H_{373}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, it_z^{-1}$
[8, 29, 67, 115, 179, 254, 346, 450, 570, 702]						
		909	H_{359}	1	m_z	$it_x, r_z^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
		910	H_{650}	$\langle m_z r_x \rangle$	m_x	$m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_y t_y^{-1}, m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_x^{-1} t_z^{-1}$
[8, 30, 62, 109, 169, 242, 329, 429, 542, 669]						
		911	H_{365}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
		912	H_{370}	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
[8, 30, 64, 111, 174, 249, 339, 442, 560, 690]						
		913	H_{361}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, it_y^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
		914	H_{372}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
[8, 30, 64, 112, 176, 252, 344, 448, 568, 700]						
		915	H_{332}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, it_y, it_y^{-1}, r_z^2 t_y^{-1}, it_z^{-1}$
		916	H_{364}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, it_z^{-1}$
[8, 30, 65, 112, 175, 251, 341, 444, 563, 693]						
		917	H_{347}	1	m_z	$r_z^2 t_x, r_y^2 r_z t_x^{-1}, m_x r_z t_x^{-1}, it_y, r_y^2 r_z t_y^{-1}, m_x r_z t_y^{-1}, r_x^2 r_z t_z^{-1}$
[8, 30, 65, 113, 176, 252, 344, 448, 568, 700]						
		918	H_{344}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, it_y, it_y^{-1}, r_z^2 t_y^{-1}, r_y^2 r_z t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
		919	H_{344}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, it_y, r_z^2 t_y, it_y^{-1},$ $r_y^2 r_z t_z^{-1}$
[8, 30, 66, 114, 178, 254, 346, 450, 570, 702]						
		920	H_{364}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ it_z^{-1}
[8, 30, 68, 114, 178, 254, 346, 450, 570, 702]						
		921	H_{648}	$\langle m_z r_x \rangle$	m_x	$m_x t_x^{-1}, it_y, it_y^{-1}, r_x^2 t_y^{-1}, r_z^2 r_x t_z, r_z^2 r_x t_z^{-1},$ $m_z r_x^{-1} t_z^{-1}$
		922	H_{350}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_z t_z^{-1}$
		923	H_{370}	1	m_z	$it_x, r_z^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z^{-1}$
		924	H_{359}	1	m_z	$it_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_z t_z^{-1}$
		925	H_{368}	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_y^2 t_z^{-1}$
		926	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z,$ $m_x r_x t_z^{-1}$
[8, 31, 67, 114, 178, 254, 346, 450, 570, 702]						
		927	H_{361}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, it_y, it_y^{-1}, r_z^2 t_y^{-1},$ $r_y^2 t_z^{-1}$
		928	H_{372}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_y^2 t_z^{-1}$
		929	H_{365}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z^{-1}$
		930	H_{370}	1	m_z	$it_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_z^2 t_z^{-1}$
		931	H_{652}	$\langle m_z r_x \rangle$	m_x	$r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_y t_y^{-1}, m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1},$ $r_x^{-1} t_z^{-1}$
		932	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z,$ $r_y^2 r_x t_z^{-1}$
[8, 32, 66, 114, 178, 254, 346, 450, 570, 702]						
		933	H_{649}	$\langle m_z r_x \rangle$	m_x	$r_z^2 r_x t_x^{-1}, it_y, it_y^{-1}, r_x^2 t_y^{-1}, r_z^2 r_x t_z, r_z^2 r_x t_z^{-1},$ $m_z r_x^{-1} t_z^{-1}$
		934	H_{364}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ it_z^{-1}

15

- [7, 23, 50, 87, 135, 194, 263, 343, 434, 535]
936*,
- [7, 23, 51, 91, 143, 207, 283, 371, 471, 583]
935*,
- [7, 23, 51, 92, 147, 214, 292, 383, 487, 604]
937*,
- [7, 23, 52, 94, 149, 217, 298, 392, 499, 619]
939*,
- [7, 23, 52, 95, 152, 221, 303, 399, 507, 627]
940*,
- [7, 23, 52, 96, 155, 227, 312, 411, 523, 648]
938*,
- [7, 24, 53, 93, 146, 210, 285, 373, 472, 583]
941*,
- [7, 24, 54, 95, 148, 214, 291, 379, 480, 593]
944*,
- [7, 24, 54, 96, 150, 216, 294, 384, 486, 600]
950*,
- [7, 24, 54, 96, 151, 219, 300, 394, 500, 619]
945*,
- [7, 24, 54, 97, 153, 222, 304, 399, 507, 628]
949*,
- [7, 24, 54, 97, 154, 224, 308, 407, 519, 644]
942*,
- [7, 24, 54, 97, 154, 225, 308, 404, 515, 639]
948*,
- [7, 24, 55, 97, 151, 220, 300, 392, 499, 616]
943*,
- [7, 24, 55, 98, 152, 218, 296, 386, 488, 602]
953*, 954*,
- [7, 24, 55, 99, 158, 233, 321, 421, 535, 663]
946*,
- [7, 24, 55, 100, 158, 229, 314, 413, 525, 650]
956*,
- [7, 24, 55, 100, 159, 231, 316, 415, 527, 652]
947*, 951*, 952*,
- [7, 24, 55, 100, 161, 239, 329, 428, 543, 679]
955*,
- [7, 24, 55, 101, 162, 237, 326, 429, 546, 677]
957*,
- [7, 24, 56, 101, 159, 231, 316, 414, 525, 649]
960*,
- [7, 24, 57, 109, 180, 268, 372, 492, 628, 780]
958*, 959*,

Nbr.	gr	N_0	H_i	L	m	X
			[7, 24, 58, 105, 165, 241, 331, 435, 553, 685]			
			961*,			
			[7, 24, 59, 108, 169, 245, 335, 439, 557, 689]			
			962*,			
			[7, 24, 59, 109, 171, 247, 337, 441, 559, 691]			
			963*,			
			[7, 25, 56, 98, 152, 218, 296, 386, 488, 602]			
			964*,			
			[7, 25, 57, 99, 152, 218, 296, 386, 488, 602]			
			968*,			
			[7, 25, 57, 102, 161, 233, 318, 417, 529, 654]			
			965*, 966*,			
			[7, 25, 58, 102, 158, 228, 311, 407, 516, 638]			
			967*, 969*,			
			[7, 25, 58, 102, 159, 231, 316, 414, 525, 649]			
			972*,			
			[7, 25, 58, 104, 163, 235, 320, 419, 531, 656]			
			970*, 971*,			
			[7, 25, 58, 105, 166, 241, 330, 433, 550, 681]			
			977*, 978*,			
			[7, 25, 59, 105, 163, 235, 321, 421, 534, 660]			
			982*, 983*,			
			[7, 25, 59, 105, 165, 241, 331, 435, 553, 685]			
			973*,			
			[7, 25, 59, 106, 166, 241, 330, 432, 548, 678]			
			974*, 975*,			
			[7, 25, 59, 107, 169, 245, 335, 439, 557, 689]			
			976*, 985*, 986*,			
			[7, 25, 59, 109, 177, 264, 368, 488, 624, 776]			
			979*,			
			[7, 25, 60, 108, 169, 245, 335, 439, 557, 689]			
			984*,			
			[7, 25, 60, 109, 169, 242, 331, 435, 551, 679]			
			990*, 991*,			
			[7, 25, 60, 109, 171, 247, 337, 441, 559, 691]			
			992*,			
			[7, 25, 60, 112, 182, 269, 373, 493, 629, 781]			
			987*,			
			[7, 25, 60, 113, 184, 272, 376, 496, 632, 784]			
			980*, 981*, 988*, 989*,			
			[7, 25, 61, 111, 173, 249, 339, 443, 561, 693]			
			993*,			
			[7, 25, 62, 116, 185, 272, 376, 496, 632, 784]			
			994*, 995*,			
			[7, 26, 57, 98, 152, 218, 296, 386, 488, 602]			
			998*,			
			[7, 26, 58, 101, 158, 228, 311, 407, 516, 638]			
			996*, 997*,			
			[7, 26, 59, 104, 163, 235, 320, 419, 531, 656]			
			999*, 1000*,			
			[7, 26, 59, 104, 163, 235, 321, 421, 534, 660]			
			1001*, 1002*,			
			[7, 26, 60, 107, 168, 243, 332, 435, 552, 683]			
			1006*, 1007*,			
			[7, 26, 60, 107, 169, 245, 335, 439, 557, 689]			
			1003*,			
			[7, 26, 61, 108, 168, 243, 332, 434, 550, 680]			
			1004*, 1005*,			
			[7, 26, 61, 109, 171, 246, 335, 439, 556, 687]			
			1008*, 1009*,			
			[7, 26, 61, 109, 171, 247, 337, 441, 559, 691]			
			1010*,			
			[7, 26, 61, 115, 186, 274, 378, 498, 634, 786]			
			1015*,			
			[7, 26, 62, 110, 171, 247, 337, 441, 559, 691]			
			1017*, 1018*, 1019*, 1020*,			
			[7, 26, 62, 111, 173, 249, 339, 443, 561, 693]			
			1021*,			
			[7, 26, 62, 112, 175, 250, 339, 443, 561, 693]			
			1022*, 1023*,			
			[7, 26, 62, 113, 181, 268, 372, 492, 628, 780]			
			1011*, 1012*,			
			[7, 26, 62, 115, 185, 272, 376, 496, 632, 784]			
			1024*, 1025*,			
			[7, 26, 62, 115, 186, 274, 378, 498, 634, 786]			
			1013*, 1014*,			
			[7, 26, 62, 118, 190, 278, 382, 502, 638, 790]			
			1016*,			
			[7, 26, 63, 112, 173, 249, 339, 443, 561, 693]			
			1028*, 1029*,			
			[7, 26, 63, 116, 186, 274, 378, 498, 634, 786]			
			1030*, 1031*,			
			[7, 26, 63, 118, 190, 278, 382, 502, 638, 790]			
			1026*, 1027*,			
			[7, 26, 65, 123, 195, 282, 385, 505, 642, 793]			
			1032*, 1033*,			
			[7, 26, 67, 126, 197, 284, 388, 508, 644, 796]			
			1034*,			
			[7, 27, 62, 109, 171, 247, 337, 441, 559, 691]			
			1036*, 1037*, 1038*,			
			[7, 27, 62, 112, 181, 268, 372, 492, 628, 780]			
			1035*,			
			[7, 27, 63, 111, 173, 249, 339, 443, 561, 693]			

Nbr.	gr	N_0	H_i	L	m	X
		1040*,				
		[7, 27, 63, 115, 185, 272, 376, 496, 632, 784]				
		1039*,				
		[7, 27, 64, 112, 173, 249, 339, 443, 561, 693]				
		1041*, 1042*, 1043*, 1044*,				
		[7, 27, 65, 118, 187, 274, 378, 498, 634, 786]				
		1045*, 1046*,				
		[7, 27, 65, 122, 194, 282, 386, 506, 642, 794]				
		1047*,				
		[7, 27, 66, 122, 194, 282, 386, 506, 642, 794]				
		1048*, 1049*,				
		[7, 27, 70, 127, 196, 284, 388, 508, 644, 796]				
		1050*,				
		[7, 28, 64, 111, 173, 249, 339, 443, 561, 693]				
		1051*, 1052*, 1053*, 1054*, 1055*,				
		[7, 28, 65, 117, 187, 274, 378, 498, 634, 786]				
		1056*, 1057*,				
		[7, 28, 65, 117, 188, 276, 380, 500, 636, 788]				
		1058*,				
		[7, 28, 66, 120, 192, 280, 384, 504, 640, 792]				
		1059*, 1060*, 1061*,				
		[7, 28, 67, 124, 196, 284, 388, 508, 644, 796]				
		1062*,				
		[7, 28, 68, 124, 196, 284, 388, 508, 644, 796]				
		1063*,				
		[7, 28, 68, 126, 198, 284, 388, 508, 644, 796]				
		1064*,				
		[7, 28, 69, 126, 197, 284, 388, 508, 644, 796]				
		1065*,				
		[7, 29, 68, 122, 194, 282, 386, 506, 642, 794]				
		1066*, 1067*, 1068*,				
		[7, 29, 70, 125, 196, 284, 388, 508, 644, 796]				
		1069*,				
		[7, 30, 70, 124, 196, 284, 388, 508, 644, 796]				
		1070*,				
		[8, 26, 56, 98, 152, 218, 296, 386, 488, 602]				
935		H_{431}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, m_z t_z, i t_z^{-1},$ $m_z t_z^{-1}$	
936		H_{461}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_x^2 t_z,$ $m_z t_z^{-1}$	
[8, 26, 57, 102, 159, 227, 308, 402, 509, 629]						
937		H_{468}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1},$ $m_z t_z^{-1}$	
[8, 26, 57, 102, 161, 234, 321, 421, 534, 661]						
938		H_{460}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z, r_x^2 t_z,$ $m_z t_z^{-1}$	
[8, 26, 59, 104, 163, 234, 319, 416, 527, 650]						
939		H_{433}	1	r_z^2	$i t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1}, m_z t_z, i t_z^{-1},$ $m_z t_z^{-1}$	
[8, 26, 59, 105, 165, 235, 319, 417, 529, 651]						
940		H_{466}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_x^2 t_y^{-1}, m_z t_z, i t_z^{-1},$ $m_z t_z^{-1}$	
[8, 27, 58, 102, 159, 227, 309, 403, 509, 629]						
941		H_{469}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1},$ $r_x^2 t_z^{-1}$	
[8, 27, 58, 103, 161, 232, 318, 417, 530, 657]						
942		H_{460}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z, i t_z^{-1},$ $m_z t_z^{-1}$	
[8, 27, 59, 102, 160, 229, 310, 406, 513, 631]						
943		H_{433}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y^{-1}, m_z t_z, i t_z^{-1},$ $m_z t_z^{-1}$	
[8, 27, 59, 103, 162, 232, 315, 411, 520, 641]						
944		H_{485}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1},$ $r_x^2 t_z^{-1}$	
[8, 27, 59, 104, 161, 231, 315, 410, 518, 640]						
945		H_{461}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, r_y^2 t_z, i t_z^{-1},$ $m_z t_z^{-1}$	
[8, 27, 59, 104, 165, 239, 328, 430, 546, 674]						
946		H_{462}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1},$ $r_x^2 t_z^{-1}$	
[8, 27, 59, 105, 165, 238, 325, 425, 538, 665]						
947		H_{425}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1},$ $r_x^2 t_z^{-1}$	
[8, 27, 59, 105, 166, 238, 325, 425, 538, 663]						
948		H_{475}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1},$ $m_z t_z^{-1}$	
[8, 27, 60, 105, 164, 235, 320, 417, 528, 651]						
949		H_{434}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, i t_y^{-1}, m_z t_z, i t_z^{-1},$ $m_z t_z^{-1}$	
[8, 27, 60, 105, 165, 236, 321, 418, 529, 652]						
950		H_{474}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1},$ $r_x^2 t_z^{-1}$	

Nbr.	gr	N ₀	H _i	L	m	X
				[8, 27, 60, 107, 167, 240, 327, 427, 540, 667]		
		951	H ₄₈₁	1	r _z ²	m _x t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , m _z t _z , it _z ⁻¹ , m _z t _z ⁻¹
		952	H ₄₈₃	1	r _z ²	m _x t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , r _y ² t _z , r _x ² t _z , m _z t _z ⁻¹
	[8, 27, 61, 106, 165, 236, 321, 418, 529, 652]					
		953	H ₄₂₇	1	r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _x ² t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
		954	H ₄₆₉	1	r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , m _y t _y ⁻¹ , r _x ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
	[8, 27, 61, 107, 171, 249, 340, 441, 563, 699]					
		955	H ₄₆₂	1	r _z ²	it _x ⁻¹ , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , r _x ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
	[8, 27, 61, 108, 170, 243, 332, 433, 548, 675]					
		956	H ₄₇₃	1	r _z ²	m _z t _x , it _x ⁻¹ , m _z t _x ⁻¹ , r _x ² t _y ⁻¹ , m _z t _z , it _z ⁻¹ , m _z t _z ⁻¹
	[8, 27, 61, 108, 171, 247, 340, 444, 564, 696]					
		957	H ₄₇₁	1	r _z ²	m _z t _x , it _x ⁻¹ , m _z t _x ⁻¹ , it _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
	[8, 27, 61, 112, 181, 268, 372, 492, 628, 780]					
		958	H ₄₅₂	1	r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y ⁻¹ , r _y ² r _z t _z , r _x ² r _z t _z , m _z t _z ⁻¹
		959	H ₄₈₇	1	r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y ⁻¹ , m _z r _z ⁻¹ t _z , m _z r _z t _z , m _z t _z ⁻¹
	[8, 27, 62, 108, 169, 242, 329, 428, 542, 668]					
		960	H ₄₆₁	1	r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , m _y t _y ⁻¹ , r _x ² t _z , it _z ⁻¹ , m _z t _z ⁻¹
	[8, 27, 63, 108, 171, 246, 338, 442, 562, 694]					
		961	H ₄₆₀	1	r _z ²	r _z ² t _x ⁻¹ , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , r _y ² t _z , it _z ⁻¹ , m _z t _z ⁻¹
	[8, 27, 64, 110, 174, 250, 342, 446, 566, 698]					
		962	H ₄₂₅	1	r _z ²	r _z ² t _x ⁻¹ , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
	[8, 27, 65, 113, 177, 253, 345, 449, 569, 701]					
		963	H ₄₈₆	1	r _z ²	r _y ² t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , m _z t _z , it _z ⁻¹ , m _z t _z ⁻¹
	[8, 28, 61, 106, 165, 236, 321, 418, 529, 652]					
		964	H ₄₂₇	1	r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _x ² t _y ⁻¹ , r _x ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
	[8, 28, 61, 108, 168, 241, 328, 428, 541, 668]					
		965	H ₄₈₃	1	r _z ²	m _y t _x , m _x t _x ⁻¹ , m _y t _x ⁻¹ , m _y t _y ⁻¹ , r _y ² t _z , it _z ⁻¹ , m _z t _z ⁻¹
		966	H ₄₈₂	1	r _z ²	m _y t _x , m _x t _x ⁻¹ , m _y t _x ⁻¹ , m _y t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
	[8, 28, 62, 106, 165, 236, 321, 418, 529, 652]					
		967	H ₄₃₃	1	r _z ²	m _z t _x , it _x ⁻¹ , m _z t _x ⁻¹ , r _z ² t _y ⁻¹ , it _z , it _z ⁻¹ , m _z t _z ⁻¹
		968	H ₄₈₅	1	r _z ²	m _z t _x , it _x ⁻¹ , m _z t _x ⁻¹ , m _y t _y ⁻¹ , r _x ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
		969	H ₄₃₁	1	r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y ⁻¹ , it _z , it _z ⁻¹ , m _z t _z ⁻¹
	[8, 28, 62, 109, 169, 242, 329, 429, 542, 669]					
		970	H ₄₆₈	1	r _z ²	r _z ² t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , m _z t _z , it _z ⁻¹ , m _z t _z ⁻¹
		971	H ₄₆₁	1	r _z ²	r _z ² t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , r _y ² t _z , r _x ² t _z , m _z t _z ⁻¹
	[8, 28, 63, 108, 169, 242, 329, 428, 542, 668]					
		972	H ₄₆₁	1	r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , m _y t _y ⁻¹ , r _y ² t _z , r _x ² t _z , it _z ⁻¹
	[8, 28, 63, 108, 171, 246, 338, 442, 562, 694]					
		973	H ₄₆₀	1	r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y ⁻¹ , r _y ² t _z , r _x ² t _z , it _z ⁻¹
	[8, 28, 63, 110, 173, 248, 338, 441, 559, 689]					
		974	H ₄₈₆	1	r _z ²	r _x ² t _x , r _y ² t _x ⁻¹ , r _x ² t _x ⁻¹ , m _y t _y ⁻¹ , m _z t _z , it _z ⁻¹ , m _z t _z ⁻¹
		975	H ₄₇₉	1	r _z ²	r _x ² t _x , r _y ² t _x ⁻¹ , r _x ² t _x ⁻¹ , m _y t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
	[8, 28, 63, 110, 174, 250, 342, 446, 566, 698]					
		976	H ₄₆₂	1	r _z ²	it _x ⁻¹ , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
	[8, 28, 63, 111, 175, 251, 343, 447, 567, 699]					
		977	H ₄₇₇	1	r _z ²	r _y ² t _x ⁻¹ , r _y ² t _y , r _y ² t _y ⁻¹ , r _x ² t _y ⁻¹ , m _z t _z , it _z ⁻¹ , m _z t _z ⁻¹

Nbr.	gr	N_i	H_i	L	m	X
		978	H_{429}	1	r_z^2	$r_x^2 t_x^{-1}, r_y^2 t_y, r_z^2 t_y^{-1}, r_x^2 t_z^{-1}, r_x^2 t_z, r_y^2 t_z^{-1},$ $r_x^2 t_z^{-1}$
[8, 28, 63, 113, 181, 267, 370, 490, 626, 778]						
		979	H_{452}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_x^2 r_z t_z, i t_z^{-1},$ $m_z t_z^{-1}$
[8, 28, 63, 115, 185, 272, 376, 496, 632, 784]						
		980	H_{503}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_y^2 r_z t_z, r_x^2 r_z t_z,$ $r_y^2 t_z^{-1}$
		981	H_{519}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z,$ $r_y^2 t_z^{-1}$
[8, 28, 64, 110, 171, 244, 333, 434, 549, 676]						
		982	H_{475}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, m_y t_y^{-1}, i t_z, i t_z^{-1},$ $m_z t_z^{-1}$
		983	H_{468}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, i t_z, i t_z^{-1},$ $m_z t_z^{-1}$
[8, 28, 64, 110, 174, 250, 342, 446, 566, 698]						
		984	H_{462}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1},$ $r_x^2 t_z^{-1}$
[8, 28, 64, 112, 176, 252, 344, 448, 568, 700]						
		985	H_{483}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, i t_z^{-1},$ $m_z t_z^{-1}$
		986	H_{482}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1},$ $r_x^2 t_z^{-1}$
[8, 28, 64, 115, 185, 271, 375, 494, 631, 782]						
		987	H_{503}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_x^2 r_z t_z, r_y^2 t_z^{-1},$ $r_x^2 t_z^{-1}$
[8, 28, 64, 117, 187, 274, 378, 498, 634, 786]						
		988	H_{527}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_x^2 r_z t_z,$ $m_z t_z^{-1}$
		989	H_{528}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z,$ $m_z t_z^{-1}$
[8, 28, 65, 113, 174, 249, 341, 445, 561, 690]						
		990	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1},$ $m_z t_z^{-1}$
		991	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_x t_y, m_y t_y, m_x t_y^{-1}, m_z t_z, i t_z^{-1},$ $m_z t_z^{-1}$
[8, 28, 65, 113, 177, 253, 345, 449, 569, 701]						
		992	H_{479}	1	r_z^2	$r_y^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1},$ $r_x^2 t_z^{-1}$
[8, 28, 66, 114, 178, 254, 346, 450, 570, 702]						
		993	H_{475}	1	r_z^2	$i t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1},$ $m_z t_z^{-1}$
[8, 28, 66, 117, 186, 273, 376, 496, 632, 784]						
		994	H_{503}	1	r_z^2	$r_z^2 t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 r_z t_z, r_x^2 r_z t_z,$ $r_y^2 t_z^{-1}$
		995	H_{519}	1	r_z^2	$r_z^2 t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z,$ $r_y^2 t_z^{-1}$
[8, 29, 61, 106, 165, 236, 321, 418, 529, 652]						
		996	H_{434}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, i t_y^{-1}, i t_z, i t_z^{-1},$ $m_z t_z^{-1}$
		997	H_{433}	1	r_z^2	$i t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1}, i t_z, i t_z^{-1},$ $m_z t_z^{-1}$
		998	H_{474}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1},$ $r_x^2 t_z^{-1}$
[8, 29, 62, 109, 169, 242, 329, 429, 542, 669]						
		999	H_{461}	1	r_z^2	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z, i t_z^{-1},$ $m_z t_z^{-1}$
		1000	H_{469}	1	r_z^2	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t$

Nbr.	gr	№	H_i	L	m	X
		1034	H_{511}	1	r_z^2	$r_x^2 r_x t x, r_x t x, r_x^{-1} t x^{-1}, r_x^2 t y^{-1}, r_y^2 t z, r_y^2 t z^{-1},$ $r_x^2 t z^{-1}$
[8, 30, 64, 115, 183, 269, 372, 492, 628, 780]						
		1035	H_{452}	1	r_z^2	$t x, r_z^2 t x^{-1}, t x^{-1}, r_z^2 t y^{-1}, r_y^2 r z t z, i t z^{-1},$ $m z t z^{-1}$
[8, 30, 65, 113, 177, 253, 345, 449, 569, 701]						
		1036	H_{477}	1	r_z^2	$r_x^2 t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_x^2 t y^{-1}, i t z, i t z^{-1},$ $m z t z^{-1}$
		1037	H_{429}	1	r_z^2	$r_x^2 t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_x^2 t y^{-1}, r_x^2 t z, r_y^2 t z^{-1},$ $r_x^2 t z^{-1}$
		1038	H_{486}	1	r_z^2	$r_y^2 t x^{-1}, m x t y, m x t y^{-1}, m y t y^{-1}, i t z, i t z^{-1},$ $m z t z^{-1}$
[8, 30, 65, 117, 186, 273, 376, 496, 632, 784]						
		1039	H_{503}	1	r_z^2	$t x, r_x^2 t x^{-1}, t x^{-1}, r_z^2 t y^{-1}, r_y^2 r z t z, r_y^2 t z^{-1},$ $r_x^2 t z^{-1}$
[8, 30, 66, 114, 178, 254, 346, 450, 570, 702]						
		1040	H_{485}	1	r_z^2	$i t x^{-1}, m x t y, m x t y^{-1}, m y t y^{-1}, r_y^2 t z, r_y^2 t z^{-1},$ $r_x^2 t z^{-1}$
[8, 30, 67, 114, 178, 254, 346, 450, 570, 702]						
		1041	H_{466}	1	r_z^2	$r_x^2 t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_x^2 t y^{-1}, i t z, i t z^{-1},$ $m z t z^{-1}$
		1042	H_{427}	1	r_z^2	$r_x^2 t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_x^2 t y^{-1}, r_y^2 t z, r_y^2 t z^{-1},$ $r_x^2 t z^{-1}$
		1043	H_{468}	1	r_z^2	$r_x^2 t x^{-1}, m x t y, m x t y^{-1}, m y t y^{-1}, i t z, i t z^{-1},$ $m z t z^{-1}$
		1044	H_{461}	1	r_z^2	$r_x^2 t x^{-1}, m x t y, m x t y^{-1}, m y t y^{-1}, r_y^2 t z, r_x^2 t z,$ $i t z^{-1}$
[8, 30, 68, 120, 189, 276, 379, 499, 635, 787]						
		1045	H_{527}	1	r_z^2	$m x t x^{-1}, m x t y, m x t y^{-1}, m y t y^{-1}, r_y^2 r z t z, r_x^2 r z t z,$ $i t z^{-1}$
		1046	H_{528}	1	r_z^2	$m x t x^{-1}, m x t y, m x t y^{-1}, m y t y^{-1}, m z r z^{-1} t z, m z r z t z,$ $i t z^{-1}$
[8, 30, 68, 125, 194, 284, 386, 508, 642, 796]						
		1047	H_{505}	1	r_z^2	$r_y^2 t x^{-1}, r_y^2 t y, r_x^2 t y, r_y^2 t y^{-1}, r_y^2 r z t z, r_y^2 r z t z^{-1},$ $r_x^2 r z t z^{-1}$
[8, 30, 69, 124, 195, 283, 387, 507, 643, 795]						
		1048	H_{496}	1	r_z^2	$m x t x^{-1}, m x t y, m y t y, m x t y^{-1}, r_y^2 r z t z, r_y^2 r z t z^{-1},$ $r_x^2 r z t z^{-1}$
		1049	H_{502}	1	r_z^2	$m x t x^{-1}, m x t y, m y t y, m x t y^{-1}, m z r z^{-1} t z, m z r z t z,$ $r_y^2 r z t z^{-1}$
[8, 30, 73, 125, 196, 284, 388, 508, 644, 796]						
		1050	H_{541}	1	r_z^2	$r_x^2 r x t x, r x t x, r_x^{-1} t x^{-1}, m y t y^{-1}, i t z, i t z^{-1},$ $m z t z^{-1}$
[8, 31, 66, 114, 178, 254, 346, 450, 570, 702]						
		1051	H_{473}	1	r_z^2	$i t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_x^2 t y^{-1}, i t z, i t z^{-1},$ $m z t z^{-1}$
		1052	H_{474}	1	r_z^2	$i t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_x^2 t y^{-1}, r_y^2 t z, r_y^2 t z^{-1},$ $r_x^2 t z^{-1}$
		1053	H_{475}	1	r_z^2	$i t x^{-1}, m x t y, m x t y^{-1}, m y t y^{-1}, i t z, i t z^{-1},$ $m z t z^{-1}$
		1054	H_{511}	1	r_z^2	$r_x^2 r x t x, r_y^2 t y, r_y^2 t y^{-1}, r_x^2 t y^{-1}, r_y^2 t z, r_y^2 t z^{-1},$ $r_x^2 t z^{-1}$
		1055	H_{541}	1	r_z^2	$r_x^2 r x t x, m x t y, m x t y^{-1}, m y t y^{-1}, i t z, i t z^{-1},$ $m z t z^{-1}$
[8, 31, 67, 120, 189, 276, 379, 499, 635, 787]						
		1056	H_{527}	1	r_z^2	$m x t x^{-1}, m x t y, m x t y^{-1}, m y t y^{-1}, r_y^2 r z t z, i t z^{-1},$ $m z t z^{-1}$
		1057	H_{529}	1	r_z^2	$m x t x^{-1}, m x t y, m x t y^{-1}, m y t y^{-1}, r_y^2 r z t z, r_y^2 t z^{-1},$ $r_x^2 t$

Nbr.	gr	N ₆	H _i	L	m	X
		1077	H ₆₈₃	$\langle m_x \rangle$	r_z^2	$itx, r_y^2tx, r_x^2x^{-1}, r_y^2x^{-1}, r_z^2y^{-1}, r_y^2tz,$ $r_z^2x^{-1}, r_y^2z^{-1}$
[9, 29, 65, 112, 175, 251, 341, 444, 563, 693]						
		1078	H ₃₄₇	1	m_z	$r_z^2tx, r_y^2rztx^{-1}, m_xrztx^{-1}, ity, r_z^2ty, r_y^2rzty^{-1},$ $m_xrzty^{-1}, r_z^2rztx^{-1}$
[9, 29, 65, 113, 174, 249, 341, 445, 561, 690]						
		1079	H ₅₄₁	1	r_z^2	$r_z^2rxtx, m_xty, m_yty, m_xty^{-1}, m_yty^{-1}, m_ztz,$ $it_z^{-1}, m_zt_z^{-1}$
[9, 29, 65, 113, 176, 251, 343, 447, 566, 697]						
		1080	H ₅₁₁	1	r_z^2	$r_z^2rxtx, r_y^2ty, r_x^2ty, r_y^2ty^{-1}, r_x^2ty^{-1}, r_x^2tz,$ $r_y^2x^{-1}, r_x^2x^{-1}$
[9, 29, 65, 113, 176, 252, 344, 448, 568, 700]						
		1081	H ₃₄₄	1	m_z	$r_z^2tx, it_x^{-1}, r_z^2x^{-1}, it_y, r_z^2ty, it_y^{-1},$ $r_z^2ty^{-1}, r_y^2rztx^{-1}$
[9, 29, 65, 113, 178, 254, 346, 450, 570, 702]						
		1082	H ₃₇₀	1	m_z	$itx, r_z^2tx, r_y^2x^{-1}, m_xtx^{-1}, m_yty, r_x^2ty^{-1},$ $m_yty^{-1}, r_x^2x^{-1}$
		1083	H ₃₇₈	1	m_z	$r_z^2tx, m_xtx, r_y^2tx^{-1}, m_xtx^{-1}, m_yty, r_x^2ty^{-1},$ $m_yty^{-1}, r_y^2rztx^{-1}$
[9, 29, 66, 114, 178, 254, 346, 450, 570, 702]						
		1084	H ₆₈₂	$\langle m_y \rangle$	m_x	$r_y^2x^{-1}, r_z^2ty, m_yty, m_xty^{-1}, ty^{-1}, m_ztz,$ $r_y^2x^{-1}, m_zt_z^{-1}$
[9, 30, 66, 119, 189, 276, 380, 500, 636, 788]						
		1085	H ₆₉₀	$\langle m_x \rangle$	r_z^2	$r_z^2tx, m_xtx, m_ytx^{-1}, m_xtx^{-1}, m_yty^{-1}, r_y^2rztz,$ $m_zr_z^{-1}tz, r_y^2x^{-1}$
[9, 30, 67, 114, 178, 254, 346, 450, 570, 702]						
		1086	H ₆₈₂	$\langle m_x \rangle$	r_z^2	$itx, r_y^2tx, r_x^2x^{-1}, r_y^2x^{-1}, m_yty^{-1}, r_x^2tz,$ $r_z^2x^{-1}, r_y^2ty^{-1}$
		1087	H ₆₈₀	$\langle m_x \rangle$	r_z^2	$r_z^2tx, m_xtx, m_ytx^{-1}, m_xtx^{-1}, m_yty^{-1}, r_x^2tz,$ $r_x^2x^{-1}, r_y^2tz^{-1}$
		1088	H ₃₅₉	1	m_z	$itx, r_z^2tx, r_y^2x^{-1}, m_xtx^{-1}, r_x^2ty, r_x^2ty^{-1},$ $m_yty^{-1}, m_zt_z^{-1}$
		1089	H ₃₄₃	1	m_z	$itx, r_y^2rztx^{-1}, m_xrztx^{-1}, ity, r_z^2ty, r_y^2rzty^{-1},$ $m_xrzty^{-1}, m_zt_z^{-1}$
		1090	H ₃₇₇	1	m_z	$r_z^2tx, m_xtx, m_zr_z^{-1}x^{-1}, r_z^{-1}x^{-1}, m_zrzty, r_zty,$ $r_x^2x^{-1}, m_zt_z^{-1}$
[9, 31, 66, 114, 178, 254, 346, 450, 570, 702]						
		1091	H ₆₈₃	$\langle m_x \rangle$	r_z^2	$itx, r_y^2tx, r_x^2x^{-1}, r_y^2x^{-1}, r_z^2y^{-1}, r_x^2tz,$ $r_y^2tz, r_x^2x^{-1}$
		1092	H ₃₄₄	1	m_z	$itx, it_x^{-1}, r_z^2x^{-1}, it_y, r_z^2ty, it_y^{-1},$ $r_z^2x^{-1}, r_y^2rztx^{-1}$
		1093	H ₃₄₄	1	m_z	$itx, r_z^2tx, it_x^{-1}, r_z^2x^{-1}, it_y, r_z^2ty,$ $it_y^{-1}, r_y^2rztx^{-1}$
		1094	H ₆₈₃	$\langle m_x \rangle$	r_z^2	$itx, r_y^2tx, r_x^2x^{-1}, r_y^2x^{-1}, r_x^2ty^{-1}, r_x^2tz,$ $r_x^2x^{-1}, r_y^2x^{-1}$
		1095	H ₆₈₂	$\langle m_y \rangle$	m_x	$r_y^2tx, r_z^2ty, m_yty, m_xty^{-1}, ty^{-1}, r_y^2tz,$ $r_y^2x^{-1}, m_zt_z^{-1}$
		1096	H ₃₇₀	1	m_z	$itx, r_z^2tx, r_y^2x^{-1}, m_xtx^{-1}, r_x^2ty, r_x^2ty^{-1},$ $m_yty^{-1}, r_x^2x^{-1}$
		1097	H ₃₄₇	1	m_z	$itx, r_y^2rztx^{-1}, m_xrztx^{-1}, ity, r_z^2ty, r_y^2rzty^{-1},$ $m_xrzty^{-1}, r_z^2rztx^{-1}$
		1098	H ₃₇₈	1	m_z	$r_y^2tx, m_xtx, r_y^2tx^{-1}, m_xtx^{-1}, r_x^2ty, r_x^2ty^{-1},$ $m_yty^{-1}, r_y^2rztx^{-1}$
		1099	H ₃₈₂	1	m_z	$r_z^2tx, m_xtx, m_zr_z^{-1}x^{-1}, r_z^{-1}x^{-1}, m_zrzty, r_zty,$ $r_x^2x^{-1}, r_y^2rztx^{-1}$
		1100	H ₅₁₁	1	r_z^2	$r_z^2rxtx, r_y^2ty, r_x^2ty, r_y^2y^{-1}, r_x^2ty^{-1}, r_y^2tz,$ $r_z^2x^{-1}, r_x^2x^{-1}$
		1101	H ₅₄₁	1	r_z^2	$r_z^2rxtx, m_xty, m_yty, m_xty^{-1}, m_yty^{-1}, itz,$ $it_z^{-1}, m_zt_z^{-1}$
[9, 31, 68, 122, 194, 281, 385, 506, 641, 793]						
		1102	H ₅₄₁	1	r_z^2	$r_z^2rxtx, r_xtx, r_y^2rxtx^{-1}, r_x^{-1}tx^{-1}, m_yty^{-1}, m_ztz,$ $it_z^{-1}, m_zt_z^{-1}$
[9, 31, 69, 121, 190, 277, 380, 500, 636, 788]						
		1103	H ₆₉₀	$\langle m_x \rangle$	r_z^2	$r_z^2tx, m_xtx, m_ytx^{-1}, m_xtx^{-1}, m_yty^{-1}, r_y^2rztz,$ $m_zr_z^{-1}tz, r_x^2x^{-1}$
[9, 31, 70, 125, 196, 284, 388, 508, 644, 796]						
		1104	H ₅₁₁	1	r_z^2	$r_z^2rxtx, r_xtx, r_y^2rxtx^{-1}, r_x^{-1}tx^{-1}, r_x^2ty^{-1}, r_y^2tz,$ $r_y^2x^{-1}, r_x^2x^{-1}$
[9, 32, 68, 121, 190, 277, 380, 500, 636, 788]						

Nbr.	gr	N°	H_i	L	m	X
		1105	H_{452}	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 r_z t_z,$ $it_z^{-1}, m_z t_z^{-1}$
		1106	H_{503}	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		1107	H_{527}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z,$ $it_z^{-1}, m_z t_z^{-1}$
		1108	H_{529}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z,$ $r_z^2 t_z^{-1}, r_x^2 t_z^{-1}$
[9, 32, 71, 125, 196, 284, 388, 508, 644, 796]						
		1109	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_y^2 r_x t_x^{-1}, r_x^{-1} t_x^{-1}, m_y t_y^{-1}, it_z,$ $it_z^{-1}, m_z t_z^{-1}$
[9, 33, 70, 125, 196, 284, 388, 508, 644, 796]						
		1110	H_{453}	1	r_z^2	$it_x^{-1}, it_y, m_z t_y, it_y^{-1}, m_z t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
		1111	H_{539}	1	r_z^2	$it_x, m_z t_x, it_x^{-1}, m_z t_x^{-1}, r_x^2 t_y^{-1}, m_z r_z^{-1} t_z,$ $m_z r_z t_z, r_y^2 r_z t_z^{-1}$
		1112	H_{539}	1	r_z^2	$it_x^{-1}, r_y^2 t_y, r_x^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, m_z r_z^{-1} t_z,$ $m_z r_z t_z, r_y^2 r_z t_z^{-1}$
		1113	H_{438}	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
		1114	H_{495}	1	r_z^2	$r_z^2 t_x^{-1}, r_z^2 t_y, t_y, r_z^2 t_y^{-1}, t_y^{-1}, m_z r_z^{-1} t_z,$ $m_z r_z t_z, r_y^2 r_z t_z^{-1}$
		1115	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_y^2 r_x t_x^{-1}, r_x^{-1} t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z,$ $r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		1116	H_{505}	1	r_z^2	$r_y^2 t_x^{-1}, r_y^2 t_y, r_x^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
		1117	H_{496}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
		1118	H_{502}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z r_z^{-1} t_z,$ $m_z r_z t_z, r_y^2 r_z t_z^{-1}$

17A

[5, 14, 29, 50, 77, 110, 149, 194, 245, 302] 1119*, 1120*,				
[5, 14, 30, 52, 79, 114, 155, 200, 254, 314] 1121*,				
[5, 14, 33, 67, 114, 168, 227, 302, 391, 481] 1122*,				
[5, 16, 35, 60, 93, 134, 181, 236, 299, 368] 1123*, 1124*,				
[5, 16, 36, 63, 97, 139, 189, 247, 312, 384] 1125*,				
[5, 16, 38, 75, 128, 191, 266, 356, 456, 568] 1126*,				
[6, 19, 41, 70, 110, 157, 212, 278, 351, 431] 1119	H_{307}	1	i	$r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, r_z^2 r_x t_z^{-1}$
[6, 19, 42, 72, 112, 160, 218, 284, 359, 442] 1120	H_{310}	1	i	$m_x t_x^{-1}, r_z^2 r_x t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, r_z^2 r_x t_z^{-1}$
[6, 19, 43, 73, 114, 165, 222, 290, 368, 451] 1121	H_{322}	1	i	$m_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, r_x t_y^{-1}, m_x r_x t_z, r_x^{-1} t_z^{-1}$
[6, 19, 45, 82, 132, 195, 268, 356, 455, 559] 1122	H_{325}	1	i	$r_z^2 r_x t_x^{-1}, m_x r_x t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, m_x r_x^{-1} t_z^{-1}$
[6, 21, 45, 78, 122, 175, 236, 310, 391, 481] 1123	H_{306}	1	i	$it_x^{-1}, r_z^2 r_x t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, r_z^2 r_x t_z^{-1}$
[6, 21, 46, 80, 125, 178, 243, 316, 401, 493] 1124	H_{309}	1	i	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_y^2 r_x t_z, m_z r_x^{-1} t_z^{-1}$
[6, 21, 47, 82, 128, 183, 250, 325, 411, 507] 1125	H_{324}	1	i	$r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, r_x t_y^{-1}, m_x r_x t_z, r_x^{-1} t_z^{-1}$
[6, 21, 48, 89, 144, 207, 288, 382, 486, 602] 1126	H_{321}	1	i	$it_x^{-1}, m_x r_x^{-1} t_y^{-1}, r_x t_y^{-1}, m_x r_x t_z, r_x^{-1} t_z^{-1}$

17B

[5, 15, 37, 74, 122, 178, 244, 322, 410, 508]
1127*,
[5, 15, 38, 78, 132, 200, 282, 378, 488, 612]
1128*,
[5, 15, 40, 82, 134, 200, 278, 368, 472, 590]
1129*,
[5, 15, 40, 83, 142, 216, 300, 393, 500, 622]
1130*,
[5, 15, 40, 89, 152, 230, 319, 422, 541, 670]
1131*,
[5, 15, 41, 87, 146, 221, 306, 403, 513, 637]
1132*,
[5, 16, 39, 74, 119, 174, 239, 314, 399, 494]
1133*, 1134*,
[5, 16, 39, 76, 127, 192, 271, 364, 471, 592]
1135*,
[5, 16, 42, 80, 131, 196, 274, 364, 467, 584]

Nbr.	gr	N ₀	H_i	L	m	X
			1138*,			
			[5, 16, 42, 81, 128, 185, 253, 332, 421, 520]			
			1136*, 1137*,			
			[5, 17, 44, 83, 131, 190, 259, 339, 430, 531]			
			1139*,			
			[5, 17, 46, 93, 155, 230, 317, 421, 541, 670]			
			1140*,			
			[5, 17, 46, 95, 156, 229, 315, 419, 536, 665]			
			1141*,			
			[5, 17, 48, 95, 155, 227, 314, 415, 527, 655]			
			1142*,			
			[5, 18, 43, 78, 123, 178, 243, 318, 403, 498]			
			1143*, 1144*,			
			[5, 18, 45, 89, 148, 223, 311, 413, 528, 659]			
			1145*,			
			[5, 18, 47, 93, 151, 223, 312, 411, 523, 653]			
			1146*,			
			[6, 20, 50, 93, 148, 213, 291, 382, 484, 598]			
			1127 H_{420} 1		$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x t_y^{-1}, m_y t_z, m_x r_x^{-1} t_z^{-1}, m_y t_z^{-1}$
			[6, 20, 51, 96, 157, 230, 319, 420, 537, 666]			
			1128 H_{421} 1		$r_z^2 r_x$	$m_x t_x^{-1}, r_x t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, r_x^{-1} t_z^{-1}$
			[6, 20, 52, 96, 151, 223, 305, 401, 507, 631]			
			1129 H_{423} 1		$r_z^2 r_x$	$r_z^2 t_x, m_x r_x t_y^{-1}, m_y t_z, m_x r_x^{-1} t_z^{-1}, m_y t_z^{-1}$
			[6, 20, 52, 97, 158, 232, 318, 413, 523, 647]			
			1130 H_{423} 1		$r_z^2 r_x$	$r_z^2 t_x, m_z t_y, m_x r_x t_y^{-1}, m_z t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
			[6, 20, 52, 103, 163, 241, 328, 437, 554, 689]			
			1131 H_{416} 1		$r_z^2 r_x$	$it_x^{-1}, m_x r_x t_y^{-1}, m_y t_z, m_x r_x^{-1} t_z^{-1}, m_y t_z^{-1}$
			[6, 20, 53, 101, 161, 237, 320, 422, 533, 661]			
			1132 H_{411} 1		$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_x t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, r_x^{-1} t_z^{-1}$
			[6, 21, 50, 90, 142, 205, 280, 366, 464, 573]			
			1133 H_{387} 1		$r_z^2 r_x$	$it_x^{-1}, t_y, r_z^2 r_x t_y^{-1}, t_y^{-1}, r_z^2 r_x t_z^{-1}$
			[6, 21, 51, 92, 145, 209, 286, 374, 474, 585]			
			1134 H_{384} 1		$r_z^2 r_x$	$m_x t_x^{-1}, t_y, r_z^2 r_x t_y^{-1}, t_y^{-1}, r_z^2 r_x t_z^{-1}$
			[6, 21, 51, 94, 154, 225, 313, 412, 528, 655]			
			1135 H_{386} 1		$r_z^2 r_x$	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z^{-1}$
			[6, 21, 53, 94, 148, 213, 291, 380, 481, 593]			
			1136 H_{406} 1		$r_z^2 r_x$	$r_z^2 t_x, t_y, r_z^2 r_x t_y^{-1}, t_y^{-1}, r_z^2 r_x t_z^{-1}$
			1137 H_{406} 1		$r_z^2 r_x$	$r_z^2 t_x, r_z^2 r_x t_y^{-1}, t_z, r_z^2 r_x t_z^{-1}, t_z^{-1}$
			[6, 21, 53, 94, 153, 220, 305, 398, 509, 628]			
			1138 H_{399} 1		$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z^{-1}$
			[6, 22, 55, 97, 153, 220, 299, 391, 495, 610]			
			1139 H_{405} 1		$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, m_x r_x t_y^{-1}, m_y t_z, m_x r_x^{-1} t_z^{-1}, m_y t_z^{-1}$
			[6, 22, 56, 102, 164, 239, 330, 435, 556, 687]			
			1140 H_{403} 1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_x t_y^{-1}, m_y t_z, m_x r_x^{-1} t_z^{-1}, m_y t_z^{-1}$
			[6, 22, 57, 106, 171, 245, 337, 442, 563, 693]			
			1141 H_{417} 1		$r_z^2 r_x$	$it_x^{-1}, r_x t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, r_x^{-1} t_z^{-1}$
			[6, 22, 58, 104, 168, 238, 330, 430, 546, 674]			
			1142 H_{408} 1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_x t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, r_x^{-1} t_z^{-1}$
			[6, 23, 52, 92, 144, 207, 282, 368, 466, 575]			
			1143 H_{383} 1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, t_y, r_z^2 r_x t_y^{-1}, t_y^{-1}, r_z^2 r_x t_z^{-1}$
			[6, 23, 53, 94, 147, 211, 288, 376, 476, 587]			
			1144 H_{390} 1		$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, t_y, r_z^2 r_x t_y^{-1}, t_y^{-1}, r_z^2 r_x t_z^{-1}$
			[6, 23, 55, 102, 167, 243, 335, 438, 559, 691]			
			1145 H_{397} 1		$r_z^2 r_x$	$it_x^{-1}, m_x t_y, m_x t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z^{-1}$
			[6, 23, 56, 104, 164, 238, 328, 428, 544, 674]			
			1146 H_{385} 1		$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z^{-1}$

18A

- [7, 22, 47, 82, 127, 182, 247, 322, 407, 502]
 1147*, 1148*,
 [7, 22, 48, 85, 132, 189, 257, 336, 425, 524]
 1149*, 1150*,
 [7, 23, 50, 87, 135, 194, 263, 343, 434, 535]
 1152*,
 [7, 23, 51, 90, 140, 202, 275, 359, 455, 562]
 1151*,
 [7, 23, 51, 91, 143, 206, 280, 366, 464, 574]
 1153*,
 [7, 23, 51, 91, 143, 207, 283, 371, 471, 583]
 1154*,
 [7, 23, 52, 94, 148, 214, 292, 382, 484, 598]
 1156*,
 [7, 23, 52, 94, 150, 220, 302, 396, 504, 626]
 1157*,
 [7, 23, 52, 95, 152, 222, 305, 401, 510, 632]
 1155*,
 [7, 23, 52, 96, 155, 226, 311, 411, 523, 647]
 1158*,
 [7, 23, 52, 97, 159, 234, 321, 425, 545, 674]
 1159*,
 [7, 23, 54, 99, 156, 228, 315, 414, 527, 655]
 1160*,
 [7, 23, 55, 103, 165, 241, 331, 435, 553, 685]
 1161*,

Nbr.	gr	N ₀	H_i	L	m	X
		1160	H_{395}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y, i t_y^{-1}, m_z r_x t_z^{-1}, m_z r_x t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
[8, 26, 61, 108, 172, 248, 340, 444, 564, 696]						
		1161	H_{311}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
[8, 27, 60, 105, 164, 235, 320, 417, 528, 651]						
		1162	H_{302}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$
		1163	H_{312}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, m_z t_y, r_z^2 t_y^{-1}, m_z t_y^{-1}, r_x^2 t_z^{-1}$
		1164	H_{304}	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$
		1165	H_{317}	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, m_y t_y^{-1}, m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
[8, 27, 61, 108, 170, 245, 335, 438, 556, 687]						
		1166	H_{657}	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 r_x t_y, m_x t_y^{-1}, r_x^2 t_y^{-1}, m_x t_z, r_y^2 r_x t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
[8, 27, 62, 109, 170, 243, 332, 433, 548, 675]						
		1167	H_{313}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$
		1168	H_{316}	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$
[8, 27, 62, 109, 173, 249, 341, 445, 565, 697]						
		1169	H_{301}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, i t_y^{-1}, m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
		1170	H_{315}	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y^{-1}, m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
[8, 27, 63, 110, 173, 249, 338, 441, 559, 688]						
		1171	H_{413}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$
[8, 27, 63, 111, 174, 250, 341, 444, 563, 694]						
		1172	H_{394}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
[8, 28, 61, 106, 165, 236, 321, 418, 529, 652]						
		1173	H_{300}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, i t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$
		1174	H_{302}	1	i	$i t_x^{-1}, m_z t_y, r_z^2 t_y^{-1}, m_z t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$
		1175	H_{319}	1	i	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, r_x^2 t_y^{-1}, m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
[8, 28, 63, 110, 171, 244, 333, 434, 549, 676]						
		1176	H_{314}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z^{-1}$
		1177	H_{317}	1	i	$r_z^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
[8, 28, 63, 110, 174, 250, 342, 446, 566, 698]						
		1178	H_{312}	1	i	$i t_x^{-1}, m_z t_y, r_z^2 t_y^{-1}, m_z t_y^{-1}, m_x t_z, m_x t_z^{-1}, r_x^2 t_z^{-1}$
[8, 28, 63, 111, 174, 250, 341, 444, 562, 692]						
		1179	H_{412}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$
[8, 28, 64, 112, 176, 252, 344, 448, 568, 700]						
		1180	H_{315}	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, m_z t_y, r_z^2 t_y^{-1}, m_z t_y^{-1}, r_y^2 t_z^{-1}$
		1181	H_{316}	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, m_z t_z^{-1}$
		1182	H_{661}	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x^{-1} t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, r_z^2 t_z, m_x r_x t_z^{-1}, r_x^{-1} t_z^{-1}$
[8, 28, 64, 113, 177, 253, 345, 449, 569, 701]						
		1183	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
[8, 28, 64, 117, 187, 274, 377, 496, 631, 782]						
		1184	H_{305}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, i t_y^{-1}, m_x r_z^{-1} t_z, r_y^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
[8, 28, 66, 119, 192, 278, 384, 502, 640, 790]						
		1185	H_{308}	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y^{-1}, m_x r_z^{-1} t_z, r_y^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
[8, 29, 65, 113, 177, 253, 345, 449, 569, 701]						
		1186	H_{656}	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y, m_x t_y^{-1}, r_x^2 t_y^{-1}, m_x t_z, r_y^2 r_x t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
		1187	H_{316}	1	i	$r_z^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$

Nbr.	gr	$\mathbb{N}$	H_i	L	m	X
		1188	H_{317}	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z^{-1}$
		1189	H_{318}	1	i	$r_z^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, m_x t_z, m_x t_z^{-1}, r_z^2 t_z^{-1}$
[8, 29, 65, 114, 178, 254, 346, 450, 570, 702]						
		1190	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$
[8, 29, 67, 122, 193, 281, 385, 505, 641, 793]						
		1191	H_{323}	1	i	$r_z^2 t_x^{-1}, m_x r_y t_y, r_x^2 r_y t_y^{-1}, m_x r_y t_y^{-1}, m_x t_z, m_x t_z^{-1}, r_z^2 t_z^{-1}$
[8, 29, 69, 123, 196, 282, 388, 506, 644, 794]						
		1192	H_{326}	1	i	$m_z r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$
[8, 30, 66, 114, 178, 254, 346, 450, 570, 702]						
		1193	H_{659}	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, r_z^2 t_z, m_x r_x t_z^{-1}, r_x^{-1} t_z^{-1}$
		1194	H_{314}	1	i	$i t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, m_x t_z, m_x t_z^{-1}, r_x^2 t_z^{-1}$
[8, 30, 67, 121, 192, 280, 384, 504, 640, 792]						
		1195	H_{305}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, i t_y, m_x r_x^{-1} t_z, r_y^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
		1196	H_{308}	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y, m_x r_z^{-1} t_z, r_y^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
[8, 31, 69, 124, 195, 283, 387, 507, 643, 795]						
		1197	H_{323}	1	i	$r_z^2 t_x^{-1}, m_x r_y t_y, r_x^2 r_y t_y^{-1}, m_x r_y t_y^{-1}, m_x t_z, r_x^2 t_z, m_x t_z^{-1}$
		1198	H_{326}	1	i	$m_z r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, m_z t_z, r_z^2 t_z^{-1}$
18B						
[7, 25, 57, 103, 163, 237, 325, 427, 543, 673]						
1200*,						
[7, 25, 58, 103, 161, 235, 322, 421, 535, 663]						
1199*,						
[7, 26, 61, 107, 167, 242, 329, 431, 547, 675]						
1201*,						
[7, 26, 62, 109, 168, 243, 332, 434, 550, 680]						
1202*,						
[7, 27, 61, 107, 169, 245, 334, 436, 552, 682]						
1203*,						
[7, 27, 62, 109, 170, 245, 335, 438, 554, 685]						
1204*,						
[7, 27, 65, 113, 173, 249, 339, 443, 561, 693]						
1205*,						
[7, 29, 65, 111, 173, 249, 339, 443, 561, 693]						
1206*,						
[8, 28, 62, 108, 170, 244, 332, 434, 550, 678]						
		1199	H_{759}	$\langle m_z, r_x^2 \rangle$	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, m_x t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z, r_x t_z^{-1}$
[8, 28, 62, 110, 174, 250, 342, 446, 566, 698]						
		1200	H_{760}	$\langle m_z, r_x^2 \rangle$	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, m_x t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z, r_x t_z^{-1}$
[8, 29, 65, 111, 175, 250, 339, 443, 560, 689]						
		1201	H_{413}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, m_x r_x t_z^{-1}$
[8, 29, 66, 112, 175, 251, 341, 444, 563, 693]						
		1202	H_{395}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y, r_x^2 t_y, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, r_y^2 r_x t_z^{-1}$
[8, 30, 63, 111, 174, 250, 341, 444, 562, 692]						
		1203	H_{412}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z, m_x r_x t_z^{-1}$
[8, 30, 64, 112, 175, 251, 342, 445, 564, 695]						
		1204	H_{394}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y, r_x^2 t_y, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, r_y^2 r_x t_z^{-1}$
[8, 30, 68, 114, 178, 254, 346, 450, 570, 702]						
		1205	H_{758}	$\langle m_z, r_x^2 \rangle$	$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x t_y, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, m_x r_x^{-1} t_z, r_y^2 r_x t_z^{-1}$
[8, 32, 66, 114, 178, 254, 346, 450, 570, 702]						
		1206	H_{757}	$\langle m_z, r_x^2 \rangle$	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, m_x r_x t_y, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, m_x r_x^{-1} t_z, r_y^2 r_x t_z^{-1}$
19						
[8, 26, 56, 98, 152, 218, 296, 386, 488, 602]						
1208*,						
[8, 26, 57, 101, 158, 228, 311, 407, 516, 638]						
1207*,						
[8, 26, 57, 101, 159, 231, 316, 414, 525, 649]						
1209*,						
[8, 26, 58, 104, 162, 232, 316, 414, 524, 646]						
1213*,						

Nbr.	gr	N ₀	H _i	L	m	X
[8, 26, 58, 104, 163, 235, 321, 421, 534, 660]						
			1211*, 1212*,			
[8, 26, 58, 104, 164, 238, 326, 428, 543, 671]						
			1214*,			
[8, 26, 58, 104, 165, 241, 331, 435, 553, 685]						
			1215*, 1210*,			
[8, 26, 59, 107, 169, 245, 335, 439, 557, 689]						
			1216*,			
[8, 27, 61, 109, 171, 247, 337, 441, 559, 691]						
			1219*, 1220*, 1221*,			
[8, 27, 61, 112, 181, 268, 372, 492, 628, 780]						
			1217*, 1218*,			
[8, 27, 62, 115, 185, 272, 376, 496, 632, 784]						
			1222*, 1223*,			
[8, 28, 63, 111, 173, 249, 339, 443, 561, 693]						
			1224*, 1225*, 1226*, 1227*, 1228*, 1229*, 1230*,			
[8, 28, 64, 117, 187, 274, 378, 498, 634, 786]						
			1231*, 1232*, 1233*, 1234*,			
[8, 28, 64, 117, 188, 276, 380, 500, 636, 788]						
			1235*,			
[8, 28, 65, 120, 192, 280, 384, 504, 640, 792]						
			1236*, 1237*, 1238*,			
[8, 29, 67, 122, 194, 282, 386, 506, 642, 794]						
			1239*, 1240*, 1241*,			
[8, 30, 69, 124, 196, 284, 388, 508, 644, 796]						
			1242*, 1243*, 1244*, 1245*, 1246*, 1247*, 1248*, 1249*, 1250*,			
[9, 28, 61, 106, 165, 236, 321, 418, 529, 652]						
1207		H ₆₁₀	⟨m _z ⟩		r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y ⁻¹ , it _z , m _z t _z , r _z ² t _z ⁻¹ , t _z ⁻¹
1208		H ₆₁₆	⟨m _z ⟩		r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , m _y t _y ⁻¹ , r _y ² t _z , r _x ² t _z , m _x t _z ⁻¹ , m _y t _z ⁻¹
[9, 28, 62, 108, 169, 242, 329, 428, 542, 668]						
1209		H ₄₆₁	1		r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , m _y t _y ⁻¹ , r _y ² t _z , r _x ² t _z , it _z ⁻¹ , m _z t _z ⁻¹
[9, 28, 62, 108, 171, 246, 338, 442, 562, 694]						
1210		H ₄₆₀	1		r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y ⁻¹ , r _y ² t _z , r _x ² t _z , it _z ⁻¹ , m _z t _z ⁻¹
[9, 28, 63, 110, 171, 244, 333, 434, 549, 676]						
1211		H ₆₁₅	⟨m _z ⟩		r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , m _y t _y ⁻¹ , it _z , m _z t _z , r _z ² t _z ⁻¹ , t _z ⁻¹
1212		H ₃₀₅	1		i	t _x , it _x ⁻¹ , t _x ⁻¹ , it _y , t _y , it _y ⁻¹ , t _y ⁻¹ , r _y ² r _z t _z ⁻¹
1213		H ₅₄₀	1		r _z ²	m _z t _x , it _x ⁻¹ , m _z t _x ⁻¹ , r _x ² r _y t _y ⁻¹ , m _x t _z , m _y t _z , m _x t _z ⁻¹ , m _y t _z ⁻¹
[9, 28, 63, 110, 173, 248, 339, 442, 559, 688]						
1214		H ₅₀₄	1		r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _x ² r _y t _y ⁻¹ , r _z ² t _z , t _z , r _z ² t _z ⁻¹ , t _z ⁻¹
[9, 28, 63, 110, 173, 248, 339, 442, 562, 694]						
1215		H ₃₂₃	1		i	r _z ² t _x , m _z t _x , r _z ² t _x ⁻¹ , m _z t _x ⁻¹ , r _x ² r _y t _y ⁻¹ , m _x t _z , m _x t _z ⁻¹ , r _z ² t _z ⁻¹
[9, 28, 63, 110, 174, 250, 342, 446, 566, 698]						
1216		H ₆₁₄	⟨m _z ⟩		r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y ⁻¹ , r _y ² t _z , r _x ² t _z , m _x t _z ⁻¹ , m _y t _z ⁻¹
[9, 29, 64, 115, 183, 269, 372, 492, 628, 780]						
1217		H ₄₅₂	1		r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y ⁻¹ , r _y ² r _z t _z , r _x ² r _z t _z , it _z ⁻¹ , m _z t _z ⁻¹
1218		H ₄₈₇	1		r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y ⁻¹ , m _z r _z ⁻¹ t _z , m _z r _z t _z , it _z ⁻¹ , m _z t _z ⁻¹
[9, 29, 65, 113, 177, 253, 345, 449, 569, 701]						
1219		H ₆₁₇	⟨m _z ⟩		r _z ²	m _x t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , it _z , m _z t _z , r _z ² t _z ⁻¹ , t _z ⁻¹
1220		H ₆₁₈	⟨m _z ⟩		r _z ²	m _x t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , r _y ² t _z , r _x ² t _z , m _x t _z ⁻¹ , m _y t _z ⁻¹
1221		H ₄₈₃	1		r _z ²	m _x t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , r _y ² t _z , r _x ² t _z , it _z ⁻¹ , m _z t _z ⁻¹
[9, 29, 65, 117, 186, 273, 376, 496, 632, 784]						
1222		H ₅₀₃	1		r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y ⁻¹ , r _y ² r _z t _z , r _x ² r _z t _z , r _y ² t _z ⁻¹ , r _z ² t _z ⁻¹
1223		H ₅₁₉	1		r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y ⁻¹ , m _z r _z ⁻¹ t _z , m _z r _z t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
[9, 30, 66, 114, 178, 254, 346, 450, 570, 702]						
1224		H ₆₁₅	⟨m _z ⟩		r _z ²	r _z ² t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , it _z , m _z t _z , r _z ² t _z ⁻¹ , t _z ⁻¹
1225		H ₆₁₆	⟨m _z ⟩		r _z ²	r _z ² t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , r _y ² t _z , r _x ² t _z , m _x t _z ⁻¹ , m _y t _z ⁻¹
1226		H ₃₀₈	1		i	m _z t _x , r _z ² t _x ⁻¹ , m _z t _x ⁻¹ , r _z ² t _y , m _z t _y , r _z ² t _y ⁻¹ , m _z t _y ⁻¹ , r _y ² r _z t _z ⁻¹

Nbr.	gr	N ₀	H_i	L	m	X
		1227	H_{326}	1	i	$r_z^2 r_x t_x^{-1}, r_y^2 t_y, m_y t_y, r_y^2 t_y^{-1}, m_y t_y^{-1}, r_z^2 t_z,$ $r_z^2 t_z^{-1}, m_z t_z^{-1}$
		1228	H_{461}	1	r_z^2	$r_z^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_x^2 t_z,$ $it_x^{-1}, m_z t_z^{-1}$
		1229	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_x^2 t_z,$ $r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		1230	H_{541}	1	r_z^2	$r_z^2 r_x t_x, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, it_z, m_z t_z,$ $it_z^{-1}, m_z t_z^{-1}$
[9, 30, 67, 120, 189, 276, 379, 499, 635, 787]						
		1231	H_{527}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_x^2 r_z t_z,$ $it_z^{-1}, m_z t_z^{-1}$
		1232	H_{528}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z,$ $it_z^{-1}, m_z t_z^{-1}$
		1233	H_{529}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_x^2 r_z t_z,$ $r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		1234	H_{530}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z,$ $r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
[9, 30, 67, 121, 191, 278, 381, 500, 636, 788]						
		1235	H_{539}	1	r_z^2	$m_z t_x, it_x^{-1}, m_z t_x^{-1}, r_x^2 t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z,$ $r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
[9, 30, 67, 121, 192, 280, 384, 504, 640, 792]						
		1236	H_{611}	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 r_z t_z, r_x^2 r_z t_z,$ $m_x r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
		1237	H_{619}	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_x^2 t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z,$ $r_z^{-1} t_z^{-1}, r_z t_z^{-1}$
		1238	H_{495}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_x^2 t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z,$ $r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
[9, 31, 69, 124, 195, 283, 387, 507, 643, 795]						
		1239	H_{622}	$\langle m_z \rangle$	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_x^2 r_z t_z,$ $m_x r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
		1240	H_{623}	$\langle m_z \rangle$	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z,$ $r_z^{-1} t_z^{-1}, r_z t_z^{-1}$
		1241	H_{502}	1	r_z^2	$m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z,$ $r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
[9, 32, 70, 125, 196, 284, 388, 508, 644, 796]						
		1242	H_{305}	1	i	$it_x^{-1}, it_y, t_y, it_y^{-1}, t_y^{-1}, m_x r_z^{-1} t_z,$ $r_y^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
		1243	H_{308}	1	i	$r_z^2 t_x^{-1}, r_z^2 t_y, m_z t_y, r_z^2 t_y^{-1}, m_z t_y^{-1}, m_x r_z^{-1} t_z,$ $r_y^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
		1244	H_{323}	1	i	$r_z^2 t_x, m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, m_x r_y t_y, r_x^2 r_y t_y^{-1},$ $m_x r_y t_y^{-1}, r_x^2 t_z^{-1}$
		1245	H_{326}	1	i	$m_z r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x t_x^{-1}, m_y t_y^{-1}, r_z^2 t_z, m_z t_z,$ $r_z^2 t_z^{-1}, m_z t_z^{-1}$
		1246	H_{539}	1	r_z^2	$it_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z,$ $r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
		1247	H_{540}	1	r_z^2	$it_x^{-1}, r_y t_y, r_x^2 r_y t_y^{-1}, r_y^{-1} t_y^{-1}, m_x t_z, m_y t_z,$ $m_x t_x^{-1}, m_y t_z^{-1}$
		1248	H_{504}	1	r_z^2	$r_z^2 t_x^{-1}, r_y t_y, r_x^2 r_y t_y^{-1}, r_y^{-1} t_y^{-1}, r_z^2 t_z, t_z,$ $r_z^2 t_z^{-1}, t_z^{-1}$
		1249	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_x^2 t_z,$ $r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		1250	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_y t_y^{-1}, it_z, m_z t_z,$ $it_z^{-1}, m_z t_z^{-1}$

20

- [8, 27, 59, 105, 165, 239, 327, 429, 545, 675]
 1252*,
 [8, 27, 60, 106, 167, 242, 329, 431, 547, 675]
 1254*,
 [8, 27, 60, 107, 168, 243, 332, 435, 552, 683]
 1257*,
 [8, 27, 60, 107, 169, 245, 334, 436, 552, 682]
 1251*,
 [8, 27, 61, 108, 168, 243, 332, 434, 550, 680]
 1253*, 1258*,
 [8, 27, 61, 108, 170, 247, 336, 440, 559, 690]
 1255*,
 [8, 27, 61, 109, 170, 245, 335, 438, 554, 685]
 1256*,
 [8, 27, 61, 109, 170, 245, 335, 439, 556, 687]
 1259*, 1260*,
 [8, 27, 61, 109, 172, 249, 339, 443, 561, 693]
 1261*,
 [8, 27, 62, 111, 173, 249, 339, 443, 561, 693]
 1262*,

Nbr.	gr	N ₀	H_i	L	m	X
[8, 28, 64, 112, 173, 249, 339, 443, 561, 693]						
						1263*, 1264*, 1265*, 1266*, 1267*, 1268*,
[8, 29, 64, 111, 173, 249, 339, 443, 561, 693]						
						1269*, 1270*, 1271*, 1272*, 1273*, 1274*, 1275*, 1276*, 1277*, 1278*,
[9, 29, 63, 111, 174, 250, 341, 444, 562, 692]						
		1251	H_{412}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z,$ $m_x r_x t_z^{-1}, m_z t_z^{-1}$
[9, 29, 63, 111, 174, 250, 342, 446, 566, 698]						
		1252	H_{418}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z,$ $r_y^2 t_z^{-1}, r_x t_z^{-1}$
[9, 29, 64, 111, 174, 249, 339, 442, 560, 690]						
		1253	H_{388}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_z r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1}, i t_z, m_z r_x t_z,$ $i t_z^{-1}, m_z r_x t_z^{-1}$
[9, 29, 64, 111, 175, 250, 339, 443, 560, 689]						
		1254	H_{413}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z,$ $m_x r_x t_z^{-1}, m_z t_z^{-1}$
[9, 29, 64, 111, 176, 251, 343, 448, 567, 699]						
		1255	H_{407}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z,$ $r_y^2 t_z^{-1}, r_x t_z^{-1}$
[9, 29, 64, 112, 175, 251, 342, 445, 564, 695]						
		1256	H_{394}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y, r_x^2 t_y, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z,$ $r_y^2 r_x t_z^{-1}, r_x t_z^{-1}$
[9, 29, 64, 112, 176, 252, 344, 448, 568, 700]						
		1257	H_{389}	1	$r_z^2 r_x$	$i t_x^{-1}, m_z r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1}, i t_z, m_z r_x t_z,$ $i t_z^{-1}, m_z r_x t_z^{-1}$
[9, 29, 65, 112, 175, 251, 341, 444, 563, 693]						
		1258	H_{395}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y, r_x^2 t_y, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z,$ $r_y^2 r_x t_z^{-1}, r_x t_z^{-1}$
[9, 29, 65, 113, 176, 252, 344, 448, 568, 700]						
		1259	H_{398}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, m_z r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1}, i t_z, m_z r_x t_z,$ $i t_z^{-1}, m_z r_x t_z^{-1}$
[9, 29, 65, 113, 176, 252, 344, 448, 568, 700]						
		1260	H_{400}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_z r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1}, i t_z, m_z r_x t_z,$ $i t_z^{-1}, m_z r_x t_z^{-1}$
[9, 29, 65, 113, 178, 254, 346, 450, 570, 702]						
		1261	H_{410}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z,$ $r_y^2 t_z^{-1}, r_x t_z^{-1}$
[9, 29, 66, 114, 178, 254, 346, 450, 570, 702]						
		1262	H_{414}	1	$r_z^2 r_x$	$i t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z,$ $r_y^2 t_z^{-1}, r_x t_z^{-1}$
[9, 30, 67, 114, 178, 254, 346, 450, 570, 702]						
		1263	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, m_x r_x^{-1} t_y, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_x r_x t_z^{-1}, m_z t_z^{-1}$
		1264	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_y, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_y^2 r_x t_z^{-1}, r_x t_z^{-1}$
		1265	H_{395}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1}, i t_z, m_z r_x t_z,$ $r_y^2 r_x t_z^{-1}, r_x t_z^{-1}$
		1266	H_{413}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_y^2 t_z,$ $r_x t_z, m_x r_x t_z^{-1}$
		1267	H_{419}	1	$r_z^2 r_x$	$m_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_x r_x t_z^{-1}, m_z t_z^{-1}$
		1268	H_{401}	1	$r_z^2 r_x$	$m_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z,$ $r_y^2 r_x t_z^{-1}, r_x t_z^{-1}$
[9, 31, 66, 114, 178, 254, 346, 450, 570, 702]						
		1269	H_{415}	1	$r_z^2 r_x$	$i t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_x r_x t_z^{-1}, m_z t_z^{-1}$
		1270	H_{396}	1	$r_z^2 r_x$	$i t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z,$ $r_y^2 r_x t_z^{-1}, r_x t_z^{-1}$
		1271	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z,$ $m_x r_x t_z^{-1}, m_z t_z^{-1}$
		1272	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z,$ $r_y^2 r_x t_z^{-1}, r_x t_z^{-1}$
		1273	H_{394}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1}, i t_z, m_z r_x t_z,$ $r_y^2 r_x t_z^{-1}, r_x t_z^{-1}$
		1274	H_{412}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_y^2 t_z,$ $r_x t_z, m_x r_x t_z^{-1}$
		1275	H_{402}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_x r_x t_z^{-1}, m_z t_z^{-1}$
		1276	H_{391}	1	$r_z^2 r_x$	$r_z^2 r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z,$ $r_y^2 r_x t_z^{-1}, r_x t_z^{-1}$
		1277	H_{404}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_x r_x t_z^{-1}, m_z t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
21		1278	H_{392}	1	$r_z^2 r_x$	$r_y^2 r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z,$ $r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
		1279	H_{779}	$\langle m_z, m_z r_x, r_x^2 \rangle$	$r_z^2 r_x$	$m_x t_x^{-1}, r_z^2 t_y, r_x^2 t_y, m_x t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_x r_x^{-1} t_z,$ $m_z r_x^{-1} t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
		1280	H_{690}	$\langle m_x \rangle$	r_z^2	$r_z^2 t_x, m_x t_x, m_y t_y^{-1}, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z,$ $m_z r_z^{-1} t_z, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
		1281	H_{750}	$\langle m_y, m_z \rangle$	r_z^2	$m_x t_x^{-1}, r_z^2 t_y, m_y t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z,$ $m_z r_z t_z, m_x r_z t_z^{-1}, r_z t_z^{-1}$
22		1298*				
		1306*				
		1317*				
		1320*				
		1321*				
		1318*				
		1319*				
		1323*				
		1322*				
		1324*				
		1325*				
		1326*				
		1327*				
		1328*				
		1329*				
		1331*				
		1330*				
		1333*				
		1332*				
		1334*				
		1335*				
		1336*				
		1337*				
		1338*				
		1339*				
		1340*				
		1341*				
		1342*				
		1343*				
		1346*				
		1344*				
		1345*				
		1347*				
		1282	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_y^2 t_z^{-1}$
		1283	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_y^2 t_z^{-1}$
		1284	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_y^2 t_z^{-1}$

Nbr.	gr	N ₀	H _i	L	m	X	
1283			H ₆₅₀	⟨m _x ⟩	r _y ² r _x	m _x t _x , m _x t _x ⁻¹ , m _x r _x t _y , m _y t _y ⁻¹ , m _x r _x ⁻¹ t _z	
[6, 19, 44, 83, 136, 205, 291, 392, 509, 643]			1284	H ₄₂₂	1	r _z ² r _x	r _z ² t _x , r _y ² t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , m _z t _z ⁻¹
1285			H ₅₈₀	1	m _z r _x	it _x , m _x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , m _z t _z ⁻¹	
[6, 19, 45, 89, 152, 232, 328, 440, 568, 712]			1286	H ₅₈₀	1	m _z r _x	r _z ² r _x t _x , m _x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , m _z t _z ⁻¹
1287			H ₅₇₈	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , m _z t _z ⁻¹	
[6, 20, 47, 87, 139, 203, 279, 367, 467, 579]			1288	H ₆₄₈	⟨m _x ⟩	r _y ² r _x	m _x t _x , m _x t _x ⁻¹ , r _z ² r _x t _y , r _z ² t _y ⁻¹ , r _z ² r _x t _z
[6, 20, 47, 88, 144, 216, 304, 408, 528, 664]			1289	H ₆₅₂	⟨m _x ⟩	r _y ² r _x	it _x , r _z ² t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , r _y ² t _z ⁻¹
1290			H ₆₄₈	⟨m _x ⟩	r _y ² r _x	m _x t _x , m _x t _x ⁻¹ , r _z ² t _y ⁻¹ , r _z ² t _z , r _z ² t _z ⁻¹	
[6, 20, 48, 92, 153, 232, 328, 440, 568, 712]			1291	H ₅₇₄	1	m _z r _x	r _z ² r _x t _x , it _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , m _z t _z ⁻¹
1292			H ₅₈₀	1	m _z r _x	it _x , r _y ² r _x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , m _z t _z ⁻¹	
[6, 20, 49, 93, 147, 215, 301, 397, 503, 627]			1293	H ₅₇₈	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , r _x t _y , m _y t _y ⁻¹ , r _x ⁻¹ t _z
[6, 20, 49, 96, 160, 240, 336, 448, 576, 720]			1294	H ₆₅₂	⟨m _x ⟩	r _y ² r _x	r _z ² r _x t _x , r _z ² r _x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , r _y ² t _z ⁻¹
1295			H ₄₂₂	1	r _z ² r _x	r _x ⁻¹ t _x , r _x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , m _z t _z ⁻¹	
1296			H ₆₅₀	⟨m _x ⟩	r _y ² r _x	r _y ² r _x t _x , m _z r _x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , r _y ² t _z ⁻¹	
1297			H ₅₈₀	1	m _z r _x	r _z ² r _x t _x , r _y ² r _x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , m _z t _z ⁻¹	
[6, 20, 50, 103, 177, 263, 365, 490, 628, 774]			1298	H ₅₇₁	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _y t _y , r _z ² t _y ⁻¹ , m _z t _z
[6, 21, 50, 93, 152, 227, 317, 424, 547, 685]			1299	H ₄₀₉	1	r _z ² r _x	r _z ² t _x , r _y ² t _x ⁻¹ , r _z ² t _y ⁻¹ , r _z ² t _z , r _z ² t _z ⁻¹
1300			H ₅₆₀	1	m _z r _x	it _x , m _x t _x ⁻¹ , r _z ² t _y ⁻¹ , r _z ² t _z , r _z ² t _z ⁻¹	
[6, 21, 51, 95, 152, 224, 311, 411, 524, 652]			1301	H ₅₅₇	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _z ² t _y ⁻¹ , m _z r _x ⁻¹ t _z
[6, 21, 51, 96, 154, 227, 317, 421, 539, 673]			1302	H ₅₇₂	1	m _z r _x	r _z ² r _x t _x , it _x ⁻¹ , m _x r _x t _y , r _z ² t _y ⁻¹ , m _x r _x ⁻¹ t _z
[6, 21, 51, 97, 160, 240, 336, 448, 576, 720]			1303	H ₅₆₀	1	m _z r _x	r _z ² r _x t _x , m _x t _x ⁻¹ , r _z ² t _y ⁻¹ , r _z ² t _z , r _z ² t _z ⁻¹
1304			H ₅₅₇	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , r _z ² t _y ⁻¹ , r _z ² t _z , r _z ² t _z ⁻¹	
[6, 21, 52, 96, 152, 228, 316, 412, 532, 664]			1305	H ₆₅₀	⟨m _x ⟩	r _y ² r _x	r _y ² r _x t _x , m _z r _x t _x ⁻¹ , m _x r _x t _y , m _y t _y ⁻¹ , m _x r _x ⁻¹ t _z
[6, 21, 57, 116, 177, 256, 353, 452, 575, 717]			1306	H ₅₇₁	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , r _x t _y , r _z ² t _y ⁻¹ , r _x ⁻¹ t _z
[6, 22, 51, 96, 156, 232, 324, 432, 556, 696]			1307	H ₆₄₉	⟨m _x ⟩	r _y ² r _x	it _x , r _z ² t _x ⁻¹ , r _z ² t _y ⁻¹ , r _z ² t _z , r _z ² t _z ⁻¹
[6, 22, 52, 97, 156, 230, 319, 422, 539, 671]			1308	H ₅₅₁	1	m _z r _x	r _z ² r _x t _x , it _x ⁻¹ , r _z ² r _x t _y , it _y ⁻¹ , r _z ² r _x t _z
[6, 22, 52, 98, 158, 234, 323, 428, 547, 682]			1309	H ₃₉₃	1	r _z ² r _x	r _y ² r _z t _x , r _z ² r _y t _x ⁻¹ , r _y ² r _z t _y , r _y ² r _z t _z , r _z ² r _y t _z ⁻¹
[6, 22, 52, 98, 161, 240, 336, 448, 576, 720]			1310	H ₅₅₅	1	m _z r _x	r _z ² r _x t _x , it _x ⁻¹ , r _z ² t _y ⁻¹ , r _z ² t _z , r _z ² t _z ⁻¹
1311			H ₅₆₀	1	m _z r _x	it _x , r _y ² r _x t _x ⁻¹ , r _z ² t _y ⁻¹ , r _z ² t _z , r _z ² t _z ⁻¹	
[6, 22, 53, 97, 157, 233, 321, 425, 545, 677]			1312	H ₆₄₈	⟨m _x ⟩	r _y ² r _x	r _y ² r _x t _x , m _z r _x t _x ⁻¹ , r _z ² r _x t _y , r _z ² t _y ⁻¹ , r _z ² r _x t _z
[6, 22, 53, 100, 164, 244, 340, 452, 580, 724]			1313	H ₆₄₉	⟨m _x ⟩	r _y ² r _x	r _z ² r _x t _x , r _z ² r _x t _x ⁻¹ , r _z ² t _x ⁻¹ , r _z ² t _z , r _z ² t _z ⁻¹
1314			H ₄₀₉	1	r _z ² r _x	r _x ⁻¹ t _x , r _x t _x ⁻¹ , r _z ² t _y ⁻¹ , r _z ² t _z , r _z ² t _z ⁻¹	
1315			H ₆₄₈	⟨m _x ⟩	r _y ² r _x	r _y ² r _x t _x , m _z r _x t _x ⁻¹ , r _z ² t _y ⁻¹ , r _z ² t _z , r _z ² t _z ⁻¹	
1316			H ₅₆₀	1	m _z r _x	r _z ² r _x t _x , r _y ² r _x t _x ⁻¹ , r _z ² t _y ⁻¹ , r _z ² t _z , r _z ² t _z ⁻¹	
[6, 22, 55, 101, 159, 233, 316, 412, 528, 648]			1317	H ₅₈₀	1	m _z r _x	r _z ² r _x t _x , m _x t _x ⁻¹ , r _x t _y , m _y t _y ⁻¹ , r _x ⁻¹ t _z
[6, 22, 58, 111, 176, 255, 349, 459, 582, 719]			1318	H ₅₈₀	1	m _z r _x	it _x , m _x t _x ⁻¹ , r _x t _y , m _y t _y ⁻¹ , r _x ⁻¹ t _z
[6, 22, 59, 115, 177, 256, 349, 457, 581, 717]			1319	H ₄₂₂	1	r _z ² r _x	r _z ² t _x , r _z ² t _x ⁻¹ , m _y t _y , m _x r _x ⁻¹ t _y ⁻¹ , m _x r _x t _z
[6, 22, 60, 111, 179, 261, 355, 465, 591, 729]			1320	H ₅₆₁	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , it _y ⁻¹ , m _z r _x ⁻¹ t _z
[6, 22, 60, 115, 191, 278, 381, 506, 643, 790]			1321	H ₅₆₁	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , r _z ² t _y , it _y ⁻¹ , r _z ² t _z
[6, 23, 54, 106, 182, 272, 374, 493, 632, 785]			1322	H ₅₇₁	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _y t _y , r _z ² t _y ⁻¹ , r _y ² t _z ⁻¹
[6, 23, 56, 102, 162, 235, 320, 420, 533, 658]			1323	H ₅₆₀	1	m _z r _x	r _z ² r _x t _x , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _z ² t _y ⁻¹ , m _z r _x ⁻¹ t _z
[6, 23, 59, 112, 180, 260, 354, 464, 588, 728]			1324	H ₅₆₀	1	m _z r _x	it _x , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _z ² t _y ⁻¹ , m _z r _x ⁻¹ t _z
[6, 23, 60, 112, 176, 255, 344, 455, 571, 705]			1325	H ₅₈₀	1	m _z r _x	r _z ² r _x t _x , r _y ² r _x t _x ⁻¹ , r _x t _y , m _y t _y ⁻¹ , r _x ⁻¹ t _z
[6, 23, 62, 115, 176, 257, 345, 455, 578, 708]							

Nbr.	gr	N ₀	H_i	L	m	X
		1326	H_{422}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z$
[6, 23, 63, 116, 182, 264, 364, 474, 598, 744]		1327	H_{580}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x^{-1} t_z$
[6, 23, 64, 116, 184, 266, 364, 477, 605, 749]		1328	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 t_x^{-1}, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
[6, 24, 56, 111, 184, 270, 376, 494, 632, 782]		1329	H_{576}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
[6, 24, 59, 113, 177, 253, 351, 455, 574, 715]		1330	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
[6, 24, 60, 114, 179, 257, 352, 460, 581, 720]		1331	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z$
[6, 24, 61, 115, 183, 269, 376, 494, 632, 782]		1332	H_{572}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
[6, 24, 63, 118, 185, 268, 367, 478, 606, 749]		1333	H_{560}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z$
[6, 24, 65, 119, 185, 265, 363, 476, 603, 748]		1334	H_{409}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_z^2 t_z^{-1}$
[6, 25, 60, 108, 172, 246, 338, 442, 558, 692]		1335	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x r_x t_y, m_y t_y^{-1}, m_x r_x^{-1} t_z$
[6, 25, 60, 118, 176, 253, 353, 454, 574, 718]		1336	H_{576}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x^{-1} t_z$
[6, 25, 63, 118, 183, 262, 361, 470, 592, 735]		1337	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 t_z, r_z^2 r_x t_z^{-1}$
[6, 25, 63, 119, 192, 280, 382, 505, 641, 792]		1338	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, it_y^{-1}, r_z^2 t_z, it_z^{-1}$
[6, 25, 65, 118, 182, 263, 359, 469, 597, 736]		1339	H_{574}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x^{-1} t_z$
[6, 25, 66, 120, 187, 268, 368, 481, 608, 751]		1340	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$it_x, r_x^2 t_x^{-1}, m_x r_x t_y, m_y t_y^{-1}, m_x r_x^{-1} t_z$
[6, 26, 59, 109, 169, 247, 335, 441, 557, 691]		1341	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1}, r_z^2 r_x t_z$
[6, 26, 64, 121, 183, 266, 361, 474, 599, 742]		1342	H_{555}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z$
[6, 26, 64, 122, 192, 278, 383, 505, 639, 793]		1343	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$
[6, 26, 65, 119, 182, 263, 360, 471, 594, 734]		1344	H_{556}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_z$
[6, 26, 65, 120, 191, 281, 383, 505, 639, 793]		1345	H_{556}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$
[6, 26, 65, 123, 188, 272, 369, 484, 612, 757]		1346	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$it_x, r_x^2 t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1}, r_z^2 r_x t_z$
[6, 26, 71, 119, 185, 271, 367, 479, 609, 750]		1347	H_{393}	1	$r_z^2 r_x$	$r_y r_x t_x, r_y^{-1} r_z^{-1} t_x^{-1}, r_y r_x t_y, r_y^2 r_z t_z, r_y^{-1} r_z^{-1} t_z^{-1}$

23

- [6, 19, 44, 85, 146, 229, 332, 452, 588, 740]
 1348*,
 [6, 19, 44, 87, 154, 241, 341, 460, 602, 756]
 1349*,
 [6, 20, 49, 95, 154, 224, 308, 406, 516, 640]
 1351*,
 [6, 20, 49, 95, 156, 234, 333, 452, 588, 740]
 1350*,
 [6, 20, 49, 95, 157, 237, 336, 453, 588, 740]
 1352*,
 [6, 20, 50, 101, 172, 260, 364, 484, 620, 772]
 1353*, 1354*,
 [6, 20, 52, 108, 172, 244, 339, 443, 558, 697]
 1355*,
 [6, 21, 49, 94, 165, 259, 365, 481, 615, 771]
 1356*,
 [6, 21, 49, 97, 170, 258, 362, 482, 618, 770]
 1357*,
 [6, 21, 52, 100, 162, 237, 326, 429, 546, 677]
 1359*,
 [6, 21, 52, 100, 164, 244, 341, 456, 589, 740]
 1358*,
 [6, 21, 52, 101, 168, 253, 356, 476, 612, 764]
 1361*,
 [6, 21, 53, 103, 168, 247, 340, 448, 570, 705]
 1360*,
 [6, 21, 53, 104, 173, 260, 364, 484, 620, 772]
 1362*, 1363*, 1364*,
 [6, 21, 54, 105, 167, 244, 339, 442, 559, 697]
 1365*,
 [6, 21, 56, 107, 169, 247, 340, 447, 569, 706]
 1366*,
 [6, 21, 56, 110, 180, 267, 369, 491, 635, 789]
 1367*,
 [6, 22, 54, 103, 172, 260, 364, 484, 620, 772]
 1368*,
 [6, 22, 54, 104, 170, 246, 337, 443, 560, 695]
 1369*,
 [6, 22, 54, 107, 171, 243, 337, 444, 559, 697]

Nbr.	gr	N ₀	H_i	L	m	X
			1370*,			
			[6, 22, 55, 105, 170, 249, 343, 452, 575, 713]			
			1371*,			
			[6, 22, 55, 105, 172, 256, 357, 476, 612, 764]			
			1372*,			
			[6, 22, 55, 105, 173, 257, 358, 477, 612, 764]			
			1373*,			
			[6, 22, 56, 107, 172, 253, 348, 456, 580, 718]			
			1375*,			
			[6, 22, 56, 108, 175, 256, 354, 467, 591, 732]			
			1374*,			
			[6, 22, 56, 109, 180, 268, 372, 492, 628, 780]			
			1376*, 1377*,			
			[6, 22, 58, 111, 171, 245, 339, 442, 559, 697]			
			1378*,			
			[6, 23, 54, 102, 172, 260, 364, 484, 620, 772]			
			1379*,			
			[6, 23, 56, 108, 176, 260, 361, 478, 613, 764]			
			1381*,			
			[6, 23, 57, 106, 170, 255, 361, 482, 618, 770]			
			1380*,			
			[6, 23, 57, 109, 177, 259, 357, 469, 596, 738]			
			1384*,			
			[6, 23, 57, 110, 181, 268, 372, 492, 628, 780]			
			1386*, 1387*,			
			[6, 23, 58, 106, 168, 245, 333, 439, 557, 687]			
			1382*,			
			[6, 23, 58, 111, 178, 255, 349, 460, 581, 719]			
			1385*,			
			[6, 23, 58, 111, 183, 273, 376, 495, 632, 785]			
			1388*,			
			[6, 23, 59, 110, 170, 245, 339, 442, 559, 697]			
			1389*,			
			[6, 23, 59, 110, 175, 260, 364, 484, 620, 772]			
			1383*,			
			[6, 23, 59, 112, 176, 254, 349, 460, 583, 720]			
			1390*,			
			[6, 23, 59, 112, 181, 272, 376, 496, 632, 784]			
			1391*,			
			[6, 23, 60, 112, 176, 256, 350, 458, 582, 720]			
			1392*,			
			[6, 23, 60, 114, 184, 272, 376, 496, 632, 784]			
			1394*,			
			[6, 23, 61, 114, 178, 257, 354, 467, 591, 732]			
			1393*,			
			[6, 24, 59, 108, 172, 249, 341, 448, 568, 704]			
			1397*,			
			[6, 24, 59, 109, 170, 245, 339, 442, 559, 697]			
			1396*,			
			[6, 24, 59, 109, 173, 252, 347, 457, 584, 726]			
			1395*,			
			[6, 24, 60, 111, 176, 256, 351, 460, 586, 726]			
			1398*,			
			[6, 24, 62, 113, 176, 256, 350, 458, 582, 720]			
			1400*,			
			[6, 24, 62, 115, 184, 272, 376, 496, 632, 784]			
			1403*,			
			[6, 24, 62, 116, 182, 262, 359, 471, 598, 740]			
			1401*,			
			[6, 24, 62, 117, 184, 264, 361, 474, 601, 742]			
			1399*,			
			[6, 24, 63, 117, 183, 264, 361, 474, 601, 742]			
			1402*,			
			[6, 25, 59, 110, 173, 252, 344, 452, 573, 710]			
			1404*,			
			[6, 25, 60, 112, 177, 258, 353, 464, 589, 730]			
			1405*,			
			[6, 25, 61, 114, 185, 272, 376, 496, 632, 784]			
			1406*,			
			[6, 25, 62, 112, 176, 256, 350, 458, 582, 720]			
			1407*,			
			[6, 25, 62, 114, 184, 272, 376, 496, 632, 784]			
			1408*,			
			[6, 25, 62, 116, 184, 270, 373, 496, 632, 784]			
			1409*,			
			[6, 25, 62, 118, 185, 266, 363, 476, 604, 748]			
			1410*,			
			[6, 25, 63, 118, 184, 266, 363, 476, 604, 748]			
			1411*,			
			[7, 23, 52, 98, 165, 252, 356, 476, 612, 764]			
			1348	H_{578}	1	$m_z r_x \quad m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
			[7, 23, 54, 106, 177, 261, 364, 490, 628, 774]			
			1349	H_{571}	1	$m_z r_x \quad m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, m_z t_z$
			[7, 24, 56, 104, 169, 253, 356, 476, 612, 764]			
			1350	H_{580}	1	$m_z r_x \quad i t_x, r_z^2 r_x t_x, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
			[7, 24, 57, 106, 166, 238, 326, 426, 538, 666]			
			1351	H_{578}	1	$m_z r_x \quad m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x^{-1} t_z$
			[7, 24, 57, 106, 171, 255, 357, 476, 612, 764]			
			1352	H_{580}	1	$m_z r_x \quad i t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
			[7, 24, 58, 112, 184, 272, 376, 496, 632, 784]			

Nbr.	gr	N ₀	H _i	L	m	X
1353			H ₅₈₀	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
1354			H ₅₇₈	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 24, 61, 118, 176, 255, 353, 452, 575, 717]			H ₅₇₁	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, r_z^2 t_y^{-1}, r_x^{-1} t_z$
[7, 25, 55, 107, 184, 273, 374, 493, 632, 785]			H ₅₇₁	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
[7, 25, 57, 110, 184, 270, 376, 494, 632, 782]			H ₅₇₆	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
[7, 25, 59, 109, 175, 258, 359, 477, 612, 764]			H ₅₇₄	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
[7, 25, 60, 110, 173, 250, 341, 446, 565, 698]			H ₅₅₇	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z$
[7, 25, 60, 111, 176, 255, 349, 459, 582, 719]			H ₅₈₀	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, m_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x^{-1} t_z$
[7, 25, 60, 112, 181, 268, 372, 492, 628, 780]			H ₅₅₇	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
[7, 25, 60, 113, 184, 272, 376, 496, 632, 784]			H ₅₇₄	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
1363			H ₅₈₀	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
1364			H ₅₇₁	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_z^2 t_z^{-1}, m_z t_z$
[7, 25, 62, 114, 175, 256, 352, 452, 576, 716]			H ₅₇₈	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x^{-1} t_z$
[7, 25, 65, 114, 179, 261, 355, 465, 591, 729]			H ₅₆₁	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, it_y^{-1}, m_z r_x^{-1} t_z$
[7, 25, 65, 118, 189, 276, 381, 506, 643, 790]			H ₅₆₁	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, it_y^{-1}, r_x^2 t_z$
[7, 26, 60, 112, 184, 272, 376, 496, 632, 784]			H ₅₇₁	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
[7, 26, 60, 114, 179, 254, 351, 455, 574, 715]			H ₅₇₁	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
[7, 26, 61, 117, 176, 253, 353, 454, 574, 718]			H ₅₇₆	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x^{-1} t_z$
[7, 26, 62, 113, 179, 259, 354, 464, 588, 728]			H ₅₆₀	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z$
[7, 26, 62, 114, 183, 269, 372, 492, 628, 780]			H ₅₆₀	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, m_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
[7, 26, 63, 114, 185, 269, 373, 492, 628, 780]			H ₅₆₀	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
[7, 26, 63, 116, 182, 263, 363, 474, 598, 744]			H ₅₈₀	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x^{-1} t_z$
[7, 26, 64, 115, 181, 264, 358, 468, 594, 732]			H ₅₅₇	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z$
[7, 26, 64, 118, 190, 278, 382, 502, 638, 790]			H ₅₆₀	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
1376			H ₅₆₀	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
1377			H ₅₅₇	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
[7, 26, 65, 117, 176, 256, 352, 452, 576, 716]			H ₅₇₁	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, r_z^2 t_y^{-1}, r_x^{-1} t_z$
[7, 27, 59, 112, 184, 272, 376, 496, 632, 784]			H ₅₇₆	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
[7, 27, 62, 112, 183, 269, 376, 494, 632, 782]			H ₅₇₂	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
[7, 27, 63, 117, 185, 272, 373, 493, 628, 780]			H ₅₅₅	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
[7, 27, 64, 112, 177, 255, 344, 455, 571, 705]			H ₅₈₀	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x^{-1} t_z$
[7, 27, 64, 115, 184, 272, 376, 496, 632, 784]			H ₅₇₂	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
[7, 27, 64, 117, 185, 267, 366, 478, 606, 749]			H ₅₆₀	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z$
[7, 27, 64, 119, 184, 262, 361, 470, 592, 735]			H ₅₆₁	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 t_z, r_z^2 r_x t_z^{-1}$
[7, 27, 64, 119, 190, 278, 382, 502, 638, 790]			H ₅₅₅	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
1386			H ₅₅₅	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
1387			H ₅₆₀	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
[7, 27, 64, 120, 193, 280, 382, 505, 641, 792]			H ₅₆₁	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y^{-1}, r_x^2 t_z, it_z^{-1}$
[7, 27, 65, 116, 176, 256, 352, 452, 576, 716]			H ₅₇₁	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
[7, 27, 66, 118, 182, 263, 360, 471, 594, 734]			H ₅₅₆	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_z$
[7, 27, 66, 119, 191, 281, 383, 505, 639, 793]			H ₅₅₆	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$
[7, 27, 67, 117, 183, 265, 359, 469, 595, 733]			H ₅₆₁	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, it_y^{-1}, m_z r_x^{-1} t_z$
[7, 27, 67, 118, 183, 263, 363, 474, 598, 744]						

Nbr.	gr	N ₀	H_i	L	m	X
		1393	H_{580}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x^{-1} t_z$
		[7, 27, 67, 120, 192, 280, 384, 504, 640, 792]				
		1394	H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, it_y^{-1}, r_x^2 t_z$
		[7, 28, 64, 115, 180, 260, 356, 466, 594, 735]				
		1395	H_{572}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x^{-1} t_z$
		[7, 28, 64, 116, 176, 256, 352, 452, 576, 716]				
		1396	H_{576}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x^{-1} t_z$
		[7, 28, 65, 114, 181, 258, 353, 461, 582, 721]				
		1397	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z$
		[7, 28, 65, 116, 182, 263, 359, 469, 597, 736]				
		1398	H_{574}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x^{-1} t_z$
		[7, 28, 67, 121, 187, 268, 368, 481, 608, 751]				
		1399	H_{572}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x^{-1} t_z$
		[7, 28, 68, 117, 183, 265, 359, 469, 595, 733]				
		1400	H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z, r_z^2 r_x t_z^{-1}$
		[7, 28, 68, 120, 187, 268, 367, 479, 607, 750]				
		1401	H_{560}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z$
		[7, 28, 68, 120, 187, 268, 368, 481, 608, 751]				
		1402	H_{574}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x^{-1} t_z$
		[7, 28, 68, 120, 192, 280, 384, 504, 640, 792]				
		1403	H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y^{-1}, r_x^2 t_z, it_z^{-1}$
		[7, 29, 64, 117, 180, 262, 354, 465, 586, 726]				
		1404	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_z$
		[7, 29, 65, 118, 183, 266, 361, 474, 599, 742]				
		1405	H_{555}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z$
		[7, 29, 66, 121, 192, 280, 384, 504, 640, 792]				
		1406	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$
		[7, 29, 67, 117, 183, 265, 359, 469, 595, 733]				
		1407	H_{556}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_z$
		[7, 29, 67, 120, 192, 280, 384, 504, 640, 792]				
		1408	H_{556}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$
		[7, 29, 67, 121, 192, 278, 383, 505, 639, 793]				
		1409	H_{551}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$
		[7, 29, 67, 123, 188, 272, 369, 484, 612, 757]				
		1410	H_{551}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_z$
		[7, 29, 68, 122, 188, 272, 369, 484, 612, 757]				
		1411	H_{555}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z$

24

- [6, 18, 39, 72, 120, 184, 264, 360, 472, 600]
1412*
[6, 18, 39, 73, 128, 209, 308, 417, 545, 700]
1413*
[6, 19, 44, 82, 130, 188, 258, 338, 428, 530]
1414*
[6, 19, 45, 89, 152, 232, 328, 440, 568, 712]
1415*, 1416*
[6, 19, 47, 97, 161, 235, 328, 432, 548, 686]
1417*
[6, 20, 46, 88, 152, 238, 344, 465, 598, 749]
1418*
[6, 20, 46, 90, 161, 249, 353, 473, 609, 761]
1419*
[6, 20, 47, 87, 139, 203, 279, 367, 467, 579]
1423*
[6, 20, 47, 88, 144, 216, 304, 408, 528, 664]
1424*, 1420*
[6, 20, 48, 92, 153, 232, 328, 440, 568, 712]
1421*, 1422*
[6, 20, 49, 93, 148, 219, 307, 404, 517, 649]
1425*
[6, 20, 50, 101, 172, 260, 364, 484, 620, 772]
1426*
[6, 20, 51, 97, 154, 225, 309, 406, 517, 641]
1427*
[6, 20, 51, 100, 166, 250, 349, 465, 602, 760]
1428*
[6, 21, 51, 95, 153, 227, 315, 417, 535, 667]
1432*
[6, 21, 51, 97, 160, 240, 336, 448, 576, 720]
1433*, 1434*
[6, 21, 51, 98, 160, 235, 327, 432, 549, 685]
1431*
[6, 21, 51, 100, 163, 238, 332, 437, 553, 691]
1430*
[6, 21, 51, 100, 171, 260, 364, 484, 620, 772]
1429*
[6, 21, 55, 108, 170, 245, 339, 442, 559, 697]
1435*
[6, 21, 56, 106, 167, 246, 336, 441, 563, 694]
1436*
[6, 22, 51, 96, 156, 232, 324, 432, 556, 696]
1437*
[6, 22, 52, 98, 161, 240, 336, 448, 576, 720]
1439*, 1440*

Nbr.	gr	N ₀	H_i	L	m	X
		1427	H_{388}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_z^{-1}$
	[7, 24, 60, 110, 180, 268, 369, 488, 626, 780]	1428	H_{394}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_x^2 t_y, it_y^{-1}, r_x^2 t_z^{-1}$
	[7, 25, 58, 111, 184, 272, 376, 496, 632, 784]	1429	H_{413}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_y^2 t_z$
	[7, 25, 58, 112, 173, 252, 349, 450, 571, 714]	1430	H_{412}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x r_x^{-1} t_y, r_z^2 t_y^{-1}, m_x r_x t_z^{-1}$
	[7, 25, 59, 110, 172, 250, 346, 448, 570, 710]	1431	H_{402}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z$
	[7, 25, 60, 107, 170, 249, 340, 447, 570, 705]	1432	H_{395}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z, r_x^2 t_z^{-1}$
	[7, 25, 60, 110, 178, 262, 362, 478, 610, 758]	1433	H_{409}	1	$r_z^2 r_x$	$r_x^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_x^2 t_y, r_x^2 t_z^{-1}, r_x^2 t_z$
		1434	H_{401}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
	[7, 25, 63, 116, 176, 256, 352, 452, 576, 716]	1435	H_{418}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x t_z^{-1}$
	[7, 25, 64, 112, 175, 257, 345, 455, 578, 708]	1436	H_{422}	1	$r_z^2 r_x$	$r_x^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z$
	[7, 26, 59, 110, 174, 258, 354, 470, 598, 746]	1437	H_{392}	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
	[7, 26, 59, 112, 184, 272, 376, 496, 632, 784]	1438	H_{418}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
	[7, 26, 60, 111, 178, 262, 362, 478, 610, 758]	1439	H_{396}	1	$r_z^2 r_x$	$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
		1440	H_{409}	1	$r_z^2 r_x$	$r_x^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
	[7, 26, 62, 113, 182, 270, 376, 494, 632, 782]	1441	H_{410}	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
	[7, 26, 63, 115, 176, 256, 352, 452, 576, 716]	1442	H_{419}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z$
	[7, 26, 63, 115, 180, 261, 356, 467, 591, 731]	1443	H_{394}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y, it_y^{-1}, r_y^2 r_x t_z^{-1}$
	[7, 26, 63, 115, 181, 261, 357, 467, 591, 731]	1444	H_{391}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
	[7, 26, 63, 116, 186, 276, 378, 500, 634, 788]	1445	H_{388}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$
	[7, 26, 63, 116, 187, 276, 379, 500, 635, 788]	1446	H_{394}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, it_y^{-1}, it_z, r_x^2 t_z^{-1}$
	[7, 26, 64, 115, 184, 272, 376, 496, 632, 784]	1447	H_{414}	1	$r_z^2 r_x$	$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 t_z^{-1}$
	[7, 26, 65, 116, 183, 265, 359, 469, 595, 733]	1448	H_{400}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_z^{-1}$
	[7, 26, 65, 119, 193, 280, 384, 504, 640, 792]	1449	H_{395}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_x^2 t_y, it_y^{-1}, r_x^2 t_z^{-1}$
	[7, 26, 67, 116, 184, 265, 363, 476, 603, 748]	1450	H_{409}	1	$r_z^2 r_x$	$r_x^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z$
	[7, 27, 63, 114, 179, 259, 355, 465, 593, 734]	1451	H_{414}	1	$r_z^2 r_x$	$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x t_z^{-1}$
	[7, 27, 64, 116, 176, 256, 352, 452, 576, 716]	1452	H_{413}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_x r_x^{-1} t_y, r_z^2 t_y^{-1}, m_x r_x t_z^{-1}$
	[7, 27, 65, 116, 182, 263, 359, 469, 597, 736]	1453	H_{415}	1	$r_z^2 r_x$	$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z$
	[7, 27, 66, 117, 183, 265, 359, 469, 595, 733]	1454	H_{401}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
	[7, 27, 66, 120, 187, 268, 368, 481, 608, 751]	1455	H_{410}	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x t_z^{-1}$
	[7, 27, 66, 120, 192, 280, 384, 504, 640, 792]	1456	H_{395}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, it_y^{-1}, it_z, r_x^2 t_z^{-1}$
	[7, 27, 68, 120, 187, 268, 368, 481, 608, 751]	1457	H_{404}	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z$
	[7, 28, 63, 115, 178, 259, 351, 461, 582, 721]	1458	H_{389}	1	$r_z^2 r_x$	$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_z^{-1}$
	[7, 28, 65, 118, 183, 266, 361, 474, 599, 742]	1459	H_{396}	1	$r_z^2 r_x$	$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
	[7, 28, 66, 118, 183, 265, 362, 473, 598, 741]	1460	H_{422}	1	$r_z^2 r_x$	$r_x^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z, m_z t_z^{-1}$
	[7, 28, 66, 121, 192, 280, 384, 504, 640, 792]	1461	H_{389}	1	$r_z^2 r_x$	$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$
	[7, 28, 67, 117, 183, 265, 359, 469, 595, 733]	1462	H_{395}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_y^2 r_x t_y, it_y^{-1}, r_y^2 r_x t_z^{-1}$
	[7, 28, 67, 120, 192, 280, 384, 504, 640, 792]	1463	H_{400}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$
	[7, 28, 67, 121, 188, 272, 369, 484, 612, 757]	1464	H_{398}	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_z^{-1}$
	[7, 28, 67, 122, 191, 279, 383, 505, 639, 793]	1465	H_{398}	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, it_y^{-1}, it_z, it_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
25		[7, 28, 69, 121, 188, 272, 369, 484, 612, 757]				
	1466	H_{392}	1		$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
		[7, 29, 67, 120, 189, 271, 372, 487, 617, 763]				
	1467	H_{409}	1		$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
		[7, 23, 53, 102, 172, 260, 364, 484, 620, 772]				
	1468*					
		[7, 24, 56, 105, 173, 260, 364, 484, 620, 772]				
	1469*, 1470*					
		[7, 24, 58, 109, 170, 245, 339, 442, 559, 697]				
	1471*					
		[7, 25, 59, 108, 174, 260, 364, 484, 620, 772]				
	1472*					
		[7, 25, 60, 112, 178, 257, 354, 467, 591, 732]				
	1473*					
		[7, 25, 61, 112, 176, 256, 350, 458, 582, 720]				
	1475*					
		[7, 25, 61, 113, 178, 258, 354, 465, 589, 729]				
	1474*					
		[7, 25, 61, 114, 184, 272, 376, 496, 632, 784]				
	1476*					
		[7, 26, 62, 114, 181, 262, 359, 471, 598, 740]				
	1478*					
		[7, 26, 62, 115, 183, 264, 361, 474, 601, 742]				
	1477*					
		[7, 26, 62, 115, 184, 267, 366, 481, 611, 756]				
	1479*					
		[7, 26, 62, 115, 185, 272, 376, 496, 632, 784]				
	1480*, 1481*					
		[7, 27, 63, 116, 183, 266, 363, 476, 604, 748]				
	1482*					
		[7, 27, 63, 116, 186, 272, 376, 496, 632, 784]				
	1483*					
		[8, 26, 59, 112, 184, 272, 376, 496, 632, 784]				
	1468	H_{650}	$\langle m_x \rangle$		$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_y^2 t_z^{-1}$
		[8, 27, 61, 113, 184, 272, 376, 496, 632, 784]				
	1469	H_{422}	1		$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
		[8, 27, 61, 113, 184, 272, 376, 496, 632, 784]				
	1470	H_{580}	1		$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z^{-1}$
		[8, 27, 64, 116, 176, 256, 352, 452, 576, 716]				
	1471	H_{650}	$\langle m_x \rangle$		$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, m_x r_x t_y, m_y t_y^{-1}, m_x r_x^{-1} t_z$
		[8, 28, 63, 114, 184, 272, 376, 496, 632, 784]				
	1472	H_{652}	$\langle m_x \rangle$		$r_y^2 r_x$	$it_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_y^2 t_z^{-1}$
		[8, 28, 65, 118, 183, 263, 363, 474, 598, 744]				
	1473	H_{580}	1		$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x^{-1} t_z$
		[8, 28, 66, 118, 183, 265, 362, 473, 598, 741]				
	1474	H_{422}	1		$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z$
		[8, 28, 67, 117, 183, 265, 359, 469, 595, 733]				
	1475	H_{648}	$\langle m_x \rangle$		$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1}, r_z^2 r_x t_z$
		[8, 28, 67, 120, 192, 280, 384, 504, 640, 792]				
	1476	H_{648}	$\langle m_x \rangle$		$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
		[8, 29, 66, 120, 187, 268, 368, 481, 608, 751]				
	1477	H_{652}	$\langle m_x \rangle$		$r_y^2 r_x$	$it_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, m_x r_x t_y, m_y t_y^{-1}, m_x r_x^{-1} t_z$
		[8, 29, 67, 119, 187, 268, 367, 479, 607, 750]				
	1478	H_{560}	1		$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_z$
		[8, 29, 67, 120, 189, 271, 372, 487, 617, 763]				
	1479	H_{409}	1		$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
		[8, 29, 67, 121, 192, 280, 384, 504, 640, 792]				
	1480	H_{409}	1		$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
		[8, 29, 67, 121, 188, 272, 369, 484, 612, 757]				
	1481	H_{560}	1		$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$
		[8, 30, 67, 121, 188, 272, 369, 484, 612, 757]				
	1482	H_{649}	$\langle m_x \rangle$		$r_y^2 r_x$	$it_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1}, r_z^2 r_x t_z$
		[8, 30, 67, 122, 192, 280, 384, 504, 640, 792]				
	1483	H_{649}	$\langle m_x \rangle$		$r_y^2 r_x$	$it_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
26B	[5, 14, 29, 50, 77, 110, 149, 194, 245, 302]	1484*	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_y^2 r_z t_z$
		1484				
		1484				
26C	[5, 14, 32, 66, 112, 171, 242, 327, 423, 533]	1485*	H_{393}	1	$r_z^2 r_x$	$r_x^2 r_y t_x^{-1}, r_y^{-1} r_z^{-1} t_x^{-1}, r_y r_x t_y, r_y^2 r_z t_z, r_x^2 r_y t_z^{-1}$
		1485				
		1485				
27A	[5, 18, 54, 122, 212, 299, 398, 519, 649, 804]	1486*	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_y r_x t_x, r_y^2 r_z t_y, r_y^2 r_z t_z, r_y^{-1} r_z^{-1} t_z^{-1}$
		1486				
		1486				
27A	[5, 18, 54, 122, 212, 299, 398, 519, 649, 804]	1487*	H_{393}	1	$r_z^2 r_x$	$r_y r_x t_x, r_x^2 r_y t_x^{-1}, r_y^2 r_z t_z, r_x^2 r_y t_z^{-1}, r_y^{-1} r_z^{-1} t_z^{-1}$
		1487				
		1487				
27A	[6, 18, 39, 71, 114, 167, 231, 306, 391, 487]	1488*	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$
		1488				
		1488				
27A	[7, 24, 54, 96, 150, 216, 294, 384, 486, 600]	1489*	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z, r_z^2 r_x t_z^{-1}$
		1489				
		1489				

Nbr.	gr	N ₀	H_i	L	m	X
		1490	H_{580}	1	$m_z r_x$	$r_z^2 r_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z, r_x^{-1} t_z^{-1}$
		[7, 24, 57, 105, 164, 237, 326, 426, 538, 666]				
		1491	H_{578}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z, r_x^{-1} t_z^{-1}$
		[7, 25, 59, 113, 177, 253, 351, 455, 574, 715]				
		1492	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_z t_z, m_x r_x^{-1} t_z^{-1}$
		[7, 25, 60, 118, 176, 255, 353, 452, 575, 717]				
		1493	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_x t_y, r_z^2 t_y^{-1}, r_x^{-1} t_z, m_z t_z$
		[7, 26, 59, 104, 164, 237, 322, 422, 535, 660]				
		1494	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, m_x t_x^{-1}, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z^{-1}$
		[7, 26, 60, 108, 172, 246, 338, 442, 558, 692]				
		1495	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_y t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$
		[7, 26, 60, 118, 176, 253, 353, 454, 574, 718]				
		1496	H_{576}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$
		[7, 26, 61, 111, 176, 255, 349, 459, 582, 719]				
		1497	H_{580}	1	$m_z r_x$	$it_x, m_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z, r_x^{-1} t_z^{-1}$
		[7, 26, 62, 111, 174, 252, 343, 448, 567, 700]				
		1498	H_{557}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z^{-1}$
		[7, 26, 62, 113, 177, 256, 349, 457, 581, 717]				
		1499	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z^{-1}$
		[7, 26, 62, 114, 176, 256, 352, 452, 576, 716]				
		1500	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_z r_x t_x^{-1}, m_y t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$
		[7, 26, 63, 116, 180, 260, 356, 466, 594, 735]				
		1501	H_{572}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$
		[7, 26, 64, 112, 175, 257, 345, 455, 578, 708]				
		1502	H_{422}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z^{-1}$
		[7, 26, 65, 112, 177, 255, 344, 455, 571, 705]				
		1503	H_{580}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z, r_x^{-1} t_z^{-1}$
		[7, 27, 64, 116, 180, 262, 356, 466, 592, 730]				
		1504	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, it_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z$
		[7, 27, 64, 119, 184, 263, 362, 471, 593, 736]				
		1505	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z, r_z^2 r_x t_z^{-1}$
		[7, 28, 60, 110, 170, 248, 336, 442, 558, 692]				
		1506	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z, r_z^2 r_x t_z^{-1}$
		[7, 28, 65, 115, 181, 261, 356, 466, 590, 730]				
		1507	H_{560}	1	$m_z r_x$	$it_x, m_x t_x^{-1}, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z^{-1}$
		[7, 28, 65, 116, 182, 263, 359, 469, 597, 736]				
		1508	H_{574}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z, r_x^{-1} t_z^{-1}$
		[7, 28, 65, 120, 181, 263, 355, 466, 587, 727]				
		1509	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, it_z, r_z^2 r_x t_z^{-1}$
		[7, 28, 66, 117, 185, 267, 365, 478, 606, 750]				
		1510	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
		[7, 28, 66, 118, 183, 263, 363, 474, 598, 744]				
		1511	H_{580}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z, r_x^{-1} t_z^{-1}$
		[7, 28, 66, 118, 184, 266, 360, 470, 596, 734]				
		1512	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_z r_x t_x^{-1}, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z, r_z^2 r_x t_z^{-1}$
		[7, 28, 66, 120, 183, 264, 361, 472, 595, 735]				
		1513	H_{556}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, it_z, r_z^2 r_x t_z^{-1}$
		[7, 28, 67, 115, 182, 259, 354, 462, 583, 722]				
		1514	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z^{-1}$
		[7, 28, 68, 117, 185, 266, 364, 477, 604, 749]				
		1515	H_{409}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
		[7, 30, 66, 119, 184, 267, 362, 475, 600, 743]				
		1516	H_{555}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z^{-1}$
		[7, 30, 66, 120, 187, 268, 368, 481, 608, 751]				
		1517	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$it_x, r_x^2 t_x^{-1}, m_y t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$
		[7, 30, 69, 120, 188, 269, 368, 480, 608, 751]				
		1518	H_{560}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z^{-1}$
		[7, 32, 68, 122, 189, 273, 370, 485, 613, 758]				
		1519	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$it_x, r_x^2 t_x^{-1}, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z, r_z^2 r_x t_z^{-1}$

27B

- [6, 19, 47, 95, 160, 240, 336, 448, 576, 720]
 1520*,
 [6, 20, 51, 107, 184, 274, 378, 498, 634, 786]
 1521*,
 [6, 21, 58, 119, 193, 281, 387, 508, 644, 796]
 1522*,
 [6, 21, 58, 120, 196, 284, 388, 508, 644, 796]
 1523*,
 [6, 21, 58, 124, 201, 288, 392, 512, 648, 800]
 1524*,
 [6, 22, 60, 120, 195, 285, 391, 512, 648, 800]
 1525*,
 [6, 22, 60, 126, 208, 296, 397, 516, 652, 804]
 1526*,
 [6, 22, 62, 128, 198, 283, 393, 517, 647, 795]
 1527*,
 [6, 22, 62, 129, 207, 293, 396, 516, 652, 804]
 1528*,
 [6, 22, 64, 130, 205, 292, 396, 516, 652, 804]

Nbr.	gr	N ₀	H_i	L	m	X
			1529*			
			[6, 23, 61, 125, 197, 284, 388, 508, 644, 796]			
			1531*			
			[6, 23, 62, 122, 196, 284, 388, 508, 644, 796]			
			1530*			
			[6, 23, 65, 125, 198, 288, 392, 512, 648, 800]			
			1532*			
			[6, 23, 65, 129, 200, 288, 392, 512, 648, 800]			
			1533*			
			[6, 23, 65, 131, 205, 292, 395, 515, 653, 805]			
			1534*			
			[6, 23, 65, 133, 204, 288, 392, 512, 648, 800]			
			1535*			
			[6, 23, 67, 135, 206, 291, 397, 517, 651, 803]			
			1536*			
			[6, 23, 69, 132, 200, 288, 392, 512, 648, 800]			
			1537*			
			[6, 24, 65, 130, 208, 294, 396, 516, 652, 804]			
			1538*			
			[6, 24, 65, 135, 208, 292, 396, 516, 652, 804]			
			1539*			
			[6, 24, 65, 139, 212, 292, 396, 516, 652, 804]			
			1540*			
			[6, 24, 67, 135, 207, 292, 396, 516, 652, 804]			
			1541*			
			[6, 24, 69, 133, 206, 292, 396, 516, 652, 804]			
			1542*			
			[6, 24, 71, 138, 207, 292, 396, 516, 652, 804]			
			1543*			
			[6, 25, 69, 130, 200, 288, 392, 512, 648, 800]			
			1544*			
			[6, 25, 69, 131, 200, 288, 392, 512, 648, 800]			
			1545*			
			[6, 25, 70, 129, 200, 288, 392, 512, 648, 800]			
			1546*			
			[6, 26, 70, 137, 207, 292, 396, 516, 652, 804]			
			1547*			
			[6, 26, 72, 136, 206, 292, 396, 516, 652, 804]			
			1548*, 1549*			
			[6, 27, 69, 129, 200, 288, 392, 512, 648, 800]			
			1550*			
			[6, 28, 71, 135, 206, 292, 396, 516, 652, 804]			
			1551*			
			[7, 23, 57, 110, 178, 262, 362, 478, 610, 758]			
			1520	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x \quad m_x t_x, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
			[7, 24, 61, 120, 194, 282, 386, 506, 642, 794]			
			1521	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x \quad m_x t_x, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z^{-1}$
			[7, 25, 67, 127, 198, 287, 392, 512, 648, 800]			
			1522	H_{578}	1	$m_z r_x \quad m_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z^{-1}$
			[7, 25, 67, 128, 200, 288, 392, 512, 648, 800]			
			1523	H_{580}	1	$m_z r_x \quad i t_x, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z^{-1}$
			[7, 25, 67, 133, 200, 292, 392, 516, 648, 804]			
			1524	H_{422}	1	$r_z^2 r_x \quad r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z$
			[7, 26, 68, 127, 201, 289, 393, 514, 651, 802]			
			1525	H_{571}	1	$m_z r_x \quad m_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
			[7, 26, 69, 133, 207, 293, 396, 516, 652, 804]			
			1526	H_{560}	1	$m_z r_x \quad i t_x, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z^{-1}$
			[7, 26, 71, 133, 196, 291, 395, 518, 644, 803]			
			1527	H_{571}	1	$m_z r_x \quad m_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1}, r_x^{-1} t_z$
			[7, 26, 71, 134, 205, 292, 396, 516, 652, 804]			
			1528	H_{557}	1	$m_z r_x \quad m_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z^{-1}$
			[7, 26, 73, 133, 204, 292, 396, 516, 652, 804]			
			1529	H_{409}	1	$r_z^2 r_x \quad r_z^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z$
			[7, 27, 69, 128, 200, 288, 392, 512, 648, 800]			
			1530	H_{580}	1	$m_z r_x \quad r_z^2 r_x t_x, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z^{-1}$
			[7, 27, 69, 132, 197, 291, 389, 515, 645, 803]			
			1531	H_{576}	1	$m_z r_x \quad m_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
			[7, 27, 73, 128, 202, 290, 394, 514, 650, 802]			
			1532	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x \quad r_y^2 r_x t_x, m_z r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
			[7, 27, 73, 132, 200, 292, 392, 516, 648, 804]			
			1533	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x \quad i t_x, r_x^2 t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
			[7, 27, 73, 134, 204, 292, 394, 517, 653, 804]			
			1534	H_{561}	1	$m_z r_x \quad m_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y, i t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z^{-1}$
			[7, 27, 73, 136, 200, 292, 392, 516, 648, 804]			
			1535	H_{572}	1	$m_z r_x \quad r_z^2 r_x t_x, i t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
			[7, 27, 76, 135, 202, 293, 397, 516, 650, 805]			
			1536	H_{561}	1	$m_z r_x \quad m_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y, m_z r_x^{-1} t_y, i t_y^{-1}, m_z r_x^{-1} t_z$
			[7, 27, 77, 131, 201, 291, 393, 515, 649, 803]			
			1537	H_{580}	1	$m_z r_x \quad i t_x, r_y^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z^{-1}$
			[7, 28, 72, 134, 206, 292, 396, 516, 652, 804]			
			1538	H_{560}	1	$m_z r_x \quad r_z^2 r_x t_x, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z^{-1}$
			[7, 28, 73, 138, 202, 294, 394, 518, 650, 806]			
			1539	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x \quad i t_x, r_x^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z^{-1}$
			[7, 28, 73, 142, 202, 294, 394, 518, 650, 806]			

Nbr.	gr	N ₀	H_i	L	m	X
		1540	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, it_y, it_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z^{-1}$
[7, 28, 75, 136, 203, 293, 395, 517, 651, 805]		1541	H_{556}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, it_y, it_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z^{-1}$
[7, 28, 77, 132, 206, 290, 398, 514, 654, 802]		1542	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, m_z r_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z^{-1}$
[7, 28, 79, 135, 204, 292, 396, 516, 652, 804]		1543	H_{560}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z^{-1}$
[7, 29, 75, 131, 201, 291, 393, 515, 649, 803]		1544	H_{580}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z^{-1}$
[7, 29, 75, 132, 200, 292, 392, 516, 648, 804]		1545	H_{574}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z^{-1}$
[7, 29, 76, 129, 203, 289, 395, 513, 651, 801]		1546	H_{422}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z$
[7, 30, 76, 137, 202, 294, 394, 518, 650, 806]		1547	H_{555}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z^{-1}$
[7, 30, 78, 134, 204, 292, 396, 516, 652, 804]		1548	H_{409}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z$
[7, 30, 78, 134, 204, 292, 396, 516, 652, 804]		1549	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z^{-1}$
[7, 31, 73, 132, 200, 292, 392, 516, 648, 804]		1550	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
[7, 32, 75, 136, 202, 294, 394, 518, 650, 806]		1551	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z^{-1}$

28A

[7, 23, 52, 96, 154, 224, 308, 406, 516, 640]		1552*				
[7, 23, 54, 107, 171, 244, 339, 443, 558, 697]		1553*				
[7, 24, 55, 104, 170, 246, 337, 443, 560, 695]		1554*				
[7, 24, 55, 107, 171, 243, 337, 444, 559, 697]		1556*				
[7, 24, 56, 104, 168, 247, 340, 448, 570, 705]		1555*				
[7, 25, 58, 105, 166, 241, 330, 433, 550, 681]		1557*				
[7, 25, 59, 106, 168, 245, 333, 439, 557, 687]		1558*				
[7, 25, 59, 108, 171, 249, 342, 449, 571, 708]		1559*				
[7, 25, 60, 110, 170, 245, 339, 442, 559, 697]		1560*, 1561*				
[7, 26, 60, 109, 170, 245, 339, 442, 559, 697]		1563*, 1564*				
[7, 26, 60, 109, 173, 252, 347, 457, 584, 726]		1562*				
[7, 26, 61, 110, 174, 253, 347, 456, 579, 717]		1565*				
[7, 26, 61, 111, 176, 256, 351, 460, 586, 726]		1566*				
[7, 26, 61, 113, 180, 257, 351, 462, 583, 721]		1567*				
[7, 26, 62, 113, 178, 257, 354, 467, 591, 732]		1568*				
[7, 26, 62, 114, 178, 256, 351, 462, 585, 722]		1569*				
[7, 27, 62, 110, 174, 251, 343, 450, 570, 706]		1571*				
[7, 27, 62, 112, 178, 257, 354, 467, 591, 732]		1570*				
[7, 27, 65, 115, 178, 258, 352, 460, 584, 722]		1572*, 1573*				
[7, 28, 62, 112, 175, 254, 346, 454, 575, 712]		1574*				
[7, 28, 63, 114, 179, 260, 355, 466, 591, 732]		1575*				
[7, 28, 64, 115, 183, 264, 361, 474, 601, 742]		1576*, 1577*				
[7, 28, 65, 114, 178, 258, 352, 460, 584, 722]		1578*, 1579*				
[7, 28, 66, 117, 183, 264, 361, 473, 600, 742]		1580*				
[7, 29, 66, 116, 183, 264, 361, 473, 600, 742]		1581*				
[7, 30, 67, 118, 185, 268, 365, 478, 606, 750]		1582*, 1583*				
[8, 26, 58, 106, 166, 238, 326, 426, 538, 666]		1552	H_{578}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z,$ $r_x^{-1} t_z^{-1}$
[8, 26, 61, 117, 176, 255, 353, 452, 575, 717]		1553	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, r_z^2 t_y^{-1}, r_x^{-1} t_z,$ $m_z t_z$
[8, 27, 60, 114, 179, 254, 351, 455, 574, 715]		1554	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_z t_z,$ $m_x r_x^{-1} t_z^{-1}$
[8, 27, 61, 111, 176, 255, 349, 459, 582, 719]						

Nbr.	gr	Nº	H_i	L	m	X
1555			H_{580}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, m_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z,$ $r_x^{-1} t_z^{-1}$
[8, 27, 61, 117, 176, 253, 353, 454, 574, 718]						
1556			H_{576}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z,$ $m_x r_x^{-1} t_z^{-1}$
[8, 28, 63, 112, 175, 252, 343, 448, 567, 700]						
1557			H_{557}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z^{-1}$
[8, 28, 64, 112, 177, 255, 344, 455, 571, 705]						
1558			H_{580}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z,$ $r_x^{-1} t_z^{-1}$
[8, 28, 65, 115, 180, 262, 356, 466, 592, 730]						
1559			H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, it_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z$
[8, 28, 65, 116, 176, 256, 352, 452, 576, 716]						
1560			H_{571}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_z t_z,$ $m_x r_x^{-1} t_z^{-1}$
1561			H_{578}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z,$ $r_x^{-1} t_z^{-1}$
[8, 29, 64, 115, 180, 260, 356, 466, 594, 735]						
1562			H_{572}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z,$ $m_x r_x^{-1} t_z^{-1}$
[8, 29, 64, 116, 176, 256, 352, 452, 576, 716]						
1563			H_{576}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z,$ $m_x r_x^{-1} t_z^{-1}$
1564			H_{571}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, r_z^2 t_y^{-1}, r_x^{-1} t_z,$ $m_z t_z$
[8, 29, 65, 115, 181, 261, 356, 466, 590, 730]						
1565			H_{560}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z^{-1}$
[8, 29, 65, 116, 182, 263, 359, 469, 597, 736]						
1566			H_{574}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z,$ $r_x^{-1} t_z^{-1}$
[8, 29, 65, 120, 185, 263, 362, 471, 593, 736]						
1567			H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z,$ $r_z^2 r_x t_z^{-1}$
[8, 29, 66, 118, 183, 263, 363, 474, 598, 744]						
1568			H_{580}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z,$ $r_x^{-1} t_z^{-1}$
[8, 29, 67, 119, 183, 264, 361, 472, 595, 735]						
1569			H_{556}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, it_z,$ $r_z^2 r_x t_z^{-1}$
[8, 30, 65, 118, 183, 263, 363, 474, 598, 744]						
1570			H_{580}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z,$ $r_x^{-1} t_z^{-1}$
[8, 30, 66, 115, 182, 259, 354, 462, 583, 722]						
1571			H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z^{-1}$
[8, 30, 69, 118, 184, 266, 360, 470, 596, 734]						
1572			H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z,$ $r_z^2 r_x t_z^{-1}$
1573			H_{557}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z^{-1}$
[8, 31, 65, 118, 181, 263, 355, 466, 587, 727]						
1574			H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, it_z,$ $r_z^2 r_x t_z^{-1}$
[8, 31, 66, 119, 184, 267, 362, 475, 600, 743]						
1575			H_{555}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z^{-1}$
[8, 31, 66, 120, 187, 268, 368, 481, 608, 751]						
1576			H_{572}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z,$ $m_x r_x^{-1} t_z^{-1}$
1577			H_{574}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z,$ $r_x^{-1} t_z^{-1}$
[8, 31, 68, 118, 184, 266, 360, 470, 596, 734]						
1578			H_{556}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, it_z,$ $r_z^2 r_x t_z^{-1}$
1579			H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, it_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z$
[8, 31, 69, 120, 188, 269, 368, 480, 608, 751]						
1580			H_{560}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z^{-1}$
[8, 32, 68, 120, 188, 269, 368, 480, 608, 751]						
1581			H_{560}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z^{-1}$

Nbr.	gr	N ₀	H _i	L	m	X
28B	[8, 33, 68, 122, 189, 273, 370, 485, 613, 758]					
	1582	H ₅₅₁	1	m _z r _x	it _x , it _x ⁻¹ , r _z ² r _x t _x ⁻¹ , it _y ⁻¹ , r _z ² r _x t _y ⁻¹ , it _z , r _z ² r _x t _z ⁻¹	
	1583	H ₅₅₅	1	m _z r _x	it _x , it _x ⁻¹ , r _z ² r _x t _x ⁻¹ , r _x ^{2 t_y⁻¹, m_z r_x⁻¹ t_y⁻¹, r_x^{2 t_z, m_z r_x⁻¹ t_z⁻¹}}	
[7, 24, 61, 121, 196, 284, 388, 508, 644, 796]						
1584*,						
[7, 24, 64, 128, 197, 283, 393, 517, 647, 795]						
1585*,						
[7, 25, 63, 122, 196, 284, 388, 508, 644, 796]						
1586*,						
[7, 25, 63, 122, 198, 288, 392, 512, 648, 800]						
1587*,						
[7, 25, 63, 125, 196, 284, 388, 508, 644, 796]						
1588*,						
[7, 25, 65, 131, 209, 294, 396, 516, 652, 804]						
1589*,						
[7, 25, 69, 135, 205, 291, 397, 517, 651, 803]						
1590*,						
[7, 26, 66, 130, 208, 294, 396, 516, 652, 804]						
1591*,						
[7, 26, 68, 133, 207, 293, 395, 515, 653, 805]						
1592*,						
[7, 26, 69, 135, 206, 292, 396, 516, 652, 804]						
1596*,						
[7, 26, 70, 130, 200, 288, 392, 512, 648, 800]						
1593*, 1594*,						
[7, 26, 70, 131, 200, 288, 392, 512, 648, 800]						
1595*,						
[7, 27, 69, 131, 201, 288, 392, 512, 648, 800]						
1597*,						
[7, 27, 70, 129, 200, 288, 392, 512, 648, 800]						
1598*, 1599*,						
[7, 27, 70, 130, 200, 288, 392, 512, 648, 800]						
1600*,						
[7, 27, 70, 131, 200, 288, 392, 512, 648, 800]						
1601*,						
[7, 27, 72, 137, 207, 292, 396, 516, 652, 804]						
1602*,						
[7, 27, 74, 136, 206, 292, 396, 516, 652, 804]						
1603*, 1604*,						
[7, 28, 70, 129, 200, 288, 392, 512, 648, 800]						
1605*,						
[7, 28, 70, 137, 208, 292, 396, 516, 652, 804]						
1606*,						
[7, 28, 71, 137, 207, 292, 396, 516, 652, 804]						
1607*,						
[7, 28, 73, 136, 206, 292, 396, 516, 652, 804]						
1608*,						
[7, 28, 74, 135, 206, 292, 396, 516, 652, 804]						
1609*, 1610*,						
[7, 29, 70, 129, 200, 288, 392, 512, 648, 800]						
1611*, 1612*,						
[7, 29, 73, 135, 206, 292, 396, 516, 652, 804]						
1613*,						
[7, 30, 72, 135, 206, 292, 396, 516, 652, 804]						
1614*, 1615*,						
[8, 27, 68, 128, 200, 288, 392, 512, 648, 800]						
<hr/>						
	1584	H ₅₇₈	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , r _x t _y ⁻¹ , r _x ⁻¹ t _z ⁻¹	
<hr/>						
	[8, 27, 72, 132, 196, 291, 395, 518, 644, 803]					
	1585	H ₅₇₁	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , m _y t _y , r _x t _y , r _z ² t _y ⁻¹ , r _x ⁻¹ t _z	
<hr/>						
	[8, 28, 69, 128, 200, 288, 392, 512, 648, 800]					
	1586	H ₅₈₀	1	m _z r _x	it _x , r _z ² r _x t _x , m _x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , r _x t _y ⁻¹ , r _x ⁻¹ t _z ⁻¹	
<hr/>						
	[8, 28, 69, 128, 203, 290, 393, 514, 651, 802]					
	1587	H ₅₇₁	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , m _y t _y , r _z ² t _y ⁻¹ , m _x r _x t _y ⁻¹ , m _x r _x ⁻¹ t _z ⁻¹	
<hr/>						
	[8, 28, 70, 131, 197, 291, 389, 515, 645, 803]					
	1588	H ₅₇₆	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , r _z ² t _y , r _z ² t _y ⁻¹ , m _x r _x t _y ⁻¹ , m _x r _x ⁻¹ t _z ⁻¹	
<hr/>						
	[8, 28, 72, 135, 206, 292, 396, 516, 652, 804]					
	1589	H ₅₅₇	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , r _x ² t _y , r _x ² t _y ⁻¹ , m _z r _x ⁻¹ t _y ⁻¹ , m _z r _x ⁻¹ t _z ⁻¹	
<hr/>						
	[8, 28, 77, 134, 202, 293, 397, 516, 650, 805]					
	1590	H ₅₆₁	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , r _x ² t _y , m _z r _x ⁻¹ t _y , it _y ⁻¹ , m _z r _x ⁻¹ t _z	
<hr/>						
	[8, 29, 72, 134, 206, 292, 396, 516, 652, 804]					
	1591	H ₅₆₀	1	m _z r _x	it _x , r _z ² r _x t _x , m _x t _x ⁻¹ , r _x ² t _y , r _x ² t _y ⁻¹ , m _z r _x ⁻¹ t _y ⁻¹ , m _z r _x ⁻¹ t _z ⁻¹	
<hr/>						
	[8, 29, 74, 135, 205, 292, 394, 517, 653, 804]					
	1592	H ₅₆₁	1	m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , r _x ² t _y , it _y ⁻¹ , r _z ² r _x t _y ⁻¹ , r _z ² r _x t _z ⁻¹	

Nbr.	gr	N ₀	H_i	L	m	X
[8, 29, 76, 130, 202, 290, 394, 514, 650, 802]		1593	H_{571}	1	$m_z r_x$	$r_y^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z^{-1}$
		1594	H_{578}	1	$m_z r_x$	$r_y^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}$
[8, 29, 76, 131, 201, 291, 393, 515, 649, 803]		1595	H_{580}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}$
		1596	H_{556}	1	$m_z r_x$	$m_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y, it_y^{-1}, r_z^2 r_x t_y^{-1},$ $r_z^2 r_x t_z^{-1}$
[8, 30, 74, 133, 200, 292, 392, 516, 648, 804]		1597	H_{572}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z^{-1}$
		1598	H_{576}	1	$m_z r_x$	$r_y^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z^{-1}$
[8, 30, 75, 130, 202, 290, 394, 514, 650, 802]		1599	H_{571}	1	$m_z r_x$	$r_y^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1},$ $r_x^{-1} t_z$
		1600	H_{580}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}$
[8, 30, 75, 132, 200, 292, 392, 516, 648, 804]		1601	H_{574}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}$
		1602	H_{560}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1},$ $m_z r_x^{-1} t_z^{-1}$
[8, 30, 80, 132, 206, 290, 398, 514, 654, 802]		1603	H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, it_y^{-1}, r_z^2 r_x t_y^{-1},$ $r_z^2 r_x t_z^{-1}$
		1604	H_{557}	1	$m_z r_x$	$r_y^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1},$ $m_z r_x^{-1} t_z^{-1}$
[8, 31, 74, 131, 201, 291, 393, 515, 649, 803]		1605	H_{580}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}$
		1606	H_{551}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, it_y, it_y^{-1}, r_z^2 r_x t_y^{-1},$ $r_z^2 r_x t_z^{-1}$
[8, 31, 76, 137, 202, 294, 394, 518, 650, 806]		1607	H_{555}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1},$ $m_z r_x^{-1} t_z^{-1}$
		1608	H_{560}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1},$ $m_z r_x^{-1} t_z^{-1}$
[8, 31, 79, 132, 206, 290, 398, 514, 654, 802]		1609	H_{556}	1	$m_z r_x$	$r_y^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y, it_y^{-1}, r_z^2 r_x t_y^{-1},$ $r_z^2 r_x t_z^{-1}$
		1610	H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, m_z r_x^{-1} t_y, it_y^{-1},$ $m_z r_x^{-1} t_z$
[8, 32, 73, 132, 200, 292, 392, 516, 648, 804]		1611	H_{572}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z^{-1}$
		1612	H_{574}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}$
[8, 32, 77, 134, 204, 292, 396, 516, 652, 804]		1613	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1},$ $m_z r_x^{-1} t_z^{-1}$
		1614	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, it_y, it_y^{-1}, r_z^2 r_x t_y^{-1},$ $r_z^2 r_x t_z^{-1}$
[8, 33, 75, 136, 202, 294, 394, 518, 650, 806]		1615	H_{555}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1},$ $m_z r_x^{-1} t_z^{-1}$

29A

- [7, 22, 48, 86, 134, 192, 262, 342, 432, 534]
1616*,
[7, 22, 50, 98, 161, 235, 328, 432, 548, 686]
1617*,
[7, 23, 52, 98, 160, 235, 327, 432, 549, 685]
1619*,
[7, 23, 52, 100, 163, 238, 332, 437, 553, 691]
1618*,
[7, 23, 57, 106, 167, 246, 336, 441, 563, 694]
1620*,
[7, 24, 54, 96, 150, 216, 294, 384, 486, 600]
1622*,
[7, 24, 55, 99, 156, 227, 311, 408, 519, 643]

Nbr.	gr	$\aleph$	H_i	L	m	X
			1621*, [7, 24, 57, 107, 169, 245, 339, 442, 559, 697]			
			1623*, 1624*, [7, 25, 58, 107, 171, 250, 345, 455, 582, 724]			
			1625*, [7, 25, 58, 108, 174, 252, 346, 456, 578, 716]			
			1629*, [7, 25, 59, 109, 170, 245, 339, 442, 559, 697]			
			1626*, 1627*, [7, 25, 59, 109, 173, 251, 345, 455, 579, 717]			
			1628*, [7, 25, 60, 109, 173, 252, 345, 453, 576, 713]			
			1631*, [7, 25, 60, 111, 176, 256, 351, 460, 586, 726]			
			1630*, [7, 25, 62, 114, 179, 260, 357, 470, 597, 740]			
			1632*, [7, 26, 62, 113, 178, 258, 352, 460, 584, 722]			
			1634*, 1635*, [7, 26, 62, 113, 178, 258, 354, 465, 589, 729]			
			1633*, [7, 27, 60, 109, 171, 249, 340, 447, 567, 703]			
			1636*, [7, 27, 62, 114, 179, 260, 355, 466, 591, 732]			
			1637*, [7, 27, 63, 112, 179, 260, 354, 466, 592, 734]			
			1640*, [7, 27, 63, 115, 183, 264, 361, 474, 601, 742]			
			1638*, 1639*, [7, 27, 64, 114, 178, 258, 352, 460, 584, 722]			
			1641*, 1642*, [7, 28, 65, 117, 186, 269, 368, 483, 613, 758]			
			1643*, [7, 29, 66, 118, 185, 268, 365, 478, 606, 750]			
			1644*, 1645*, [8, 25, 56, 101, 155, 224, 307, 397, 504, 625]			
		1616	H_{412}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z,$ $m_z t_z^{-1}$
		1617	H_{407}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z,$ $r_y^2 t_z^{-1}$
		1618	H_{412}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x r_x^{-1} t_y, r_z^2 t_y^{-1}, m_x r_x t_z^{-1},$ $m_z t_z^{-1}$
		1619	H_{402}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_z t_z^{-1}$
		1620	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z,$ $m_z t_z^{-1}$
		1621	H_{388}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z,$ $i t_z^{-1}$
		1622	H_{394}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z,$ $r_z^2 t_z^{-1}$
		1623	H_{413}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z,$ $m_z t_z^{-1}$
		1624	H_{419}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_z t_z^{-1}$
		1625	H_{414}	1	$r_z^2 r_x$	$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z,$ $r_y^2 t_z^{-1}$
		1626	H_{413}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_x r_x^{-1} t_y, r_z^2 t_y^{-1}, m_x r_x t_z^{-1},$ $m_z t_z^{-1}$
		1627	H_{418}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z,$ $r_y^2 t_z^{-1}$
		1628	H_{394}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y, i t_y^{-1}, r_y^2 r_x t_z^{-1},$ $r_z^2 t_z^{-1}$
		1629	H_{391}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_z^2 t_z^{-1}$
		1630	H_{415}	1	$r_z^2 r_x$	$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_z t_z^{-1}$
		1631	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_x r_y t_x^{-1}, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_y^2 r_z t_z,$ $r_z^2 r_y t_z^{-1}$
		1632	H_{415}	1	$r_z^2 r_x$	$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_z t_z^{-1}$
		1633	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_x r_y t_x^{-1}, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_y^2 r_z t_z,$ $r_z^2 r_y t_z^{-1}$
		1634	H_{415}	1	$r_z^2 r_x$	$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_z t_z^{-1}$
		1635	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_x r_y t_x^{-1}, r_y^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
		1632	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z$
[8, 29, 66, 118, 183, 265, 362, 473, 598, 741]						
		1633	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_z t_z^{-1}$
[8, 29, 67, 118, 184, 266, 360, 470, 596, 734]						
		1634	H_{395}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z,$ $r_x^2 t_z^{-1}$
		1635	H_{401}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z^{-1}$
[8, 30, 64, 116, 179, 260, 352, 462, 583, 722]						
		1636	H_{389}	1	$r_z^2 r_x$	$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z,$ $i t_z^{-1}$
[8, 30, 66, 119, 184, 267, 362, 475, 600, 743]						
		1637	H_{396}	1	$r_z^2 r_x$	$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z^{-1}$
[8, 30, 66, 120, 187, 268, 368, 481, 608, 751]						
		1638	H_{410}	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z,$ $r_y^2 t_z^{-1}$
		1639	H_{404}	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_z t_z^{-1}$
[8, 30, 67, 119, 187, 269, 367, 479, 609, 752]						
		1640	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_y r_x t_x, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_y^2 r_z t_z,$ $r_y^{-1} r_z^{-1} t_z^{-1}$
[8, 30, 68, 118, 184, 266, 360, 470, 596, 734]						
		1641	H_{400}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z,$ $i t_z^{-1}$
		1642	H_{395}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_y^2 r_x t_y, i t_y^{-1}, r_y^2 r_x t_z^{-1},$ $r_x^2 t_z^{-1}$
[8, 31, 68, 121, 190, 272, 373, 488, 618, 764]						
		1643	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z^{-1}$
[8, 32, 68, 122, 189, 273, 370, 485, 613, 758]						
		1644	H_{398}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, i t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z,$ $i t_z^{-1}$
		1645	H_{392}	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z^{-1}$

29B

- [7, 23, 57, 110, 182, 273, 376, 493, 630, 785]
1646*
[7, 23, 60, 119, 192, 282, 385, 505, 641, 793]
1647*
[7, 24, 60, 114, 184, 272, 376, 496, 632, 784]
1649*
[7, 24, 60, 116, 190, 281, 384, 503, 639, 792]
1648*
[7, 24, 61, 121, 196, 284, 387, 507, 644, 796]
1650*
[7, 24, 65, 126, 197, 283, 387, 507, 643, 795]
1651*
[7, 25, 65, 127, 198, 284, 388, 508, 644, 796]
1653*
[7, 25, 66, 127, 197, 283, 388, 508, 643, 795]
1652*
[7, 25, 67, 127, 199, 288, 392, 512, 648, 800]
1654*, 1655*
[7, 26, 67, 129, 200, 288, 392, 512, 648, 800]
1656*
[7, 26, 69, 129, 200, 288, 392, 512, 648, 800]
1657*, 1658*
[7, 26, 69, 131, 200, 288, 392, 512, 648, 800]
1659*
[7, 26, 70, 129, 200, 288, 392, 512, 648, 800]
1660*
[7, 26, 71, 134, 206, 292, 396, 516, 652, 804]
1661*, 1662*
[7, 27, 69, 135, 206, 292, 396, 516, 652, 804]
1664*
[7, 27, 70, 128, 200, 288, 392, 512, 648, 800]
1663*
[7, 27, 71, 137, 206, 292, 396, 516, 652, 804]
1665*
[7, 27, 72, 136, 206, 292, 396, 516, 652, 804]
1666*
[7, 27, 73, 135, 206, 292, 396, 516, 652, 804]
1667*, 1668*
[7, 28, 69, 129, 200, 288, 392, 512, 648, 800]
1669*, 1670*
[7, 28, 72, 135, 206, 292, 396, 516, 652, 804]
1671*
[7, 29, 71, 135, 206, 292, 396, 516, 652, 804]
1672*, 1673*
[7, 29, 71, 135, 210, 291, 395, 518, 651, 803]

Nbr.	gr	N _i	H _i	L	m	X
			1674*, [7, 29, 75, 135, 206, 291, 395, 518, 651, 803]			
			1675*, [8, 26, 66, 120, 193, 282, 385, 504, 641, 794]			
		1646	H ₄₁₂	1	r _z ² r _x	t _x , r _z ² r _x t _x ⁻¹ , t _x ⁻¹ , m _y t _y , r _z ² t _y ⁻¹ , r _x ⁻¹ t _y ⁻¹ , r _x t _z
			[8, 26, 68, 126, 197, 288, 388, 512, 644, 800]			
		1647	H ₄₀₇	1	r _z ² r _x	t _x , r _z ² r _x t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y , r _z ² t _y ⁻¹ , r _x ⁻¹ t _y ⁻¹ , r _x t _z
			[8, 27, 67, 124, 198, 287, 388, 510, 645, 799]			
		1648	H ₄₁₂	1	r _z ² r _x	t _x , r _z ² r _x t _x ⁻¹ , t _x ⁻¹ , m _x r _x ⁻¹ t _y , m _y t _y , r _z ² t _y ⁻¹ , m _x r _x t _z ⁻¹
			[8, 27, 68, 122, 194, 282, 386, 506, 642, 794]			
		1649	H ₄₀₂	1	r _z ² r _x	t _x , r _z ² r _x t _x ⁻¹ , t _x ⁻¹ , m _y t _y , m _x r _x ⁻¹ t _y ⁻¹ , m _y t _y ⁻¹ , m _x r _x t _z
			[8, 27, 70, 127, 200, 287, 392, 511, 648, 799]			
		1650	H ₃₉₄	1	r _z ² r _x	t _x , r _z ² r _x t _x ⁻¹ , t _x ⁻¹ , r _x ² t _y , i t _y ⁻¹ , m _z r _x t _y ⁻¹ , m _z r _x t _z
			[8, 27, 73, 128, 200, 286, 392, 510, 648, 798]			
		1651	H ₃₈₈	1	r _z ² r _x	t _x , r _z ² r _x t _x ⁻¹ , t _x ⁻¹ , i t _y , i t _y ⁻¹ , m _z r _x t _y ⁻¹ , m _z r _x t _z
			[8, 28, 73, 129, 200, 287, 392, 511, 648, 799]			
		1652	H ₃₉₄	1	r _z ² r _x	t _x , r _z ² r _x t _x ⁻¹ , t _x ⁻¹ , r _y ² r _x t _y , r _x ² t _y , i t _y ⁻¹ , r _y ² r _x t _z ⁻¹
			[8, 28, 73, 130, 200, 288, 392, 512, 648, 800]			
		1653	H ₃₉₁	1	r _z ² r _x	t _x , r _z ² r _x t _x ⁻¹ , t _x ⁻¹ , r _x ² t _y , r _y ² r _x t _y ⁻¹ , r _x ² t _y ⁻¹ , r _y ² r _x t _z
			[8, 28, 74, 129, 202, 290, 394, 514, 650, 802]			
		1654	H ₄₁₃	1	r _z ² r _x	m _z r _x ⁻¹ t _x , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _x ⁻¹ , m _y t _y , r _z ² t _y ⁻¹ , r _x ⁻¹ t _y ⁻¹ , r _x t _z
			[8, 28, 74, 129, 202, 290, 394, 514, 650, 802]			
		1655	H ₄₁₉	1	r _z ² r _x	m _z r _x ⁻¹ t _x , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _x ⁻¹ , m _y t _y , m _x r _x ⁻¹ t _y ⁻¹ , m _y t _y ⁻¹ , m _x r _x t _z
			[8, 29, 73, 132, 200, 292, 392, 516, 648, 804]			
		1656	H ₄₁₀	1	r _z ² r _x	r _z ² t _x , r _y ² r _x t _x ⁻¹ , r _x ² t _x ⁻¹ , r _z ² t _y , r _z ² t _y ⁻¹ , r _x ⁻¹ t _y ⁻¹ , r _x t _z
			[8, 29, 75, 130, 202, 290, 394, 514, 650, 802]			
		1657	H ₄₁₃	1	r _z ² r _x	m _z r _x ⁻¹ t _x , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _x ⁻¹ , m _x r _x ⁻¹ t _y , m _y t _y , r _z ² t _y ⁻¹ , m _x r _x t _z ⁻¹
			[8, 29, 75, 132, 200, 292, 392, 516, 648, 804]			
		1658	H ₄₁₈	1	r _z ² r _x	m _z r _x ⁻¹ t _x , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _x ⁻¹ , r _z ² t _y , r _z ² t _y ⁻¹ , r _x ⁻¹ t _y ⁻¹ , r _x t _z
			[8, 29, 75, 132, 200, 292, 392, 516, 648, 804]			
		1659	H ₄₀₄	1	r _z ² r _x	r _z ² t _x , r _y ² r _x t _x ⁻¹ , r _x ² t _x ⁻¹ , m _y t _y , m _x r _x ⁻¹ t _y ⁻¹ , m _y t _y ⁻¹ , m _x r _x t _z
			[8, 29, 76, 129, 203, 289, 395, 513, 651, 801]			
		1660	H ₄₂₂	1	r _z ² r _x	r _z ² t _x , r _x ⁻¹ t _x , r _x t _x ⁻¹ , m _y t _y , m _x r _x ⁻¹ t _y ⁻¹ , m _y t _y ⁻¹ , m _x r _x t _z
			[8, 29, 78, 132, 206, 290, 398, 514, 654, 802]			
		1661	H ₃₉₅	1	r _z ² r _x	m _z r _x ⁻¹ t _x , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _x ⁻¹ , r _x ² t _y , i t _y ⁻¹ , m _z r _x t _y ⁻¹ , m _z r _x t _z
			[8, 29, 78, 132, 206, 290, 398, 514, 654, 802]			
		1662	H ₄₀₁	1	r _z ² r _x	m _z r _x ⁻¹ t _x , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _x ⁻¹ , r _x ² t _y , r _y ² r _x t _y ⁻¹ , r _x ² t _y ⁻¹ , r _y ² r _x t _z
			[8, 30, 75, 129, 203, 289, 395, 513, 651, 801]			
		1663	H ₄₂₂	1	r _z ² r _x	r _z ² t _x , r _x ⁻¹ t _x , r _x t _x ⁻¹ , m _x r _x ⁻¹ t _y ⁻¹ , m _x r _x t _z , m _z t _z , m _z t _z ⁻¹
			[8, 30, 75, 136, 202, 294, 394, 518, 650, 806]			
		1664	H ₃₉₈	1	r _z ² r _x	r _z ² t _x , r _y ² r _x t _x ⁻¹ , r _x ² t _x ⁻¹ , i t _y , i t _y ⁻¹ , m _z r _x t _y ⁻¹ , m _z r _x t _z
			[8, 30, 77, 136, 202, 294, 394, 518, 650, 806]			
		1665	H ₃₉₂	1	r _z ² r _x	r _z ² t _x , r _y ² r _x t _x ⁻¹ , r _x ² t _x ⁻¹ , r _x ² t _y , r _y ² r _x t _y ⁻¹ , r _x ² t _y ⁻¹ , r _y ² r _x t _z
			[8, 30, 78, 134, 204, 292, 396, 516, 652, 804]			
		1666	H ₄₀₉	1	r _z ² r _x	r _z ² t _x , r _x ⁻¹ t _x , r _x t _x ⁻¹ , r _x ² t _y , r _y ² r _x t _y ⁻¹ , r _x ² t _y ⁻¹ , r _y ² r _x t _z
			[8, 30, 79, 132, 206, 290, 398, 514, 654, 802]			
		1667	H ₄₀₀	1	r _z ² r _x	m _z r _x ⁻¹ t _x , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _x ⁻¹ , i t _y , i t _y ⁻¹ , m _z r _x t _y ⁻¹ , m _z r _x t _z
			[8, 30, 79, 132, 206, 290, 398, 514, 654, 802]			
		1668	H ₃₉₅	1	r _z ² r _x	m _z r _x ⁻¹ t _x , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _x ⁻¹ , r _y ² r _x t _y , r _x ² t _y , i t _y ⁻¹ , r _y ² r _x t _z ⁻¹
			[8, 31, 73, 132, 200, 292, 392, 516, 648, 804]			
		1669	H ₄₁₄	1	r _z ² r _x	m _z r _x t _x , i t _x ⁻¹ , m _z r _x t _x ⁻¹ , r _z ² t _y , r _z ² t _y ⁻¹ , r _x ⁻¹ t _y ⁻¹ , r _x t _z
			[8, 31, 73, 132, 200, 292, 392, 516, 648, 804]			
		1670	H ₄₁₅	1	r _z ² r _x	m _z r _x t _x , i t _x ⁻¹ , m _z r _x t _x ⁻¹ , m _y t _y , m _x r _x ⁻¹ t _y ⁻¹ , m _y t _y ⁻¹ , m _x r _x t _z
			[8, 31, 77, 134, 204, 292, 396, 516, 652, 804]			
		1671	H ₄₀₉	1	r _z ² r _x	r _z ² t _x , r _x ⁻¹ t _x , r _x t _x ⁻¹ , r _y ² r _x t _y ⁻¹ , r _y ² r _x t _z , r _x ² t _z , r _x ² t _z ⁻¹
			[8, 32, 75, 136, 202, 294, 394, 518, 650, 806]			

Nbr.	gr	$\aleph$	H_i	L	m	X
		1672	H_{389}	1	$r_z^2 r_x$	$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, it_y, it_y^{-1}, m_z r_x t_y^{-1},$ $m_z r_x t_z$
		1673	H_{396}	1	$r_z^2 r_x$	$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, r_y^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z$
[8, 32, 75, 137, 204, 291, 397, 516, 651, 805]						
		1674	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_y r_x t_x, r_x^2 r_y t_x^{-1}, r_y^2 r_z t_y, r_y^2 r_z t_z, r_x^2 r_y t_z^{-1},$ $r_y^{-1} r_z^{-1} t_z^{-1}$
[8, 32, 79, 133, 204, 291, 397, 516, 651, 805]						
		1675	H_{393}	1	$r_z^2 r_x$	$r_y r_x t_x, r_x^2 r_y t_x^{-1}, r_y^{-1} r_z^{-1} t_x^{-1}, r_y r_x t_y, r_y^2 r_z t_z, r_x^2 r_y t_z^{-1},$ $r_y^{-1} r_z^{-1} t_z^{-1}$

30A

[8, 26, 59, 109, 170, 245, 339, 442, 559, 697]	1676*				
[8, 27, 61, 112, 178, 257, 354, 467, 591, 732]	1677*				
[8, 27, 62, 113, 178, 258, 354, 465, 589, 729]	1678*				
[8, 28, 63, 115, 183, 264, 361, 474, 601, 742]	1679*				
[8, 28, 64, 114, 178, 258, 352, 460, 584, 722]	1680*				
[8, 29, 65, 116, 183, 264, 361, 473, 600, 742]	1681*				
[8, 29, 65, 117, 186, 269, 368, 483, 613, 758]	1682*				
[8, 30, 66, 118, 185, 268, 365, 478, 606, 750]	1683*				
[9, 28, 64, 116, 176, 256, 352, 452, 576, 716]					
1676	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$\frac{r_y^2}{r_y^2 t_z, m_x r_x^{-1} t_z^{-1}} r_x^2 t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y^{-1}, m_x r_x t_y^{-1},$	
[9, 29, 65, 118, 183, 263, 363, 474, 598, 744]					
1677	H_{580}	1	$m_z r_x$	$\frac{it_x, r_z^2 r_x t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y^{-1}, r_x t_y^{-1},}{m_z t_z, r_x^{-1} t_z^{-1}}$	
[9, 29, 66, 118, 183, 265, 362, 473, 598, 741]					
1678	H_{422}	1	$r_z^2 r_x$	$\frac{r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},}{m_x r_x t_z, m_z t_z^{-1}}$	
[9, 30, 66, 120, 187, 268, 368, 481, 608, 751]					
1679	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$\frac{it_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y^{-1}, m_x r_x t_y^{-1},}{r_y^2 t_z, m_x r_x^{-1} t_z^{-1}}$	
[9, 30, 68, 118, 184, 266, 360, 470, 596, 734]					
1680	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$\frac{r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1},}{r_x^2 t_z, r_z^2 r_x t_z^{-1}}$	
[9, 31, 68, 120, 188, 269, 368, 480, 608, 751]					
1681	H_{560}	1	$m_z r_x$	$\frac{it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1},}{r_z^2 t_z, m_z r_x^{-1} t_z^{-1}}$	
[9, 31, 68, 121, 190, 272, 373, 488, 618, 764]					
1682	H_{409}	1	$r_z^2 r_x$	$\frac{r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},}{r_y^2 t_z, r_z^2 r_x t_z^{-1}}$	
[9, 32, 68, 122, 189, 273, 370, 485, 613, 758]					
1683	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$\frac{it_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1},}{r_y^2 t_z, r_z^2 r_x t_z^{-1}}$	

30B

[8, 27, 69, 129, 200, 288, 392, 512, 648, 800] 1684*					
[8, 28, 69, 129, 200, 288, 392, 512, 648, 800] 1685*					
[8, 28, 70, 128, 200, 288, 392, 512, 648, 800] 1686*					
[8, 28, 73, 135, 206, 292, 396, 516, 652, 804] 1687*					
[8, 29, 69, 129, 200, 288, 392, 512, 648, 800] 1688*					
[8, 29, 72, 135, 206, 292, 396, 516, 652, 804] 1689*, 1690*					
[8, 30, 71, 135, 206, 292, 396, 516, 652, 804] 1691*					
[9, 29, 75, 130, 202, 290, 394, 514, 650, 802]	1684	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1},$ $m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
[9, 30, 74, 131, 201, 291, 393, 515, 649, 803]	1685	H_{580}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1},$ $r_x t_y^{-1}, r_x^{-1} t_z^{-1}$
[9, 30, 75, 129, 203, 289, 395, 513, 651, 801]	1686	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1},$ $m_y t_y^{-1}, m_x r_x t_z$
[9, 30, 79, 132, 206, 290, 398, 514, 654, 802]	1687	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1},$ $r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z^{-1}$
[9, 31, 73, 132, 200, 292, 392, 516, 648, 804]					

Nbr.	gr	N _t	H _i	L	m	X
		1688	H ₆₅₂	$\langle m_x \rangle$	$r_y^2 r_x$	$it_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}$
[9, 31, 77, 134, 204, 292, 396, 516, 652, 804]						
		1689	H ₄₀₉	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, r_z^2 t_y, r_y^2 r_x t_y^{-1}, r_z^2 t_y^{-1}, r_z^2 r_x t_z$
		1690	H ₅₆₀	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z^{-1}$
[9, 32, 75, 136, 202, 294, 394, 518, 650, 806]						
		1691	H ₆₄₉	$\langle m_x \rangle$	$r_y^2 r_x$	$it_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z^{-1}$
31						
[7, 22, 50, 96, 160, 240, 336, 448, 576, 720]						
1692*,						
[7, 23, 58, 117, 192, 281, 387, 508, 644, 796]						
1693*,						
[7, 23, 59, 119, 195, 285, 391, 512, 648, 800]						
1694*,						
[7, 24, 60, 124, 197, 284, 388, 508, 644, 796]						
1695*,						
[7, 24, 61, 126, 198, 283, 393, 517, 647, 795]						
1696*,						
[7, 24, 64, 124, 198, 288, 392, 512, 648, 800]						
1697*,						
[7, 25, 60, 114, 186, 274, 378, 498, 634, 786]						
1698*,						
[7, 25, 62, 120, 195, 284, 388, 508, 644, 796]						
1699*, 1700*,						
[7, 25, 63, 124, 199, 288, 392, 512, 648, 800]						
1701*,						
[7, 26, 66, 127, 202, 291, 396, 516, 652, 804]						
1702*,						
[7, 26, 66, 128, 203, 292, 395, 515, 653, 805]						
1703*,						
[7, 26, 68, 129, 200, 288, 392, 512, 648, 800]						
1704*, 1705*,						
[7, 26, 69, 128, 200, 288, 392, 512, 648, 800]						
1706*,						
[7, 27, 68, 131, 204, 291, 397, 517, 651, 803]						
1707*,						
[7, 27, 68, 132, 205, 292, 396, 516, 652, 804]						
1708*,						
[7, 27, 70, 130, 204, 292, 396, 516, 652, 804]						
1709*,						
[7, 28, 68, 128, 200, 288, 392, 512, 648, 800]						
1710*, 1711*, 1712*, 1713*,						
[7, 28, 69, 128, 203, 292, 396, 516, 652, 804]						
1714*, 1715*, 1716*, 1717*,						
[7, 29, 73, 133, 204, 292, 396, 516, 652, 804]						
1718*, 1719*, 1720*, 1721*,						
[7, 31, 72, 132, 204, 292, 396, 516, 652, 804]						
1722*, 1723*, 1724*, 1725*, 1726*, 1727*, 1728*,						
[8, 25, 58, 110, 178, 262, 362, 478, 610, 758]						
		1692	H ₆₅₀	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
[8, 26, 66, 126, 198, 287, 392, 512, 648, 800]						
		1693	H ₅₇₈	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
[8, 26, 67, 127, 201, 289, 393, 514, 651, 802]						
		1694	H ₅₇₁	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
[8, 27, 68, 132, 197, 291, 389, 515, 645, 803]						
		1695	H ₅₇₆	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
[8, 27, 69, 133, 196, 291, 395, 518, 644, 803]						
		1696	H ₅₇₁	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1}, r_x^{-1} t_z, m_z t_z$
[8, 27, 72, 128, 202, 290, 394, 514, 650, 802]						
		1697	H ₆₅₀	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, m_z r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
[8, 28, 66, 122, 194, 282, 386, 506, 642, 794]						
		1698	H ₆₄₈	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z, r_z^2 t_z^{-1}, r_z^2 r_x t_z^{-1}$
[8, 28, 68, 127, 200, 288, 392, 512, 648, 800]						
		1699	H ₅₈₀	1	$m_z r_x$	$it_x, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
		1700	H ₅₈₀	1	$m_z r_x$	$r_z^2 r_x t_x, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
[8, 28, 69, 131, 200, 292, 392, 516, 648, 804]						
		1701	H ₄₂₂	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_z t_z$
[8, 29, 72, 131, 203, 292, 396, 516, 652, 804]						

Nbr.	gr	Nº	H_i	L	m	X
		1702	H_{557}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1},$ $m_z r_x^{-1} t_z^{-1}$
[8, 29, 72, 132, 204, 292, 394, 517, 653, 804]						
		1703	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, i t_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z, i t_z^{-1},$ $r_z^2 r_x t_z^{-1}$
[8, 29, 74, 131, 201, 291, 393, 515, 649, 803]						
		1704	H_{580}	1	$m_z r_x$	$i t_x, r_y^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z^{-1},$ $m_z t_z^{-1}$
		1705	H_{580}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z^{-1},$ $m_z t_z^{-1}$
[8, 29, 75, 129, 203, 289, 395, 513, 651, 801]						
		1706	H_{422}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_z t_z$
[8, 30, 74, 133, 202, 293, 397, 516, 650, 805]						
		1707	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y, m_z r_x^{-1} t_y, i t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z$
[8, 30, 74, 134, 203, 293, 395, 517, 651, 805]						
		1708	H_{556}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, i t_y^{-1}, r_z^2 r_x t_y^{-1}, i t_z, i t_z^{-1},$ $r_z^2 r_x t_z^{-1}$
[8, 30, 76, 130, 206, 290, 398, 514, 654, 802]						
		1709	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_z r_x t_x^{-1}, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1},$ $r_z^2 r_x t_z^{-1}$
[8, 31, 72, 132, 200, 292, 392, 516, 648, 804]						
		1710	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$i t_x, r_x^2 t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1},$ $r_y^2 t_z^{-1}$
		1711	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1},$ $r_y^2 t_z^{-1}$
		1712	H_{572}	1	$m_z r_x$	$r_z^2 r_x t_x, i t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1},$ $r_y^2 t_z^{-1}$
		1713	H_{574}	1	$m_z r_x$	$r_z^2 r_x t_x, i t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z^{-1},$ $m_z t_z^{-1}$
[8, 31, 73, 131, 204, 292, 396, 516, 652, 804]						
		1714	H_{409}	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z,$ $r_x^2 t_z^{-1}$
		1715	H_{560}	1	$m_z r_x$	$i t_x, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1},$ $m_z r_x^{-1} t_z^{-1}$
		1716	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1},$ $m_z r_x^{-1} t_z^{-1}$
		1717	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, m_x t_x^{-1}, r_x^2 t_y, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z$
[8, 32, 77, 132, 204, 292, 396, 516, 652, 804]						
		1718	H_{409}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z,$ $r_x^2 t_z^{-1}$
		1719	H_{560}	1	$m_z r_x$	$i t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1},$ $m_z r_x^{-1} t_z^{-1}$
		1720	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1},$ $m_z r_x^{-1} t_z^{-1}$
		1721	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z$
[8, 34, 74, 134, 202, 294, 394, 518, 650, 806]						
		1722	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$i t_x, r_x^2 t_x^{-1}, r_x^2 t_y, r_z^2 r_x t_y, r_x^2 t_y^{-1}, r_x^2 t_z,$ $r_z^2 r_x t_z$
		1723	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1},$ $r_z^2 r_x t_z^{-1}$
		1724	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$i t_x, r_x^2 t_x^{-1}, r_x^2 t_y, r_z^2 r_x t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1},$ $r_z^2 r_x t_z^{-1}$
		1725	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, i t_x^{-1}, i t_y^{-1}, r_z^2 r_x t_y^{-1}, i t_z, i t_z^{-1},$ $r_z^2 r_x t_z^{-1}$
		1726	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, i t_x^{-1}, i t_y, r_z^2 r_x t_y, i t_y^{-1}, i t_z,$ $r_z^2 r_x t_z$
		1727	H_{555}	1	$m_z r_x$	$r_z^2 r_x t_x, i t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1},$ $m_z r_x^{-1} t_z^{-1}$
		1728	H_{555}	1	$m_z r_x$	$i t_x, r_z^2 r_x t_x^{-1}, r_x^2 t_y, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z$

Nbr.	gr	N ₀	H_i	L	m	X
		1733*, [8, 27, 69, 129, 200, 288, 392, 512, 648, 800]				
		1734*, 1735*, [8, 28, 69, 128, 200, 288, 392, 512, 648, 800]				
		1736*, 1737*, [8, 28, 69, 129, 200, 288, 392, 512, 648, 800]				
		1738*, [8, 29, 69, 128, 200, 288, 392, 512, 648, 800]				
		1739*, 1740*, [8, 29, 69, 129, 204, 292, 396, 516, 652, 804]				
		1741*, [8, 29, 69, 130, 205, 293, 395, 515, 653, 805]				
		1742*, [8, 29, 70, 131, 203, 291, 397, 517, 651, 803]				
		1743*, [8, 29, 70, 132, 204, 292, 396, 516, 652, 804]				
		1744*, [8, 30, 69, 128, 200, 288, 392, 512, 648, 800]				
		1745*, 1746*, 1747*, 1748*, [8, 30, 70, 128, 203, 292, 396, 516, 652, 804]				
		1749*, [8, 30, 75, 133, 204, 292, 396, 516, 652, 804]				
		1750*, 1751*, [8, 31, 74, 133, 204, 292, 396, 516, 652, 804]				
		1752*, [8, 31, 75, 132, 204, 292, 396, 516, 652, 804]				
		1753*, 1754*, [8, 32, 74, 132, 204, 292, 396, 516, 652, 804]				
		1755*, 1756*, 1757*, [8, 33, 73, 132, 204, 292, 396, 516, 652, 804]				
		1758*, 1759*, 1760*, 1761*, 1762*, 1763*, [9, 28, 67, 127, 200, 288, 392, 512, 648, 800]				
		1729	H_{578}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
		[9, 28, 68, 128, 203, 290, 393, 514, 651, 802]				
		1730	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
		[9, 28, 69, 131, 197, 291, 389, 515, 645, 803]				
		1731	H_{576}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
		[9, 28, 70, 132, 196, 291, 395, 518, 644, 803]				
		1732	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1},$ $r_x^{-1} t_z, m_z t_z$
		[9, 29, 68, 127, 200, 288, 392, 512, 648, 800]				
		1733	H_{580}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
		[9, 29, 75, 130, 202, 290, 394, 514, 650, 802]				
		1734	H_{571}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
		1735	H_{578}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
		[9, 30, 74, 130, 202, 290, 394, 514, 650, 802]				
		1736	H_{576}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
		1737	H_{571}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1},$ $r_x^{-1} t_z, m_z t_z$
		[9, 30, 74, 131, 201, 291, 393, 515, 649, 803]				
		1738	H_{580}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
		[9, 31, 73, 131, 201, 291, 393, 515, 649, 803]				
		1739	H_{580}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
		1740	H_{580}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
		[9, 31, 73, 132, 204, 292, 396, 516, 652, 804]				
		1741	H_{557}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
		[9, 31, 73, 133, 205, 292, 394, 517, 653, 804]				
		1742	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z,$ $it_z^{-1}, r_z^2 r_x t_z^{-1}$
		[9, 31, 75, 132, 202, 293, 397, 516, 650, 805]				
		1743	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, m_z r_x^{-1} t_y, it_y^{-1},$ $r_x^2 t_z, m_z r_x^{-1} t_z$
		[9, 31, 75, 133, 203, 293, 395, 517, 651, 805]				
		1744	H_{556}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, it_z,$ $it_z^{-1}, r_z^2 r_x t_z^{-1}$
		[9, 32, 72, 132, 200, 292, 392, 516, 648, 804]				
		1745	H_{572}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
		1746	H_{572}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z^{-1}, r_z^2 t_z^{-1}$
		1747	H_{574}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
		1748	H_{574}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
[9, 32, 73, 131, 204, 292, 396, 516, 652, 804]						
		1749	H_{560}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
[9, 32, 79, 130, 206, 290, 398, 514, 654, 802]						
		1750	H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z,$ $it_x^{-1}, r_z^2 r_x t_z^{-1}$
		1751	H_{557}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
[9, 33, 77, 132, 204, 292, 396, 516, 652, 804]						
		1752	H_{560}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
[9, 33, 78, 130, 206, 290, 398, 514, 654, 802]						
		1753	H_{556}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, it_z,$ $it_x^{-1}, r_z^2 r_x t_z^{-1}$
		1754	H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, m_z r_x^{-1} t_y, it_y^{-1},$ $r_x^2 t_z, m_z r_x^{-1} t_z$
[9, 34, 76, 132, 204, 292, 396, 516, 652, 804]						
		1755	H_{560}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
		1756	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
		1757	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, m_z r_x^{-1} t_y, r_x^2 t_y^{-1},$ $r_x^2 t_z, m_z r_x^{-1} t_z$
[9, 35, 74, 134, 202, 294, 394, 518, 650, 806]						
		1758	H_{551}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, it_z,$ $it_z^{-1}, r_z^2 r_x t_z^{-1}$
		1759	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, it_y^{-1}, r_z^2 r_x t_y^{-1}, it_z,$ $it_z^{-1}, r_z^2 r_x t_z^{-1}$
		1760	H_{551}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, it_y, r_z^2 r_x t_y, it_y^{-1},$ $it_z, r_z^2 r_x t_z$
		1761	H_{555}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
		1762	H_{555}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
		1763	H_{555}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_x^2 t_y, m_z r_x^{-1} t_y, r_x^2 t_y^{-1},$ $r_x^2 t_z, m_z r_x^{-1} t_z$

33

- [8, 25, 58, 110, 182, 273, 376, 493, 630, 785]
1764*,
[8, 25, 59, 113, 184, 272, 376, 496, 632, 784]
1766*,
[8, 25, 59, 115, 190, 281, 384, 503, 639, 792]
1765*,
[8, 25, 60, 118, 192, 282, 385, 505, 641, 793]
1767*,
[8, 26, 66, 126, 199, 288, 392, 512, 648, 800]
1768*, 1769*,
[8, 27, 68, 128, 200, 288, 392, 512, 648, 800]
1770*, 1771*,
[8, 27, 69, 128, 200, 288, 392, 512, 648, 800]
1772*,
[8, 28, 66, 123, 196, 284, 387, 507, 644, 796]
1774*,
[8, 28, 66, 124, 196, 284, 388, 508, 644, 796]
1776*,
[8, 28, 67, 123, 195, 283, 387, 507, 643, 795]
1773*,
[8, 28, 67, 124, 195, 283, 388, 508, 643, 795]
1775*,
[8, 28, 69, 127, 200, 288, 392, 512, 648, 800]
1777*,
[8, 29, 68, 128, 200, 288, 392, 512, 648, 800]
1778*, 1779*, 1780*, 1781*,
[8, 29, 72, 131, 204, 292, 396, 516, 652, 804]
1782*, 1783*,
[8, 30, 73, 133, 204, 292, 396, 516, 652, 804]
1784*,
[8, 30, 74, 132, 204, 292, 396, 516, 652, 804]
1785*, 1786*,
[8, 31, 73, 132, 204, 292, 396, 516, 652, 804]
1787*,
[8, 32, 72, 132, 204, 292, 396, 516, 652, 804]
1788*, 1789*, 1790*, 1791*,
[9, 27, 66, 120, 193, 282, 385, 504, 641, 794]

Nbr.	gr	N ₀	H_i	L	m	X
		1764	H_{412}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_y^2 t_z, r_x t_z$
[9, 27, 66, 124, 198, 287, 388, 510, 645, 799]						
		1765	H_{412}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1},$ $m_x r_x t_z^{-1}, m_z t_z^{-1}$
[9, 27, 67, 122, 194, 282, 386, 506, 642, 794]						
		1766	H_{402}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_z t_z$
[9, 27, 67, 126, 197, 288, 388, 512, 644, 800]						
		1767	H_{407}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1},$ $r_y^2 t_z^{-1}, r_x t_z^{-1}$
[9, 28, 73, 129, 202, 290, 394, 514, 650, 802]						
		1768	H_{413}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_y^2 t_z, r_x t_z$
		1769	H_{419}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_z t_z$
[9, 29, 74, 130, 202, 290, 394, 514, 650, 802]						
		1770	H_{413}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1},$ $m_x r_x t_z^{-1}, m_z t_z^{-1}$
		1771	H_{418}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1},$ $r_y^2 t_z^{-1}, r_x t_z^{-1}$
[9, 29, 75, 129, 203, 289, 395, 513, 651, 801]						
		1772	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_z t_z$
[9, 30, 72, 126, 200, 286, 392, 510, 648, 798]						
		1773	H_{388}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, i t_y^{-1}, m_z r_x t_y^{-1}, i t_z,$ $m_z r_x t_z, i t_z^{-1}$
[9, 30, 72, 127, 200, 287, 392, 511, 648, 799]						
		1774	H_{394}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, i t_y^{-1}, m_z r_x t_y^{-1}, i t_z,$ $m_z r_x t_z, r_x t_z^{-1}$
		1775	H_{394}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y, r_z^2 t_y, i t_y^{-1},$ $r_y^2 r_x t_z^{-1}, r_x t_z^{-1}$
[9, 30, 72, 128, 200, 288, 392, 512, 648, 800]						
		1776	H_{391}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z, r_x t_z^{-1}$
[9, 30, 74, 129, 203, 289, 395, 513, 651, 801]						
		1777	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_z t_z, m_z t_z^{-1}$
[9, 31, 72, 132, 200, 292, 392, 516, 648, 804]						
		1778	H_{414}	1	$r_z^2 r_x$	$m_z r_x t_x, i t_z^{-1}, m_z r_x t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1},$ $r_y^2 t_z^{-1}, r_x t_z^{-1}$
		1779	H_{415}	1	$r_z^2 r_x$	$m_z r_x t_x, i t_z^{-1}, m_z r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_z t_z$
		1780	H_{410}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1},$ $r_y^2 t_z, r_x t_z^{-1}$
		1781	H_{404}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_z t_z$
[9, 31, 77, 130, 206, 290, 398, 514, 654, 802]						
		1782	H_{395}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, i t_y^{-1}, m_z r_x t_y^{-1}, i t_z,$ $m_z r_x t_z, r_x^2 t_z^{-1}$
		1783	H_{401}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z, r_x t_z^{-1}$
[9, 32, 77, 132, 204, 292, 396, 516, 652, 804]						
		1784	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_x^2 t_z$
[9, 32, 78, 130, 206, 290, 398, 514, 654, 802]						
		1785	H_{400}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, i t_y^{-1}, m_z r_x t_y^{-1}, i t_z,$ $m_z r_x t_z, i t_z^{-1}$
		1786	H_{395}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_y^2 r_x t_y, r_x^2 t_y, i t_y^{-1},$ $r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
[9, 33, 76, 132, 204, 292, 396, 516, 652, 804]						
		1787	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z, r_x t_z^{-1}$
[9, 34, 74, 134, 202, 294, 394, 518, 650, 806]						
		1788	H_{389}	1	$r_z^2 r_x$	$m_z r_x t_x, i t_z^{-1}, m_z r_x t_x^{-1}, i t_y^{-1}, m_z r_x t_y^{-1}, i t_z,$ $m_z r_x t_z, i t_z^{-1}$
		1789	H_{396}	1	$r_z^2 r_x$	$m_z r_x t_x, i t_z^{-1}, m_z r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z, r_x t_z^{-1}$
		1790	H_{398}	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, i t_y^{-1}, m_z r_x t_y^{-1}, i t_z,$ $m_z r_x t_z, i t_z^{-1}$
		1791	H_{392}	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z, r_x t_z^{-1}$

Nbr.	gr	N°	H_i	L	m	X
[9, 28, 68, 128, 200, 288, 392, 512, 648, 800]		1792*	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1},$ $m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
[10, 30, 73, 132, 204, 292, 396, 516, 652, 804]		1796*	H_{580}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1},$ $r_x t_y^{-1}, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
[10, 30, 74, 129, 203, 289, 395, 513, 651, 801]		1794*	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1},$ $m_y t_y^{-1}, m_x r_x t_z, m_z t_z$
[10, 31, 72, 132, 200, 292, 392, 516, 648, 804]		1795*	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$it_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1},$ $m_x r_x t_y^{-1}, m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
[10, 32, 78, 130, 206, 290, 398, 514, 654, 802]		1796*	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1},$ $r_x^2 t_z, r_x^2 t_z^{-1}, r_z^2 r_x t_z^{-1}$
[10, 33, 76, 132, 204, 292, 396, 516, 652, 804]		1797*	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_x^2 t_z, r_x^2 t_z^{-1}$
[10, 33, 77, 133, 205, 291, 397, 517, 653, 805]		1798*	H_{560}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1},$ $r_x^2 t_z, r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
[10, 34, 74, 134, 202, 294, 394, 518, 650, 806]		1799*	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$it_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1},$ $r_x^2 t_z, r_x^2 t_z^{-1}, r_z^2 r_x t_z^{-1}$
[10, 34, 75, 133, 204, 291, 397, 516, 651, 805]		1800*	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_y r_x t_x, r_x^2 r_y t_x^{-1}, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y,$ $r_y^2 r_z t_z, r_x^2 r_y t_z^{-1}, r_y^{-1} r_z^{-1} t_z^{-1}$

35

- [7, 24, 56, 104, 168, 248, 344, 456, 584, 728]
1801*,
- [7, 25, 60, 112, 180, 264, 364, 480, 612, 760]
1802*,
- [7, 25, 60, 113, 184, 273, 379, 500, 636, 788]
1803*,
- [7, 25, 61, 116, 188, 276, 380, 500, 636, 788]
1804*,
- [7, 26, 62, 114, 182, 266, 366, 482, 614, 762]
1805*,
- [7, 26, 64, 120, 192, 280, 384, 504, 640, 792]
1806*, 1807*,
- [7, 26, 64, 122, 196, 284, 388, 508, 644, 796]
1808*,
- [7, 26, 65, 123, 196, 284, 388, 508, 644, 796]
1809*, 1810*,
- [7, 26, 65, 123, 197, 286, 390, 510, 646, 798]
1811*,
- [7, 26, 65, 124, 198, 286, 390, 510, 646, 798]
1812*,
- [7, 26, 66, 124, 196, 284, 388, 508, 644, 796]
1813*,
- [7, 26, 66, 126, 198, 284, 388, 508, 644, 796]
1814*,
- [7, 27, 67, 124, 196, 284, 388, 508, 644, 796]
1815*, 1816*, 1817*, 1818*, 1819*, 1820*,
- [7, 27, 67, 125, 199, 289, 395, 516, 652, 804]
1821*,
- [7, 27, 68, 125, 196, 284, 388, 508, 644, 796]
1822*, 1823*,
- [7, 27, 68, 127, 200, 288, 392, 512, 648, 800]
1824*,
- [7, 27, 70, 130, 203, 292, 396, 516, 652, 804]
1825*,
- [7, 28, 68, 124, 196, 284, 388, 508, 644, 796]
1826*, 1827*, 1828*, 1829*, 1830*, 1831*, 1832*, 1833*,
- [7, 28, 70, 128, 200, 288, 392, 512, 648, 800]
1834*, 1835*, 1836*,
- [7, 28, 70, 129, 203, 292, 396, 516, 652, 804]
1837*,
- [7, 28, 70, 130, 204, 292, 396, 516, 652, 804]
1838*, 1839*,

Nbr.	gr	N ₀	H _i	L	m	X	
				[7, 28, 71, 131, 204, 292, 396, 516, 652, 804]			
				1840*,			
				[7, 28, 72, 132, 204, 292, 396, 516, 652, 804]			
				1841*,			
				[7, 28, 73, 133, 204, 292, 396, 516, 652, 804]			
				1842*,			
				[7, 29, 71, 128, 200, 288, 392, 512, 648, 800]			
				1843*,			
				[7, 29, 71, 129, 203, 292, 396, 516, 652, 804]			
				1844*,			
				[7, 29, 73, 132, 204, 292, 396, 516, 652, 804]			
				1845*, 1846*, 1847*, 1848*, 1849*,			
				[7, 29, 75, 134, 204, 292, 396, 516, 652, 804]			
				1850*, 1851*, 1852*,			
				[7, 30, 72, 128, 200, 288, 392, 512, 648, 800]			
				1853*, 1854*, 1855*,			
				[7, 30, 74, 132, 204, 292, 396, 516, 652, 804]			
				1856*, 1857*, 1858*, 1859*, 1860*, 1861*, 1862*,			
				[7, 30, 75, 134, 205, 292, 396, 516, 652, 804]			
				1863*,			
				[7, 30, 76, 134, 204, 292, 396, 516, 652, 804]			
				1864*, 1865*, 1866*,			
				[7, 31, 75, 132, 204, 292, 396, 516, 652, 804]			
				1867*, 1868*, 1869*, 1870*,			
				[7, 32, 76, 132, 204, 292, 396, 516, 652, 804]			
				1871*, 1872*, 1873*, 1874*, 1875*, 1876*, 1877*,			
				[8, 28, 64, 116, 184, 268, 368, 484, 616, 764]			
		1801	H ₇₇₉	$\langle m_z, m_z r_x, r_x^2 \rangle$	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_x^2 t_y, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z,$ $r_z^2 t_z^{-1}$	
		[8, 29, 67, 121, 191, 277, 379, 497, 631, 781]					
		1802	H ₄₅₂	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, t_y, t_y^{-1}, r_y^2 r_z t_z,$ $m_z t_z^{-1}$	
		[8, 29, 67, 122, 194, 283, 388, 508, 644, 796]					
		1803	H ₅₀₃	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, t_y, t_y^{-1}, r_y^2 r_z t_z,$ $r_z^2 t_z^{-1}$	
		[8, 29, 68, 124, 196, 284, 388, 508, 644, 796]					
		1804	H ₆₈₀	$\langle m_x \rangle$	r_z^2	$m_x t_x, m_x t_x^{-1}, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_y^2 t_z,$ $r_z^2 t_z^{-1}$	
		[8, 30, 68, 122, 192, 278, 380, 498, 632, 782]					
		1805	H ₆₁₁	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, t_y, t_y^{-1}, r_y^2 r_z t_z,$ $m_x r_z t_z^{-1}$	
		[8, 30, 70, 126, 198, 286, 390, 510, 646, 798]					
		1806	H ₇₄₉	$\langle m_y, r_z^2 \rangle$	i	$r_y^2 t_x, m_z t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_z^2 t_z, m_z t_z^{-1},$ $r_z^2 t_z^{-1}$	
		1807	H ₆₈₂	$\langle m_y \rangle$	m_x	$m_z t_x, r_y^2 t_x^{-1}, m_z t_x^{-1}, m_y t_y, t_y^{-1}, m_z t_z,$ $r_y^2 t_z^{-1}$	
		[8, 30, 70, 128, 200, 288, 392, 512, 648, 800]					
		1808	H ₅₉₈	$\langle r_y^2 \rangle$	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_y, r_x^2 t_y^{-1}, r_y^2 t_y^{-1}, r_x^2 r_z t_z,$ $r_z^2 t_z^{-1}$	
		[8, 30, 71, 128, 200, 288, 392, 512, 648, 800]					
		1809	H ₆₅₀	$\langle m_z r_x \rangle$	m_x	$t_x, m_x t_x^{-1}, t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_z,$ $m_x r_x t_z^{-1}$	
		1810	H ₃₇₈	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1},$ $m_x r_z t_z^{-1}$	
		[8, 30, 71, 128, 201, 289, 393, 513, 649, 801]					
		1811	H ₅₀₃	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, t_y, t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 t_z^{-1}$	
		[8, 30, 71, 129, 201, 289, 393, 513, 649, 801]					
		1812	H ₄₅₂	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, t_y, t_y^{-1}, r_y^2 r_z t_z,$ $i t_z^{-1}$	
		[8, 30, 72, 128, 200, 288, 392, 512, 648, 800]					
		1813	H ₆₄₈	$\langle m_z r_x \rangle$	m_x	$t_x, m_x t_x^{-1}, t_x^{-1}, r_x^2 t_y, i t_y^{-1}, m_z r_x^{-1} t_z,$ $r_z^2 r_x t_z^{-1}$	
		[8, 30, 72, 130, 200, 288, 392, 512, 648, 800]					
		1814	H ₅₄₁	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_z t_z,$ $i t_z^{-1}$	
		[8, 31, 72, 128, 200, 288, 392, 512, 648, 800]					
		1815	H ₃₆₁	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_y, i t_y^{-1}, m_x t_z, r_y^2 t_z^{-1},$ $m_x t_z^{-1}$	
		1816	H ₆₈₀	$\langle m_x \rangle$	r_z^2	$r_z^2 t_x, m_y t_x^{-1}, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_y^2 t_z,$ $r_x^2 t_z^{-1}$	
		1817	H ₃₆₈	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_x t_z, r_y^2 t_z^{-1},$ $m_x t_z^{-1}$	
		1818	H ₅₂₇	1	r_z^2	$m_x t_x, m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z,$ $m_z t_z^{-1}$	
		1819	H ₅₂₇	1	r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1}, r_y^2 r_z t_z,$ $m_z t_z^{-1}$	
		1820	H ₅₂₉	1	r_z^2	$m_x t_x, m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 t_z^{-1}$	

Nbr.	gr	N ₀	H_i	L	m	X
[8, 31, 72, 129, 202, 291, 396, 516, 652, 804]						
1821		H_{529}	1		r_z^2	$m_y t_x, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 t_z^{-1}$
[8, 31, 73, 128, 200, 288, 392, 512, 648, 800]						
1822		H_{422}	1		$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z,$ $m_z t_z^{-1}$
1823		H_{409}	1		$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z^{-1}$
[8, 31, 73, 130, 202, 290, 394, 514, 650, 802]						
1824		H_{359}	1		m_z	$r_z^2 t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, t_z, m_z t_z^{-1},$ t_z^{-1}
[8, 31, 75, 131, 204, 292, 396, 516, 652, 804]						
1825		H_{377}	1		m_z	$r_y^2 t_x, r_z^{-1} t_x^{-1}, r_z t_y, m_y t_y^{-1}, t_z, m_z t_z^{-1},$ t_z^{-1}
[8, 32, 72, 128, 200, 288, 392, 512, 648, 800]						
1826		H_{779}	$\langle m_z, m_z r_x, r_x^2 \rangle$		$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}, m_x r_x^{-1} t_z,$ $r_y^2 r_x t_z^{-1}$
1827		H_{750}	$\langle m_y, r_z^2 \rangle$		i	$r_y^2 t_x, m_z t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1},$ $m_x r_z t_z^{-1}$
1828		H_{622}	$\langle m_z \rangle$		r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_y^{-1}, m_x t_y, m_x t_y^{-1}, r_y^2 r_z t_z,$ $m_x r_z t_z^{-1}$
1829		H_{649}	$\langle m_z r_x \rangle$		m_x	$m_z r_x^{-1} t_x, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_z^2 t_y, i t_y^{-1}, m_z r_x^{-1} t_z,$ $r_z^2 r_x t_z^{-1}$
1830		H_{682}	$\langle m_y \rangle$		m_x	$m_z t_x, r_y^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}, m_z t_z,$ $r_y^2 t_z^{-1}$
1831		H_{652}	$\langle m_z r_x \rangle$		m_x	$m_z r_x^{-1} t_x, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_z,$ $m_x r_x^{-1} t_z^{-1}$
1832		H_{378}	1		m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1},$ $m_x r_z t_z^{-1}$
1833		H_{541}	1		r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_z t_z,$ $i t_z^{-1}$
[8, 32, 74, 130, 202, 290, 394, 514, 650, 802]						
1834		H_{370}	1		m_z	$r_z^2 t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_z, r_x^2 t_z^{-1},$ $m_y t_z^{-1}$
1835		H_{527}	1		r_z^2	$m_x t_x, m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z,$ $i t_z^{-1}$
1836		H_{529}	1		r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 t_z^{-1}$
[8, 32, 74, 131, 204, 292, 396, 516, 652, 804]						
1837		H_{529}	1		r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 t_z^{-1}$
[8, 32, 74, 132, 204, 292, 396, 516, 652, 804]						
1838		H_{604}	$\langle r_y^2 \rangle$		r_z^2	$i t_x, m_y t_x^{-1}, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_x^2 r_z t_z,$ $r_z t_z^{-1}$
1839		H_{527}	1		r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1}, r_y^2 r_z t_z,$ $i t_z^{-1}$
[8, 32, 75, 132, 204, 292, 396, 516, 652, 804]						
1840		H_{359}	1		m_z	$i t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, t_z, m_z t_z^{-1},$ t_z^{-1}
[8, 32, 76, 132, 204, 292, 396, 516, 652, 804]						
1841		H_{359}	1		m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, t_z, m_z t_z^{-1},$ t_z^{-1}
[8, 32, 77, 132, 204, 292, 396, 516, 652, 804]						
1842		H_{382}	1		m_z	$r_y^2 t_x, r_z^{-1} t_x^{-1}, r_z t_y, m_y t_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1},$ $m_x r_z t_z^{-1}$
[8, 33, 74, 130, 202, 290, 394, 514, 650, 802]						
1843		H_{682}	$\langle m_x \rangle$		r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_y^2 t_z,$ $r_x^2 t_z^{-1}$
[8, 33, 74, 131, 204, 292, 396, 516, 652, 804]						
1844		H_{343}	1		m_z	$r_z^2 t_x, m_x r_z t_x^{-1}, i t_y, m_x r_z t_y^{-1}, t_z, m_z t_z^{-1},$ t_z^{-1}
[8, 33, 76, 132, 204, 292, 396, 516, 652, 804]						
1845		H_{370}	1		m_z	$i t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_z, r_x^2 t_z^{-1},$ $m_y t_z^{-1}$
1846		H_{370}	1		m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_z, r_x^2 t_z^{-1},$ $m_y t_z^{-1}$
1847		H_{359}	1		m_z	$i t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, t_z, m_z t_z^{-1},$ t_z^{-1}
1848		H_{452}	1		r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z,$ $m_z t_z^{-1}$
1849		H_{503}	1		r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z,$ $r_x^2 t_z^{-1}$

Nbr.	gr	N ₀	H _i	L	m	X
[8, 33, 78, 132, 204, 292, 396, 516, 652, 804]						
1850			H ₃₇₇	1	m_z	$r_z^2 t_x, m_z r_z^{-1} t_x^{-1}, m_z r_z t_y, m_y t_y^{-1}, t_z, m_z t_z^{-1},$ t_z^{-1}
1851			H ₅₄₁	1	r_z^2	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z,$ it^{-1}
1852			H ₅₄₁	1	r_z^2	$r_x t_x, r_x^{-1} t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z,$ it^{-1}
[8, 34, 74, 130, 202, 290, 394, 514, 650, 802]						
1853			H ₆₀₄	$\langle r_y^2 \rangle$	r_z^2	$m_x t_x, m_x t_x^{-1}, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_z^2 r_z t_z,$ $r_z t_z^{-1}$
1854			H ₆₂₂	$\langle m_z \rangle$	r_z^2	$m_x t_x, m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z,$ $m_x r_z t_z^{-1}$
1855			H ₆₈₃	$\langle m_x \rangle$	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_y, r_x^2 t_y^{-1}, r_y^2 t_y^{-1}, r_y^2 t_z,$ $r_x^2 t_z^{-1}$
[8, 34, 76, 132, 204, 292, 396, 516, 652, 804]						
1856			H ₃₄₄	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1},$ $m_x r_z t_z^{-1}$
1857			H ₃₅₀	1	m_z	$r_z^2 t_x, it_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, t_z, m_z t_z^{-1},$ t_z^{-1}
1858			H ₃₅₀	1	m_z	$r_z^2 t_x, it_x^{-1}, r_x^2 t_y, m_y t_y^{-1}, t_z, m_z t_z^{-1},$ t_z^{-1}
1859			H ₃₇₀	1	m_z	$it_x, r_x^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_z, r_x^2 t_z^{-1},$ $m_y t_z^{-1}$
1860			H ₃₄₇	1	m_z	$r_z^2 t_x, m_x r_z t_x^{-1}, it_y, m_x r_z t_y^{-1}, m_x r_z^{-1} t_z, r_x^2 r_z t_z^{-1},$ $m_x r_z^{-1} t_z^{-1}$
1861			H ₄₅₂	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z,$ it_z^{-1}
1862			H ₅₀₃	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 t_z^{-1}$
[8, 34, 77, 133, 204, 292, 396, 516, 652, 804]						
1863			H ₅₁₁	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, r_x^2 t_z,$ $r_y^2 t_z^{-1}$
[8, 34, 78, 132, 204, 292, 396, 516, 652, 804]						
1864			H ₃₈₂	1	m_z	$r_y^2 t_x, m_z r_z^{-1} t_x^{-1}, m_z r_z t_y, m_y t_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1},$ $m_x r_z t_z^{-1}$
1865			H ₅₁₁	1	r_z^2	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z,$ $r_y^2 t_z^{-1}$
1866			H ₅₁₁	1	r_z^2	$r_x t_x, r_x^{-1} t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z,$ $r_y^2 t_z^{-1}$
[8, 35, 76, 132, 204, 292, 396, 516, 652, 804]						
1867			H ₆₈₂	$\langle m_x \rangle$	r_z^2	$it_x, r_x^2 t_x^{-1}, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_z^2 t_z,$ $r_z^2 t_z^{-1}$
1868			H ₃₇₂	1	m_z	$r_z^2 t_x, it_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_x t_z, r_y^2 t_z^{-1},$ $m_x t_z^{-1}$
1869			H ₃₆₅	1	m_z	$r_z^2 t_x, it_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_z, r_x^2 t_z^{-1},$ $m_y t_z^{-1}$
1870			H ₃₄₃	1	m_z	$r_z^2 t_x, r_y^2 r_z t_x^{-1}, it_y, r_y^2 r_z t_y^{-1}, t_z, m_z t_z^{-1},$ t_z^{-1}
[8, 36, 76, 132, 204, 292, 396, 516, 652, 804]						
1871			H ₅₉₈	$\langle r_y^2 \rangle$	r_z^2	$r_z^2 t_x, r_x^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_y^2 t_y^{-1}, r_x^2 r_z t_z,$ $r_z t_z^{-1}$
1872			H ₆₁₁	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_y^2 r_z t_z,$ $m_x r_z t_z^{-1}$
1873			H ₆₈₃	$\langle m_x \rangle$	r_z^2	$it_x, r_x^2 t_x^{-1}, r_y^2 t_y, r_x^2 t_y^{-1}, r_y^2 t_y^{-1}, r_y^2 t_z,$ $r_y^2 t_z^{-1}$
1874			H ₃₄₄	1	m_z	$r_z^2 t_x, it_x^{-1}, it_y, it_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1},$ $m_x r_z t_z^{-1}$
1875			H ₃₆₄	1	m_z	$r_z^2 t_x, it_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_z^2 t_z, it_z^{-1},$ $r_z^2 t_z^{-1}$
1876			H ₃₄₇	1	m_z	$r_z^2 t_x, r_y^2 r_z t_x^{-1}, it_y, r_y^2 r_z t_y^{-1}, m_x r_z^{-1} t_z, r_x^2 r_z t_z^{-1},$ $m_x r_z^{-1} t_z^{-1}$
1877			H ₅₁₁	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_z,$ $r_y^2 t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
		1882*, [7, 27, 65, 117, 184, 268, 368, 484, 616, 764]				
		1883*, [7, 27, 68, 126, 197, 284, 388, 508, 644, 796]				
		1884*, [7, 27, 68, 127, 200, 288, 392, 512, 648, 800]				
		1885*, 1886*, [7, 27, 69, 129, 202, 290, 394, 514, 650, 802]				
		1887*, [7, 27, 69, 130, 204, 292, 396, 516, 652, 804]				
		1888*, [7, 27, 70, 132, 205, 292, 396, 516, 652, 804]				
		1889*, [7, 27, 70, 133, 207, 293, 396, 516, 652, 804]				
		1890*, 1891*, [7, 27, 70, 134, 209, 294, 396, 516, 652, 804]				
		1892*, [7, 27, 71, 132, 204, 292, 396, 516, 652, 804]				
		1893*, [7, 27, 71, 139, 212, 293, 396, 516, 652, 804]				
		1894*, [7, 28, 65, 116, 184, 268, 368, 484, 616, 764]				
		1895*, [7, 28, 69, 125, 196, 284, 388, 508, 644, 796]				
		1896*, [7, 28, 70, 130, 202, 288, 392, 512, 648, 800]				
		1897*, 1898*, [7, 28, 71, 126, 193, 279, 381, 499, 633, 783]				
		1899*, [7, 28, 71, 130, 202, 290, 394, 514, 650, 802]				
		1900*, 1901*, 1902*, [7, 28, 71, 131, 204, 292, 396, 516, 652, 804]				
		1903*, 1904*, [7, 28, 71, 132, 204, 290, 394, 514, 650, 802]				
		1905*, [7, 28, 72, 135, 207, 292, 396, 516, 652, 804]				
		1906*, [7, 28, 72, 135, 210, 296, 397, 516, 652, 804]				
		1907*, 1908*, [7, 28, 72, 139, 211, 292, 396, 516, 652, 804]				
		1909*, [7, 28, 73, 133, 204, 292, 396, 516, 652, 804]				
		1910*, [7, 28, 73, 134, 204, 290, 394, 514, 650, 802]				
		1911*, [7, 28, 73, 135, 206, 292, 396, 516, 652, 804]				
		1912*, 1913*, 1914*, 1915*, [7, 28, 74, 137, 207, 292, 396, 516, 652, 804]				
		1916*, [7, 28, 74, 137, 209, 294, 396, 516, 652, 804]				
		1917*, [7, 29, 74, 136, 209, 294, 396, 516, 652, 804]				
		1918*, 1919*, 1920*, [7, 29, 75, 137, 208, 293, 396, 516, 652, 804]				
		1921*, 1922*, 1923*, [7, 29, 76, 137, 207, 293, 396, 516, 652, 804]				
		1924*, [7, 30, 76, 136, 207, 293, 396, 516, 652, 804]				
		1925*, [7, 30, 77, 137, 206, 292, 396, 516, 652, 804]				
		1926*, 1927*, 1928*, 1929*, [7, 31, 75, 131, 202, 290, 394, 514, 650, 802]				
		1930*, [7, 31, 76, 135, 207, 293, 396, 516, 652, 804]				
		1931*, 1932*, 1933*, 1934*, [7, 31, 77, 134, 204, 292, 396, 516, 652, 804]				
		1935*, [7, 31, 77, 136, 206, 292, 396, 516, 652, 804]				
		1936*, [7, 32, 75, 130, 202, 290, 394, 514, 650, 802]				
		1937*, 1938*, [7, 32, 77, 133, 204, 292, 396, 516, 652, 804]				
		1939*, 1940*, [7, 32, 77, 135, 206, 292, 396, 516, 652, 804]				
		1941*, 1942*, 1943*, 1944*, 1945*, 1946*, [7, 32, 78, 134, 204, 292, 396, 516, 652, 804]				
		1947*, [8, 29, 69, 128, 203, 292, 396, 516, 652, 804]				
		1878	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z,$ $m_x r_x^{-1} t_z^{-1}$
		[8, 30, 69, 123, 193, 279, 381, 499, 633, 783]				
		1879	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z,$ $r_z^2 r_x t_z^{-1}$
		[8, 30, 71, 128, 200, 288, 392, 512, 648, 800]				
		1880	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, m_x r_x t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z,$ $m_x r_x^{-1} t_z^{-1}$
		[8, 30, 71, 130, 204, 292, 396, 516, 652, 804]				
		1881	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1}, r_x^2 t_z, r_z^2 r_x t_z,$ $r_x^2 t_z^{-1}$
		[8, 30, 73, 134, 207, 293, 396, 516, 652, 804]				

Nbr.	gr	N°	H_i	L	m	X
		1882	H_{578}	1	$m_z r_x$	$m_x t x, r_y^2 r_x t x^{-1}, m_y t y, m_y t y^{-1}, r_x t y^{-1}, m_z t z, r_x^{-1} t z^{-1}$
		[8, 31, 70, 123, 193, 279, 381, 499, 633, 783]				
		1883	H_{560}	1	$m_z r_x$	$r_z^2 r_x t x, m_x t x^{-1}, m_z r_x^{-1} t y, r_x^2 t y^{-1}, m_z r_x^{-1} t y^{-1}, m_z r_x^{-1} t z, m_z r_x^{-1} t z^{-1}$
		[8, 31, 73, 129, 200, 288, 392, 512, 648, 800]				
		1884	H_{580}	1	$m_z r_x$	$r_z^2 r_x t x, m_x t x^{-1}, r_x t y, m_y t y^{-1}, r_x t y^{-1}, r_x^{-1} t z, r_x^{-1} t z^{-1}$
		[8, 31, 73, 130, 202, 290, 394, 514, 650, 802]				
		1885	H_{560}	1	$m_z r_x$	$i t x, m_x t x^{-1}, m_z r_x^{-1} t y, r_x^2 t y^{-1}, m_z r_x^{-1} t y^{-1}, m_z r_x^{-1} t z, m_z r_x^{-1} t z^{-1}$
		1886	H_{557}	1	$m_z r_x$	$m_x t x, r_y^2 r_x t x^{-1}, m_z r_x^{-1} t y, r_x^2 t y^{-1}, m_z r_x^{-1} t y^{-1}, m_z r_x^{-1} t z, m_z r_x^{-1} t z^{-1}$
		[8, 31, 74, 131, 203, 291, 395, 515, 651, 803]				
		1887	H_{409}	1	$r_z^2 r_x$	$r_z^2 t x, r_y^2 t x^{-1}, r_y^2 r_x t y, r_y^2 r_x t y^{-1}, r_x^2 t y^{-1}, r_y^2 r_x t z, r_y^2 r_x t z^{-1}$
		[8, 31, 74, 132, 204, 292, 396, 516, 652, 804]				
		1888	H_{578}	1	$m_z r_x$	$m_x t x, r_y^2 r_x t x^{-1}, r_x t y, m_y t y^{-1}, r_x t y^{-1}, r_x^{-1} t z, r_x^{-1} t z^{-1}$
		[8, 31, 75, 133, 204, 292, 396, 516, 652, 804]				
		1889	H_{580}	1	$m_z r_x$	$i t x, m_x t x^{-1}, r_x t y, m_y t y^{-1}, r_x t y^{-1}, r_x^{-1} t z, r_x^{-1} t z^{-1}$
		[8, 31, 75, 134, 205, 292, 396, 516, 652, 804]				
		1890	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t x, m_z r_x t x^{-1}, m_y t y, m_y t y^{-1}, m_x r_x t y^{-1}, r_y^2 t z, m_x r_x^{-1} t z^{-1}$
		1891	H_{571}	1	$m_z r_x$	$m_x t x, r_y^2 r_x t x^{-1}, m_y t y, r_z^2 t y^{-1}, m_x r_x t y^{-1}, m_z t z, m_x r_x^{-1} t z^{-1}$
		[8, 31, 75, 135, 206, 292, 396, 516, 652, 804]				
		1892	H_{557}	1	$m_z r_x$	$m_x t x, r_y^2 r_x t x^{-1}, m_z r_x^{-1} t y, r_x^2 t y^{-1}, r_x^2 t z, m_z r_x^{-1} t z, r_x^2 t z^{-1}$
		[8, 31, 76, 132, 204, 292, 396, 516, 652, 804]				
		1893	H_{422}	1	$r_z^2 r_x$	$r_z^2 t x, r_y^2 t x^{-1}, m_x r_x^{-1} t y, m_x r_x^{-1} t y^{-1}, m_y t y^{-1}, m_x r_x t z, m_x r_x t z^{-1}$
		[8, 31, 76, 139, 205, 292, 396, 516, 652, 804]				
		1894	H_{572}	1	$m_z r_x$	$r_z^2 r_x t x, i t x^{-1}, r_z^2 t y, r_z^2 t y^{-1}, m_x r_x t y^{-1}, r_y^2 t z, m_x r_x^{-1} t z^{-1}$
		[8, 32, 69, 123, 193, 279, 381, 499, 633, 783]				
		1895	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t x, r_z^2 r_x t x^{-1}, r_z^2 r_x t y, r_x^2 t y^{-1}, r_z^2 r_x t y^{-1}, r_z^2 r_x t z, r_z^2 r_x t z^{-1}$
		[8, 32, 73, 128, 200, 288, 392, 512, 648, 800]				
		1896	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t x, r_z^2 r_x t x^{-1}, m_x r_x t y, m_y t y^{-1}, m_x r_x t y^{-1}, m_x r_x^{-1} t z, m_x r_x^{-1} t z^{-1}$
		[8, 32, 74, 132, 202, 290, 394, 514, 650, 802]				
		1897	H_{555}	1	$m_z r_x$	$r_z^2 r_x t x, i t x^{-1}, m_z r_x^{-1} t y, r_x^2 t y^{-1}, m_z r_x^{-1} t y^{-1}, m_z r_x^{-1} t z, m_z r_x^{-1} t z^{-1}$
		1898	H_{560}	1	$m_z r_x$	$r_z^2 r_x t x, r_y^2 r_x t x^{-1}, m_z r_x^{-1} t y, r_x^2 t y^{-1}, m_z r_x^{-1} t y^{-1}, m_z r_x^{-1} t z, m_z r_x^{-1} t z^{-1}$
		[8, 32, 75, 127, 198, 285, 388, 507, 642, 793]				
		1899	H_{393}	1	$r_z^2 r_x$	$r_y r_x t x, r_y^{-1} r_z^{-1} t x^{-1}, r_y r_x t y, r_y^{-1} r_z^{-1} t y^{-1}, r_y^2 r_z t z, r_y r_x t z, r_y^{-1} r_z^{-1} t z^{-1}$
		[8, 32, 75, 131, 203, 291, 395, 515, 651, 803]				
		1900	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$i t x, r_x^2 t x^{-1}, r_z^2 r_x t y, r_x^2 t y^{-1}, r_z^2 r_x t y^{-1}, r_z^2 r_x t z, r_z^2 r_x t z^{-1}$
		1901	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t x, m_z r_x t x^{-1}, r_z^2 r_x t y, r_x^2 t y^{-1}, r_z^2 r_x t y^{-1}, r_z^2 r_x t z, r_z^2 r_x t z^{-1}$
		1902	H_{561}	1	$m_z r_x$	$m_x t x, r_y^2 r_x t x^{-1}, m_z r_x^{-1} t y, i t y^{-1}, r_z^2 r_x t y^{-1}, m_z r_x^{-1} t z, r_z^2 r_x t z^{-1}$
		[8, 32, 75, 132, 204, 292, 396, 516, 652, 804]				
		1903	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t x, m_z r_x t x^{-1}, m_x r_x t y, m$

Nbr.	gr	N ₀	H_i	L	m	X
		1909	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, it_z, r_z^2 r_x t_z,$ it_z^{-1}
[8, 32, 77, 132, 204, 292, 396, 516, 652, 804]						
		1910	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$it_x, r_x^2 t_x^{-1}, m_x r_x t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z,$ $m_x r_x^{-1} t_z^{-1}$
[8, 32, 77, 133, 203, 291, 395, 515, 651, 803]						
		1911	H_{560}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z,$ $m_z r_x^{-1} t_z^{-1}$
[8, 32, 77, 134, 204, 292, 396, 516, 652, 804]						
		1912	H_{422}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_x r_x t_z^{-1}$
		1913	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_z r_x t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1}, r_x^2 t_z, r_z^2 r_x t_z,$ $r_x^2 t_z^{-1}$
		1914	H_{574}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z,$ $r_x^{-1} t_z^{-1}$
		1915	H_{561}	1	$m_z r_x$	$m_x t_x, r_z^2 r_x t_x^{-1}, r_x^2 t_y, it_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z,$ $r_z^2 r_x t_z^{-1}$
[8, 32, 78, 135, 204, 292, 396, 516, 652, 804]						
		1916	H_{580}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z,$ $r_x^{-1} t_z^{-1}$
[8, 32, 78, 135, 206, 292, 396, 516, 652, 804]						
		1917	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_z t_z^{-1}$
[8, 33, 77, 135, 206, 292, 396, 516, 652, 804]						
		1918	H_{560}	1	$m_z r_x$	$it_x, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z,$ $r_x^2 t_z^{-1}$
		1919	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z,$ $r_x^2 t_z^{-1}$
		1920	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z^{-1}$
[8, 33, 78, 135, 205, 292, 396, 516, 652, 804]						
		1921	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z^{-1}$
		1922	H_{580}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z,$ $r_x^{-1} t_z^{-1}$
		1923	H_{580}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z,$ $r_x^{-1} t_z^{-1}$
[8, 33, 79, 134, 205, 292, 396, 516, 652, 804]						
		1924	H_{422}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z,$ $m_z t_z^{-1}$
[8, 34, 78, 134, 205, 292, 396, 516, 652, 804]						
		1925	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1}, r_x^{-1} t_z,$ $r_y^2 t_z^{-1}$
[8, 34, 79, 134, 204, 292, 396, 516, 652, 804]						
		1926	H_{409}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z^{-1}$
		1927	H_{560}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z,$ $r_x^2 t_z^{-1}$
		1928	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z,$ $r_x^2 t_z^{-1}$
		1929	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z^{-1}$
[8, 35, 76, 131, 203, 291, 395, 515, 651, 803]						
		1930	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 r_x t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z,$ $r_z^2 r_x t_z^{-1}$
[8, 35, 77, 134, 205, 292, 396, 516, 652, 804]						
		1931	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$it_x, r_x^2 t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z,$ $m_x r_x^{-1} t_z^{-1}$
		1932	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z,$ $m_x r_x^{-1} t_z^{-1}$
		1933	H_{574}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1}, m_z t_z,$ $r_x^{-1} t_z^{-1}$
		1934	H_{576}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_x r_x t_y^{-1}, r_y^2 t_z,$ $m_x r_x^{-1} t_z^{-1}$
[8, 35, 78, 132, 204, 292, 396, 516, 652, 804]						
		1935	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, r_x t_y, m_x r_x t_y^{-1}, r_x^{-1} t_z,$ $m_x r_x^{-1} t_z^{-1}$
[8, 35, 78, 134, 204, 292, 396, 516, 652, 804]						
		1936	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, it_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z,$ it_z^{-1}
[8, 36, 75, 131, 203, 291, 395, 515, 651, 803]						
		1937	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z,$ $r_z^2 r_x t_z^{-1}$

Nbr.	gr	H_i	L	m	X
		1938	H_{556}	1	$m_z r_x$
$m_x t_x, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, i t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$					
[8, 36, 77, 132, 204, 292, 396, 516, 652, 804]					
		1939	H_{572}	1	$m_z r_x$
$r_z^2 r_x t_x, i t_x^{-1}, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$					
		1940	H_{576}	1	$m_z r_x$
$m_x t_x, r_z^2 r_x t_x^{-1}, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$					
[8, 36, 77, 134, 204, 292, 396, 516, 652, 804]					
		1941	H_{649}	$\langle m_x \rangle$	$r_z^2 y r_x$
$i t_x, r_x^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z, r_z^2 r_x t_z^{-1}$					
		1942	H_{649}	$\langle m_x \rangle$	$r_z^2 y r_x$
$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1}, r_x^2 t_z, r_z^2 r_x t_z, r_z^2 t_z^{-1}$					
		1943	H_{649}	$\langle m_x \rangle$	$r_z^2 y r_x$
$i t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1}, r_x^2 t_z, r_z^2 r_x t_z, r_z^2 t_z^{-1}$					
		1944	H_{555}	1	$m_z r_x$
$r_z^2 r_x t_x, i t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z, m_z r_x^{-1} t_z^{-1}$					
		1945	H_{555}	1	$m_z r_x$
$i t_x, r_z^2 r_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z^{-1}$					
		1946	H_{556}	1	$m_z r_x$
$m_x t_x, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, i t_y^{-1}, i t_z, r_z^2 r_x t_z, i t_z^{-1}$					
[8, 36, 78, 132, 204, 292, 396, 516, 652, 804]					
		1947	H_{393}	1	$r_z^2 r_x$
$r_z^2 r_z t_x, r_x^2 r_y t_x^{-1}, r_z^2 r_z t_y, r_y^{-1} r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, r_y r_x t_z, r_z^2 r_y t_z^{-1}$					
37					
[8, 29, 68, 124, 196, 284, 388, 508, 644, 796]					
1948*, 1949*,					
[8, 30, 70, 126, 198, 286, 390, 510, 646, 798]					
1950*, 1951*, 1952*, 1953*,					
[8, 30, 71, 128, 200, 288, 392, 512, 648, 800]					
1954*, 1955*, 1956*, 1957*, 1958*,					
[8, 30, 72, 131, 204, 292, 396, 516, 652, 804]					
1959*, 1960*, 1961*, 1962*, 1963*, 1964*,					
[8, 30, 73, 134, 206, 292, 396, 516, 652, 804]					
1965*,					
[8, 31, 72, 128, 200, 288, 392, 512, 648, 800]					
1966*,					
[8, 31, 73, 129, 200, 288, 392, 512, 648, 800]					
1967*, 1968*, 1969*,					
[8, 31, 73, 131, 204, 292, 396, 516, 652, 804]					
1970*,					
[8, 31, 74, 132, 204, 292, 396, 516, 652, 804]					
1971*, 1972*, 1973*, 1974*, 1975*, 1976*, 1977*, 1978*, 1979*,					
[8, 31, 75, 133, 204, 292, 396, 516, 652, 804]					
1980*,					
[8, 31, 75, 134, 205, 292, 396, 516, 652, 804]					
1981*, 1982*, 1983*,					
[8, 32, 73, 128, 200, 288, 392, 512, 648, 800]					
1984*, 1985*, 1986*, 1987*, 1988*, 1989*, 1990*, 1991*, 1992*, 1993*, 1994*, 1995*,					
[8, 32, 75, 132, 204, 292, 396, 516, 652, 804]					
1996*, 1997*, 1998*, 1999*, 2000*, 2001*, 2002*, 2003*, 2004*, 2005*, 2006*, 2007*, 2008*,					
2009*, 2010*, 2011*, 2012*, 2013*, 2014*, 2015*, 2016*, 2017*, 2018*, 2019*, 2020*, 2021*,					
2022*, 2023*, 2024*, 2025*,					
[8, 32, 76, 133, 204, 292, 396, 516, 652, 804]					
2026*, 2027*, 2028*, 2029*, 2030*, 2031*, 2032*,					
[8, 32, 76, 134, 205, 292, 396, 516, 652, 804]					
2033*, 2034*, 2035*, 2036*,					
[8, 32, 77, 134, 204, 292, 396, 516, 652, 804]					
2037*, 2038*, 2039*, 2040*,					
[8, 32, 77, 135, 205, 292, 396, 516, 652, 804]					
2041*,					
[8, 33, 76, 132, 204, 292, 396, 516, 652, 804]					
2042*, 2043*, 2044*, 2045*, 2046*, 2047*, 2048*, 2049*, 2050*, 2051*, 2052*, 2053*, 2054*,					
2055*, 2056*, 2057*, 2058*, 2059*, 2060*, 2061*, 2062*, 2063*,					
[8, 33, 77, 133, 204, 292, 396, 516, 652, 804]					
2064*, 2065*, 2066*,					
[8, 33, 77, 134, 205, 292, 396, 516, 652, 804]					
2067*,					
[8, 33, 78, 135, 205, 292, 396, 516, 652, 804]					
2068*, 2069*, 2070*,					
[8, 34, 77, 132, 204, 292, 396, 516, 652, 804]					
2071*, 2072*, 2073*, 2074*, 2075*, 2076*, 2077*, 2078*, 2079*, 2080*, 2081*, 2082*, 2083*,					
2084*, 2085*, 2086*, 2087*, 2088*, 2089*, 2090*, 2091*, 2092*, 2093*, 2094*, 2095*, 2096*,					
2097*, 2098*, 2099*, 2100*, 2101*, 2102*, 2103*, 2104*, 2105*, 2106*, 2107*, 2108*, 2109*,					
2110*,					
[8, 34, 78, 134, 205, 292, 396, 516, 652, 804]					
2111*, 2112*, 2113*,					
[9, 32, 72, 128, 200, 288, 392, 512, 648, 800]					
		1948	H_{680}	$\langle m_x \rangle$	r_z^2
$m_x t_x, m_x t_x^{-1}, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_y^2 t_z, r_z^2 t_x^{-1}, r_z^2 t_y^{-1}$					
		1949	H_{690}	$\langle m_x \rangle$	r_z^2
$m_x t_x, m_x t_x^{-1}, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_y^2 r_z t_z, m_z r_z^{-1} t_z, r_z^2 t_z^{-1}$					
[9, 33, 73, 129, 201, 289, 393, 513, 649, 801]					

Nbr.	gr	N ₀	H_i	L	m	X
		1980	H_{359}	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
[9, 34, 77, 133, 204, 292, 396, 516, 652, 804]						
		1981	H_{382}	1	m_z	$r_y^2 t_x, m_x t_x, r_z^{-1} t_x^{-1}, r_z t_y, r_x^2 t_y^{-1}, m_x r_z t_z,$ $r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
		1982	H_{382}	1	m_z	$r_y^2 t_x, m_x t_x, r_z^{-1} t_x^{-1}, r_z t_y, m_y t_y^{-1}, m_x r_z t_z,$ $r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
		1983	H_{377}	1	m_z	$r_y^2 t_x, m_x t_x, r_z^{-1} t_x^{-1}, r_z t_y, r_x^2 t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
[9, 35, 74, 130, 202, 290, 394, 514, 650, 802]						
		1984	H_{683}	$\langle m_x \rangle$	r_z^2	$r_z^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_y, r_x^2 t_y^{-1}, r_y^2 t_y^{-1}, r_x^2 t_z,$ $r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
		1985	H_{683}	$\langle m_x \rangle$	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_y, r_x^2 t_y^{-1}, r_y^2 t_y^{-1}, r_y^2 t_z,$ $r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
		1986	H_{682}	$\langle m_x \rangle$	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_x^2 t_z,$ $r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
		1987	H_{453}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, m_z t_y, m_z t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
		1988	H_{539}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_z r_z^{-1} t_z,$ $m_z r_z t_z, r_y^2 r_z t_z^{-1}$
		1989	H_{539}	1	r_z^2	$m_z t_x, m_z t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, m_z r_z^{-1} t_z,$ $m_z r_z t_z, r_y^2 r_z t_z^{-1}$
		1990	H_{505}	1	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_z t_z,$ $r_x^2 r_z t_z^{-1}, r_y^2 r_z t_z^{-1}$
		1991	H_{505}	1	r_z^2	$r_y^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_z t_z,$ $r_x^2 r_z t_z, r_y^2 r_z t_z^{-1}$
		1992	H_{527}	1	r_z^2	$m_x t_x, m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z,$ $i t_z^{-1}, m_z t_z^{-1}$
		1993	H_{529}	1	r_z^2	$m_x t_x, m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
		1994	H_{496}	1	r_z^2	$m_x t_x, m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z,$ $r_y^2 r_z t_z^{-1}, r_x^2 r_z t_z^{-1}$
		1995	H_{502}	1	r_z^2	$m_x t_x, m_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z r_z^{-1} t_z,$ $m_z r_z t_z, r_y^2 r_z t_z^{-1}$
[9, 35, 76, 132, 204, 292, 396, 516, 652, 804]						
		1996	H_{344}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, i t_y, r_z^2 t_y^{-1}, m_x r_z t_z,$ $r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
		1997	H_{344}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_z t_z,$ $r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
		1998	H_{330}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, i t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
		1999	H_{330}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, i t_y, r_z^2 t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
		2000	H_{682}	$\langle m_y \rangle$	m_x	$m_z t_x, r_y^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}, r_y^2 t_z,$ $r_y^2 t_z^{-1}, m_z t_z^{-1}$
		2001	H_{682}	$\langle m_y \rangle$	m_x	$m_z t_x, r_y^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y, m_x t_y^{-1}, m_z t_z,$ $r_y^2 t_z^{-1}, m_z t_z^{-1}$
		2002	H_{680}	$\langle m_x \rangle$	r_z^2	$r_z^2 t_x, m_y t_x^{-1}, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_x^2 t_z,$ $r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
		2003	H_{350}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
		2004	H_{350}	1	m_z	$r_z^2 t_x, i t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
		2005	H_{350}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_x^2 t_y, m_y t_y, m_y t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
		2006	H_{680}	$\langle m_x \rangle$	r_z^2	$r_z^2 t_x, m_y t_x^{-1}, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_x^2 t_z,$ $r_y^2 t_z, r_x^2 t_z^{-1}$
		2007	H_{370}	1	m_z	$i t_x, r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_z,$ $r_x^2 t_z^{-1}, m_y t_z^{-1}$
		2008	H_{359}	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
		2009	H_{373}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_z^2 t_z,$ $i t_z^{-1}, r_z^2 t_z^{-1}$
		2010	H_{373}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, r_z^2 t_z,$ $i t_z^{-1}, r_z^2 t_z^{-1}$
		2011	H_{368}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, r_z^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_x t_z,$ $r_y^2 t_z^{-1}, m_x t_z^{-1}$

Nbr.	gr	N°	H_i	L	m	X
		2012	H_{378}	1	m_z	$r_y^2 t x, r_y^2 t x^{-1}, m_x t x^{-1}, r_x^2 t y, r_x^2 t y^{-1}, m_x r_z t z,$ $r_y^2 r_z t z^{-1}, m_x r_z t z^{-1}$
		2013	H_{378}	1	m_z	$r_y^2 t x, r_y^2 t x^{-1}, m_x t x^{-1}, m_y t y, r_y^2 t y^{-1}, m_x r_z t z,$ $r_y^2 r_z t z^{-1}, m_x r_z t z^{-1}$
		2014	H_{378}	1	m_z	$r_y^2 t x, r_y^2 t x^{-1}, m_x t x^{-1}, r_x^2 t y, m_y t y^{-1}, m_x r_z t z,$ $r_y^2 r_z t z^{-1}, m_x r_z t z^{-1}$
		2015	H_{378}	1	m_z	$r_y^2 t x, r_y^2 t x^{-1}, m_x t x^{-1}, m_y t y, m_y t y^{-1}, m_x r_z t z,$ $r_y^2 r_z t z^{-1}, m_x r_z t z^{-1}$
		2016	H_{378}	1	m_z	$r_y^2 t x, r_y^2 t x^{-1}, m_y t y, r_x^2 t y^{-1}, m_y t y^{-1}, m_x r_z t z,$ $r_y^2 r_z t z^{-1}, m_x r_z t z^{-1}$
		2017	H_{378}	1	m_z	$m_x t x, r_y^2 t x^{-1}, m_x t x^{-1}, m_y t y, r_x^2 t y^{-1}, m_x r_z t z,$ $r_y^2 r_z t z^{-1}, m_x r_z t z^{-1}$
		2018	H_{690}	$\langle m_x \rangle$	r_z^2	$r_z^2 t x, m_y t x^{-1}, m_x t y, m_y t y^{-1}, m_x t y^{-1}, r_y^2 r_z t z,$ $m_z r_z^{-1} t z, r_x^2 t z^{-1}$
		2019	H_{541}	1	r_z^2	$r_z^2 r_x t x, r_x t x, r_x^{-1} t x^{-1}, m_x t y, m_x t y^{-1}, i t z,$ $i t z^{-1}, m_z t z^{-1}$
		2020	H_{541}	1	r_z^2	$r_z^2 r_x t x, r_x t x, r_x^{-1} t x^{-1}, m_y t y, m_y t y^{-1}, i t z,$ $i t z^{-1}, m_z t z^{-1}$
		2021	H_{541}	1	r_z^2	$r_z^2 r_x t x, r_x t x, r_x^{-1} t x^{-1}, m_x t y, m_x t y^{-1}, m_z t z,$ $i t z^{-1}, m_z t z^{-1}$
		2022	H_{527}	1	r_z^2	$m_y t x, m_x t x^{-1}, m_y t x^{-1}, m_x t y, m_x t y^{-1}, r_y^2 r_z t z,$ $i t z^{-1}, m_z t z^{-1}$
		2023	H_{529}	1	r_z^2	$m_y t x, m_x t x^{-1}, m_y t x^{-1}, m_x t y, m_x t y^{-1}, r_y^2 r_z t z,$ $r_y^2 t z^{-1}, r_x^2 t z^{-1}$
		2024	H_{496}	1	r_z^2	$m_y t x, m_x t x^{-1}, m_y t x^{-1}, m_x t y, m_x t y^{-1}, r_y^2 r_z t z,$ $r_y^2 r_z t z^{-1}, r_x^2 r_z t z^{-1}$
		2025	H_{502}	1	r_z^2	$m_y t x, m_x t x^{-1}, m_y t x^{-1}, m_x t y, m_x t y^{-1}, m_z r_z^{-1} t z,$ $m_z r_z t z, r_y^2 r_z t z^{-1}$
[9, 35, 77, 132, 204, 292, 396, 516, 652, 804]						
		2026	H_{370}	1	m_z	$i t x, m_x t x^{-1}, r_x^2 t y, r_x^2 t y^{-1}, m_y t y^{-1}, m_y t z,$ $r_x^2 t z^{-1}, m_y t z^{-1}$
		2027	H_{370}	1	m_z	$i t x, m_x t x^{-1}, m_y t y, r_x^2 t y^{-1}, m_y t y^{-1}, m_y t z,$ $r_x^2 t z^{-1}, m_y t z^{-1}$
		2028	H_{370}	1	m_z	$r_x^2 t x, r_y^2 t x^{-1}, r_x^2 t y, r_x^2 t y^{-1}, m_y t y^{-1}, m_y t z,$ $r_x^2 t z^{-1}, m_y t z^{-1}$
		2029	H_{370}	1	m_z	$r_x^2 t x, r_y^2 t x^{-1}, m_y t y, r_x^2 t y^{-1}, m_y t y^{-1}, m_y t z,$ $r_x^2 t z^{-1}, m_y t z^{-1}$
		2030	H_{359}	1	m_z	$i t x, r_x^2 t x^{-1}, m_y t y, r_x^2 t y^{-1}, m_y t y^{-1}, t z,$ $m_z t z^{-1}, t z^{-1}$
		2031	H_{359}	1	m_z	$i t x, m_x t x^{-1}, r_x^2 t y, r_x^2 t y^{-1}, m_y t y^{-1}, t z,$ $m_z t z^{-1}, t z^{-1}$
		2032	H_{359}	1	m_z	$r_z^2 t x, r_y^2 t x^{-1}, r_x^2 t y, r_x^2 t y^{-1}, m_y t y^{-1}, t z,$ $m_z t z^{-1}, t z^{-1}$
[9, 35, 77, 133, 204, 292, 396, 516, 652, 804]						
		2033	H_{347}	1	m_z	$i t x, m_x r_z t z^{-1}, i t y, r_x^2 t y, m_x r_z t y^{-1}, m_x r_z^{-1} t z,$ $r_x^2 r_z t z^{-1}, m_x r_z^{-1} t z^{-1}$
		2034	H_{347}	1	m_z	$r_x^2 t x, m_x r_z t x^{-1}, i t y, r_x^2 t y, m_x r_z t y^{-1}, m_x r_z^{-1} t z,$ $r_x^2 r_z t z^{-1}, m_x r_z^{-1} t z^{-1}$
		2035	H_{343}	1	m_z	$i t x, m_x r_z t z^{-1}, i t y, r_x^2 t y, m_x r_z t y^{-1}, t z,$ $m_z t z^{-1}, t z^{-1}$
		2036	H_{511}	1	r_z^2	$r_x^2 r_x t x, r_x t x, r_x^{-1} t x^{-1}, r_x^2 t y, r_x^2 t y^{-1}, r_x^2 t z,$ $r_y^2 t z^{-1}, r_x^2 t z^{-1}$
[9, 35, 78, 132, 204, 292, 396, 516, 652, 804]						
		2037	H_{511}	1	r_z^2	$r_x^2 r_x t x, r_y^2 r_x t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_x^2 t y^{-1}, r_y^2 t z,$ $r_y^2 t z^{-1}, r_x^2 t z^{-1}$
		2038	H_{511}	1	r_z^2	$r_x t x, r_x^{-1} t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_x^2 t y^{-1}, r_y^2 t z,$ $r_y^2 t z^{-1}, r_x^2 t z^{-1}$
		2039	H_{541}	1	r_z^2	$r_x^2 r_x t x, r_y^2 r_x t x^{-1}, m_x t y, m_x t y^{-1}, m_y t y^{-1}, i t z,$ $i t z^{-1}, m_z t z^{-1}$
		2040	H_{541}	1	r_z^2	$r_x t x, r_x^{-1} t x^{-1}, m_x t y, m_x t y^{-1}, m_y t y^{-1}, i t z,$ $i t z^{-1}, m_z t z^{-1}$
[9, 35, 78, 133, 204, 292, 396, 516, 652, 804]						
		2041	H_{377}	1	m_z	$r_y^2 t x, m_x t x, m_z r_z^{-1} t x^{-1}, m_z r_z t y, m_y t y^{-1}, t z,$ $m_z t z^{-1}, t z^{-1}$
[9, 36, 76, 132, 204, 292, 396, 516, 652, 804]						
		2042	H_{361}	1	m_z	$i t x, i t x^{-1}, r_x^2 t x^{-1}, r_x^2 t y, i t y^{-1}, m_x t z,$ $r_y^2 t z^{-1}, m_x t z^{-1}$
		2043	H_{682}	$\langle m_x \rangle$	r_z^2	$i t x, r_x^2 t x^{-1}, m_x t y, m_y t y^{-1}, m_x t y^{-1}, r_y^2 t z,$ $r_x^2 t z^{-1}, r_y^2 t z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
		2044	H_{361}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, it_y^{-1}, m_x t_z,$ $r_z^2 t_z^{-1}, m_x t_z^{-1}$
		2045	H_{361}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_y, it_y^{-1}, r_z^2 t_y^{-1}, m_x t_z,$ $r_z^2 t_z^{-1}, m_x t_z^{-1}$
		2046	H_{330}	1	m_z	$r_z^2 t_x, it_x^{-1}, it_y, it_y^{-1}, r_z^2 t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
		2047	H_{682}	$\langle m_x \rangle$	r_z^2	$it_x, r_x^2 t_x^{-1}, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_x^2 t_z,$ $r_y^2 t_z, r_y^2 t_z^{-1}$
		2048	H_{372}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_x t_z,$ $r_y^2 t_z^{-1}, m_x t_z^{-1}$
		2049	H_{372}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_x t_z,$ $r_y^2 t_z^{-1}, m_x t_z^{-1}$
		2050	H_{372}	1	m_z	$r_z^2 t_x, it_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_x t_z,$ $r_y^2 t_z^{-1}, m_x t_z^{-1}$
		2051	H_{372}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_x^2 t_y, m_y t_y, m_y t_y^{-1}, m_x t_z,$ $r_y^2 t_z^{-1}, m_x t_z^{-1}$
		2052	H_{365}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_z,$ $r_y^2 t_z^{-1}, m_y t_z^{-1}$
		2053	H_{365}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_y t_z,$ $r_y^2 t_z^{-1}, m_y t_z^{-1}$
		2054	H_{365}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_x^2 t_y, m_y t_y, r_x^2 t_y^{-1}, m_y t_z,$ $r_y^2 t_z^{-1}, m_y t_z^{-1}$
		2055	H_{365}	1	m_z	$r_z^2 t_x, it_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_y t_z,$ $r_y^2 t_z^{-1}, m_y t_z^{-1}$
		2056	H_{365}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_x^2 t_y, m_y t_y, m_y t_y^{-1}, m_y t_z,$ $r_y^2 t_z^{-1}, m_y t_z^{-1}$
		2057	H_{350}	1	m_z	$it_x, it_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
		2058	H_{350}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
		2059	H_{350}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_x^2 t_y, m_y t_y, r_x^2 t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
		2060	H_{370}	1	m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_z,$ $r_y^2 t_z^{-1}, m_y t_z^{-1}$
		2061	H_{359}	1	m_z	$it_x, r_x^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
		2062	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z,$ $it_z^{-1}, m_z t_z^{-1}$
		2063	H_{541}	1	r_z^2	$r_x t_x, r_x^{-1} t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z,$ $it_z^{-1}, m_z t_z^{-1}$
[9, 36, 77, 132, 204, 292, 396, 516, 652, 804]						
		2064	H_{370}	1	m_z	$it_x, r_x^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_y t_z,$ $r_y^2 t_z^{-1}, m_y t_z^{-1}$
		2065	H_{370}	1	m_z	$it_x, r_x^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, m_y t_z,$ $r_y^2 t_z^{-1}, m_y t_z^{-1}$
		2066	H_{359}	1	m_z	$it_x, r_y^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
[9, 36, 77, 133, 204, 292, 396, 516, 652, 804]						
		2067	H_{343}	1	m_z	$r_z^2 t_x, r_y^2 r_z t_x^{-1}, it_y, r_z^2 t_y, r_y^2 r_z t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
[9, 36, 78, 133, 204, 292, 396, 516, 652, 804]						
		2068	H_{382}	1	m_z	$r_y^2 t_x, m_x t_x, m_z r_z^{-1} t_x^{-1}, m_z r_z t_y, r_x^2 t_y^{-1}, m_x r_z t_z,$ $r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
		2069	H_{382}	1	m_z	$r_y^2 t_x, m_x t_x, m_z r_z^{-1} t_x^{-1}, m_z r_z t_y, m_y t_y^{-1}, m_x r_z t_z,$ $r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
		2070	H_{377}	1	m_z	$r_y^2 t_x, m_x t_x, m_z r_z^{-1} t_x^{-1}, m_z r_z t_y, r_x^2 t_y^{-1}, t_z,$ $m_z t_z^{-1}, t_z^{-1}$
[9, 37, 76, 132, 204, 292, 396, 516, 652, 804]						
		2071	H_{683}	$\langle m_x \rangle$	r_z^2	$it_x, r_x^2 t_x^{-1}, r_y^2 t_y, r_x^2 t_y^{-1}, r_y^2 t_y^{-1}, r_x^2 t_z,$ $r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
		2072	H_{683}	$\langle m_x \rangle$	r_z^2	$it_x, r_x^2 t_x^{-1}, r_y^2 t_y, r_x^2 t_y^{-1}, r_y^2 t_y^{-1}, r_y^2 t_z,$ $r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
		2073	H_{332}	1	m_z	$r_z^2 t_x, it_x^{-1}, it_y, it_y^{-1}, r_z^2 t_y^{-1}, r_z^2 t_z,$ $it_z^{-1}, r_z^2 t_z^{-1}$
		2074	H_{332}	1	m_z	$r_z^2 t_x, it_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, it_y^{-1}, r_z^2 t_z,$ $it_z^{-1}, r_z^2 t_z^{-1}$
		2075	H_{682}	$\langle m_x \rangle$	r_z^2	$it_x, r_x^2 t_x^{-1}, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_x^2 t_z,$ $r_y^2 t_z, r_x^2 t_z^{-1}$

Nbr.	gr	N ₀	H _i	L	m	X
2076		H ₃₆₁	1	m _z	$r_z^2 t x, i t_x^{-1}, i t_y, i t_y^{-1}, r_z^2 t y^{-1}, m_x t z,$ $r_y^2 t z^{-1}, m_x t z^{-1}$	
2077		H ₃₄₄	1	m _z	$i t_x, i t_x^{-1}, r_z^2 t x^{-1}, i t_y, i t_y^{-1}, m_x r_z t z,$ $r_y^2 r_z t z^{-1}, m_x r_z t z^{-1}$	
2078		H ₃₄₄	1	m _z	$r_z^2 t x, i t_x^{-1}, r_z^2 t x^{-1}, i t_y, i t_y^{-1}, m_x r_z t z,$ $r_y^2 r_z t z^{-1}, m_x r_z t z^{-1}$	
2079		H ₃₄₄	1	m _z	$r_z^2 t x, i t_x^{-1}, i t_y, i t_y^{-1}, r_z^2 t y^{-1}, m_x r_z t z,$ $r_y^2 r_z t z^{-1}, m_x r_z t z^{-1}$	
2080		H ₃₄₄	1	m _z	$r_z^2 t x, i t_x^{-1}, i t_y, r_z^2 t y, i t_y^{-1}, m_x r_z t z,$ $r_y^2 r_z t z^{-1}, m_x r_z t z^{-1}$	
2081		H ₃₄₄	1	m _z	$r_z^2 t x, i t_x^{-1}, r_z^2 t x^{-1}, r_z^2 t y, i t_y^{-1}, m_x r_z t z,$ $r_y^2 r_z t z^{-1}, m_x r_z t z^{-1}$	
2082		H ₃₄₄	1	m _z	$i t_x, i t_x^{-1}, r_z^2 t x^{-1}, i t_y, r_z^2 t y^{-1}, m_x r_z t z,$ $r_y^2 r_z t z^{-1}, m_x r_z t z^{-1}$	
2083		H ₃₄₄	1	m _z	$i t_x, i t_x^{-1}, r_z^2 t x^{-1}, r_z^2 t y, r_z^2 t y^{-1}, m_x r_z t z,$ $r_y^2 r_z t z^{-1}, m_x r_z t z^{-1}$	
2084		H ₆₈₂	$\langle m_x \rangle$	r_z^2	$i t_x, r_x^2 t x^{-1}, m_x t y, m_y t y^{-1}, m_x t y^{-1}, r_x^2 t z,$ $r_x^2 t z^{-1}, r_y^2 t z^{-1}$	
2085		H ₆₈₃	$\langle m_x \rangle$	r_z^2	$i t_x, r_x^2 t x^{-1}, r_y^2 t y, r_x^2 t y^{-1}, r_y^2 t y^{-1}, r_x^2 t z,$ $r_y^2 t z^{-1}, r_x^2 t z^{-1}$	
2086		H ₆₈₃	$\langle m_x \rangle$	r_z^2	$i t_x, r_x^2 t x^{-1}, r_y^2 t y, r_x^2 t y^{-1}, r_y^2 t y^{-1}, r_x^2 t z,$ $r_y^2 t z^{-1}, r_x^2 t z^{-1}$	
2087		H ₃₆₄	1	m _z	$i t_x, i t_x^{-1}, r_z^2 t x^{-1}, m_y t y, r_x^2 t y^{-1}, r_z^2 t z,$ $i t_z^{-1}, r_z^2 t z^{-1}$	
2088		H ₃₆₄	1	m _z	$r_z^2 t x, i t_x^{-1}, r_z^2 t x^{-1}, m_y t y, r_x^2 t y^{-1}, r_z^2 t z,$ $i t_z^{-1}, r_z^2 t z^{-1}$	
2089		H ₃₆₄	1	m _z	$r_z^2 t x, i t_x^{-1}, r_x^2 t y, r_x^2 t y^{-1}, m_y t y^{-1}, r_z^2 t z,$ $i t_z^{-1}, r_z^2 t z^{-1}$	
2090		H ₃₆₄	1	m _z	$r_z^2 t x, i t_x^{-1}, r_x^2 t y, m_y t y, r_x^2 t y^{-1}, r_z^2 t z,$ $i t_z^{-1}, r_z^2 t z^{-1}$	
2091		H ₃₆₄	1	m _z	$r_z^2 t x, i t_x^{-1}, m_y t y, r_x^2 t y^{-1}, m_y t y^{-1}, r_z^2 t z,$ $i t_z^{-1}, r_z^2 t z^{-1}$	
2092		H ₃₆₄	1	m _z	$r_z^2 t x, i t_x^{-1}, r_x^2 t y, m_y t y, m_y t y^{-1}, r_z^2 t z,$ $i t_z^{-1}, r_z^2 t z^{-1}$	
2093		H ₃₇₂	1	m _z	$r_z^2 t x, i t_x^{-1}, r_x^2 t y, r_x^2 t y^{-1}, m_y t y^{-1}, m_x t z,$ $r_y^2 t z^{-1}, m_x t z^{-1}$	
2094		H ₃₇₂	1	m _z	$r_z^2 t x, i t_x^{-1}, r_x^2 t y, m_y t y, r_x^2 t y^{-1}, m_x t z,$ $r_y^2 t z^{-1}, m_x t z^{-1}$	
2095		H ₃₆₅	1	m _z	$i t_x, i t_x^{-1}, r_z^2 t x^{-1}, m_y t y, r_x^2 t y^{-1}, m_y t z,$ $r_x^2 t z^{-1}, m_y t z^{-1}$	
2096		H ₃₇₀	1	m _z	$i t_x, r_x^2 t x^{-1}, m_x t x^{-1}, m_y t y, r_x^2 t y^{-1}, m_y t z,$ $r_x^2 t z^{-1}, m_y t z^{-1}$	
2097		H ₄₅₃	1	r_z^2	$m_z t x, i t_x^{-1}, m_z t x^{-1}, i t_y, i t_y^{-1}, r_y^2 r_z t z,$ $r_y^2 r_z t z^{-1}, r_x^2 r_z t z^{-1}$	
2098		H ₅₃₉	1	r_z^2	$i t_x, i t_x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_x^2 t y^{-1}, m_z r_z^{-1} t z,$ $m_z r_z t z, r_y^2 r_z t z^{-1}$	
2099		H ₅₃₉	1	r_z^2	$m_z t x, i t_x^{-1}, m_z t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, m_z r_z^{-1} t z,$ $m_z r_z t z, r_y^2 r_z t z^{-1}$	
2100		H ₄₅₂	1	r_z^2	$t x, r_z^2 t x^{-1}, t_x^{-1}, r_z^2 t y, r_z^2 t y^{-1}, r_y^2 r_z t z,$ $i t_z^{-1}, m_z t z^{-1}$	
2101		H ₅₀₃	1	r_z^2	$t x, r_z^2 t x^{-1}, t_x^{-1}, r_z^2 t y, r_z^2 t y^{-1}, r_y^2 r_z t z,$ $r_y^2 t z^{-1}, r_x^2 t z^{-1}$	
2102		H ₄₃₈	1	r_z^2	$t x, r_z^2 t x^{-1}, t_x^{-1}, r_z^2 t y, r_z^2 t y^{-1}, r_y^2 r_z t z,$ $r_y^2 r_z t z^{-1}, r_x^2 r_z t z^{-1}$	
2103		H ₄₉₅	1	r_z^2	$t x, r_z^2 t x^{-1}, t_x^{-1}, r_z^2 t y, r_z^2 t y^{-1}, m_z r_z^{-1} t z,$ $m_z r_z t z, r_y^2 r_z t z^{-1}$	
2104		H ₅₁₁	1	r_z^2	$r_z^2 r_x t x, r_y^2 r_x t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_x^2 t y^{-1}, r_x^2 t z,$ $r_y^2 t z^{-1}, r_x^2 t z^{-1}$	
2105		H ₅₁₁	1	r_z^2	$r_z^2 r_x t x, r_x t x, r_x^{-1} t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_y^2 t z,$ $r_y^2 t z^{-1}, r_x^2 t z^{-1}$	
2106		H ₅₁₁	1	r_z^2	$r_z^2 r_x t x, r_x t x, r_x^{-1} t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_x^2 t z,$ $r_y^2 t z^{-1}, r_x^2 t z^{-1}$	
2107		H ₅₁₁	1	r_z^2	$r_z^2 r_x t x, r_x t x, r_x^{-1} t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_y^2 t z,$ $r_y^2 t z^{-1}, r_x^2 t z^{-1}$	
2108		H ₅₁₁	1	r_z^2	$r_x t x, r_x^{-1} t x^{-1}, r_y^2 t y, r_y^2 t y^{-1}, r_x^2 t y^{-1}, r_x^2 t z,$ $r_y^2 t z^{-1}, r_x^2 t z^{-1}$	

Nbr.	gr	N ₀	H_i	L	m	X
		2136*				
[6, 22, 61, 121, 195, 285, 390, 510, 646, 798]		2137*				
[6, 23, 62, 120, 192, 280, 384, 504, 640, 792]		2138*				
[6, 23, 62, 122, 196, 284, 388, 508, 644, 796]		2139*				
[6, 23, 62, 124, 196, 284, 388, 508, 644, 796]		2140*				
[6, 23, 64, 126, 200, 288, 392, 512, 648, 800]		2141*				
[6, 23, 66, 128, 201, 290, 393, 512, 648, 800]		2142*				
[6, 23, 67, 129, 200, 288, 392, 512, 648, 800]		2143*				
[6, 24, 60, 112, 180, 264, 364, 480, 612, 760]		2144*				
[6, 24, 62, 120, 194, 282, 386, 506, 642, 794]		2145*				
[6, 24, 63, 120, 192, 280, 384, 504, 640, 792]		2146*				
[6, 24, 65, 123, 194, 282, 386, 506, 642, 794]		2147*				
[6, 24, 65, 124, 195, 282, 386, 506, 642, 794]		2148*				
[6, 24, 65, 124, 196, 284, 388, 508, 644, 796]		2149*				
[6, 25, 68, 128, 200, 288, 392, 512, 648, 800]		2150*, 2151*				
[6, 25, 69, 129, 200, 288, 392, 512, 648, 800]		2152*				
[6, 26, 67, 124, 196, 284, 388, 508, 644, 796]		2153*				
[6, 26, 68, 125, 196, 284, 388, 508, 644, 796]		2154*				
[6, 26, 68, 126, 198, 286, 390, 510, 646, 798]		2155*				
[6, 27, 70, 128, 200, 288, 392, 512, 648, 800]		2156*				
[6, 28, 70, 126, 198, 286, 390, 510, 646, 798]		2157*				
[7, 24, 58, 110, 178, 262, 362, 478, 610, 758]		2130	H_{651}	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_z, m_x r_x t_z, m_y t_z^{-1}$
[7, 25, 59, 109, 175, 257, 355, 469, 599, 745]		2131	H_{646}	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, m_x t_y, m_z r_x t_y^{-1}, m_x t_y^{-1}, m_z r_x t_z$
[7, 26, 66, 124, 196, 284, 388, 508, 644, 796]		2132	H_{581}	1	$m_z r_x$	$r_z^2 r_x t_x, m_x t_x^{-1}, r_x^{-1} t_y^{-1}, m_y t_z, r_x t_z, m_y t_z^{-1}$
[7, 26, 67, 126, 199, 288, 392, 512, 648, 800]		2133	H_{581}	1	$m_z r_x$	$i t_x, m_x t_x^{-1}, r_x^{-1} t_y^{-1}, m_y t_z, r_x t_z, m_y t_z^{-1}$
[7, 26, 67, 128, 201, 290, 394, 514, 650, 802]		2134	H_{423}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x r_x t_y^{-1}, m_y t_z, m_x r_x^{-1} t_z^{-1}, m_y t_z^{-1}$
[7, 27, 65, 119, 189, 275, 377, 495, 629, 779]		2135	H_{552}	1	$m_z r_x$	$r_z^2 r_x t_x, m_x t_x^{-1}, t_y, m_z r_x t_y^{-1}, t_y^{-1}, m_z r_x t_z$
[7, 27, 66, 121, 193, 282, 386, 506, 642, 794]		2136	H_{552}	1	$m_z r_x$	$i t_x, m_x t_x^{-1}, t_y, m_z r_x t_y^{-1}, t_y^{-1}, m_z r_x t_z$
[7, 27, 70, 127, 200, 289, 393, 513, 649, 801]		2137	H_{406}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 t_x^{-1}, t_y, r_z^2 r_x t_y^{-1}, t_y^{-1}, r_z^2 r_x t_z^{-1}$
[7, 28, 70, 126, 198, 286, 390, 510, 646, 798]		2138	H_{653}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_z, m_x r_x t_z, m_y t_z^{-1}$
[7, 28, 70, 128, 200, 288, 392, 512, 648, 800]		2139	H_{579}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_x^{-1} t_y^{-1}, m_y t_z, r_x t_z, m_y t_z^{-1}$
[7, 28, 70, 130, 198, 290, 390, 514, 646, 802]		2140	H_{577}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, r_z^2 t_z, m_x r_x t_z, r_z^2 t_z^{-1}$
[7, 28, 72, 130, 202, 290, 394, 514, 650, 802]		2141	H_{653}	$\langle m_x \rangle$	$r_y^2 r_x$	$i t_x, r_z^2 t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_z, m_x r_x t_z, m_y t_z^{-1}$
[7, 28, 74, 130, 203, 291, 394, 514, 650, 802]		2142	H_{573}	1	$m_z r_x$	$r_z^2 r_x t_x, i t_x^{-1}, m_x r_x^{-1} t_y^{-1}, t_z^2 t_z, m_x r_x t_z, r_z^2 t_z^{-1}$
[7, 28, 75, 130, 202, 290, 394, 514, 650, 802]		2143	H_{575}	1	$m_z r_x$	$r_z^2 r_x t_x, i t_x^{-1}, r_x^{-1} t_y^{-1}, m_y t_z, r_x t_z, m_y t_z^{-1}$
[7, 29, 67, 121, 191, 277, 379, 497, 631, 781]		2144	H_{647}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_y, m_z r_x t_y^{-1}, m_x t_y^{-1}, m_z r_x t_z$
[7, 29, 69, 127, 199, 287, 391, 511, 647, 799]		2145	H_{647}	$\langle m_x \rangle$	$r_y^2 r_x$	$i t_x, r_z^2 t_x^{-1}, m_x t_y, m_z r_x t_y^{-1}, m_x t_y^{-1}, m_z r_x t_z$
[7, 29, 70, 126, 198, 286, 390, 510, 646, 798]		2146	H_{546}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, t_y, m_z r_x t_y^{-1}, t_y^{-1}, m_z r_x t_z$
[7, 29, 72, 127, 199, 287, 391, 511, 647, 799]		2147	H_{549}	1	$m_z r_x$	$r_z^2 r_x t_x, i t_x^{-1}, t_y, m_z r_x t_y^{-1}, t_y^{-1}, m_z r_x t_z$
[7, 29, 72, 128, 199, 287, 391, 511, 647, 799]		2148	H_{554}	1	$m_z r_x$	$r_z^2 r_x t_x, i t_x^{-1}, m_x t_y, r_y^2 r_x t_y^{-1}, m_x t_y^{-1}, r_y^2 r_x t_z$
[7, 29, 72, 128, 200, 288, 392, 512, 648, 800]		2149	H_{548}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_y, r_y^2 r_x t_y^{-1}, m_x t_y^{-1}, r_y^2 r_x t_z$
[7, 30, 74, 130, 202, 290, 394, 514, 650, 802]		2150	H_{423}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, m_x r_x t_y^{-1}, m_y t_z, m_x r_x^{-1} t_z^{-1}, m_y t_z^{-1}$

Nbr.	gr	N ₀	H _i	L	m	X
		2151	H ₅₈₁	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_x^{-1} t_y^{-1}, m_y t_z, r_x t_z, m_y t_z^{-1}$
	[7, 30, 75, 130, 202, 290, 394, 514, 650, 802]	2152	H ₅₈₁	1	$m_z r_x$	$i t_x, r_y^2 r_x t_x^{-1}, r_x^{-1} t_y^{-1}, m_y t_z, r_x t_z, m_y t_z^{-1}$
	[7, 31, 72, 128, 200, 288, 392, 512, 648, 800]	2153	H ₅₅₂	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, t_y, m_z r_x t_y^{-1}, t_y^{-1}, m_z r_x t_z$
	[7, 31, 73, 128, 200, 288, 392, 512, 648, 800]	2154	H ₅₅₂	1	$m_z r_x$	$i t_x, r_y^2 r_x t_x^{-1}, t_y, m_z r_x t_y^{-1}, t_y^{-1}, m_z r_x t_z$
	[7, 31, 73, 129, 201, 289, 393, 513, 649, 801]	2155	H ₄₀₆	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, t_y, r_z^2 r_x t_y^{-1}, t_y^{-1}, r_z^2 r_x t_z^{-1}$
	[7, 32, 74, 130, 202, 290, 394, 514, 650, 802]	2156	H ₆₅₁	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_z r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_z, m_x r_x t_z, m_y t_z^{-1}$
	[7, 33, 73, 129, 201, 289, 393, 513, 649, 801]	2157	H ₆₄₆	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_z r_x t_x^{-1}, m_x t_y, m_z r_x t_y^{-1}, m_x t_y^{-1}, m_z r_x t_z$
39A						
	[8, 28, 64, 116, 184, 268, 368, 484, 616, 764]	2158*				
	[8, 29, 67, 121, 191, 277, 379, 497, 631, 781]	2159*				
	[8, 29, 68, 124, 196, 284, 388, 508, 644, 796]	2160*, 2161*, 2162*				
	[8, 29, 68, 125, 198, 286, 390, 510, 646, 798]	2163*				
	[8, 29, 68, 125, 199, 288, 392, 512, 648, 800]	2164*				
	[8, 30, 70, 126, 198, 286, 390, 510, 646, 798]	2165*				
	[8, 30, 71, 128, 200, 288, 392, 512, 648, 800]	2166*, 2167*, 2168*, 2169*, 2170*, 2171*,				
	[8, 30, 71, 129, 203, 292, 396, 516, 652, 804]	2172*				
	[8, 30, 72, 130, 202, 290, 394, 514, 650, 802]	2173*				
	[8, 31, 72, 128, 200, 288, 392, 512, 648, 800]	2174*, 2175*, 2176*, 2177*, 2178*, 2179*, 2180*, 2181*, 2182*, 2183*,				
	[8, 31, 73, 130, 202, 290, 394, 514, 650, 802]	2184*, 2185*, 2186*, 2187*,				
	[8, 31, 73, 131, 204, 292, 396, 516, 652, 804]	2188*				
	[8, 31, 74, 131, 202, 290, 394, 514, 650, 802]	2189*				
	[8, 31, 74, 132, 204, 292, 396, 516, 652, 804]	2190*, 2191*, 2192*, 2193*, 2194*, 2195*,				
	[8, 32, 74, 130, 202, 290, 394, 514, 650, 802]	2196*, 2197*, 2198*, 2199*, 2200*, 2201*,				
	[8, 32, 75, 132, 204, 292, 396, 516, 652, 804]	2202*, 2203*, 2204*, 2205*, 2206*, 2207*, 2208*, 2209*, 2210*, 2211*, 2212*, 2213*,				
	[8, 32, 76, 133, 204, 292, 396, 516, 652, 804]	2214*				
	[8, 33, 76, 132, 204, 292, 396, 516, 652, 804]	2215*, 2216*, 2217*, 2218*, 2219*, 2220*, 2221*, 2222*, 2223*, 2224*, 2225*, 2226*, 2227*,				
	[9, 31, 69, 123, 193, 279, 381, 499, 633, 783]	2228*, 2229*, 2230*, 2231*,				
		2158	H ₇₄₅	$\langle m_z r_x^{-1}, r_z^2 r_x \rangle$	i	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_y, m_z r_x t_y^{-1}, m_x t_y^{-1}, r_x^2 t_z, r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$
	[9, 32, 71, 126, 197, 284, 387, 506, 641, 792]	2159	H ₃₀₅	1	i	$t_x, i t_x^{-1}, t_x^{-1}, t_y, t_y^{-1}, m_x r_z^{-1} t_z, r_y^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
	[9, 32, 72, 128, 200, 288, 392, 512, 648, 800]	2160	H ₆₁₅	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, t_z^{-1}$
		2161	H ₇₄₇	$\langle m_z r_x^{-1}, r_z^2 r_x \rangle$	i	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, r_y^2 t_y, m_x r_x^{-1} t_y^{-1}, r_y^2 t_y^{-1}, m_x r_x^{-1} t_z, r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$
		2162	H ₄₆₀	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 t_z, m_z t_z^{-1}$
	[9, 32, 72, 129, 201, 289, 393, 513, 649, 801]	2163	H ₅₀₄	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_y t_y, r_x^2 r_y t_y^{-1}, r_y^{-1} t_y^{-1}, t_z, t_z^{-1}$
	[9, 32, 72, 129, 202, 290, 394, 514, 650, 802]	2164	H ₅₀₃	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_x^2 r_z t_z, r_y^2 t_z^{-1}$
	[9, 33, 73, 129, 201, 289, 393, 513, 649, 801]	2165	H ₆₁₄	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 t_z, m_x t_z^{-1}$
	[9, 33, 74, 130, 202, 290, 394, 514, 650, 802]	2166	H ₆₂₉	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, t_y, m_z r_x t_y^{-1}, t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z, m_z r_x^{-1} t_z^{-1}$
		2167	H ₄₆₁	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, m_z t_z^{-1}$
		2168	H ₄₆₁	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z, m_z t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
		2169	H_{483}	1	r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_y^2 t_z, m_z t_z^{-1}$
		2170	H_{531}	1	r_z^2	$m_x r_z t_x, m_x r_z t_x^{-1}, m_x r_z^{-1} t_x^{-1}, m_x r_z t_y, m_x r_z^{-1} t_y, m_x r_z t_y^{-1},$ $r_y^2 t_z, m_z t_z^{-1}$
		2171	H_{533}	1	r_z^2	$m_x r_z t_x, m_x r_z t_x^{-1}, m_x r_z^{-1} t_x^{-1}, m_x r_z t_y, m_x r_z^{-1} t_y, m_x r_z t_y^{-1},$ $r_y^2 r_z t_z, r_y^2 t_z^{-1}$
[9, 33, 74, 131, 204, 292, 396, 516, 652, 804]						
		2172	H_{529}	1	r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1},$ $r_y^2 r_z t_z, r_y^2 t_z^{-1}$
[9, 33, 75, 131, 203, 291, 395, 515, 651, 803]						
		2173	H_{669}	$\langle r_y^2 r_x \rangle$	$r_z^2 r_x$	$r_y^2 t_x, r_y^2 t_x^{-1}, t_y, r_x^2 t_y^{-1}, t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z^{-1}, r_y^2 r_x t_z^{-1}$
[9, 34, 74, 130, 202, 290, 394, 514, 650, 802]						
		2174	H_{616}	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_y^2 t_z, m_x t_z^{-1}$
		2175	H_{616}	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z, m_y t_z^{-1}$
		2176	H_{618}	$\langle m_z \rangle$	r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z, m_x t_z^{-1}$
		2177	H_{308}	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, m_z t_y, m_z t_y^{-1}, m_x r_z^{-1} t_z,$ $r_y^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
		2178	H_{323}	1	i	$r_z^2 t_x, r_z^2 t_x^{-1}, m_x r_y t_y, r_x^2 r_y t_y^{-1}, m_x r_y t_y^{-1}, m_x t_z,$ $m_x t_z^{-1}, r_x^2 t_z^{-1}$
		2179	H_{323}	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, m_x r_y t_y, r_x^2 r_y t_y^{-1}, m_x r_y t_y^{-1},$ $m_x t_z, m_x t_z^{-1}$
		2180	H_{326}	1	i	$m_z r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_z^2 t_z,$ $r_x^2 t_z^{-1}, m_z t_z^{-1}$
		2181	H_{540}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_y t_y, r_x^2 r_y t_y^{-1}, r_y^{-1} t_y^{-1},$ $m_y t_z, m_y t_z^{-1}$
		2182	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 t_z, r_y^2 t_z^{-1}$
		2183	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $m_z t_z, m_z t_z^{-1}$
[9, 34, 75, 131, 203, 291, 395, 515, 651, 803]						
		2184	H_{433}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1},$ $m_z t_z, i t_z^{-1}$
		2185	H_{462}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}$
		2186	H_{460}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1},$ $r_y^2 t_z, i t_z^{-1}$
		2187	H_{503}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, t_y, r_z^2 t_y^{-1}, t_y^{-1},$ $r_y^2 r_z t_z, r_y^2 t_z^{-1}$
[9, 34, 75, 132, 204, 292, 396, 516, 652, 804]						
		2188	H_{540}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_y t_y, r_x^2 r_y t_y^{-1}, r_y^{-1} t_y^{-1},$ $m_x t_z, m_x t_z^{-1}$
[9, 34, 76, 131, 203, 291, 395, 515, 651, 803]						
		2189	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, i t_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1}$
[9, 34, 76, 132, 204, 292, 396, 516, 652, 804]						
		2190	H_{675}	$\langle r_y^2 r_x \rangle$	$r_z^2 r_x$	$r_y^2 t_x, r_z^2 t_x^{-1}, m_x r_x^{-1} t_y, m_z t_y^{-1}, m_y t_y^{-1}, m_y t_z,$ $m_x r_x^{-1} t_z^{-1}, m_x r_x t_z^{-1}$
		2191	H_{468}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $m_z t_z, i t_z^{-1}$
		2192	H_{469}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}$
		2193	H_{640}	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_z t_y, r_x^{-1} t_y^{-1}, m_z t_y^{-1}, r_x^{-1} t_z,$ $m_z t_z, r_x^{-1} t_z^{-1}$
		2194	H_{535}	1	r_z^2	$r_z t_x, r_z^{-1} t_x^{-1}, r_z t_x^{-1}, r_z^{-1} t_y, r_z t_y, r_z^{-1} t_y^{-1},$ $r_y^2 t_z, m_z t_z^{-1}$
		2195	H_{512}	1	r_z^2	$r_z t_x, r_z^{-1} t_x^{-1}, r_z t_x^{-1}, r_z^{-1} t_y, r_z t_y, r_z^{-1} t_y^{-1},$ $r_y^2 r_z t_z, r_y^2 t_z^{-1}$
[9, 35, 75, 131, 203, 291, 395, 515, 651, 803]						
		2196	H_{745}	$\langle m_z r_x^{-1}, r_z^2 r_x \rangle$	i	$r_y^2 r_x t_x, m_z r_x t_x^{-1}, m_x t_y, m_z r_x t_y^{-1}, m_x t_y^{-1}, r_x^2 t_z,$ $r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$
		2197	H_{631}	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_y, r_y^2 r_x t_y^{-1}, m_x t_y^{-1}, i t_z,$ $r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$
		2198	H_{674}	$\langle r_y^2 r_x \rangle$	$r_z^2 r_x$	$r_y^2 t_x, r_y^2 t_x^{-1}, m_z r_x t_y, i t_y^{-1}, m_x t_y^{-1}, m_x t_z,$ $m_z r_x^{-1} t_z^{-1}, m_z r_x t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
		2199	H_{624}	$\langle m_z \rangle$	r_z^2	$m_x r_z t_x, m_x r_z t_x^{-1}, m_x r_z^{-1} t_x^{-1}, m_x r_z t_y, m_x r_z^{-1} t_y, m_x r_z t_y^{-1},$ $r_y^2 t_z, m_x t_z^{-1}$
		2200	H_{531}	1	r_z^2	$m_x r_z t_x, m_x r_z t_x^{-1}, m_x r_z^{-1} t_x^{-1}, m_x r_z t_y, m_x r_z^{-1} t_y, m_x r_z t_y^{-1},$ $r_y^2 t_z, i t_z^{-1}$
		2201	H_{533}	1	r_z^2	$m_x r_z^{-1} t_x, m_x r_z t_x^{-1}, m_x r_z^{-1} t_x^{-1}, m_x r_z^{-1} t_y, m_x r_z t_y^{-1}, m_x r_z^{-1} t_y^{-1},$ $r_y^2 r_z t_z, r_y^2 t_z^{-1}$
[9, 35, 76, 132, 204, 292, 396, 516, 652, 804]						
		2202	H_{475}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $m_z t_z, i t_z^{-1}$
		2203	H_{485}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}$
		2204	H_{466}	1	r_z^2	$t_x, r_x^2 t_x^{-1}, t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1},$ $m_z t_z, i t_z^{-1}$
		2205	H_{427}	1	r_z^2	$t_x, r_x^2 t_x^{-1}, t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}$
		2206	H_{461}	1	r_z^2	$t_x, r_x^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_y^2 t_z, i t_z^{-1}$
		2207	H_{461}	1	r_z^2	$t_x, r_x^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z, i t_z^{-1}$
		2208	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $m_z t_z, i t_z^{-1}$
		2209	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1},$ $m_z t_z, i t_z^{-1}$
		2210	H_{486}	1	r_z^2	$r_x^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $m_z t_z, i t_z^{-1}$
		2211	H_{479}	1	r_z^2	$r_x^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}$
		2212	H_{483}	1	r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_y^2 t_z, i t_z^{-1}$
		2213	H_{529}	1	r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_y^2 r_z t_z, r_y^2 t_z^{-1}$
[9, 35, 77, 132, 204, 292, 396, 516, 652, 804]						
		2214	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, r_x^{-1} t_z,$ $m_z t_z, m_x r_x^{-1} t_z^{-1}$
[9, 36, 76, 132, 204, 292, 396, 516, 652, 804]						
		2215	H_{615}	$\langle m_z \rangle$	r_z^2	$t_x, r_x^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $i t_z, r_y^2 t_z^{-1}$
		2216	H_{305}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, i t_y, i t_y^{-1}, m_x r_x^{-1} t_z,$ $r_y^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
		2217	H_{747}	$\langle m_z r_x^{-1}, r_z^2 r_x \rangle$	i	$r_y^2 r_x t_x, m_z r_x t_x^{-1}, r_y^2 t_y, m_x r_x^{-1} t_y^{-1}, r_y^2 t_y^{-1}, m_x r_x^{-1} t_z,$ $r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$
		2218	H_{308}	1	i	$m_z t_x, r_x^2 t_x^{-1}, m_z t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_x r_x^{-1} t_z,$ $r_y^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
		2219	H_{326}	1	i	$m_z r_x t_x, r_x^2 r_x t_x^{-1}, m_z r_x t_x^{-1}, r_x^2 t_y, r_y^2 t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}$
		2220	H_{473}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1},$ $m_z t_z, i t_z^{-1}$
		2221	H_{474}	1	r_z^2	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}$
		2222	H_{504}	1	r_z^2	$t_x, r_x^2 t_x^{-1}, t_x^{-1}, r_y t_y, r_x^2 r_y t_y^{-1}, r_y^{-1} t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}$
		2223	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}$
		2224	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_y^2 t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}$
		2225	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}$
		2226	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $i t_z, i t_z^{-1}$
		2227	H_{639}	$\langle m_z r_x^{-1} \rangle$	r_z^2	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_y^2 t_y, m_x r_x^{-1} t_y^{-1}, r_y^2 t_y^{-1}, m_x r_x^{-1} t_z,$ $r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$
		2228	H_{671}	$\langle r_y^2 r_x \rangle$	$r_z^2 r_x$	$r_y^2 t_x, r_x^2 t_x^{-1}, r_x^{-1} t_y, r_x^2 t_y^{-1}, r_y^2 t_y^{-1}, r_x^2 t_z,$ $r_x t_z^{-1}, r_x^{-1} t_z^{-1}$
		2229	H_{626}	$\langle m_z \rangle$	r_z^2	$r_z t_x, r_x^{-1} t_x^{-1}, r_z t_x^{-1}, r_z^{-1} t_y, r_z t_y, r_z^{-1} t_y^{-1},$ $r_y^2 t_z, m_x t_z^{-1}$
		2230	H_{535}	1	r_z^2	$r_z t_x, r_z^{-1} t_x^{-1}, r_z t_x^{-1}, r_z^{-1} t_y, r_z t_y, r_z^{-1} t_y^{-1},$ $r_y^2 t_z, i t_z^{-1}$

Nbr.	gr	Nº	H_i	L	m	X
39B		2231	H_{512}	1	r_z^2	$r_x^{-1}tx, r_z^{-1}t_x^{-1}, r_ztx^{-1}, r_zty, r_z^{-1}t_y^{-1}, r_ztx^{-1}, r_y^2r_ztz, r_y^2t_z^{-1}$
		[8, 31, 74, 132, 204, 292, 396, 516, 652, 804] 2232*,				
		[8, 33, 78, 134, 204, 292, 396, 516, 652, 804] 2233*,				
		[8, 34, 78, 133, 204, 292, 396, 516, 652, 804] 2234*, 2235*,				
		[8, 35, 78, 132, 204, 292, 396, 516, 652, 804] 2236*, 2237*,				
		[9, 34, 76, 132, 204, 292, 396, 516, 652, 804]				
		2232	H_{779}	$\langle i, r_x^2, r_z^2 \rangle$	$r_z^2 r_x$	$m_x tx, t_x^{-1}, m_y ty, m_x r_x^{-1} ty, t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z, m_x r_x t_z^{-1}$
		[9, 36, 78, 132, 204, 292, 396, 516, 652, 804]				
		2233	H_{766}	$\langle m_y, r_x^2 \rangle$	$m_z r_x^{-1}$	$r_z^2 r_x tx, m_x t_x^{-1}, m_y ty, r_x^{-1} ty, t_y^{-1}, m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z, r_x t_z^{-1}$
		[9, 37, 77, 132, 204, 292, 396, 516, 652, 804]				
40		2234	H_{561}	1	$m_z r_x$	$m_x tx, r_y^2 r_x t_x^{-1}, r_x^2 ty, m_z r_x^{-1} ty, i t_y^{-1}, r_z^2 r_x t_y^{-1}, m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1}$
		2235	H_{571}	1	$m_z r_x$	$m_x tx, r_y^2 r_x t_x^{-1}, m_y ty, r_x ty, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$
		[9, 38, 76, 132, 204, 292, 396, 516, 652, 804]				
		2236	H_{779}	$\langle i, r_x^2, r_z^2 \rangle$	$r_z^2 r_x$	$m_z r_x^{-1} tx, r_z^2 r_x t_x^{-1}, m_y ty, m_x r_x^{-1} ty, t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z, m_x r_x t_z^{-1}$
		2237	H_{768}	$\langle m_y, r_x^2 \rangle$	$m_z r_x^{-1}$	$r_z^2 r_x tx, m_x t_x^{-1}, r_z^2 ty, m_x r_x^{-1} ty, m_x t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z, m_x r_x t_z^{-1}$
		[9, 32, 72, 128, 200, 288, 392, 512, 648, 800] 2238*, 2239*, 2240*,				
		[9, 33, 75, 132, 204, 292, 396, 516, 652, 804] 2241*, 2242*, 2243*, 2244*, 2245*, 2246*, 2247*, 2248*,				
		[9, 34, 76, 132, 204, 292, 396, 516, 652, 804] 2249*, 2250*, 2251*, 2252*, 2253*, 2254*, 2255*, 2256*, 2257*, 2258*, 2259*, 2260*, 2261*, 2262*, 2263*, 2264*, 2265*, 2266*, 2267*, 2268*, 2269*,				
		[10, 34, 74, 130, 202, 290, 394, 514, 650, 802]				
		2238	H_{749}	$\langle m_y, r_z^2 \rangle$	i	$r_y^2 tx, r_z^2 tx, m_z t_x^{-1}, r_z^2 t_x^{-1}, r_z^2 ty, r_z^2 t_y^{-1}, r_z^2 t_z, m_z t_z^{-1}, r_z^2 t_z^{-1}$
		2239	H_{750}	$\langle m_y, m_z \rangle$	r_z^2	$m_y tx, m_x t_x^{-1}, m_y t_x^{-1}, m_y ty, m_y t_y^{-1}, r_y^2 r_z tz, m_z r_z tz, m_x r_z t_z^{-1}, r_z t_z^{-1}$
		2240	H_{690}	$\langle m_x \rangle$	r_z^2	$m_x tx, m_x t_x^{-1}, m_x ty, m_y t_y^{-1}, m_x t_y^{-1}, r_y^2 r_z tz, m_z r_z^{-1} t_z, r_z^2 t_z^{-1}, r_y^2 t_z^{-1}$
		[10, 35, 76, 132, 204, 292, 396, 516, 652, 804]				
		2241	H_{682}	$\langle m_x \rangle$	r_z^2	$itx, r_y^2 tx, r_z^2 t_x^{-1}, r_z^2 t_x^{-1}, m_x ty, m_y t_y^{-1}, m_x t_y^{-1}, r_y^2 tz, r_z^2 t_z^{-1}$
		2242	H_{680}	$\langle m_x \rangle$	r_z^2	$r_z^2 tx, m_x tx, m_y t_x^{-1}, m_x t_x^{-1}, m_x ty, m_y t_y^{-1}, m_x t_y^{-1}, r_y^2 tz, r_z^2 t_z^{-1}$
		2243	H_{359}	1	m_z	$itx, r_z^2 tx, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y ty, r_z^2 t_y^{-1}, t_z, m_z t_z^{-1}, t_z^{-1}$
		2244	H_{452}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 ty, ty, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 r_z tz, m_z t_z^{-1}$
		2245	H_{503}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 ty, ty, r_z^2 t_y^{-1}, t_y^{-1}, r_y^2 r_z tz, r_z^2 t_z^{-1}$
		2246	H_{541}	1	r_z^2	$r_z^2 r_x tx, r_x tx, r_y^2 r_x t_x^{-1}, r_x^{-1} t_x^{-1}, m_x ty, m_x t_y^{-1}, m_y t_y^{-1}, m_z tz, it_z^{-1}$
		2247	H_{527}	1	r_z^2	$m_x tx, m_y ty, m_x t_x^{-1}, m_y t_x^{-1}, m_x ty, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z tz, m_z t_z^{-1}$
		2248	H_{529}	1	r_z^2	$m_x tx, m_y ty, m_x t_x^{-1}, m_y t_x^{-1}, m_x ty, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z tz, r_y^2 t_z^{-1}$
		[10, 36, 76, 132, 204, 292, 396, 516, 652, 804]				
		2249	H_{749}	$\langle m_y, r_z^2 \rangle$	i	$r_y^2 tx, r_z^2 tx, m_z t_x^{-1}, r_z^2 t_x^{-1}, r_z^2 ty, m_z t_y^{-1}, r_z^2 t_z, m_z t_z^{-1}, r_z^2 t_z^{-1}$
		2250	H_{604}	$\langle r_y^2 \rangle$	r_z^2	$itx, m_x tx, m_y t_x^{-1}, m_x t_x^{-1}, m_x ty, m_y t_y^{-1}, m_x t_y^{-1}, r_z^2 r_z tz, r_z t_z^{-1}$
		2251	H_{750}	$\langle m_y, m_z \rangle$	r_z^2	$m_y tx, m_x t_x^{-1}, m_y t_x^{-1}, r_z^2 ty, m_x t_y^{-1}, r_y^2 r_z tz, m_z r_z t_z^{-1}, r_z t_z^{-1}$
		2252	H_{750}	$\langle m_y, r_z^2 \rangle$	i	$r_y^2 tx, r_z^2 tx, m_z t_x^{-1}, r_z^2 t_x^{-1}, r_z^2 ty, m_z t_y^{-1}, m_x r_z tz, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
		2253	H_{750}	$\langle m_y, r_z^2 \rangle$	i	$r_y^2 tx, r_z^2 tx, m_z t_x^{-1}, r_z^2 t_x^{-1}, r_z^2 ty, r_z^2 t_y^{-1}, m_x r_z tz, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
		2254	H_{598}	$\langle r_y^2 \rangle$	r_z^2	$r_z^2 tx, r_y^2 tx, r_z^2 t_x^{-1}, r_z^2 t_x^{-1}, r_y^2 ty, r_z^2 t_y^{-1}, r_z^2 t_y^{-1}, r_x^2 r_z tz, r_z t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
2255			H_{611}	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y, t_y, r_z^2 t_y^{-1},$ $t_y^{-1}, r_z^2 r_z t_z, m_x r_z t_z^{-1}$
2256			H_{622}	$\langle m_z \rangle$	r_z^2	$m_x t_x, m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1},$ $m_y t_y^{-1}, r_z^2 r_z t_z, m_x r_z t_z^{-1}$
2257			H_{683}	$\langle m_x \rangle$	r_z^2	$it_x, r_z^2 t_x, r_x^2 t_x^{-1}, r_z^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1},$ $r_z^2 t_y^{-1}, r_z^2 t_z, r_x^2 t_z^{-1}, r_z^2 t_z^{-1}$
2258			H_{344}	1	m_z	$r_z^2 t_x, it_x^{-1}, it_y, r_z^2 t_y, it_y^{-1}, r_z^2 t_y^{-1},$ $m_x r_z t_z, r_z^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
2259			H_{682}	$\langle m_y \rangle$	m_x	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y, m_y t_y, m_x t_y^{-1},$ $t_y^{-1}, m_z t_z, r_z^2 t_z^{-1}$
2260			H_{370}	1	m_z	$it_x, r_z^2 t_x, r_z^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1},$ $m_y t_z, r_z^2 t_z^{-1}, m_y t_z^{-1}$
2261			H_{378}	1	m_z	$r_z^2 t_x, m_x t_x, r_z^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_z^2 t_y^{-1},$ $m_x r_z t_z, r_z^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
2262			H_{690}	$\langle m_x \rangle$	r_z^2	$r_z^2 t_x, m_y t_x, m_x t_y, m_y t_y^{-1}, m_x t_y^{-1}, r_z^2 r_z t_z,$ $m_z r_z^{-1} t_z, r_x^2 t_z^{-1}, r_z^2 t_z^{-1}$
2263			H_{452}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y, t_y, r_z^2 t_y^{-1},$ $t_y^{-1}, r_z^2 r_z t_z, it_z^{-1}$
2264			H_{503}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_z^2 t_y, t_y, r_z^2 t_y^{-1},$ $t_y^{-1}, r_z^2 r_z t_z, r_z^2 t_z^{-1}$
2265			H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_z^2 r_x t_x^{-1}, r_x^{-1} t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1},$ $r_z^2 t_y^{-1}, r_x^2 t_z, r_z^2 t_z^{-1}$
2266			H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_z^2 t_y^{-1},$ $r_z^2 t_y^{-1}, r_x^2 t_z, r_z^2 t_z^{-1}$
2267			H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1},$ $m_y t_y^{-1}, m_z t_z, it_z^{-1}$
2268			H_{527}	1	r_z^2	$m_x t_x, m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1},$ $m_y t_y^{-1}, r_z^2 r_z t_z, it_z^{-1}$
2269			H_{529}	1	r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1},$ $m_y t_y^{-1}, r_z^2 r_z t_z, r_z^2 t_z^{-1}$

41

[9, 33, 75, 132, 204, 292, 396, 516, 652, 804]

2270*, 2271*,

[9, 34, 77, 133, 204, 292, 396, 516, 652, 804]

2272*, 2273*, 2274*, 2275*, 2276*, 2277*, 2278*, 2279*, 2280*, 2281*,

[9, 35, 77, 132, 204, 292, 396, 516, 652, 804]

2282*, 2283*, 2284*, 2285*, 2286*, 2287*, 2288*, 2289*, 2290*, 2291*, 2292*, 2293*, 2294*,

2295*, 2296*, 2297*, 2298*, 2299*, 2300*, 2301*,

[10, 35, 76, 132, 204, 292, 396, 516, 652, 804]

2270			H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, r_z^2 r_x t_y, r_z^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z,$ $r_z^2 r_x t_z, r_x^2 t_z^{-1}, r_z^2 r_x t_z^{-1}$
2271			H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$m_x t_x, m_x t_x^{-1}, m_y t_y, m_x r_x t_y, m_y t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_z^2 t_z^{-1}$
[10, 36, 77, 132, 204, 292, 396, 516, 652, 804]						
2272			H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_z^2 t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$
2273			H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_z^2 t_x^{-1}, r_z^2 r_x t_y, r_z^2 r_x t_y^{-1}, r_z^2 t_y^{-1}, r_z^2 r_x t_z,$ $r_x^2 t_z, r_z^2 r_x t_z^{-1}, r_z^2 t_z^{-1}$
2274			H_{560}	1	$m_z r_x$	$it_x, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_z^2 t_z,$ $m_z r_x^{-1} t_z, r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
2275			H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_z^2 t_z,$ $m_z r_x^{-1} t_z, r_z^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
2276			H_{580}	1	$m_z r_x$	$it_x, m_x t_x^{-1}, m_y t_y, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
2277			H_{580}	1	$m_z r_x$	$r_z^2 r_x t_x, m_x t_x^{-1}, m_y t_y, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
2278			H_{561}	1	$m_z r_x$	$m_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, it_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 t_z,$ $m_z r_x^{-1} t_z, it_z^{-1}, r_z^2 r_x t_z^{-1}$
2279			H_{571}	1	$m_z r_x$	$m_x t_x, r_z^2 r_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_z^2 t_z^{-1}$
2280			H_{557}	1	$m_z r_x$	$m_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_z^2 t_z,$ $m_z r_x^{-1} t_z, r_z^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
2281			H_{578}	1	$m_z r_x$	$m_x t_x, r_z^2 r_x t_x^{-1}, m_y t_y, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
[10, 37, 76, 132, 204, 292, 396, 516, 652, 804]						
2282			H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$it_x, r_z^2 t_x^{-1}, r_z^2 r_x t_y, r_z^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 t_z,$ $r_z^2 r_x t_z, r_z^2 t_z^{-1}, r_z^2 r_x t_z^{-1}$
2283			H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, r_z^2 t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 t_z,$ $r_z^2 r_x t_z, r_z^2 t_z^{-1}, r_z^2 r_x t_z^{-1}$

Nbr.	gr	Nº	H_i	L	m	X
2284			H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$itx, r_x^2 t_x^{-1}, m_y t_y, m_x r_x t_y, m_y t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
2285			H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_x^2 r_x t_x, r_x^2 r_x t_x^{-1}, m_y t_y, m_x r_x t_y, m_y t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
2286			H_{422}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$
2287			H_{409}	1	$r_z^2 r_x$	$r_x^{-1} t_x, r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 r_x t_z,$ $r_x^2 t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
2288			H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_x^2 r_x t_x, m_z r_x t_x^{-1}, r_x^2 r_x t_y, r_x^2 t_y^{-1}, r_x^2 r_x t_y^{-1}, r_x^2 t_z,$ $r_x^2 r_x t_z, r_x^2 t_z^{-1}, r_x^2 r_x t_z^{-1}$
2289			H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_z r_x t_x^{-1}, m_y t_y, m_x r_x t_y, m_y t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
2290			H_{551}	1	$m_z r_x$	$r_x^2 r_x t_x, it_x^{-1}, r_x^2 r_x t_y, it_y, r_x^2 r_x t_y^{-1}, it_z,$ $r_x^2 r_x t_z, it_z^{-1}, r_x^2 r_x t_z^{-1}$
2291			H_{572}	1	$m_z r_x$	$r_x^2 r_x t_x, it_x^{-1}, r_x^2 r_x t_y, m_x r_x t_y, r_x^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
2292			H_{555}	1	$m_z r_x$	$r_x^2 r_x t_x, it_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z, r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
2293			H_{574}	1	$m_z r_x$	$r_x^2 r_x t_x, it_x^{-1}, m_y t_y, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
2294			H_{560}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z, r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
2295			H_{560}	1	$m_z r_x$	$r_x^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z, r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
2296			H_{580}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_y t_y, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
2297			H_{580}	1	$m_z r_x$	$r_x^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$
2298			H_{556}	1	$m_z r_x$	$m_x t_x, r_x^2 r_x t_x^{-1}, r_x^2 r_x t_y, it_y^{-1}, r_x^2 r_x t_y^{-1}, it_z,$ $r_x^2 r_x t_z, it_z^{-1}, r_x^2 r_x t_z^{-1}$
2299			H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_y, m_z r_x^{-1} t_y, it_y^{-1}, r_x^2 r_x t_y^{-1},$ $r_x^2 t_z, m_z r_x^{-1} t_z, r_x^2 r_x t_z^{-1}$
2300			H_{576}	1	$m_z r_x$	$m_x t_x, r_x^2 r_x t_x^{-1}, r_x^2 t_y, m_x r_x t_y, r_x^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$
2301			H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_y t_y, r_x t_y, r_x^2 t_y^{-1}, m_x r_x t_y^{-1},$ $r_x^{-1} t_z, m_z t_z, m_x r_x^{-1} t_z^{-1}$

42A

[6, 24, 64, 130, 207, 289, 396, 519, 649, 804]

2302*,

[6, 24, 65, 116, 179, 260, 354, 467, 593, 734]

2303*,

[7, 29, 70, 134, 205, 289, 398, 517, 649, 806]

2302

 H_{393}

1

[7, 29, 71, 119, 188, 269, 368, 481, 609, 752]

2303

 H_{393}

1

$$r_z^2 r_x \quad r_y^2 r_z t_x, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_x^2 r_y t_y^{-1}, r_y^2 r_z t_z$$

$$r_z^2 r_x \quad r_y^2 r_z t_x, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_y^{-1} r_z^{-1} t_y^{-1}, r_y r_x t_z$$

42B

[6, 24, 56, 98, 153, 222, 303, 396, 503, 622]

2304*,

[6, 24, 57, 101, 158, 228, 310, 405, 513, 633]

2305*,

[7, 29, 63, 110, 172, 249, 338, 441, 560, 691]

2304

 H_{393}

1

[7, 29, 64, 112, 175, 252, 342, 446, 565, 697]

2305

 H_{393}

1

$$r_z^2 r_x \quad r_y^2 r_z t_x, r_y r_x t_x, r_y^2 r_z t_y, r_y^{-1} r_z^{-1} t_y^{-1}, r_y r_x t_z, r_y^{-1} r_z^{-1} t_z^{-1}$$

$$r_z^2 r_x \quad r_y^2 r_z t_x, r_y r_x t_x, r_y^2 r_z t_y, r_y^2 r_y t_y^{-1}, r_y^2 r_z t_z, r_y^{-1} r_z^{-1} t_z^{-1}$$

43

[8, 30, 73, 135, 210, 296, 397, 516, 652, 804]

2306*, 2307*,

[8, 31, 73, 129, 200, 288, 392, 512, 648, 800]

2308*, 2309*,

[8, 31, 75, 134, 205, 292, 396, 516, 652, 804]

2310*, 2311*,

[8, 31, 75, 136, 209, 294, 396, 516, 652, 804]

2312*, 2313*,

[8, 31, 76, 137, 208, 293, 396, 516, 652, 804]

2314*, 2315*, 2316*, 2317*,

[8, 32, 73, 128, 200, 288, 392, 512, 648, 800]

2318*, 2319*,

[8, 32, 76, 132, 202, 290, 394, 514, 650, 802]

2320*, 2321*, 2322*, 2323*, 2324*, 2325*,

[8, 32, 76, 133, 204, 292, 396, 516, 652, 804]

2326*, 2327*,

[8, 32, 77, 135, 205, 292, 396, 516, 652, 804]

2328*, 2329*, 2330*, 2331*,

[8, 32, 77, 136, 207, 293, 396, 516, 652, 804]

2332*,

[8, 32, 78, 135, 204, 292, 396, 516, 652, 804]

2333*, 2334*,

Nbr.	gr	N ₀	H _i	L	m	X
[8, 32, 78, 137, 206, 292, 396, 516, 652, 804]						
						2335*, 2336*, 2337*, 2338*,
[8, 33, 76, 131, 202, 290, 394, 514, 650, 802]						
						2339*,
[8, 33, 77, 135, 207, 293, 396, 516, 652, 804]						
						2340*, 2341*, 2342*, 2343*, 2344*, 2345*, 2346*, 2347*, 2348*, 2349*, 2350*,
[8, 33, 78, 134, 204, 292, 396, 516, 652, 804]						
						2351*,
[8, 33, 78, 136, 206, 292, 396, 516, 652, 804]						
						2352*,
[8, 34, 76, 130, 202, 290, 394, 514, 650, 802]						
						2353*, 2354*, 2355*, 2356*, 2357*, 2358*, 2359*,
[8, 34, 78, 133, 204, 292, 396, 516, 652, 804]						
						2360*, 2361*, 2362*, 2363*, 2364*, 2365*, 2366*,
[8, 34, 78, 135, 206, 292, 396, 516, 652, 804]						
						2367*, 2368*, 2369*, 2370*, 2371*, 2372*, 2373*, 2374*, 2375*, 2376*, 2377*, 2378*, 2379*,
[9, 33, 76, 135, 207, 293, 396, 516, 652, 804]						
2306	H ₅₈₀	1		m _z r x	it _x , r _z ² r x t _x , m _x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , r x t _y ⁻¹ , m _z t _z , r _x ⁻¹ t _z ⁻¹	
2307	H ₅₇₈	1		m _z r x	m _x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , r x t _y ⁻¹ , m _z t _z , r _x ⁻¹ t _z ⁻¹	
[9, 34, 75, 130, 202, 290, 394, 514, 650, 802]						
2308	H ₅₆₀	1		m _z r x	it _x , r _z ² r x t _x , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _x ² t _y ⁻¹ , m _z r _x ⁻¹ t _y ⁻¹ , m _z r _x ⁻¹ t _z , m _z r _x ⁻¹ t _z ⁻¹	
2309	H ₅₅₇	1		m _z r x	m _x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _x ² t _y ⁻¹ , m _z r _x ⁻¹ t _y ⁻¹ , m _z r _x ⁻¹ t _z , m _z r _x ⁻¹ t _z ⁻¹	
[9, 34, 77, 133, 204, 292, 396, 516, 652, 804]						
2310	H ₅₈₀	1		m _z r x	it _x , r _z ² r x t _x , m _x t _x ⁻¹ , r x t _y , m _y t _y ⁻¹ , r x t _y ⁻¹ , r _x ⁻¹ t _z , r _x ⁻¹ t _z ⁻¹	
2311	H ₅₇₈	1		m _z r x	m _x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , r x t _y , m _y t _y ⁻¹ , r x t _y ⁻¹ , r _x ⁻¹ t _z , r _x ⁻¹ t _z ⁻¹	
[9, 34, 77, 135, 206, 292, 396, 516, 652, 804]						
2312	H ₅₆₀	1		m _z r x	it _x , r _z ² r x t _x , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _x ² t _y ⁻¹ , r _x ² t _z , m _z r _x ⁻¹ t _z , r _x ² t _z ⁻¹	
2313	H ₅₅₇	1		m _z r x	m _x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _x ² t _y ⁻¹ , r _x ² t _z , m _z r _x ⁻¹ t _z , r _x ² t _z ⁻¹	
[9, 34, 78, 135, 205, 292, 396, 516, 652, 804]						
2314	H ₅₈₀	1		m _z r x	it _x , r _z ² r x t _x , r _y ² r x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , r x t _y ⁻¹ , m _z t _z , r _x ⁻¹ t _z ⁻¹	
2315	H ₅₇₁	1		m _z r x	r _y ² r x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , m _y t _y , r _x ² t _y ⁻¹ , m _x r x t _y ⁻¹ , m _z t _z , m _x r _x ⁻¹ t _z ⁻¹	
2316	H ₅₇₁	1		m _z r x	m _x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , m _y t _y , r _x ² t _y ⁻¹ , m _x r x t _y ⁻¹ , m _z t _z , m _x r _x ⁻¹ t _z ⁻¹	
2317	H ₅₇₈	1		m _z r x	r _y ² r x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , m _y t _y , m _y t _y ⁻¹ , r x t _y ⁻¹ , m _z t _z , r _x ⁻¹ t _z ⁻¹	
[9, 35, 74, 130, 202, 290, 394, 514, 650, 802]						
2318	H ₅₅₅	1		m _z r x	r _z ² r x t _x , i t _x ⁻¹ , r _z ² r x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _x ² t _y ⁻¹ , m _z r _x ⁻¹ t _y ⁻¹ , m _z r _x ⁻¹ t _z , m _z r _x ⁻¹ t _z ⁻¹	
2319	H ₅₆₀	1		m _z r x	r _z ² r x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _x ² t _y ⁻¹ , m _z r _x ⁻¹ t _y ⁻¹ , m _z r _x ⁻¹ t _z , m _z r _x ⁻¹ t _z ⁻¹	
[9, 35, 77, 131, 203, 291, 395, 515, 651, 803]						
2320	H ₅₅₅	1		m _z r x	it _x , i t _x ⁻¹ , r _z ² r x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _x ² t _y ⁻¹ , m _z r _x ⁻¹ t _y ⁻¹ , m _z r _x ⁻¹ t _z , m _z r _x ⁻¹ t _z ⁻¹	
2321	H ₅₆₀	1		m _z r x	it _x , r _z ² r x t _x , r _y ² r x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _x ² t _y ⁻¹ , m _z r _x ⁻¹ t _y ⁻¹ , m _z r _x ⁻¹ t _z , m _z r _x ⁻¹ t _z ⁻¹	
2322	H ₅₆₀	1		m _z r x	it _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _x ² t _y ⁻¹ , m _z r _x ⁻¹ t _y ⁻¹ , m _z r _x ⁻¹ t _z , m _z r _x ⁻¹ t _z ⁻¹	
2323	H ₅₆₁	1		m _z r x	r _y ² r x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , i t _y ⁻¹ , r _z ² r x t _y ⁻¹ , m _z r _x ⁻¹ t _z , r _z ² r x t _z ⁻¹	
2324	H ₅₆₁	1		m _z r x	m _x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , i t _y ⁻¹ , r _z ² r x t _y ⁻¹ , m _z r _x ⁻¹ t _z , r _z ² r x t _z ⁻¹	
2325	H ₅₅₇	1		m _z r x	r _y ² r x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _x ² t _y ⁻¹ , m _z r _x ⁻¹ t _y ⁻¹ , m _z r _x ⁻¹ t _z , m _z r _x ⁻¹ t _z ⁻¹	
[9, 35, 77, 132, 204, 292, 396, 516, 652, 804]						
2326	H ₅₇₄	1		m _z r x	r _z ² r x t _x , i t _x ⁻¹ , r _z ² r x t _x ⁻¹ , r x t _y , m _y t _y ⁻¹ , r x t _y ⁻¹ , r _x ⁻¹ t _z , r _x ⁻¹ t _z ⁻¹	
2327	H ₅₈₀	1		m _z r x	r _z ² r x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , r x t _y , m _y t _y ⁻¹ , r x t _y ⁻¹ , r _x ⁻¹ t _z , r _x ⁻¹ t _z ⁻¹	
[9, 35, 78, 133, 204, 292, 396, 516, 652, 804]						
2328	H ₅₈₀	1		m _z r x	it _x , r _z ² r x t _x , r _y ² r x t _x ⁻¹ , r x t _y , m _y t _y ⁻¹ , r x t _y ⁻¹ , r _x ⁻¹ t _z , r _x ⁻¹ t _z ⁻¹	
2329	H ₅₇₁	1		m _z r x	r _y ² r x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , r x t _y , r _x ² t _y ⁻¹ , m _x r x t _y ⁻¹ , r _x ⁻¹ t _z , m _x r _x ⁻¹ t _z ⁻¹	
2330	H ₅₇₁	1		m _z r x	m _x t _x , r _y ² r x t _x ⁻¹ , m _x t _x ⁻¹ , r x t _y , r _x ² t _y ⁻¹ , m _x r x t _y ⁻¹ , r _x ⁻¹ t _z , m _x r _x ⁻¹ t _z ⁻¹	

Nbr.	gr	N ₀	H_i	L	m	X
		2331	H_{578}	1	$m_z r_x$	$r_y^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z, r_x^{-1} t_z^{-1}$
[9, 35, 78, 134, 205, 292, 396, 516, 652, 804]						
		2332	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1},$ $r_x^{-1} t_z, r_y^2 t_z^{-1}$
[9, 35, 79, 132, 204, 292, 396, 516, 652, 804]						
		2333	H_{574}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z, r_x^{-1} t_z^{-1}$
		2334	H_{580}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $r_x^{-1} t_z, r_x^{-1} t_z^{-1}$
[9, 35, 79, 134, 204, 292, 396, 516, 652, 804]						
		2335	H_{560}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z, r_z^2 t_z^{-1}$
		2336	H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, it_y^{-1}, r_z^2 r_x t_y^{-1},$ $r_x^2 t_z, r_z^2 r_x t_z^{-1}$
		2337	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, it_y^{-1}, r_z^2 r_x t_y^{-1},$ $r_x^2 t_z, r_z^2 r_x t_z^{-1}$
		2338	H_{557}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z, r_z^2 t_z^{-1}$
[9, 36, 76, 131, 203, 291, 395, 515, 651, 803]						
		2339	H_{561}	1	$m_z r_x$	$m_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 r_x t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1}$
[9, 36, 77, 134, 205, 292, 396, 516, 652, 804]						
		2340	H_{572}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $r_x^2 t_z, m_x r_x^{-1} t_z^{-1}$
		2341	H_{572}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $r_x^2 t_z, m_x r_x^{-1} t_z^{-1}$
		2342	H_{574}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $m_z t_z, r_x^{-1} t_z^{-1}$
		2343	H_{574}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $m_z t_z, r_x^{-1} t_z^{-1}$
		2344	H_{580}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $m_z t_z, r_x^{-1} t_z^{-1}$
		2345	H_{580}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1}, r_x t_y^{-1},$ $m_z t_z, r_x^{-1} t_z^{-1}$
		2346	H_{576}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $r_x^2 t_z, m_x r_x^{-1} t_z^{-1}$
		2347	H_{576}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $r_x^2 t_z, m_x r_x^{-1} t_z^{-1}$
		2348	H_{576}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, m_x r_x t_y, r_z^2 t_y^{-1},$ $m_x r_x^{-1} t_z, r_z^2 t_z^{-1}$
		2349	H_{576}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, m_x r_x t_y^{-1}, r_y^2 t_z,$ $m_x r_x^{-1} t_z^{-1}, r_z^2 t_z^{-1}$
		2350	H_{571}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1},$ $r_x^{-1} t_z, r_y^2 t_z^{-1}$
[9, 36, 78, 132, 204, 292, 396, 516, 652, 804]						
		2351	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, m_x r_x t_y^{-1},$ $r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$
[9, 36, 78, 134, 204, 292, 396, 516, 652, 804]						
		2352	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, it_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z, it_z^{-1}$
[9, 37, 75, 131, 203, 291, 395, 515, 651, 803]						
		2353	H_{551}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_y^{-1},$ $r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$
		2354	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_y^{-1},$ $r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$
		2355	H_{551}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, r_z^2 r_x t_y^{-1}, it_z,$ $r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$
		2356	H_{556}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_y^{-1},$ $r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$
		2357	H_{556}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_y^{-1},$ $r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$
		2358	H_{556}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y, r_z^2 r_x t_y^{-1}, it_z,$ $r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$
		2359	H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 r_x t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1}$
[9, 37, 77, 132, 204, 292, 396, 516, 652, 804]						
		2360	H_{572}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
		2361	H_{572}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$
		2362	H_{576}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$
		2363	H_{576}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$
		2364	H_{576}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, m_x r_x t_y, m_x r_x t_y^{-1},$ $m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$
		2365	H_{576}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_x r_x t_y, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z,$ $m_x r_x^{-1} t_z^{-1}, r_z^2 t_y^{-1}$
		2366	H_{571}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, m_x r_x t_y^{-1},$ $r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$
[9, 37, 77, 134, 204, 292, 396, 516, 652, 804]						
		2367	H_{551}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, it_z,$ $r_z^2 r_x t_z, it_z^{-1}$
		2368	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, it_z,$ $r_z^2 r_x t_z, it_z^{-1}$
		2369	H_{551}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, it_y, it_y^{-1}, r_z^2 r_x t_y^{-1},$ $it_z, r_z^2 r_x t_z^{-1}$
		2370	H_{555}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, r_z^2 t_z,$ $m_z r_x^{-1} t_z, r_z^2 t_z^{-1}$
		2371	H_{555}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z, r_z^2 t_z^{-1}$
		2372	H_{555}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1},$ $r_x^2 t_z, m_z r_x^{-1} t_z^{-1}$
		2373	H_{560}	1	$m_z r_x$	$it_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z, r_z^2 t_z^{-1}$
		2374	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z, r_z^2 t_z^{-1}$
		2375	H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1},$ $r_x^2 t_z, m_z r_x^{-1} t_z^{-1}$
		2376	H_{556}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, it_z,$ $r_z^2 r_x t_z, it_z^{-1}$
		2377	H_{556}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, it_z,$ $r_z^2 r_x t_z, it_z^{-1}$
		2378	H_{556}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, it_y, it_y^{-1}, r_z^2 r_x t_y^{-1},$ $it_z, r_z^2 r_x t_z^{-1}$
		2379	H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, it_y^{-1}, r_x^2 t_z,$ $m_z r_x^{-1} t_z, it_z^{-1}$

44

- [8, 29, 69, 128, 203, 292, 396, 516, 652, 804]
 2380*,
 [8, 30, 69, 123, 193, 279, 381, 499, 633, 783]
 2381*,
 [8, 30, 71, 128, 200, 288, 392, 512, 648, 800]
 2382*,
 [8, 30, 71, 130, 204, 292, 396, 516, 652, 804]
 2383*,
 [8, 30, 73, 134, 207, 293, 396, 516, 652, 804]
 2384*, 2385*, 2386*,
 [8, 31, 70, 123, 193, 279, 381, 499, 633, 783]
 2387*, 2388*,
 [8, 31, 73, 129, 200, 288, 392, 512, 648, 800]
 2389*,
 [8, 31, 73, 130, 202, 290, 394, 514, 650, 802]
 2390*, 2391*, 2392*, 2393*,
 [8, 31, 74, 132, 204, 292, 396, 516, 652, 804]
 2394*, 2395*, 2396*,
 [8, 31, 75, 133, 204, 292, 396, 516, 652, 804]
 2397*,
 [8, 31, 75, 135, 206, 292, 396, 516, 652, 804]
 2398*, 2399*, 2400*,
 [8, 31, 75, 135, 207, 293, 396, 516, 652, 804]
 2401*,
 [8, 31, 76, 136, 207, 293, 396, 516, 652, 804]
 2402*, 2403*,
 [8, 31, 76, 137, 208, 293, 396, 516, 652, 804]
 2404*,
 [8, 32, 74, 130, 202, 290, 394, 514, 650, 802]
 2405*,
 [8, 32, 76, 133, 204, 292, 396, 516, 652, 804]
 2406*,
 [8, 32, 76, 135, 206, 292, 396, 516, 652, 804]
 2407*,
 [8, 32, 76, 135, 207, 293, 396, 516, 652, 804]
 2408*, 2409*, 2410*, 2411*, 2412*, 2413*, 2414*,
 [8, 32, 77, 136, 206, 292, 396, 516, 652, 804]
 2415*, 2416*,
 [8, 33, 75, 130, 202, 290, 394, 514, 650, 802]

Nbr.	gr	Nº	H_i	L	m	X
2417*, 2418*, 2419*, 2420*, 2421*, 2422*, 2423*, [8, 33, 77, 133, 204, 292, 396, 516, 652, 804] 2424*, 2425*, 2426*, 2427*, 2428*, 2429*, 2430*, 2431*, [8, 33, 77, 135, 206, 292, 396, 516, 652, 804] 2432*, 2433*, 2434*, 2435*, 2436*, 2437*, 2438*, [8, 33, 78, 135, 206, 293, 396, 516, 652, 804] 2439*, [9, 32, 73, 131, 204, 292, 396, 516, 652, 804]						
2380	H_{412}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_x t_z, m_z t_z^{-1}$	
[9, 33, 72, 127, 198, 285, 388, 507, 642, 793]						
2381	H_{388}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_z r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1},$ $m_z r_x t_z, m_z r_x t_z^{-1}$	
[9, 33, 74, 130, 202, 290, 394, 514, 650, 802]						
2382	H_{407}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_x t_z, r_x t_z^{-1}$	
[9, 33, 74, 132, 204, 292, 396, 516, 652, 804]						
2383	H_{394}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_x^2 t_y, i t_y^{-1}, m_z r_x t_y^{-1},$ $m_z r_x t_z, r_x^2 t_z^{-1}$	
[9, 33, 76, 134, 205, 292, 396, 516, 652, 804]						
2384	H_{402}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_z t_z^{-1}$	
2385	H_{413}	1	$r_z^2 r_x$		$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_x t_z, m_z t_z^{-1}$	
2386	H_{419}	1	$r_z^2 r_x$		$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_z t_z^{-1}$	
[9, 34, 72, 127, 198, 285, 388, 507, 642, 793]						
2387	H_{389}	1	$r_z^2 r_x$		$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, m_z r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1},$ $m_z r_x t_z, m_z r_x t_z^{-1}$	
2388	H_{393}	1	$r_z^2 r_x$		$r_y^2 r_z t_x, r_y r_x t_x, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_y^{-1} r_z^{-1} t_y^{-1},$ $r_y r_x t_z, r_y^{-1} r_z^{-1} t_z^{-1}$	
[9, 34, 75, 130, 202, 290, 394, 514, 650, 802]						
2389	H_{414}	1	$r_z^2 r_x$		$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_x t_z, r_x t_z^{-1}$	
[9, 34, 75, 131, 203, 291, 395, 515, 651, 803]						
2390	H_{394}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y, m_z r_x t_y^{-1}, m_z r_x t_z,$ $r_y^2 r_x t_z^{-1}, r_z^2 t_z^{-1}$	
2391	H_{398}	1	$r_z^2 r_x$		$r_z^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, m_z r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1},$ $m_z r_x t_z, m_z r_x t_z^{-1}$	
2392	H_{400}	1	$r_z^2 r_x$		$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_z r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1},$ $m_z r_x t_z, m_z r_x t_z^{-1}$	
2393	H_{395}	1	$r_z^2 r_x$		$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_y^2 r_x t_y, m_z r_x t_y^{-1}, m_z r_x t_z,$ $r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$	
[9, 34, 76, 132, 204, 292, 396, 516, 652, 804]						
2394	H_{412}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_x^{-1} t_y^{-1},$ $r_x t_z, m_x r_x t_z^{-1}$	
2395	H_{413}	1	$r_z^2 r_x$		$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_x^{-1} t_y^{-1},$ $r_x t_z, m_x r_x t_z^{-1}$	
2396	H_{418}	1	$r_z^2 r_x$		$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_x t_z, r_x t_z^{-1}$	
[9, 34, 77, 132, 204, 292, 396, 516, 652, 804]						
2397	H_{410}	1	$r_z^2 r_x$		$r_z^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_x t_z, r_x t_z^{-1}$	
[9, 34, 77, 134, 204, 292, 396, 516, 652, 804]						
2398	H_{391}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_x^2 t_z^{-1}$	
2399	H_{395}	1	$r_z^2 r_x$		$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_x^2 t_y, i t_y^{-1}, m_z r_x t_y^{-1},$ $m_z r_x t_z, r_x^2 t_z^{-1}$	
2400	H_{401}	1	$r_z^2 r_x$		$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_x^2 t_z^{-1}$	
[9, 34, 77, 134, 205, 292, 396, 516, 652, 804]						
2401	H_{407}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_x t_z, r_y^2 t_z^{-1}$	
[9, 34, 78, 134, 205, 292, 396, 516, 652, 804]						
2402	H_{422}	1	$r_z^2 r_x$		$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_z t_z^{-1}$	
2403	H_{422}	1	$r_z^2 r_x$		$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z,$ $m_z t_z, m_z t_z^{-1}$	
[9, 34, 78, 135, 205, 292, 396, 516, 652, 804]						
2404	H_{393}	1	$r_z^2 r_x$		$r_y^2 r_z t_x, r_x^2 r_y t_x^{-1}, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_x^2 r_y t_y^{-1},$ $r_y^2 r_z t_z, r_x^2 r_y t_z^{-1}$	
[9, 35, 75, 131, 203, 291, 395, 515, 651, 803]						
2405	H_{394}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1},$ $m_z r_x t_z, r_y^2 r_x t_z^{-1}$	

Nbr.	gr	N ₀	H _i	L	m	X
[9, 35, 77, 132, 204, 292, 396, 516, 652, 804]						
2406	H ₄₁₂	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_x t_z, m_x r_x t_z^{-1}$		
[9, 35, 77, 134, 204, 292, 396, 516, 652, 804]						
2407	H ₃₈₈	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_z r_x t_y, i t_y^{-1}, i t_z,$ $i t_z^{-1}, m_z r_x t_z^{-1}$		
[9, 35, 77, 134, 205, 292, 396, 516, 652, 804]						
2408	H ₄₁₄	1	$r_z^2 r_x$	$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_x t_z, r_y^2 t_z^{-1}$		
2409	H ₄₁₅	1	$r_z^2 r_x$	$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_z t_z^{-1}$		
2410	H ₄₁₂	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1},$ $r_y^2 t_z, m_x r_x t_z^{-1}$		
2411	H ₄₁₀	1	$r_z^2 r_x$	$r_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_x t_z, r_y^2 t_z^{-1}$		
2412	H ₄₀₄	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_z t_z^{-1}$		
2413	H ₄₁₃	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1},$ $r_y^2 t_z, m_x r_x t_z^{-1}$		
2414	H ₄₁₈	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_x t_z, r_y^2 t_z^{-1}$		
[9, 35, 78, 134, 204, 292, 396, 516, 652, 804]						
2415	H ₄₀₉	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_z^2 r_x t_z, r_z^2 t_z^{-1}$		
2416	H ₄₀₉	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z,$ $r_z^2 t_z, r_x^2 t_z^{-1}$		
[9, 36, 75, 131, 203, 291, 395, 515, 651, 803]						
2417	H ₃₉₆	1	$r_z^2 r_x$	$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}$		
2418	H ₄₀₉	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}$		
2419	H ₄₀₉	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_y^2 r_x t_z,$ $r_y^2 r_x t_z^{-1}, r_z^2 t_z^{-1}$		
2420	H ₃₉₁	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}$		
2421	H ₃₉₂	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}$		
2422	H ₃₉₅	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_y^2 r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1},$ $m_z r_x t_z, r_y^2 r_x t_z^{-1}$		
2423	H ₄₀₁	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}$		
[9, 36, 77, 132, 204, 292, 396, 516, 652, 804]						
2424	H ₄₁₅	1	$r_z^2 r_x$	$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_x r_x t_z^{-1}$		
2425	H ₄₂₂	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_x r_x t_z^{-1}$		
2426	H ₄₂₂	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_x r_x t_z,$ $m_x r_x t_z^{-1}, m_z t_z^{-1}$		
2427	H ₄₀₂	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_x r_x t_z^{-1}$		
2428	H ₄₀₄	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_x r_x t_z^{-1}$		
2429	H ₄₁₃	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_x r_x^{-1} t_y, r_z^2 t_y^{-1}, r_x^{-1} t_y^{-1},$ $r_x t_z, m_x r_x t_z^{-1}$		
2430	H ₄₁₉	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_x r_x t_z^{-1}$		
2431	H ₃₉₃	1	$r_z^2 r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_y^{-1} r_z^{-1} t_y^{-1},$ $r_y r_x t_z, r_y^2 r_y t_z^{-1}$		
[9, 36, 77, 134, 204, 292, 396, 516, 652, 804]						
2432	H ₃₈₉	1	$r_z^2 r_x$	$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, m_z r_x t_y, i t_y^{-1}, i t_z,$ $i t_z^{-1}, m_z r_x t_z^{-1}$		
2433	H ₃₉₆	1	$r_z^2 r_x$	$m_z r_x t_x, i t_x^{-1}, m_z r_x t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_z^2 t_z^{-1}$		
2434	H ₃₉₄	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y, i t_y^{-1}, i t_z,$ $r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$		
2435	H ₃₉₈	1	$r_z^2 r_x$	$r_x t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, m_z r_x t_y, i t_y^{-1}, i t_z,$ $i t_z^{-1}, m_z r_x t_z^{-1}$		
2436	H ₃₉₂	1	$r_z^2 r_x$	$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_x^2 t_z^{-1}$		

Nbr.	gr	N ₀	H_i	L	m	X
		2437	H_{400}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_z r_x t_y, i t_y^{-1}, i t_z,$ $i t_z^{-1}, m_z r_x t_z^{-1}$
		2438	H_{395}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_y^2 r_x t_y, i t_y^{-1}, i t_z,$ $r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
[9, 36, 78, 133, 205, 292, 396, 516, 652, 804]						
		2439	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_y r_x t_x, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_x^2 r_y t_y^{-1},$ $r_y^2 r_z t_z, r_y^{-1} r_z^{-1} t_z^{-1}$
45						
[9, 33, 76, 135, 207, 293, 396, 516, 652, 804]						
2440*, 2441*, 2442*, 2443*,						
[9, 34, 75, 130, 202, 290, 394, 514, 650, 802]						
2444*, 2445*, 2446*, 2447*,						
[9, 34, 77, 133, 204, 292, 396, 516, 652, 804]						
2448*, 2449*, 2450*, 2451*,						
[9, 34, 77, 135, 206, 292, 396, 516, 652, 804]						
2452*, 2453*, 2454*, 2455*,						
[10, 35, 77, 134, 205, 292, 396, 516, 652, 804]						
		2440	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$i t_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_y t_y^{-1},$ $m_x r_x t_y^{-1}, r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$
		2441	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1},$ $m_y t_y^{-1}, m_x r_x t_z, m_z t_z^{-1}$
		2442	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1},$ $m_x r_x t_y^{-1}, r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$
		2443	H_{580}	1	$m_z r_x$	$i t_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_y t_y^{-1},$ $r_x t_y^{-1}, m_z t_z, r_x^{-1} t_z^{-1}$
[10, 36, 75, 131, 203, 291, 395, 515, 651, 803]						
		2444	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$i t_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1},$ $r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$
		2445	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1},$ $r_z^2 t_z^{-1}, r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}$
		2446	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1},$ $r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$
		2447	H_{560}	1	$m_z r_x$	$i t_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1},$ $m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z, m_z r_x^{-1} t_z^{-1}$
[10, 36, 77, 132, 204, 292, 396, 516, 652, 804]						
		2448	H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$i t_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, m_x r_x t_y, m_y t_y^{-1},$ $m_x r_x t_y^{-1}, m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$
		2449	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1},$ $m_y t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}$
		2450	H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, m_x r_x t_y, m_y t_y^{-1},$ $m_x r_x t_y^{-1}, m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$
		2451	H_{580}	1	$m_z r_x$	$i t_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, m_y t_y^{-1},$ $r_x t_y^{-1}, r_x^{-1} t_z, r_x^{-1} t_z^{-1}$
[10, 36, 77, 134, 204, 292, 396, 516, 652, 804]						
		2452	H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$i t_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1},$ $r_z^2 t_z, r_z^2 r_x t_z, r_x^2 t_z^{-1}$
		2453	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1},$ $r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_x^2 t_z^{-1}$
		2454	H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1},$ $r_z^2 t_z, r_z^2 r_x t_z, r_x^2 t_z^{-1}$
		2455	H_{560}	1	$m_z r_x$	$i t_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1},$ $r_x^2 t_z, m_z r_x^{-1} t_z, r_x^2 t_z^{-1}$
46						
[9, 33, 75, 132, 204, 292, 396, 516, 652, 804]						
2456*, 2457*,						
[9, 34, 76, 132, 204, 292, 396, 516, 652, 804]						
2458*, 2459*, 2460*,						
[9, 34, 77, 133, 204, 292, 396, 516, 652, 804]						
2461*, 2462*, 2463*, 2464*, 2465*, 2466*, 2467*, 2468*,						
[9, 34, 78, 134, 204, 292, 396, 516, 652, 804]						
2469*,						
[9, 35, 77, 132, 204, 292, 396, 516, 652, 804]						
2470*, 2471*, 2472*, 2473*, 2474*, 2475*, 2476*, 2477*, 2478*, 2479*, 2480*, 2481*, 2482*,						
2483*,						
[9, 35, 78, 133, 204, 292, 396, 516, 652, 804]						
2484*, 2485*, 2486*, 2487*, 2488*, 2489*, 2490*, 2491*, 2492*, 2493*, 2494*, 2495*, 2496*,						
2497*, 2498*,						
[9, 36, 78, 132, 204, 292, 396, 516, 652, 804]						
2499*, 2500*, 2501*, 2502*, 2503*, 2504*, 2505*, 2506*, 2507*, 2508*, 2509*, 2510*, 2511*,						
2512*, 2513*, 2514*, 2515*, 2516*, 2517*, 2518*, 2519*, 2520*,						
[10, 35, 76, 132, 204, 292, 396, 516, 652, 804]						
		2456	H_{359}	1	m_z	$i t_x, r_z^2 t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
		2457	H_{650}	$\langle m_z r_x \rangle$	m_x	$t_x, m_x t_x^{-1}, t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_x^{-1} t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
[10, 36, 76, 132, 204, 292, 396, 516, 652, 804]						
2458		H_{648}		$\langle m_z r_x \rangle$	m_x	$t_x, m_x t_x^{-1}, t_x^{-1}, r_x^2 t_y, i t_y^{-1}, r_x^2 t_y^{-1},$ $m_z r_x^{-1} t_z, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_z^{-1},$
2459		H_{350}	1		m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
2460		H_{359}	1		m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
[10, 36, 77, 132, 204, 292, 396, 516, 652, 804]						
2461		H_{370}	1		m_z	$i t_x, r_x^2 t_x, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_y t_z, r_x^2 t_z^{-1}, m_y t_z^{-1}$
2462		H_{370}	1		m_z	$i t_x, r_x^2 t_x, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_y t_z, r_x^2 t_z^{-1}, m_y t_z^{-1}$
2463		H_{359}	1		m_z	$i t_x, r_x^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
2464		H_{359}	1		m_z	$i t_x, r_x^2 t_x, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
2465		H_{368}	1		m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_x t_z, r_x^2 t_z^{-1}, m_x t_z^{-1}$
2466		H_{368}	1		m_z	$m_x t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_x t_z, r_y^2 t_z^{-1}, m_x t_z^{-1}$
2467		H_{353}	1		m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
2468		H_{377}	1		m_z	$r_y^2 t_x, m_z r_z^{-1} t_x^{-1}, r_z^{-1} t_x^{-1}, m_z r_z t_y, r_z t_y, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
[10, 36, 78, 132, 204, 292, 396, 516, 652, 804]						
2469		H_{422}	1		$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_z t_z, m_z t_z^{-1}$
[10, 37, 76, 132, 204, 292, 396, 516, 652, 804]						
2470		H_{361}	1		m_z	$i t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, i t_y^{-1}, r_x^2 t_y^{-1},$ $m_x t_z, r_y^2 t_z^{-1}, m_x t_z^{-1}$
2471		H_{361}	1		m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, i t_y^{-1}, r_x^2 t_y^{-1},$ $m_x t_z, r_y^2 t_z^{-1}, m_x t_z^{-1}$
2472		H_{330}	1		m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, i t_y, i t_y^{-1}, r_x^2 t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
2473		H_{372}	1		m_z	$i t_x, i t_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_x t_z, r_y^2 t_z^{-1}, m_x t_z^{-1}$
2474		H_{372}	1		m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_x t_z, r_y^2 t_z^{-1}, m_x t_z^{-1}$
2475		H_{365}	1		m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_y t_z, r_x^2 t_z^{-1}, m_y t_z^{-1}$
2476		H_{365}	1		m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_y t_z, r_x^2 t_z^{-1}, m_y t_z^{-1}$
2477		H_{350}	1		m_z	$i t_x, i t_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
2478		H_{350}	1		m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
2479		H_{370}	1		m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_y t_z, r_x^2 t_z^{-1}, m_y t_z^{-1}$
2480		H_{370}	1		m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_y t_z, r_x^2 t_z^{-1}, m_y t_z^{-1}$
2481		H_{359}	1		m_z	$i t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
2482		H_{359}	1		m_z	$r_z^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
2483		H_{343}	1		m_z	$r_z^2 t_x, r_y^2 r_z t_x^{-1}, m_x r_z t_x^{-1}, i t_y, r_y^2 r_z t_y^{-1}, m_x r_z t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
[10, 37, 77, 132, 204, 292, 396, 516, 652, 804]						
2484		H_{370}	1		m_z	$i t_x, r_z^2 t_x, r_x^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_y t_z, r_x^2 t_z^{-1}, m_y t_z^{-1}$
2485		H_{370}	1		m_z	$i t_x, r_z^2 t_x, r_y^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_y t_z, r_x^2 t_z^{-1}, m_y t_z^{-1}$
2486		H_{359}	1		m_z	$i t_x, r_z^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
2487		H_{652}	$\langle m_z r_x \rangle$		m_x	$m_z r_x^{-1} t_x, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_z^2 t_y, r_z^2 t_y^{-1}, m_y t_y^{-1},$ $m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_x^{-1} t_z^{-1}$
2488		H_{373}	1		m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_z^2 t_z, i t_z^{-1}, r_z^2 t_z^{-1}$
2489		H_{652}	$\langle m_z r_x \rangle$		m_x	$m_z r_x^{-1} t_x, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_y t_y, r_z^2 t_y^{-1}, m_y t_y^{-1},$ $r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_x^{-1} t_z^{-1}$

Nbr.	gr	Nº	H_i	L	m	X
		2490	H_{368}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_x t_z, r_y^2 t_z^{-1}, m_x t_z^{-1}$
		2491	H_{368}	1	m_z	$m_x t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_x t_z, r_y^2 t_z^{-1}, m_x t_z^{-1}$
		2492	H_{650}	$\langle m_z r_x \rangle$	m_x	$t_x, m_x t_x^{-1}, t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_x^{-1} t_z^{-1}$
		2493	H_{378}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_x r_z t_z, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
		2494	H_{378}	1	m_z	$r_y^2 t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, m_y t_y, m_y t_y^{-1},$ $m_x r_z t_z, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
		2495	H_{650}	$\langle m_z r_x \rangle$	m_x	$t_x, m_x t_x^{-1}, t_x^{-1}, r_x^2 t_y, m_y t_y, r_x^2 t_y^{-1},$ $m_x r_x^{-1} t_z, r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$
		2496	H_{382}	1	m_z	$r_y^2 t_x, m_z r_z^{-1} t_x^{-1}, r_z^{-1} t_x^{-1}, m_z r_z t_y, r_z t_y, m_y t_y^{-1},$ $m_x r_z t_z, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
		2497	H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_z t_z, m_x r_x t_z^{-1}$
		2498	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_x^2 t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_x^2 t_z, r_x^2 t_z^{-1}$
[10, 38, 76, 132, 204, 292, 396, 516, 652, 804]						
		2499	H_{649}	$\langle m_z r_x \rangle$	m_x	$m_z r_x^{-1} t_x, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, i t_y, i t_y^{-1}, r_x^2 t_y^{-1},$ $r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
		2500	H_{332}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, i t_y, i t_y^{-1}, r_z^2 t_y^{-1},$ $r_z^2 t_z, i t_z^{-1}, r_z^2 t_z^{-1}$
		2501	H_{649}	$\langle m_z r_x \rangle$	m_x	$m_z r_x^{-1} t_x, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_x^2 t_y, i t_y^{-1}, r_x^2 t_y^{-1},$ $m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
		2502	H_{361}	1	m_z	$i t_x, i t_x^{-1}, r_z^2 t_x^{-1}, i t_y, i t_y^{-1}, r_z^2 t_y^{-1},$ $m_x t_z, r_y^2 t_z^{-1}, m_x t_z^{-1}$
		2503	H_{361}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, i t_y, i t_y^{-1}, r_z^2 t_y^{-1},$ $m_x t_z, r_y^2 t_z^{-1}, m_x t_z^{-1}$
		2504	H_{648}	$\langle m_z r_x \rangle$	m_x	$t_x, m_x t_x^{-1}, t_x^{-1}, i t_y, i t_y^{-1}, r_x^2 t_y^{-1},$ $r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}, m_z r_x^{-1} t_z^{-1}$
		2505	H_{344}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, i t_y, i t_y^{-1}, r_z^2 t_y^{-1},$ $m_x r_z t_z, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
		2506	H_{344}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, i t_y, r_z^2 t_y, i t_y^{-1},$ $m_x r_z t_z, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
		2507	H_{364}	1	m_z	$i t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_z^2 t_z, i t_z^{-1}, r_z^2 t_z^{-1}$
		2508	H_{364}	1	m_z	$i t_x, i t_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_z^2 t_z, i t_z^{-1}, r_z^2 t_z^{-1}$
		2509	H_{364}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_z^2 t_z, i t_z^{-1}, r_z^2 t_z^{-1}$
		2510	H_{364}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $r_z^2 t_z, i t_z^{-1}, r_z^2 t_z^{-1}$
		2511	H_{372}	1	m_z	$i t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_x t_z, r_y^2 t_z^{-1}, m_x t_z^{-1}$
		2512	H_{372}	1	m_z	$r_z^2 t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_x t_z, r_y^2 t_z^{-1}, m_x t_z^{-1}$
		2513	H_{365}	1	m_z	$i t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
		2514	H_{365}	1	m_z	$i t_x, i t_x^{-1}, r_z^2 t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
		2515	H_{350}	1	m_z	$i t_x, i t_x^{-1}, r_z^2 t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
		2516	H_{370}	1	m_z	$i t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
		2517	H_{370}	1	m_z	$i t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $m_y t_z, r_y^2 t_z^{-1}, m_y t_z^{-1}$
		2518	H_{359}	1	m_z	$i t_x, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 t_y, r_x^2 t_y^{-1}, m_y t_y^{-1},$ $t_z, m_z t_z^{-1}, t_z^{-1}$
		2519	H_{347}	1	m_z	$r_z^2 t_x, r_y^2 r_z t_x^{-1}, m_x r_z t_x^{-1}, i t_y, r_y^2 r_z t_y^{-1}, m_x r_z t_y^{-1},$ $m_x r_x^{-1} t_z, r_z^2 r_x t_z^{-1}, m_x r_x^{-1} t_z^{-1}$
		2520	H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_z^2 r_x t_z, r_z^2 t_z, r_z^2 r_x t_z^{-1}$

47A

- [7, 23, 50, 87, 135, 194, 263, 343, 434, 535]
 2521*,
 [7, 24, 55, 99, 156, 227, 311, 408, 519, 643]
 2522*, 2523*,
 [7, 25, 56, 98, 152, 218, 296, 386, 488, 602]

Nbr.	gr	N ₀	H_i	L	m	X
			2524*, 2525*, [7, 25, 57, 99, 152, 218, 296, 386, 488, 602]			
			2526*, 2527*, [7, 26, 57, 98, 152, 218, 296, 386, 488, 602]			
			2528*, 2529*, [7, 26, 59, 105, 166, 240, 328, 430, 545, 675]			
			2530*, 2531*, [7, 26, 60, 106, 166, 240, 328, 430, 545, 675]			
			2532*, 2533*, [7, 27, 60, 105, 166, 240, 328, 430, 545, 675]			
			2534*, [7, 28, 63, 109, 172, 249, 338, 444, 564, 695]			
			2535*, 2536*, [8, 27, 58, 101, 158, 226, 306, 401, 506, 623]			
		2521	H_{697}	$\langle m_x \rangle$	r_z^2	$m_x r_z^{-1} t_x, r_z t_x^{-1}, r_z t_y^{-1}, m_x r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, m_z r_z^{-1} t_z,$ $r_y^2 t_z^{-1}$
		2522	H_{693}	$\langle m_x \rangle$	r_z^2	$r_x^2 r_z t_x, m_z r_z t_x^{-1}, m_z r_z t_y^{-1}, r_x^2 r_z t_y^{-1}, r_y^2 t_z, r_x^2 t_z^{-1},$ $r_y^2 t_z^{-1}$
		2523	H_{695}	$\langle m_x \rangle$	r_z^2	$m_x r_z^{-1} t_x, r_z t_x^{-1}, r_z t_y^{-1}, m_x r_z^{-1} t_y^{-1}, r_y^2 t_z, r_x^2 t_z^{-1},$ $r_y^2 t_z^{-1}$
		2524	H_{458}	1	r_z^2	$m_x r_z t_x^{-1}, m_x r_z^{-1} t_x^{-1}, m_x r_z^{-1} t_y, m_x r_z t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1},$ $r_x^2 r_z t_z^{-1}$
		2525	H_{534}	1	r_z^2	$m_x r_z t_x^{-1}, m_x r_z^{-1} t_x^{-1}, m_x r_z^{-1} t_y, m_x r_z t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z,$ $r_y^2 r_z t_z^{-1}$
		2526	H_{510}	1	r_z^2	$r_z^{-1} t_x^{-1}, r_z t_x^{-1}, r_z t_y, r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1},$ $r_x^2 r_z t_z^{-1}$
		2527	H_{538}	1	r_z^2	$r_z^{-1} t_x^{-1}, r_z t_x^{-1}, r_z t_y, r_z^{-1} t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z,$ $r_y^2 r_z t_z^{-1}$
		2528	H_{440}	1	r_z^2	$r_y^2 r_z t_z^{-1}, r_x^2 r_z t_x^{-1}, r_x^2 r_z t_y, r_y^2 r_z t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1},$ $r_x^2 r_z t_z^{-1}$
		2529	H_{501}	1	r_z^2	$m_z r_z^{-1} t_x^{-1}, m_z r_z t_x^{-1}, m_z r_z t_y, m_z r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, r_y^2 r_z t_z^{-1},$ $r_x^2 r_z t_z^{-1}$
		2530	H_{459}	1	r_z^2	$m_x r_z t_x^{-1}, m_x r_z^{-1} t_x^{-1}, m_x r_z^{-1} t_y, m_x r_z t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1},$ $m_z t_z^{-1}$
		2531	H_{533}	1	r_z^2	$m_x r_z t_x^{-1}, m_x r_z^{-1} t_x^{-1}, m_x r_z^{-1} t_y, m_x r_z t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1},$ $r_x^2 t_z^{-1}$
		2532	H_{536}	1	r_z^2	$r_z^{-1} t_x^{-1}, r_z t_x^{-1}, r_z t_y, r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, i t_z^{-1},$ $m_z t_z^{-1}$
		2533	H_{512}	1	r_z^2	$r_z^{-1} t_x^{-1}, r_z t_x^{-1}, r_z t_y, r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, r_y^2 t_z^{-1},$ $r_x^2 t_z^{-1}$
		2534	H_{697}	$\langle m_x \rangle$	r_z^2	$m_x r_z^{-1} t_x, r_z t_x^{-1}, r_z t_y^{-1}, m_x r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, m_z r_z^{-1} t_z,$ $r_x^2 t_z^{-1}$
		2535	H_{693}	$\langle m_x \rangle$	r_z^2	$r_x^2 r_z t_x, m_z r_z t_x^{-1}, m_z r_z t_y^{-1}, r_x^2 r_z t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1},$ $r_y^2 t_z^{-1}$
		2536	H_{695}	$\langle m_x \rangle$	r_z^2	$m_x r_z^{-1} t_x, r_z t_x^{-1}, r_z t_y^{-1}, m_x r_z^{-1} t_y^{-1}, r_x^2 t_z, r_x^2 t_z^{-1},$ $r_y^2 t_z^{-1}$

47B

- [7, 24, 60, 119, 195, 284, 388, 508, 644, 796]
 2537*,
 [7, 25, 60, 113, 184, 272, 376, 496, 632, 784]
 2538*,
 [7, 25, 63, 122, 196, 284, 388, 508, 644, 796]
 2539*,
 [7, 25, 63, 124, 196, 284, 388, 508, 644, 796]
 2540*,
 [7, 26, 64, 120, 192, 280, 384, 504, 640, 792]
 2541*,
 [7, 26, 66, 124, 196, 284, 388, 508, 644, 796]
 2542*,
 [7, 26, 68, 128, 200, 288, 392, 512, 648, 800]
 2543*,
 [7, 26, 69, 129, 200, 288, 392, 512, 648, 800]
 2544*,
 [7, 27, 66, 122, 194, 282, 386, 506, 642, 794]
 2545*,
 [7, 27, 67, 123, 194, 282, 386, 506, 642, 794]
 2546*,
 [7, 27, 69, 128, 200, 288, 392, 512, 648, 800]
 2547*, 2548*, 2549*,
 [7, 27, 70, 129, 200, 288, 392, 512, 648, 800]
 2550*,
 [7, 28, 67, 122, 194, 282, 386, 506, 642, 794]
 2551*, 2552*, 2553*,

Nbr.	gr	N ₀	H _i	L	m	X
		2560	H ₅₄₈	1	m _z r _x	r _y ² r _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , m _x t _y , r _y ² r _x t _y ⁻¹ , m _x t _y ⁻¹ , r _y ² r _x t _z
		2561	H ₅₄₆	1	m _z r _x	r _y ² r _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , t _y , m _z r _x t _y ⁻¹ , t _y ⁻¹ , m _z r _x t _z
48A						
[9, 32, 72, 128, 200, 288, 392, 512, 648, 800]						
2562*, 2563*,						
[9, 33, 74, 130, 202, 290, 394, 514, 650, 802]						
2564*, 2565*, 2566*, 2567*, 2568*, 2569*,						
[9, 33, 75, 131, 202, 290, 394, 514, 650, 802]						
2570*,						
[9, 33, 75, 132, 204, 292, 396, 516, 652, 804]						
2571*, 2572*, 2573*, 2574*,						
[9, 34, 75, 130, 202, 290, 394, 514, 650, 802]						
2575*, 2576*, 2577*, 2578*, 2579*, 2580*, 2581*, 2582*, 2583*, 2584*, 2585*, 2586*, 2587*,						
[9, 34, 76, 132, 204, 292, 396, 516, 652, 804]						
2588*, 2589*, 2590*, 2591*, 2592*, 2593*, 2594*, 2595*, 2596*, 2597*, 2598*, 2599*, 2600*, 2601*, 2602*, 2603*,						
[9, 34, 77, 133, 204, 292, 396, 516, 652, 804]						
2604*,						
[9, 35, 77, 132, 204, 292, 396, 516, 652, 804]						
2605*, 2606*, 2607*, 2608*, 2609*, 2610*, 2611*, 2612*, 2613*, 2614*, 2615*, 2616*, 2617*, 2618*, 2619*, 2620*, 2621*, 2622*, 2623*, 2624*, 2625*, 2626*, 2627*, 2628*, 2629*, 2630*, 2631*, 2632*, 2633*, 2634*, 2635*,						
[10, 34, 74, 130, 202, 290, 394, 514, 650, 802]						
2562	H ₆₂₉		⟨m _z r _x ⁻¹ ⟩		r _x ²	r _z ² r _x t _x , r _y ² r _x t _x ⁻¹ , r _z ² r _x t _x ⁻¹ , t _y , m _z r _x t _y ⁻¹ , t _y ⁻¹ , r _z ² t _z , m _z r _x ⁻¹ t _z , m _z r _x ⁻¹ t _z ⁻¹
2563	H ₆₃₈		⟨m _z r _x ⁻¹ ⟩		r _x ²	r _z ² r _x t _x , r _z ² t _x ⁻¹ , m _x r _x t _x ⁻¹ , t _y , m _z r _x t _y ⁻¹ , t _y ⁻¹ , r _x ² t _z , m _z r _x ⁻¹ t _z , m _z r _x ⁻¹ t _z ⁻¹
[10, 35, 75, 131, 203, 291, 395, 515, 651, 803]						
2564	H ₄₃₃	1			r _z ²	m _z t _x , i t _x ⁻¹ , m _z t _x ⁻¹ , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , m _z t _z , i t _z ⁻¹ , m _z t _z ⁻¹
2565	H ₄₆₂	1			r _z ²	m _z t _x , i t _x ⁻¹ , m _z t _x ⁻¹ , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
2566	H ₄₆₀	1			r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , r _y ² t _z , i t _z ⁻¹ , m _z t _z ⁻¹
2567	H ₄₂₅	1			r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
2568	H ₅₀₃	1			r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , r _y ² r _z t _z , r _y ² r _z t _z , r _y ² t _z ⁻¹
2569	H ₅₁₉	1			r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , m _z r _z ⁻¹ t _z , m _z r _z t _z , r _y ² t _z ⁻¹
[10, 35, 76, 131, 203, 291, 395, 515, 651, 803]						
2570	H ₅₆₁	1			m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , i t _y ⁻¹ , r _z ² r _x t _y ⁻¹ , r _x ² t _z , m _z r _x ⁻¹ t _z , r _z ² r _x t _z ⁻¹
[10, 35, 76, 132, 204, 292, 396, 516, 652, 804]						
2571	H ₄₆₈	1			r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , m _z t _z , i t _z ⁻¹ , m _z t _z ⁻¹
2572	H ₄₆₁	1			r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , m _z t _z ⁻¹
2573	H ₆₄₀		⟨m _z r _x ⁻¹ ⟩		r _x ²	r _z ² r _x t _x , r _y ² r _x t _x ⁻¹ , r _z ² r _x t _x ⁻¹ , m _z t _y , r _x ⁻¹ t _y ⁻¹ , m _z t _y ⁻¹ , r _x ⁻¹ t _z , m _z t _z , r _x ⁻¹ t _z ⁻¹
2574	H ₆₄₅		⟨m _z r _x ⁻¹ ⟩		r _x ²	r _z ² r _x t _x , r _z ² t _x ⁻¹ , m _x r _x t _x ⁻¹ , m _z t _y , r _x ⁻¹ t _y ⁻¹ , m _z t _y ⁻¹ , r _x ⁻¹ t _z , m _z t _z , r _x ⁻¹ t _z ⁻¹
[10, 36, 75, 131, 203, 291, 395, 515, 651, 803]						
2575	H ₆₃₁		⟨m _z r _x ⁻¹ ⟩		r _x ²	r _y ² r _x t _x , r _y ² r _x t _x ⁻¹ , r _z ² r _x t _x ⁻¹ , m _x t _y , r _y ² r _x t _y ⁻¹ , m _x t _y ⁻¹ , i t _z , r _z ² r _x t _z , r _z ² r _x t _z ⁻¹
2576	H ₆₃₁		⟨m _z r _x ⁻¹ ⟩		r _x ²	r _z ² r _x t _x , r _y ² r _x t _x ⁻¹ , r _z ² r _x t _x ⁻¹ , m _x t _y , r _y ² r _x t _y ⁻¹ , m _x t _y ⁻¹ , i t _z , r _z ² r _x t _z , r _z ² r _x t _z ⁻¹
2577	H ₄₇₁	1			r _z ²	m _z t _x , i t _x ⁻¹ , m _z t _x ⁻¹ , m _z t _y , i t _y ⁻¹ , m _z t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
2578	H ₄₃₃	1			r _z ²	m _z t _x , i t _x ⁻¹ , m _z t _x ⁻¹ , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , i t _z , i t _z ⁻¹ , m _z t _z ⁻¹
2579	H ₄₆₂	1			r _z ²	m _z t _x , i t _x ⁻¹ , m _z t _x ⁻¹ , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , r _z ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
2580	H ₆₂₉		⟨m _z r _x ⁻¹ ⟩		r _x ²	r _y ² r _x t _x , r _y ² r _x t _x ⁻¹ , r _z ² r _x t _x ⁻¹ , t _y , m _z r _x t _y ⁻¹ , t _y ⁻¹ , r _x ⁻¹ t _z , m _z r _x ⁻¹ t _z , m _z r _x ⁻¹ t _z ⁻¹
2581	H ₆₃₈		⟨m _z r _x ⁻¹ ⟩		r _x ²	r _z ² r _x t _x , r _z ² t _x ⁻¹ , m _x r _x t _x ⁻¹ , t _y , m _z r _x t _y ⁻¹ , t _y ⁻¹ , r _y ² t _z , m _z r _x ⁻¹ t _z , m _z r _x ⁻¹ t _z ⁻¹
2582	H ₅₀₇	1			r _z ²	r _y ² r _z t _x , r _y ² r _z t _x ⁻¹ , r _x ² r _z t _x ⁻¹ , r _y ² r _z t _y , r _x ² r _z t _y , r _y ² r _z t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
2583	H ₅₃₁	1			r _z ²	m _x r _z t _x , m _x r _z t _x ⁻¹ , m _x r _z ⁻¹ t _x ⁻¹ , m _x r _z t _y , m _x r _z ⁻¹ t _y , m _x r _z t _y ⁻¹ , r _z ² t _z , i t _z ⁻¹ , m _z t _z ⁻¹

Nbr.	gr	N ₀	H _i	L	m	X
2584	H ₅₂₂	1	r _z ²	$m_x r_z t_x, m_x r_z t_x^{-1}, m_x r_z^{-1} t_x^{-1}, m_x r_z t_y, m_x r_z^{-1} t_y, m_x r_z t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2585	H ₅₃₃	1	r _z ²	$m_x r_z t_x, m_x r_z t_x^{-1}, m_x r_z^{-1} t_x^{-1}, m_x r_z t_y, m_x r_z^{-1} t_y, m_x r_z t_y^{-1}, r_y^2 r_z t_z, r_x^2 r_z t_z, r_y^2 t_z^{-1}$		
2586	H ₅₂₆	1	r _z ²	$m_x r_z t_x, m_x r_z t_x^{-1}, m_x r_z^{-1} t_x^{-1}, m_x r_z t_y, m_x r_z^{-1} t_y, m_x r_z t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z, r_y^2 t_z^{-1}$		
2587	H ₅₆₁	1	m _z r _x	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, i t_y^{-1}, r_z^2 r_x t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1}$		
[10, 36, 76, 132, 204, 292, 396, 516, 652, 804]						
2588	H ₄₇₅	1	r _z ²	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}, m_z t_z^{-1}$		
2589	H ₄₈₅	1	r _z ²	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2590	H ₄₆₆	1	r _z ²	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, m_z t_z, i t_z^{-1}, m_z t_z^{-1}$		
2591	H ₄₂₇	1	r _z ²	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2592	H ₄₆₁	1	r _z ²	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, i t_z^{-1}, m_z t_z^{-1}$		
2593	H ₄₆₁	1	r _z ²	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z, i t_z^{-1}, m_z t_z^{-1}$		
2594	H ₄₆₉	1	r _z ²	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2595	H ₄₆₉	1	r _z ²	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2596	H ₅₄₁	1	r _z ²	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}, m_z t_z^{-1}$		
2597	H ₅₄₁	1	r _z ²	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_x t_y, m_y t_y, m_x t_y^{-1}, m_z t_z, i t_z^{-1}, m_z t_z^{-1}$		
2598	H ₄₈₆	1	r _z ²	$r_x^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z t_z, i t_z^{-1}, m_z t_z^{-1}$		
2599	H ₄₇₉	1	r _z ²	$r_x^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2600	H ₄₈₃	1	r _z ²	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, i t_z^{-1}, m_z t_z^{-1}$		
2601	H ₄₈₂	1	r _z ²	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2602	H ₅₂₉	1	r _z ²	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_y^2 r_z t_z, r_x^2 r_z t_z, r_y^2 t_z^{-1}$		
2603	H ₅₃₀	1	r _z ²	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z, r_y^2 t_z^{-1}$		
[10, 36, 77, 132, 204, 292, 396, 516, 652, 804]						
2604	H ₅₇₁	1	m _z r _x	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, r_x^{-1} t_z, m_z t_z, m_x r_x^{-1} t_z^{-1}$		
[10, 37, 76, 132, 204, 292, 396, 516, 652, 804]						
2605	H ₄₇₃	1	r _z ²	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, i t_z, i t_z^{-1}, m_z t_z^{-1}$		
2606	H ₄₇₃	1	r _z ²	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, m_z t_z, i t_z^{-1}, m_z t_z^{-1}$		
2607	H ₄₇₄	1	r _z ²	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2608	H ₄₇₄	1	r _z ²	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2609	H ₅₃₉	1	r _z ²	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z, r_y^2 r_z t_z^{-1}$		
2610	H ₅₃₉	1	r _z ²	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, m_z r_z^{-1} t_z, m_z r_z t_z, r_y^2 r_z t_z^{-1}$		
2611	H ₄₇₅	1	r _z ²	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, i t_z, i t_z^{-1}, m_z t_z^{-1}$		
2612	H ₄₈₅	1	r _z ²	$m_z t_x, i t_x^{-1}, m_z t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2613	H ₄₆₆	1	r _z ²	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, i t_z, i t_z^{-1}, m_z t_z^{-1}$		
2614	H ₄₂₇	1	r _z ²	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1}, r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2615	H ₄₆₈	1	r _z ²	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1}, i t_z, i t_z^{-1}, m_z t_z^{-1}$		

Nbr.	gr	N	H_i	L	m	X
2616	H_{461}	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_y^2 t_z, r_y^2 t_z, i t_z^{-1}$		
2617	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2618	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 t_z, r_y^2 t_z, r_y^2 t_z^{-1}$		
2619	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2620	H_{511}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_y^2 t_y, r_x^2 t_y, r_y^2 t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2621	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $i t_z, i t_z^{-1}, m_z t_z^{-1}$		
2622	H_{541}	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $i t_z, m_z t_z, i t_z^{-1}$		
2623	H_{639}	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 r_x t_x^{-1}, r_y^2 t_y, m_x r_x^{-1} t_y^{-1}, r_y^2 t_y^{-1},$ $m_x r_x^{-1} t_z, r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$		
2624	H_{639}	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 r_x t_x^{-1}, r_y^2 t_y, m_x r_x^{-1} t_y^{-1}, r_y^2 t_y^{-1},$ $m_x r_x^{-1} t_z, r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$		
2625	H_{429}	1	r_z^2	$r_x^2 t_x, r_y^2 t_x^{-1}, r_y^2 t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2626	H_{486}	1	r_z^2	$r_x^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $i t_z, i t_z^{-1}, m_z t_z^{-1}$		
2627	H_{479}	1	r_z^2	$r_x^2 t_x, r_y^2 t_x^{-1}, r_x^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_x^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2628	H_{640}	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, r_z^2 r_x t_x^{-1}, m_z t_y, r_x^{-1} t_y^{-1}, m_z t_y^{-1},$ $r_y^2 t_z, m_z t_z, r_x^{-1} t_z^{-1}$		
2629	H_{645}	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_y^2 r_x t_x, r_z^2 t_x^{-1}, m_x r_x t_x^{-1}, m_z t_y, r_x^{-1} t_y^{-1}, m_z t_y^{-1},$ $r_x^{-1} t_z, m_z t_z, r_x^{-1} t_z^{-1}$		
2630	H_{524}	1	r_z^2	$m_z r_z t_x, m_z r_z t_x^{-1}, m_z r_z t_x^{-1}, m_z r_z^{-1} t_y, m_z r_z t_y, m_z r_z^{-1} t_y^{-1},$ $r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2631	H_{535}	1	r_z^2	$r_z t_x, r_z^{-1} t_x^{-1}, r_z t_x^{-1}, r_z^{-1} t_y, r_z t_y, r_z^{-1} t_y^{-1},$ $r_y^2 t_z, i t_z^{-1}, m_z t_z^{-1}$		
2632	H_{509}	1	r_z^2	$r_y^2 t_x, r_z^{-1} t_x^{-1}, r_z t_x^{-1}, r_z^{-1} t_y, r_z t_y, r_z^{-1} t_y^{-1},$ $r_y^2 t_z, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$		
2633	H_{512}	1	r_z^2	$r_z t_x, r_z^{-1} t_x^{-1}, r_z t_x^{-1}, r_z^{-1} t_y, r_z t_y, r_z^{-1} t_y^{-1},$ $r_y^2 r_z t_z, r_x^2 r_z t_z, r_y^2 t_z^{-1}$		
2634	H_{537}	1	r_z^2	$r_z t_x, r_z^{-1} t_x^{-1}, r_z t_x^{-1}, r_z^{-1} t_y, r_z t_y, r_z^{-1} t_y^{-1},$ $m_z r_z^{-1} t_z, m_z r_z t_z, r_y^2 t_z^{-1}$		
2635	H_{571}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_x t_y, r_y^2 t_y^{-1}, m_x r_x t_y^{-1},$ $r_x^{-1} t_z, m_z t_z, m_x r_x^{-1} t_z^{-1}$		

48B

[9, 35, 79, 134, 204, 292, 396, 516, 652, 804] 2636*	H_{766}	$\langle m_y, r_x^2 \rangle$	$m_z r_x^{-1}$	$m_x t_x, m_x t_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, r_x^{-1} t_y, t_y^{-1},$ $m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z, r_x t_z^{-1}$
[10, 38, 77, 132, 204, 292, 396, 516, 652, 804]				
2637	H_{561}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, m_z r_x^{-1} t_y, i t_y^{-1},$ $r_z^2 r_x t_y^{-1}, m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1}$
2638	H_{571}	1	$m_z r_x$	$m_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1},$ $m_x r_x t_y^{-1}, r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$
[10, 39, 76, 132, 204, 292, 396, 516, 652, 804]				
2639	H_{768}	$\langle m_y, r_x^2 \rangle$	$m_z r_x^{-1}$	$m_x t_x, m_x t_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, m_x r_x^{-1} t_y, m_x t_y^{-1},$ $r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z, m_x r_x t_z^{-1}$
2640	H_{768}	$\langle m_y, r_x^2 \rangle$	$m_z r_x^{-1}$	$r_z^2 r_x t_x, m_x t_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, m_x r_x^{-1} t_y, m_x t_y^{-1},$ $r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z, m_x r_x t_z^{-1}$
2641	H_{766}	$\langle m_y, r_x^2 \rangle$	$m_z r_x^{-1}$	$r_z^2 r_x t_x, m_x t_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, r_x^{-1} t_y, t_y^{-1},$ $m_z r_x^{-1} t_y^{-1}, m_z r_x^{-1} t_z, r_x t_z^{-1}$
2642	H_{561}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, m_z r_x^{-1} t_y, i t_y^{-1},$ $r_z^2 r_x t_y^{-1}, m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1}$
2643	H_{571}	1	$m_z r_x$	$r_y^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1},$ $m_x r_x t_y^{-1}, r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}$

49

[10, 35, 76, 132, 204, 292, 396, 516, 652, 804]
 2644*, 2645*, 2646*, 2647*, 2648*, 2649*, 2650*,
 [10, 36, 77, 132, 204, 292, 396, 516, 652, 804]

Nbr.	gr	N_0	H_i	L	m	X
2651*, 2652*, 2653*, 2654*, 2655*, 2656*, 2657*, 2658*, 2659*, 2660*, 2661*, 2662*, 2663*, 2664*, 2665*, 2666*, 2667*, 2668*, 2669*, 2670*, 2671*, 2672*, 2673*, 2674*, 2675*, 2676*, 2677*, 2678*, 2679*, 2680*, 2681*, 2682*, 2683*, 2684*, 2685*, 2686*, 2687*, 2688*, 2689*, 2690*, 2691*, 2692*, 2693*, 2694*, [11, 36, 76, 132, 204, 292, 396, 516, 652, 804]						
2644	H_{682}	$\langle m_x \rangle$	r_z^2			$itx, r_y^2 tx, r_x^2 t_x^{-1}, r_y^2 t_x^{-1}, m_x ty, m_y t_y^{-1},$ $m_x t_y^{-1}, r_y^2 tz, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
2645	H_{680}	$\langle m_x \rangle$	r_z^2			$r_z^2 tx, m_x tx, m_y t_x^{-1}, m_x t_x^{-1}, m_x ty, m_y t_y^{-1},$ $m_x t_y^{-1}, r_y^2 tz, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
2646	H_{359}	1	m_z			$itx, r_z^2 tx, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y ty, r_x^2 t_y^{-1},$ $m_y t_y^{-1}, t_z, m_z t_z^{-1}, t_z^{-1}$
2647	H_{343}	1	m_z			$r_z^2 tx, r_y^2 r_z t_x^{-1}, m_x r_z t_x^{-1}, ity, r_z^2 ty, r_y^2 r_z t_y^{-1},$ $m_x r_z t_y^{-1}, t_z, m_z t_z^{-1}, t_z^{-1}$
2648	H_{377}	1	m_z			$r_y^2 tx, m_x tx, m_z r_z^{-1} t_x^{-1}, r_z^{-1} t_x^{-1}, m_z r_z ty, r_z ty,$ $m_y t_y^{-1}, t_z, m_z t_z^{-1}, t_z^{-1}$
2649	H_{690}	$\langle m_x \rangle$	r_z^2			$r_z^2 tx, m_x tx, m_y t_x^{-1}, m_x t_x^{-1}, m_x ty, m_y t_y^{-1},$ $m_x t_y^{-1}, r_y^2 r_z t_z, m_z r_z^{-1} t_z, r_y^2 t_z^{-1}$
2650	H_{541}	1	r_z^2			$r_z^2 r_x tx, r_x tx, r_y^2 r_x t_x^{-1}, r_x^{-1} t_x^{-1}, m_x ty, m_x t_y^{-1},$ $m_y t_y^{-1}, m_z tz, it_z^{-1}, m_z t_z^{-1}$
[11, 37, 76, 132, 204, 292, 396, 516, 652, 804]						
2651	H_{683}	$\langle m_x \rangle$	r_z^2			$itx, r_y^2 tx, r_x^2 t_x^{-1}, r_y^2 t_x^{-1}, r_y^2 ty, r_x^2 t_y^{-1},$ $r_y^2 t_y^{-1}, r_x^2 tz, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
2652	H_{683}	$\langle m_x \rangle$	r_z^2			$itx, r_y^2 tx, r_x^2 t_x^{-1}, r_y^2 t_x^{-1}, r_y^2 ty, r_x^2 t_y^{-1},$ $r_y^2 t_y^{-1}, r_x^2 tz, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
2653	H_{682}	$\langle m_x \rangle$	r_z^2			$itx, r_y^2 tx, r_x^2 t_x^{-1}, r_y^2 t_x^{-1}, m_x ty, m_y t_y^{-1},$ $m_x t_y^{-1}, r_x^2 tz, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
2654	H_{344}	1	m_z			$itx, it_x^{-1}, r_z^2 t_x^{-1}, ity, r_z^2 ty, it_y^{-1},$ $r_z^2 t_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
2655	H_{344}	1	m_z			$itx, r_z^2 tx, it_x^{-1}, r_z^2 t_x^{-1}, ity, r_z^2 ty,$ $it^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
2656	H_{344}	1	m_z			$r_z^2 tx, it_x^{-1}, r_z^2 t_x^{-1}, ity, r_z^2 ty, it_y^{-1},$ $r_z^2 t_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
2657	H_{344}	1	m_z			$itx, r_z^2 tx, it_x^{-1}, r_z^2 t_x^{-1}, ity, r_z^2 ty,$ $r_z^2 t_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
2658	H_{682}	$\langle m_x \rangle$	r_z^2			$itx, r_y^2 tx, r_x^2 t_x^{-1}, r_y^2 t_x^{-1}, m_x ty, m_y t_y^{-1},$ $m_x t_y^{-1}, r_x^2 tz, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
2659	H_{683}	$\langle m_x \rangle$	r_z^2			$itx, r_y^2 tx, r_x^2 t_x^{-1}, r_y^2 t_x^{-1}, r_y^2 ty, r_x^2 t_y^{-1},$ $r_y^2 t_y^{-1}, r_x^2 tz, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
2660	H_{683}	$\langle m_x \rangle$	r_z^2			$itx, r_y^2 tx, r_x^2 t_x^{-1}, r_y^2 t_x^{-1}, r_y^2 ty, r_x^2 t_y^{-1},$ $r_y^2 t_y^{-1}, r_x^2 tz, r_y^2 t_z^{-1}, r_x^2 t_z^{-1}$
2661	H_{682}	$\langle m_y \rangle$	m_x			$m_z tx, r_y^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 ty, m_y ty, m_x t_y^{-1},$ $t_y^{-1}, r_y^2 tz, r_y^2 t_z^{-1}, m_z t_z^{-1}$
2662	H_{682}	$\langle m_y \rangle$	m_x			$m_z tx, r_y^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 ty, m_y ty, m_x t_y^{-1},$ $t_y^{-1}, m_z tz, r_y^2 t_z^{-1}, m_z t_z^{-1}$
2663	H_{680}	$\langle m_x \rangle$	r_z^2			$r_z^2 tx, m_x tx, m_y t_x^{-1}, m_x t_x^{-1}, m_x ty, m_y t_y^{-1},$ $m_x t_y^{-1}, r_x^2 tz, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$
2664	H_{370}	1	m_z			$itx, r_z^2 tx, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_z^2 ty, r_x^2 t_y^{-1},$ $m_y t_y^{-1}, m_y tz, r_x^2 t_z^{-1}, m_y t_z^{-1}$
2665	H_{370}	1	m_z			$itx, r_z^2 tx, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y ty, r_x^2 t_y^{-1},$ $m_y t_y^{-1}, m_y tz, r_x^2 t_z^{-1}, m_y t_z^{-1}$
2666	H_{359}	1	m_z			$itx, r_z^2 tx, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_z^2 ty, r_x^2 t_y^{-1},$ $m_y t_y^{-1}, t_z, m_z t_z^{-1}, t_z^{-1}$
2667	H_{347}	1	m_z			$itx, r_y^2 r_z t_x^{-1}, m_x r_z t_x^{-1}, ity, r_z^2 ty, r_y^2 r_z t_y^{-1},$ $m_x r_z t_y^{-1}, m_x r_z^{-1} t_z, r_x^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
2668	H_{347}	1	m_z			$r_z^2 tx, r_y^2 r_z t_x^{-1}, m_x r_z t_x^{-1}, ity, r_z^2 ty, r_y^2 r_z t_y^{-1},$ $m_x r_z t_y^{-1}, m_x r_z^{-1} t_z, r_x^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$
2669	H_{343}	1	m_z			$itx, r_y^2 r_z t_x^{-1}, m_x r_z t_x^{-1}, ity, r_z^2 ty, r_y^2 r_z t_y^{-1},$ $m_x r_z t_y^{-1}, t_z, m_z t_z^{-1}, t_z^{-1}$
2670	H_{378}	1	m_z			$r_y^2 tx, m_x tx, r_y^2 t_x^{-1}, m_x t_x^{-1}, r_x^2 ty, r_x^2 t_y^{-1},$ $m_y t_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
2671	H_{378}	1	m_z			$r_y^2 tx, m_x tx, r_y^2 t_x^{-1}, m_x t_x^{-1}, m_y ty, r_x^2 t_y^{-1},$ $m_y t_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
2672	H_{382}	1	m_z			$r_y^2 tx, m_x tx, m_z r_z^{-1} t_x^{-1}, r_z^{-1} t_x^{-1}, m_z r_z ty, r_z ty,$ $r_x^2 t_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$
2673	H_{382}	1	m_z			$r_y^2 tx, m_x tx, m_z r_z^{-1} t_x^{-1}, r_z^{-1} t_x^{-1}, m_z r_z ty, r_z ty,$ $m_y t_y^{-1}, m_x r_z t_z, r_y^2 r_z t_z^{-1}, m_x r_z t_z^{-1}$

Nbr.	gr	N ₀	H _i	L	m	X
2674	H ₃₇₇	1			m _z	r _z ² t _x , m _x t _x , m _z r _z ⁻¹ t _x ⁻¹ , r _z ⁻¹ t _x ⁻¹ , m _z r _z t _y , r _z t _y , r _x ² t _y ⁻¹ , t _z , m _z t _z ⁻¹ , t _z ⁻¹
2675	H ₄₅₃	1			r _z ²	m _z t _x , i t _x ⁻¹ , m _z t _x ⁻¹ , i t _y , m _z t _y , i t _y ⁻¹ , m _z t _y ⁻¹ , r _y ² r _z t _z , r _y ² r _z t _z ⁻¹ , r _y ² r _z t _z ⁻¹
2676	H ₅₃₉	1			r _z ²	i t _x , m _z t _x , i t _x ⁻¹ , m _z t _x ⁻¹ , r _y ² t _y , r _x ² t _y , r _y ² t _y ⁻¹ , r _x ² t _y ⁻¹ , m _z r _z ⁻¹ t _z , m _z r _z t _z , r _y ² r _z t _z ⁻¹
2677	H ₅₃₉	1			r _z ²	m _z t _x , i t _x ⁻¹ , m _z t _x ⁻¹ , r _y ² t _y , r _x ² t _y , r _y ² t _y ⁻¹ , r _x ² t _y ⁻¹ , m _z r _z ⁻¹ t _z , m _z r _z t _z , r _y ² r _z t _z ⁻¹
2678	H ₆₉₀	⟨m _x ⟩			r _z ²	r _z ² t _x , m _x t _x , m _y t _x ⁻¹ , m _x t _x ⁻¹ , m _x t _y , m _y t _y ⁻¹ , m _x t _y ⁻¹ , r _y ² r _z t _z , m _z r _z ⁻¹ t _z , r _y ² t _z ⁻¹
2679	H ₄₅₂	1			r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , r _y ² r _z t _z , i t _z ⁻¹ , m _z t _z ⁻¹
2680	H ₅₀₃	1			r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , r _y ² r _z t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
2681	H ₄₃₈	1			r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , r _y ² r _z t _z , r _y ² r _z t _z ⁻¹ , r _x ² r _z t _z ⁻¹
2682	H ₄₉₅	1			r _z ²	t _x , r _z ² t _x ⁻¹ , t _x ⁻¹ , r _z ² t _y , t _y , r _z ² t _y ⁻¹ , t _y ⁻¹ , m _z r _z ⁻¹ t _z , m _z r _z t _z , r _y ² r _z t _z ⁻¹
2683	H ₅₁₁	1			r _z ²	r _z ² r _x t _x , r _x t _x , r _y ² r _x t _x ⁻¹ , r _x ⁻¹ t _x ⁻¹ , r _y ² t _y , r _y ² t _y ⁻¹ , r _x ² t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
2684	H ₅₁₁	1			r _z ²	r _z ² r _x t _x , r _x t _x , r _y ² r _x t _x ⁻¹ , r _x ⁻¹ t _x ⁻¹ , r _y ² t _y , r _y ² t _y ⁻¹ , r _x ² t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
2685	H ₅₁₁	1			r _z ²	r _z ² r _x t _x , r _x t _x , r _x ⁻¹ t _x ⁻¹ , r _y ² t _y , r _y ² t _y ⁻¹ , r _x ² t _y ⁻¹ , r _y ² t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
2686	H ₅₁₁	1			r _z ²	r _z ² r _x t _x , r _x t _x , r _x ⁻¹ t _x ⁻¹ , r _y ² t _y , r _y ² t _y ⁻¹ , r _x ² t _y ⁻¹ , r _x ^{2t_z, r_y²t_z⁻¹, r_x²t_z⁻¹}
2687	H ₅₄₁	1			r _z ²	r _z ² r _x t _x , r _x t _x , r _y ² r _x t _x ⁻¹ , r _x ⁻¹ t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , i t _z , i t _z ⁻¹ , m _z t _z ⁻¹
2688	H ₅₄₁	1			r _z ²	r _z ² r _x t _x , r _x t _x , r _x ⁻¹ t _x ⁻¹ , m _x t _y , m _y t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , i t _z , i t _z ⁻¹ , m _z t _z ⁻¹
2689	H ₅₄₁	1			r _z ²	r _z ² r _x t _x , r _x t _x , r _x ⁻¹ t _x ⁻¹ , m _x t _y , m _y t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , m _z t _z , i t _z ⁻¹ , m _z t _z ⁻¹
2690	H ₅₀₅	1			r _z ²	r _y ² t _x , r _x ² t _x , r _y ² t _x ⁻¹ , r _x ⁻¹ t _x ⁻¹ , r _y ² t _y , r _y ² t _y ⁻¹ , r _x ² t _y ⁻¹ , r _y ² r _z t _z , r _y ² r _z t _z ⁻¹ , r _x ² r _z t _z ⁻¹
2691	H ₅₂₇	1			r _z ²	m _x t _x , m _y t _x , m _x t _x ⁻¹ , m _y t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , r _y ² r _z t _z , i t _z ⁻¹ , m _z t _z ⁻¹
2692	H ₅₂₉	1			r _z ²	m _x t _x , m _y t _x , m _x t _x ⁻¹ , m _y t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , r _y ² r _z t _z , r _y ² t _z ⁻¹ , r _x ² t _z ⁻¹
2693	H ₄₉₆	1			r _z ²	m _x t _x , m _y t _x , m _x t _x ⁻¹ , m _y t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , r _y ² r _z t _z , r _y ² r _z t _z ⁻¹ , r _x ² r _z t _z ⁻¹
2694	H ₅₀₂	1			r _z ²	m _x t _x , m _y t _x , m _x t _x ⁻¹ , m _y t _x ⁻¹ , m _x t _y , m _x t _y ⁻¹ , m _y t _y ⁻¹ , m _z r _z ⁻¹ t _z , m _z r _z t _z , r _y ² r _z t _z ⁻¹
50						
[10, 36, 78, 133, 204, 292, 396, 516, 652, 804]						
2695*, 2696*, 2697*, 2698*, 2699*, 2700*,						
[10, 37, 78, 132, 204, 292, 396, 516, 652, 804]						
2701*, 2702*, 2703*, 2704*, 2705*, 2706*, 2707*, 2708*, 2709*, 2710*, 2711*, 2712*, 2713*,						
2714*, 2715*, 2716*, 2717*, 2718*, 2719*, 2720*, 2721*, 2722*, 2723*, 2724*, 2725*, 2726*,						
2727*, 2728*, 2729*, 2730*, 2731*,						
[11, 37, 77, 132, 204, 292, 396, 516, 652, 804]						
2695	H ₅₆₀	1			m _z r _x	i t _x , r _z ² r _x t _x , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _x ² t _y ⁻¹ , m _z r _x ⁻¹ t _y ⁻¹ , r _x ² t _z , m _z r _x ⁻¹ t _z , r _x ² t _z ⁻¹ , m _z r _x ⁻¹ t _z ⁻¹
2696	H ₅₈₀	1			m _z r _x	i t _x , r _z ² r _x t _x , m _x t _x ⁻¹ , m _y t _y , r _x t _y , m _y t _y ⁻¹ , r _x ⁻¹ t _y ⁻¹ , r _x ⁻¹ t _z , r _x ⁻¹ t _z ⁻¹ , m _z t _z ⁻¹
2697	H ₅₆₁	1			m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , i t _y ⁻¹ , r _z ² r _x t _y ⁻¹ , r _x ² t _z , m _z r _x ⁻¹ t _z , i t _z ⁻¹ , r _z ² r _x t _z ⁻¹
2698	H ₅₇₁	1			m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , m _y t _y , r _x t _y , r _z ² t _y ⁻¹ , m _x r _x t _y ⁻¹ , r _x ⁻¹ t _z , m _x r _x ⁻¹ t _z ⁻¹ , r _y ² t _z ⁻¹
2699	H ₅₅₇	1			m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , m _z r _x ⁻¹ t _y , r _x ² t _y ⁻¹ , m _z r _x ⁻¹ t _y ⁻¹ , r _x ² t _z , m _z r _x ⁻¹ t _z , r _x ² t _z ⁻¹ , m _z r _x ⁻¹ t _z ⁻¹
2700	H ₅₇₈	1			m _z r _x	m _x t _x , r _y ² r _x t _x ⁻¹ , m _x t _x ⁻¹ , m _y t _y , r _x t _y , m _y t _y ⁻¹ , r _x ⁻¹ t _y ⁻¹ , r _x ⁻¹ t _z , r _x ⁻¹ t _z ⁻¹ , m _z t _z ⁻¹
[11, 38, 76, 132, 204, 292, 396, 516, 652, 804]						
2701	H ₅₅₁	1			m _z r _x	i t _x , i t _x ⁻¹ , r _z ² r _x t _x ⁻¹ , r _z ² r _x t _x , i t _y ⁻¹ , r _z ² r _x t _y ⁻¹ , i t _z , r _z ² r _x t _z , i t _z ⁻¹ , r _z ² r _x t _z ⁻¹
2702	H ₅₅₁	1			m _z r _x	r _z ² r _x t _x , i t _x ⁻¹ , r _z ² r _x t _x ⁻¹ , r _z ² r _x t _x , i t _y ⁻¹ , r _z ² r _x t _y ⁻¹ , i t _z , r _z ² r _x t _z , i t _z ⁻¹ , r _z ² r _x t _z ⁻¹

Nbr.	gr	Nº	H_i	L	m	X
2703		H_{551}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, it_y, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_y^{-1}, it_z, r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$	
2704		H_{572}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_z^2 t_z^{-1}$	
2705		H_{572}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_z^2 t_z^{-1}$	
2706		H_{555}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_z^2 t_z, m_z r_x^{-1} t_z, r_z^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$	
2707		H_{555}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_z^2 t_z, m_z r_x^{-1} t_z, r_z^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$	
2708		H_{555}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 t_y, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_z^2 t_z, m_z r_x^{-1} t_z, m_z r_x^{-1} t_z^{-1}$	
2709		H_{574}	1	$m_z r_x$	$it_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$	
2710		H_{574}	1	$m_z r_x$	$r_z^2 r_x t_x, it_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$	
2711		H_{560}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_z^2 t_z, m_z r_x^{-1} t_z, r_z^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$	
2712		H_{560}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_z^2 t_z, m_z r_x^{-1} t_z, r_z^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$	
2713		H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y r_x t_x, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_z^2 t_z, m_z r_x^{-1} t_z, r_z^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$	
2714		H_{560}	1	$m_z r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_z^2 t_z, m_z r_x^{-1} t_z, m_z r_x^{-1} t_z^{-1}$	
2715		H_{580}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_y t_y, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$	
2716		H_{580}	1	$m_z r_x$	$it_x, r_y r_x t_x, m_x t_x^{-1}, m_y t_y, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$	
2717		H_{580}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$	
2718		H_{556}	1	$m_z r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_y^{-1}, it_z, r_z^2 r_x t_z, it_z^{-1}, r_z^2 r_x t_z^{-1}$	
2719		H_{556}	1	$m_z r_x$	$m_x t_x, r_y r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_y^{-1}, it_z, r_z^2 r_x t_z, it_z^{-1}, r_z^2 r_x t_z^{-1}$	
2720		H_{556}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y r_x t_x^{-1}, m_x t_x^{-1}, it_y, r_z^2 r_x t_y, it_y^{-1}, r_z^2 r_x t_y^{-1}, it_z, r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$	
2721		H_{561}	1	$m_z r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, it_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 t_z, m_z r_x^{-1} t_z, it_z^{-1}, r_z^2 r_x t_z^{-1}$	
2722		H_{561}	1	$m_z r_x$	$r_z^2 r_x t_x, r_y r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, m_z r_x^{-1} t_y, it_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 t_z, m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1}$	
2723		H_{561}	1	$m_z r_x$	$m_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, m_z r_x^{-1} t_y, it_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 t_z, m_z r_x^{-1} t_z, r_z^2 r_x t_z^{-1}$	
2724		H_{576}	1	$m_z r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_z^2 t_z^{-1}$	
2725		H_{576}	1	$m_z r_x$	$m_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, m_x r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_z^2 t_z^{-1}$	
2726		H_{576}	1	$m_z r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 t_y, m_x r_x t_y, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z, r_z^2 t_z, m_x r_x^{-1} t_z^{-1}, r_z^2 t_z^{-1}$	
2727		H_{571}	1	$m_z r_x$	$r_y r_x t_x, r_y r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_z^2 t_z^{-1}$	
2728		H_{571}	1	$m_z r_x$	$r_y r_x t_x, r_y r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, r_x^{-1} t_z, m_z t_z, m_x r_x^{-1} t_z^{-1}$	
2729		H_{571}	1	$m_z r_x$	$m_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, r_z^2 t_y^{-1}, m_x r_x t_y^{-1}, r_x^{-1} t_z, m_z t_z, m_x r_x^{-1} t_z^{-1}$	
2730		H_{557}	1	$m_z r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_z^2 t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_z^2 t_z, m_z r_x^{-1} t_z, r_z^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$	
2731		H_{578}	1	$m_z r_x$	$r_z^2 r_x t_x, r_z^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y, m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$	

51A

- [7, 23, 50, 87, 135, 194, 263, 343, 434, 535] 2732*.
 [7, 23, 52, 97, 158, 233, 325, 431, 547, 682] 2733*.
 [7, 24, 53, 94, 147, 212, 289, 378, 479, 592] 2734*.
 [7, 24, 54, 96, 150, 216, 294, 384, 486, 600] 2735*.
 [7, 25, 56, 98, 152, 218, 296, 386, 488, 602] 2736*, 2737*.
 [7, 27, 62, 109, 172, 249, 338, 444, 564, 695]

Nbr.	gr	N ₀	H_i	L	m	X
2738*, 2739*, [8, 27, 58, 101, 158, 226, 306, 401, 506, 623]						
2732		H_{306}	1	i		$t_x, it_x^{-1}, t_x^{-1}, r_z^2 r_x t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z,$ $r_z^2 r_x t_z^{-1}$
[8, 27, 60, 109, 172, 246, 338, 446, 564, 701]						
2733		H_{321}	1	i		$t_x, it_x^{-1}, t_x^{-1}, m_x r_x^{-1} t_y^{-1}, r_x t_y^{-1}, m_x r_x t_z,$ $r_x^{-1} t_z^{-1}$
[8, 28, 60, 107, 166, 239, 325, 425, 537, 664]						
2734		H_{307}	1	i		$m_z r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x t_x^{-1}, r_z^2 r_x t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z,$ $r_z^2 r_x t_z^{-1}$
[8, 28, 61, 108, 168, 241, 328, 428, 541, 668]						
2735		H_{325}	1	i		$m_z r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x t_x^{-1}, m_x r_x t_y^{-1}, r_x^{-1} t_y^{-1}, r_x t_z,$ $m_x r_x^{-1} t_z^{-1}$
[8, 29, 62, 109, 169, 242, 329, 429, 542, 669]						
2736		H_{324}	1	i		$m_z r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, r_x t_y^{-1}, m_x r_x t_z,$ $r_x^{-1} t_z^{-1}$
2737		H_{309}	1	i		$m_z r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x t_x^{-1}, r_y^2 r_x t_y^{-1}, m_z r_x^{-1} t_y^{-1}, r_y^2 r_x t_z,$ $m_z r_x^{-1} t_z^{-1}$
[8, 31, 66, 115, 181, 258, 349, 459, 578, 711]						
2738		H_{310}	1	i		$r_x^2 t_x, m_x t_x^{-1}, r_x^2 t_x^{-1}, r_z^2 r_x t_y^{-1}, m_z r_x t_y^{-1}, m_z r_x t_z,$ $r_x^2 r_x t_z^{-1}$
2739		H_{322}	1	i		$r_x^2 t_x, m_x t_x^{-1}, r_x^2 t_x^{-1}, m_x r_x^{-1} t_y^{-1}, r_x t_y^{-1}, m_x r_x t_z,$ $r_x^{-1} t_z^{-1}$
51B						
[7, 24, 62, 118, 190, 278, 382, 502, 638, 790]						
2740*, [7, 24, 62, 120, 192, 280, 384, 504, 640, 792]						
2741*, [7, 25, 59, 109, 175, 257, 355, 469, 599, 745]						
2742*, [7, 25, 61, 116, 188, 276, 380, 500, 636, 788]						
2743*, [7, 25, 65, 124, 196, 284, 388, 508, 644, 796]						
2744*, [7, 25, 66, 127, 200, 288, 392, 512, 648, 800]						
2745*, [7, 26, 63, 117, 187, 273, 375, 493, 627, 777]						
2746*, [7, 26, 64, 121, 194, 282, 386, 506, 642, 794]						
2747*, [7, 26, 68, 128, 200, 288, 392, 512, 648, 800]						
2748*, 2749*, 2750*, [7, 27, 66, 122, 194, 282, 386, 506, 642, 794]						
2751*, 2752*, [7, 27, 68, 126, 198, 286, 390, 510, 646, 798]						
2753*, [7, 27, 69, 128, 200, 288, 392, 512, 648, 800]						
2754*, [7, 28, 69, 126, 198, 286, 390, 510, 646, 798]						
2755*, [7, 28, 70, 128, 200, 288, 392, 512, 648, 800]						
2756*, 2757*, [7, 29, 70, 126, 198, 286, 390, 510, 646, 798]						
2758*, 2759*, [8, 28, 70, 124, 198, 284, 390, 508, 646, 796]						
2740		H_{408}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_x t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1},$ $r_x^{-1} t_z^{-1}$
[8, 28, 70, 126, 198, 286, 390, 510, 646, 798]						
2741		H_{403}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x r_x t_y^{-1}, m_y t_z, m_x r_x^{-1} t_z^{-1},$ $m_y t_z^{-1}$
[8, 29, 66, 119, 188, 273, 374, 491, 624, 773]						
2742		H_{383}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, t_y, r_z^2 r_x t_y^{-1}, t_y^{-1},$ $r_z^2 r_x t_z^{-1}$
[8, 29, 68, 124, 196, 284, 388, 508, 644, 796]						
2743		H_{385}	1	$r_z^2 r_x$		$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_z r_x^{-1} t_y^{-1},$ $m_z r_x^{-1} t_z^{-1}$
[8, 29, 72, 128, 200, 288, 392, 512, 648, 800]						
2744		H_{416}	1	$r_z^2 r_x$		$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, m_x r_x t_y^{-1}, m_y t_z, m_x r_x^{-1} t_z^{-1},$ $m_y t_z^{-1}$
[8, 29, 73, 130, 202, 290, 394, 514, 650, 802]						
2745		H_{411}	1	$r_z^2 r_x$		$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_x t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1},$ $r_x^{-1} t_z^{-1}$
[8, 30, 69, 124, 195, 282, 385, 504, 639, 790]						
2746		H_{387}	1	$r_z^2 r_x$		$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, t_y, r_z^2 r_x t_y^{-1}, t_y^{-1},$ $r_z^2 r_x t_z^{-1}$
[8, 30, 70, 127, 199, 287, 391, 511, 647, 799]						
2747		H_{399}	1	$r_z^2 r_x$		$r_x^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_z r_x^{-1} t_y^{-1},$ $m_z r_x^{-1} t_z^{-1}$
[8, 30, 74, 130, 202, 290, 394, 514, 650, 802]						
2748		H_{417}	1	$r_z^2 r_x$		$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, r_x t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1},$ $r_x^{-1} t_z^{-1}$

Nbr.	gr	N ₀	H_i	L	m	X
		2769	H_{651}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, m_x r_x^{-1} t_y^{-1}, m_y t_z,$ $m_x r_x t_z, m_y t_z^{-1}$
		[9, 33, 73, 129, 201, 289, 393, 513, 649, 801]				
		2770	H_{646}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, m_x t_y, m_z r_x t_y^{-1},$ $m_x t_y^{-1}, m_z r_x t_z$
53A		[7, 27, 64, 113, 179, 260, 354, 467, 593, 734]				
		2771*				
		[8, 31, 68, 119, 188, 269, 368, 481, 609, 752]				
		2771	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_y^{-1} r_z^{-1} t_y^{-1}, r_y^2 r_z t_z,$ $r_y r_x t_z$
53B		[7, 24, 55, 98, 153, 222, 303, 396, 503, 622]				
		2772*				
		[7, 27, 60, 103, 160, 230, 312, 407, 515, 635]				
		2773*				
		[8, 28, 63, 110, 172, 249, 338, 441, 560, 691]				
		2772	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_y r_x t_x, r_y^2 r_z t_y, r_y^{-1} r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, r_y r_x t_z,$ $r_y^{-1} r_z^{-1} t_z^{-1}$
		[8, 31, 65, 113, 176, 253, 343, 447, 566, 698]				
		2773	H_{393}	1	$r_z^2 r_x$	$r_x^2 r_y t_x^{-1}, r_y^{-1} r_z^{-1} t_x^{-1}, r_y r_x t_y, r_y^{-1} r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, r_y r_x t_z,$ $r_x^2 r_y t_z^{-1}$
53C		[7, 29, 77, 134, 203, 294, 395, 515, 654, 803]				
		2774*				
		[8, 33, 79, 131, 205, 292, 395, 517, 652, 803]				
		2774	H_{393}	1	$r_z^2 r_x$	$r_y r_x t_x, r_x^2 r_y t_x^{-1}, r_y^{-1} r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, r_y r_x t_z, r_x^2 r_y t_z^{-1},$ $r_y^{-1} r_z^{-1} t_z^{-1}$
54A		[8, 32, 76, 131, 203, 294, 395, 515, 654, 803]				
		2775*				
		[9, 35, 76, 131, 205, 292, 395, 517, 652, 803]				
		2775	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_x^2 r_y t_y^{-1}, r_y^{-1} r_z^{-1} t_y^{-1},$ $r_y^2 r_z t_z, r_y r_x t_z$
54B		[8, 27, 59, 103, 160, 230, 312, 407, 515, 635]				
		2776*				
		[9, 30, 65, 113, 176, 253, 343, 447, 566, 698]				
		2776	H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_y r_x t_x, r_y^2 r_z t_y, r_x^2 r_y t_y^{-1}, r_y^{-1} r_z^{-1} t_y^{-1}, r_y^2 r_z t_z,$ $r_y r_x t_z, r_y^{-1} r_z^{-1} t_z^{-1}$
55A		[9, 31, 69, 123, 193, 279, 381, 499, 633, 783]				
		2777*				
		[9, 32, 72, 128, 200, 288, 392, 512, 648, 800]				
		2778*, 2779*				
		[9, 32, 73, 130, 202, 290, 394, 514, 650, 802]				
		2780*, 2781*				
		[9, 33, 74, 130, 202, 290, 394, 514, 650, 802]				
		2782*, 2783*, 2784*, 2785*, 2786*, 2787*, 2788*, 2789*,				
		[9, 33, 75, 132, 204, 292, 396, 516, 652, 804]				
		2790*, 2791*				
		[9, 34, 76, 132, 204, 292, 396, 516, 652, 804]				
		2792*, 2793*, 2794*, 2795*, 2796*, 2797*, 2798*, 2799*, 2800*, 2801*,				
		[10, 33, 72, 127, 198, 285, 388, 507, 642, 793]				
		2777	H_{777}	$\langle m_z r_x, r_y r_x \rangle$	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x r_z^{-1} t_y, m_x r_y^{-1} r_x^{-1} t_y^{-1}, m_x r_z^{-1} t_y^{-1},$ $r_y^{-1} r_z^{-1} t_z, r_z^2 r_y t_z^{-1}, r_y^{-1} r_z^{-1} t_z^{-1}$
		[10, 34, 74, 130, 202, 290, 394, 514, 650, 802]				
		2778	H_{301}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, t_y, i t_y^{-1}, t_y^{-1},$ $m_y t_z, r_z^2 t_z^{-1}, m_y t_z^{-1}$
		2779	H_{658}	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_x^{-1} t_y, r_z^2 t_y^{-1}, m_z t_y^{-1},$ $m_y t_z, m_x r_x t_z^{-1}, r_x t_z^{-1}$
		[10, 34, 75, 131, 203, 291, 395, 515, 651, 803]				
		2780	H_{406}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, t_y, r_z^2 r_x t_y^{-1}, t_y^{-1},$ $t_z, r_z^2 r_x t_z^{-1}, t_z^{-1}$
		2781	H_{394}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y, i t_y^{-1}, m_z r_x t_y^{-1},$ $m_z r_x t_z, r_z^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$
		[10, 35, 75, 131, 203, 291, 395, 515, 651, 803]				
		2782	H_{655}	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_z r_x t_y, i t_y^{-1}, t_y^{-1},$ $t_z, r_z^2 r_x t_z^{-1}, m_z r_x t_z^{-1}$
		2783	H_{302}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, m_z t_y, r_z^2 t_y^{-1}, m_z t_y^{-1},$ $r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$
		2784	H_{312}	1	i	$t_x, i t_x^{-1}, t_x^{-1}, m_z t_y, r_z^2 t_y^{-1}, m_z t_y^{-1},$ $m_x t_z, m_x t_z^{-1}, r_z^2 t_z^{-1}$
		2785	H_{656}	$\langle m_z r_x \rangle$	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y, m_x t_y^{-1}, r_x^2 t_y^{-1},$ $m_x t_z, r_z^2 r_x t_z^{-1}, m_z r_x t_z^{-1}$

Nbr.	gr	N ₀	H _i	L	m	X
[10, 35, 76, 132, 204, 292, 396, 516, 652, 804]						
2812*, 2813*, 2814*, 2815*, 2816*, 2817*, 2818*, 2819*, 2820*, 2821*, 2822*, 2823*, 2824*, 2825*, 2826*, 2827*, 2828*, 2829*, [11, 35, 75, 131, 203, 291, 395, 515, 651, 803]						
2812	H ₇₄₅	$\langle m_z r_x^{-1}, r_z^2 r_x \rangle$	i	$r_z^2 r_x t x, r_z^2 r_x t x, m_z r_x t_x^{-1}, r_z^2 r_x t_x^{-1}, m_x t_y, m_z r_x t_y^{-1},$ $m_x t_y^{-1}, r_z^2 t_z, r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$		
2813	H ₇₄₆	$\langle m_z r_x^{-1}, r_z^2 r_x \rangle$	i	$r_z^2 t_x, m_x r_x t_x, m_y t_x^{-1}, r_x t_x^{-1}, m_x t_y, m_z r_x t_y^{-1},$ $m_x t_y^{-1}, r_z^2 t_z, r_z^2 r_x t_z, r_z^2 r_x t_z^{-1}$		
2814	H ₆₃₈	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_z^2 r_x t x, r_z^2 r_x t x, r_z^2 t_x^{-1}, m_x r_x t_x^{-1}, t_y, m_z r_x t_y^{-1},$ $t_y^{-1}, r_z^2 t_z, m_z r_x^{-1} t_z, m_z r_x^{-1} t_z^{-1}$		
[11, 36, 76, 132, 204, 292, 396, 516, 652, 804]						
2815	H ₆₁₅	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $it_z, m_z t_z, r_z^2 t_z^{-1}, t_z^{-1}$		
2816	H ₃₀₅	1	i	$t_x, it_x^{-1}, t_x^{-1}, it_y, t_y, it_y^{-1},$ $t_y^{-1}, m_x r_x^{-1} t_z, r_z^2 r_x t_z^{-1}, m_x r_x^{-1} t_z^{-1}$		
2817	H ₇₄₇	$\langle m_z r_x^{-1}, r_z^2 r_x \rangle$	i	$r_z^2 r_x t x, r_z^2 r_x t x, m_z r_x t_x^{-1}, r_z^2 r_x t_x^{-1}, r_y^2 t_y, m_x r_x^{-1} t_y^{-1},$ $r_y^2 t_y^{-1}, m_x r_x^{-1} t_z, r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$		
2818	H ₆₁₆	$\langle m_z \rangle$	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_z^2 t_z, r_z^2 t_z, m_x t_z^{-1}, m_y t_z^{-1}$		
2819	H ₇₄₈	$\langle m_z r_x^{-1}, r_z^2 r_x \rangle$	i	$r_z^2 t_x, m_x r_x t_x, m_y t_x^{-1}, r_x t_x^{-1}, r_y^2 t_y, m_x r_x^{-1} t_y^{-1},$ $r_y^2 t_y^{-1}, m_x r_x^{-1} t_z, r_y^2 t_z, m_x r_x^{-1} t_z^{-1}$		
2820	H ₃₀₈	1	i	$m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, r_z^2 t_y, m_z t_y, r_z^2 t_y^{-1},$ $m_z t_y^{-1}, m_x r_z^{-1} t_z, r_z^2 r_z t_z^{-1}, m_x r_z^{-1} t_z^{-1}$		
2821	H ₃₂₃	1	i	$r_z^2 t_x, m_z t_x, r_z^2 t_x^{-1}, m_z t_x^{-1}, m_x r_y t_y, r_x r_y t_y^{-1},$ $m_x r_y t_y^{-1}, m_x t_z, m_x t_z^{-1}, r_z^2 t_z^{-1}$		
2822	H ₃₂₆	1	i	$m_z r_x t_x, r_z^2 r_x t_x^{-1}, m_z r_x t_x^{-1}, r_y^2 t_y, m_y t_y, r_y^2 t_y^{-1},$ $m_y t_y^{-1}, r_z^2 t_z, r_z^2 t_z^{-1}, m_z t_z^{-1}$		
2823	H ₅₃₉	1	r_z^2	$m_z t_x, it_x^{-1}, m_z t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_z^2 t_y^{-1},$ $m_z r_z^{-1} t_z, m_z r_z t_z, r_y^2 r_z t_z^{-1}, r_z^2 r_z t_z^{-1}$		
2824	H ₅₄₀	1	r_z^2	$m_z t_x, it_x^{-1}, m_z t_x^{-1}, r_y t_y, r_x r_y t_y^{-1}, r_y^{-1} t_y^{-1},$ $m_x t_z, m_y t_z, m_x t_z^{-1}, m_y t_z^{-1}$		
2825	H ₄₆₁	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $r_y^2 t_z, r_z^2 t_z, it_z^{-1}, m_z t_z^{-1}$		
2826	H ₅₀₄	1	r_z^2	$t_x, r_z^2 t_x^{-1}, t_x^{-1}, r_y t_y, r_x r_y t_y^{-1}, r_y^{-1} t_y^{-1},$ $r_z^2 t_z, t_z, r_z^2 t_z^{-1}, t_z^{-1}$		
2827	H ₅₁₁	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, r_y^2 t_y, r_y^2 t_y^{-1}, r_x t_y^{-1},$ $r_z^2 t_z, r_x t_z, r_y^2 t_z^{-1}, r_x t_z^{-1}$		
2828	H ₅₄₁	1	r_z^2	$r_z^2 r_x t_x, r_x t_x, r_x^{-1} t_x^{-1}, m_x t_y, m_x t_y^{-1}, m_y t_y^{-1},$ $it_z, m_z t_z, it_z^{-1}, m_z t_z^{-1}$		
2829	H ₆₄₅	$\langle m_z r_x^{-1} \rangle$	r_x^2	$r_y^2 r_x t_x, r_z^2 r_x t_x, r_z^2 t_x^{-1}, m_x r_x t_x^{-1}, m_z t_y, r_x^{-1} t_y^{-1},$ $m_z t_y^{-1}, r_x^{-1} t_z, m_z t_z, r_x^{-1} t_z^{-1}$		
56B						
[10, 37, 78, 132, 204, 292, 396, 516, 652, 804]						
2830*, [11, 38, 76, 132, 204, 292, 396, 516, 652, 804]						
2830	H ₇₇₉	$\langle i, r_x^2, r_z^2 \rangle$	$r_z^2 r_x$	$m_x t_x, m_z r_x^{-1} t_x, t_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_x r_x^{-1} t_y,$ $t_y^{-1}, r_z^2 r_x t_y^{-1}, r_z^2 r_x t_z, m_x r_x t_z^{-1}$		
57						
[10, 35, 76, 132, 204, 292, 396, 516, 652, 804]						
2831*, 2832*, 2833*, 2834*, [10, 36, 77, 132, 204, 292, 396, 516, 652, 804]						
2835*, 2836*, 2837*, 2838*, 2839*, 2840*, 2841*, 2842*, 2843*, 2844*, 2845*, 2846*, 2847*, 2848*, 2849*, 2850*, 2851*, 2852*, 2853*, 2854*, 2855*, 2856*, 2857*, 2858*, [10, 36, 78, 133, 204, 292, 396, 516, 652, 804]						
2859*, 2860*, [11, 36, 76, 132, 204, 292, 396, 516, 652, 804]						
2831	H ₃₈₈	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_y^{-1},$ $it_z, m_z r_x t_z, it_z^{-1}, m_z r_x t_z^{-1}$		
2832	H ₃₉₄	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y r_x t_y, r_z^2 t_y, it_y^{-1},$ $m_z r_x t_y^{-1}, m_z r_x t_z, r_y^2 r_x t_z^{-1}, r_z^2 t_z^{-1}$		
2833	H ₄₁₂	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1},$ $r_x^{-1} t_y^{-1}, r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$		
2834	H ₄₀₇	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1},$ $r_x^{-1} t_y^{-1}, r_x t_z, r_y^2 t_z^{-1}, r_x t_z^{-1}$		
[11, 37, 76, 132, 204, 292, 396, 516, 652, 804]						
2835	H ₃₈₉	1	$r_z^2 r_x$	$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_y^{-1},$ $it_z, m_z r_x t_z, it_z^{-1}, m_z r_x t_z^{-1}$		
2836	H ₄₁₄	1	$r_z^2 r_x$	$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1},$ $r_x^{-1} t_y^{-1}, r_x t_z, r_y^2 t_z^{-1}, r_x t_z^{-1}$		

Nbr.	gr	Nº	H_i	L	m	X
2837		H_{415}	1	$r_z^2 r_x$	$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, m_x r_x^{-1} t_y^{-1},$ $m_y t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$	
2838		H_{396}	1	$r_z^2 r_x$	$m_z r_x t_x, it_x^{-1}, m_z r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_x^2 t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$	
2839		H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, m_x r_x^{-1} t_y^{-1},$ $m_y t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$	
2840		H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, m_x r_x^{-1} t_y, m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1},$ $m_x r_x t_z, m_z t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$	
2841		H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_x^2 t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$	
2842		H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_x^2 t_y^{-1}, r_y^2 r_x t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$	
2843		H_{394}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y, it_y^{-1}, m_z r_x t_y^{-1},$ $it_z, m_z r_x t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$	
2844		H_{412}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1},$ $r_x^{-1} t_y^{-1}, r_y^2 t_z, r_x t_z, m_x r_x t_z^{-1}$	
2845		H_{402}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, m_x r_x^{-1} t_y^{-1},$ $m_y t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$	
2846		H_{391}	1	$r_z^2 r_x$	$t_x, r_z^2 r_x t_x^{-1}, t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_x^2 t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$	
2847		H_{398}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_y^{-1},$ $it_z, m_z r_x t_z, it_z^{-1}, m_z r_x t_z^{-1}$	
2848		H_{410}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1},$ $r_x^{-1} t_y^{-1}, r_x t_z, r_y^2 t_z^{-1}, r_x t_z^{-1}$	
2849		H_{404}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, m_x r_x^{-1} t_y^{-1},$ $m_y t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$	
2850		H_{392}	1	$r_z^2 r_x$	$r_z^2 t_x, r_y^2 r_x t_x^{-1}, r_x^2 t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_x^2 t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$	
2851		H_{400}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_z r_x t_y, it_y^{-1}, m_z r_x t_y^{-1},$ $it_z, m_z r_x t_z, it_z^{-1}, m_z r_x t_z^{-1}$	
2852		H_{395}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_y^2 r_x t_y, it_y^{-1}, m_z r_x t_y^{-1},$ $it_z, m_z r_x t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$	
2853		H_{395}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_y^2 r_x t_y, r_x^2 t_y, it_y^{-1},$ $m_z r_x t_y^{-1}, m_z r_x t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$	
2854		H_{413}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1},$ $r_x^{-1} t_y^{-1}, r_y^2 t_z, r_x t_z, m_x r_x t_z^{-1}$	
2855		H_{413}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, r_z^2 t_y^{-1},$ $r_x^{-1} t_y^{-1}, r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$	
2856		H_{418}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_z^2 t_y, r_x^{-1} t_y, r_z^2 t_y^{-1},$ $r_x^{-1} t_y^{-1}, r_x t_z, r_y^2 t_z^{-1}, r_x t_z^{-1}$	
2857		H_{419}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y, m_x r_x^{-1} t_y^{-1},$ $m_y t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$	
2858		H_{401}	1	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1}, r_x^2 t_y^{-1},$ $r_y^2 r_x t_z, r_x^2 t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$	
[11, 37, 77, 132, 204, 292, 396, 516, 652, 804]						
2859		H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_x^2 r_y t_x^{-1}, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_x^2 r_y t_y^{-1},$ $r_y^{-1} r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, r_y r_x t_z, r_x^2 r_y t_z^{-1}$	
2860		H_{393}	1	$r_z^2 r_x$	$r_y^2 r_z t_x, r_y r_x t_x, r_y^{-1} r_z^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y, r_x^2 r_y t_y^{-1},$ $r_y^{-1} r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, r_y r_x t_z, r_y^{-1} r_z^{-1} t_z^{-1}$	
58						
[11, 36, 76, 132, 204, 292, 396, 516, 652, 804]						
2861*, 2862*, 2863*,						
[12, 36, 76, 132, 204, 292, 396, 516, 652, 804]						
2861		H_{779}	$\langle m_z, m_z r_x, r_x^2 \rangle$	$r_z^2 r_x$	$m_z r_x^{-1} t_x, m_x t_x^{-1}, m_z r_x^{-1} t_x^{-1}, r_z^2 t_y, r_x^2 t_y, m_x t_y^{-1},$ $m_z r_x^{-1} t_y^{-1}, m_x r_x^{-1} t_z, m_z r_x^{-1} t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$	
2862		H_{750}	$\langle m_y, m_z \rangle$	r_z^2	$m_y t_x, m_x t_x^{-1}, m_y t_x^{-1}, r_z^2 t_y, m_y t_y, m_x t_y^{-1},$ $m_y t_y^{-1}, r_y^2 r_z t_z, m_z r_z t_z, m_x r_z t_z^{-1}, r_z t_z^{-1}$	
2863		H_{690}	$\langle m_x \rangle$	r_z^2	$r_z^2 t_x, m_x t_x, m_y t_x^{-1}, m_x t_x^{-1}, m_x t_y, m_y t_y^{-1},$ $m_x t_y^{-1}, r_y^2 r_z t_z, m_z r_z^{-1} t_z, r_x^2 t_z^{-1}, r_y^2 t_z^{-1}$	
59						
[11, 37, 77, 132, 204, 292, 396, 516, 652, 804]						
2864*, 2865*, 2866*, 2867*, 2868*, 2869*, 2870*, 2871*, 2872*,						
[12, 37, 76, 132, 204, 292, 396, 516, 652, 804]						
2864		H_{649}	$\langle m_x \rangle$	$r_y^2 r_x$	$it_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1},$ $r_z^2 r_x t_y^{-1}, r_x^2 t_z, r_z^2 r_x t_z, r_x^2 t_z^{-1}, r_z^2 r_x t_z^{-1}$	
2865		H_{652}	$\langle m_x \rangle$	$r_y^2 r_x$	$it_x, r_z^2 r_x t_x, r_x^2 t_x^{-1}, r_z^2 r_x t_x^{-1}, m_y t_y, m_x r_x t_y,$ $m_y t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x^{-1} t_z, m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$	

Nbr.	gr	N ₀	H_i	L	m	X
2866		H_{422}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, m_x r_x^{-1} t_y, m_y t_y,$ $m_x r_x^{-1} t_y^{-1}, m_y t_y^{-1}, m_x r_x t_z, m_x r_x t_z^{-1}, m_z t_z^{-1}$	
2867		H_{409}	1	$r_z^2 r_x$	$r_z^2 t_x, r_x^{-1} t_x, r_y^2 t_x^{-1}, r_x t_x^{-1}, r_y^2 r_x t_y, r_y^2 r_x t_y^{-1},$ $r_y^2 t_y^{-1}, r_y r_x t_z, r_x^2 t_z, r_y^2 r_x t_z^{-1}, r_x^2 t_z^{-1}$	
2868		H_{648}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, r_z^2 r_x t_y, r_x^2 t_y^{-1},$ $r_z^2 r_x t_y^{-1}, r_z^2 t_z, r_z^2 r_x t_z, r_x^2 t_z^{-1}, r_z^2 r_x t_z^{-1}$	
2869		H_{650}	$\langle m_x \rangle$	$r_y^2 r_x$	$r_y^2 r_x t_x, m_x t_x, m_z r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, m_x r_x t_y,$ $m_y t_y^{-1}, m_x r_x t_y^{-1}, m_x r_x t_z, m_x r_x^{-1} t_z^{-1}, r_y^2 t_z^{-1}$	
2870		H_{393}	1	$r_z^2 r_x$	$r_y^2 r_x t_x, r_y r_x t_x, r_x^2 r_y t_x^{-1}, r_y^{-1} r_x^{-1} t_x^{-1}, r_y^2 r_z t_y, r_y r_x t_y,$ $r_y^{-1} r_z^{-1} t_y^{-1}, r_y^2 r_z t_z, r_y r_x t_z, r_x^2 t_z^{-1}, r_y^{-1} r_x^{-1} t_z^{-1}$	
2871		H_{560}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_x^2 r_x t_x^{-1}, m_x t_x^{-1}, m_z r_x^{-1} t_y, r_x^2 t_y^{-1},$ $m_z r_x^{-1} t_y^{-1}, r_x^2 t_z, m_z r_x^{-1} t_z, r_x^2 t_z^{-1}, m_z r_x^{-1} t_z^{-1}$	
2872		H_{580}	1	$m_z r_x$	$it_x, r_z^2 r_x t_x, r_y^2 r_x t_x^{-1}, m_x t_x^{-1}, m_y t_y, r_x t_y,$ $m_y t_y^{-1}, r_x t_y^{-1}, r_x^{-1} t_z, r_x^{-1} t_z^{-1}, m_z t_z^{-1}$	

ORCID iDs

Kirill V. Kostousov <https://orcid.org/0000-0002-8955-5912>

References

- [1] B. Eick, F. Gähler and W. Nickel, Cryst manual. a gap4 package, version 4.1.10: [e-resource], <https://www.gap-system.org/Manuals/pkg/cryst/htm/chapters.htm>.
- [2] gap-system.org, Gap - groups, algorithms, programming - a system for computational discrete algebra, ver. 4.5.7: [e-resource], <http://www.gap-system.org>.
- [3] E. A. Konovalchik and K. V. Kostousov, Symmetrical 2-extensions of the 2-dimensional grid. i, *Trudy Inst. Mat. Mekh. UrO RAN* **22** (2016), 159–179, In Russian, http://journal.imm.uran.ru/sites/default/files/archive/trudy_imm-2016-1.pdf.
- [4] E. A. Konovalchik and K. V. Kostousov, Symmetrical 2-extensions of the 2-dimensional grid. ii, *Trudy Inst. Mat. Mekh. UrO RAN* **23** (2017), 192–211, doi:10.21538/0134-4889-2017-23-4-192-211, In Russian.
- [5] E. A. Neganova and V. I. Trofimov, Symmetrical extensions of graphs, *Izv. Math.* **78** (2014), 809–835, doi:10.1070/IM2014v078n04ABEH002707.
- [6] V. I. Trofimov, Symmetrical extensions of graphs and some other topics in graph theory related with group theory, *Proc. Steklov Inst. Math.* **279** (2012), 107–112, doi:10.1134/S0081543812090088.
- [7] V. I. Trofimov, The finiteness of the number of symmetrical 2-extensions of the d -dimensional grid and similar graphs, *Proc. Steklov Inst. Math.* **285** (2014), 169–182, doi:10.1134/s0081543814050198.